libbfd

The Binary File Descriptor Library

First Edition—BFD version < 3.0 % Since no product is stable before version 3.0 :-)
Original Document Created: April 1991

Steve Chamberlain
Cygnus Support

Free Software Foundation
sac@www.gnu.org
BFD, 1.5
TEXinfo 2023-09-19.19

Copyright © 1991-2025 Free Software Foundation, Inc.

Permission is granted to copy, distribute and/or modify this document under the terms of the GNU Free Documentation License, Version 1.3 or any later version published by the Free Software Foundation; with no Invariant Sections, with no Front-Cover Texts, and with no Back-Cover Texts. A copy of the license is included in the section entitled "GNU Free Documentation License".

Table of Contents

1 Introduction ... 1

1.1 History ... 1
1.2 How To Use BFD ... 1
1.3 What BFD Version 2 Can Do ... 2
1.3.1 Information Loss ... 2
1.3.2 The BFD canonical object-file format ... 3

2 BFD Front End ... 5

2.1 `typedef bfd` ... 5
2.2 Error reporting ... 12
2.2.1 Type `bfd_error_type` ... 12
2.2.1.1 `bfd_get_error` ... 13
2.2.1.2 `bfd_set_error` ... 13
2.2.1.3 `bfd_set_input_error` ... 13
2.2.1.4 `bfd_errmsg` ... 13
2.2.1.5 `bfd_perror` ... 13
2.2.1.6 `bfd_asprintf` ... 14
2.2.2 BFD error handler ... 14
2.2.2.1 `bfd_print_error` ... 14
2.2.2.2 `_bfd_error_handler` ... 14
2.2.2.3 `bfd_set_error_handler` ... 14
2.2.2.4 `_bfd_set_error_handler_caching` ... 15
2.2.2.5 `_bfd_restore_error_handler_caching` ... 15
2.2.2.6 `bfd_set_error_program_name` ... 15
2.2.2.7 `_bfd_get_error_program_name` ... 15
2.2.3 BFD assert handler ... 15
2.2.3.1 `bfd_set_assert_handler` ... 15
2.2.3.2 `bfd_init` ... 16
2.3 Threading ... 16
2.3.1 Thread functions ... 16
2.3.1.1 `_bfd_threading_enabled` ... 16
2.3.1.2 `bfd_thread_init` ... 16
2.3.1.3 `bfd_thread_cleanup` ... 16
2.3.1.4 `bfd_lock` ... 16
2.3.1.5 `bfd_unlock` ... 17
2.4 Miscellaneous ... 17
2.4.1 Miscellaneous functions ... 17
2.4.1.1 `bfd_get_reloc_upper_bound` ... 17
2.4.1.2 `bfd_canonicalize_reloc` ... 17
2.4.1.3 `bfd_set_reloc` ... 17
2.4.1.4 `bfd_set_file_flags` ... 17
2.4.1.5 `bfd_get_arch_size` ... 18
2.4.1.6 `bfd_get_sign_extend_vma` ... 18

2.4.1.7 bfd_set_start_address ... 18
2.4.1.8 bfd_get_gp_size ... 18
2.4.1.9 bfd_set_gp_size ... 18
2.4.1.10 bfd_set_gp_value ... 18
2.4.1.11 bfd_scan_vma ... 18
2.4.1.12 bfd_copy_private_header_data ... 19
2.4.1.13 bfd_copy_private_bfd_data ... 19
2.4.1.14 bfd_set_private_flags ... 19
2.4.1.15 Other functions ... 19
2.4.1.16 bfd_get_relocated_section_contents ... 22
2.4.1.17 bfd_record_phdr ... 22
2.4.1.18 bfd_sprintf_vma ... 22
2.4.1.19 bfd_alt_mach_code ... 22
2.4.1.20 bfd_emul_get_maxpagesize ... 22
2.4.1.21 bfd_emul_get_commonpagesize ... 22
2.4.1.22 bfd_demangle ... 22
2.4.1.23 bfd_group_signature ... 22
2.4.1.24 struct bfd_iovec ... 23
2.4.1.25 bfd_read ... 23
2.4.1.26 bfd_write ... 24
2.4.1.27 bfd_tell ... 24
2.4.1.28 bfd_flush ... 24
2.4.1.29 bfd_stat ... 24
2.4.1.30 bfd_seek ... 24
2.4.1.31 bfd_get_mtime ... 24
2.4.1.32 bfd_get_size ... 24
2.4.1.33 bfd_get_file_size ... 25
2.4.1.34 bfd_mmap ... 25
2.4.1.35 bfd_get_current_time ... 25
2.5 Memory Usage ... 25
2.6 Sections ... 26
2.6.1 Section input ... 26
2.6.2 Section output ... 26
2.6.3 Link orders ... 27
2.6.4 typedef asection ... 27
2.6.5 Section prototypes ... 36
2.6.5.1 bfd_section_list_clear ... 36
2.6.5.2 bfd_get_section_by_name ... 36
2.6.5.3 bfd_get_next_section_by_name ... 36
2.6.5.4 bfd_get_linker_section ... 36
2.6.5.5 bfd_get_section_by_name_if ... 36
2.6.5.6 bfd_get_unique_section_name ... 37
2.6.5.7 bfd_make_section_old_way ... 37
2.6.5.8 bfd_make_section_anyway_with_flags ... 37
2.6.5.9 bfd_make_section_anyway ... 37
2.6.5.10 bfd_make_section_with_flags ... 38
2.6.5.11 bfd_make_section ... 38

2.6.5.12 bfd_set_section_flags ... 38
2.6.5.13 bfd_rename_section ... 38
2.6.5.14 bfd_map_over_sections ... 38
2.6.5.15 bfd_sections_find_if ... 39
2.6.5.16 bfd_set_section_size ... 39
2.6.5.17 bfd_set_section_contents ... 39
2.6.5.18 bfd_get_section_contents ... 39
2.6.5.19 bfd_malloc_and_get_section ... 40
2.6.5.20 bfd_copy_private_section_data ... 40
2.6.5.21 bfd_generic_is_group_section ... 40
2.6.5.22 bfd_generic_group_name ... 40
2.6.5.23 bfd_generic_discard_group ... 40
2.6.5.24 bfd_section_size_insane ... 40
2.7 Symbols ... 40
2.7.1 Reading symbols ... 41
2.7.2 Writing symbols ... 41
2.7.3 Mini Symbols ... 42
2.7.4 typedef asymbol ... 43
2.7.5 Symbol handling functions ... 46
2.7.5.1 bfd_get_symtab_upper_bound ... 46
2.7.5.2 bfd_is_local_label ... 46
2.7.5.3 bfd_is_local_label_name ... 46
2.7.5.4 bfd_is_target_special_symbol ... 46
2.7.5.5 bfd_canonicalize_symtab ... 47
2.7.5.6 bfd_set_symtab ... 47
2.7.5.7 bfd_print_symbol_vandf ... 47
2.7.5.8 bfd_make_empty_symbol ... 47
2.7.5.9 _bfd_generic_make_empty_symbol ... 47
2.7.5.10 bfd_make_debug_symbol ... 47
2.7.5.11 bfd_decode_symclass ... 47
2.7.5.12 bfd_is_undefined_symclass ... 48
2.7.5.13 bfd_symbol_info ... 48
2.7.5.14 bfd_copy_private_symbol_data ... 48
2.8 Archives ... 48
2.8.1 Archive functions ... 49
2.8.1.1 bfd_get_next_mapent ... 49
2.8.1.2 bfd_set_archive_head ... 49
2.8.1.3 bfd_openr_next_archived_file ... 49
2.9 File formats ... 49
2.9.1 File format functions ... 50
2.9.1.1 bfd_check_format_lto ... 50
2.9.1.2 bfd_check_format ... 50
2.9.1.3 bfd_check_format_matches_lto ... 50
2.9.1.4 bfd_check_format_matches ... 51
2.9.1.5 bfd_set_format ... 51
2.9.1.6 bfd_format_string ... 51
2.10 Relocations ... 51

2.10.1 typedef arelent 51
2.10.1.1 enum complain_overflow 54
2.10.1.2 reloc_howto_type 54
2.10.1.3 The HOWTO Macro 56
2.10.1.4 arelent_chain 57
2.10.1.5 bfd_check_overflow 57
2.10.1.6 bfd_reloc_offset_in_range 57
2.10.1.7 bfd_perform_relocation 57
2.10.1.8 bfd_install_relocation 58
2.10.2 The howto manager 58
2.10.2.1 bfd_reloc_code_real_type 58
2.10.2.2 bfd_reloc_type_lookup 139
2.10.2.3 bfd_default_reloc_type_lookup 139
2.10.2.4 bfd_get_reloc_code_name 139
2.10.2.5 bfd_generic_relax_section 139
2.10.2.6 bfd_generic_gc_sections 140
2.10.2.7 bfd_generic_lookup_section_flags 140
2.10.2.8 bfd_generic_merge_sections 140
2.10.2.9 bfd_generic_get_relocated_section_contents . 140
2.10.2.10 _bfd_generic_set_reloc 140
2.10.2.11 _bfd_unrecognized_reloc 140
2.11 Core files 140
2.11.1 Core file functions 140
2.11.1.1 bfd_core_file_failing_command 141
2.11.1.2 bfd_core_file_failing_signal 141
2.11.1.3 bfd_core_file_pid 141
2.11.1.4 core_file_matches_executable_p 141
2.11.1.5 generic_core_file_matches_executable_p 141
2.12 Targets 141
2.12.1 bfd_target 142
2.12.1.1 bfd_set_default_target 153
2.12.1.2 bfd_find_target 153
2.12.1.3 bfd_get_target_info 154
2.12.1.4 bfd_target_list 154
2.12.1.5 bfd_iterate_over_targets 154
2.12.1.6 bfd_flavour_name 154
2.13 Architectures 154
2.13.1 bfd_architecture 155
2.13.2 bfd_arch_info 166
2.13.2.1 bfd_printable_name 167
2.13.2.2 bfd_scan_arch 167
2.13.2.3 bfd_arch_list 167
2.13.2.4 bfd_arch_get_compatible 167
2.13.2.5 bfd_default_arch_struct 167
2.13.2.6 bfd_set_arch_info 167
2.13.2.7 bfd_default_set_arch_mach 167
2.13.2.8 bfd_get_arch 168

2.13.2.9 bfd_get_mach ... 168
2.13.2.10 bfd_arch_bits_per_byte ... 168
2.13.2.11 bfd_arch_bits_per_address ... 168
2.13.2.12 bfd_default_compatible ... 168
2.13.2.13 bfd_default_scan ... 168
2.13.2.14 bfd_get_arch_info ... 168
2.13.2.15 bfd_lookup_arch ... 168
2.13.2.16 bfd_printable_arch_mach ... 168
2.13.2.17 bfd_octets_per_byte ... 169
2.13.2.18 bfd_arch_mach_octets_per_byte ... 169
2.13.2.19 bfd_arch_default_fill ... 169
2.14 Opening and closing BFDs ... 169
2.14.1 Functions for opening and closing ... 169
2.14.1.1 _bfd_new_bfd ... 169
2.14.1.2 _bfd_new_bfd_contained_in ... 169
2.14.1.3 _bfd_free_cached_info ... 169
2.14.1.4 bfd_fopen ... 169
2.14.1.5 bfd_openr ... 170
2.14.1.6 bfd_fdopenr ... 170
2.14.1.7 bfd_fdopenw ... 170
2.14.1.8 bfd_openstreamr ... 171
2.14.1.9 bfd_openr_iovec ... 171
2.14.1.10 bfd_openw ... 171
2.14.1.11 bfd_elf_bfd_from_remote_memory ... 172
2.14.1.12 bfd_close ... 172
2.14.1.13 bfd_close_all_done ... 172
2.14.1.14 bfd_create ... 172
2.14.1.15 bfd_make_writable ... 173
2.14.1.16 bfd_make_readable ... 173
2.14.1.17 bfd_calc_gnu_debuglink_crc32 ... 173
2.14.1.18 bfd_get_debug_link_info ... 173
2.14.1.19 bfd_get_alt_debug_link_info ... 173
2.14.1.20 bfd_follow_gnu_debuglink ... 174
2.14.1.21 bfd_follow_gnu_debugaltlink ... 174
2.14.1.22 bfd_create_gnu_debuglink_section ... 174
2.14.1.23 bfd_fill_in_gnu_debuglink_section ... 174
2.14.1.24 bfd_follow_build_id_debuglink ... 175
2.14.1.25 bfd_set_filename ... 175
2.14.1.26 bfd_extract_object_only_section ... 175
2.15 Implementation details ... 175
2.15.1 Internal functions ... 175
2.15.1.1 bfd_malloc ... 175
2.15.1.2 bfd_realloc ... 175
2.15.1.3 bfd_realloc_or_free ... 176
2.15.1.4 bfd_zmalloc ... 176
2.15.1.5 bfd_alloc ... 176
2.15.1.6 bfd_zalloc ... 176

2.15.1.7 bfd_release ... 176
2.15.1.8 bfd_write_bigendian_4byte_int ... 177
2.15.1.9 bfd_put_size ... 177
2.15.1.10 bfd_get_size ... 177
2.15.1.11 bfd_h_put_size ... 178
2.15.1.12 Byte swapping routines ... 180
2.15.1.13 bfd_log2 ... 180
2.16 File caching ... 180
2.16.1 Caching functions ... 181
2.16.1.1 bfd_cache_init ... 181
2.16.1.2 bfd_cache_close ... 181
2.16.1.3 bfd_cache_close_all ... 181
2.16.1.4 bfd_cache_set_uncloseable ... 181
2.16.1.5 bfd_cache_size ... 181
2.16.1.6 bfd_open_file ... 181
2.17 Linker Functions ... 182
2.17.1 Creating a linker hash table ... 182
2.17.2 Adding symbols to the hash table ... 182
2.17.2.1 Differing file formats ... 183
2.17.2.2 Adding symbols from an object file ... 183
2.17.2.3 Adding symbols from an archive ... 184
2.17.3 Performing the final link ... 184
2.17.3.1 Information provided by the linker ... 185
2.17.3.2 Relocating the section contents ... 185
2.17.3.3 Writing the symbol table ... 185
2.17.3.4 _bfd_generic_link_add_one_symbol ... 186
2.17.3.5 bfd_link_align_section ... 186
2.17.3.6 bfd_link_split_section ... 187
2.17.3.7 bfd_section_already_linked ... 187
2.17.3.8 bfd_generic_define_common_symbol ... 187
2.17.3.9 _bfd_generic_link_hide_symbol ... 187
2.17.3.10 bfd_generic_define_start_stop ... 188
2.17.3.11 bfd_find_version_for_sym ... 188
2.17.3.12 bfd_hide_sym_by_version ... 188
2.17.3.13 bfd_link_check_relocs ... 188
2.17.3.14 _bfd_generic_link_check_relocs ... 188
2.17.3.15 bfd_merge_private_bfd_data ... 188
2.17.3.16 _bfd_generic_verify_endian_match ... 189
2.18 Hash Tables ... 189
2.18.1 Creating and freeing a hash table ... 189
2.18.2 Looking up or entering a string ... 189
2.18.3 Traversing a hash table ... 190
2.18.4 Deriving a new hash table type ... 190
2.18.4.1 Define the derived structures ... 190
2.18.4.2 Write the derived creation routine ... 191
2.18.4.3 Write other derived routines ... 192
2.18.4.4 bfd_hash_table_init_n ... 192

2.18.4.5 `bfd_hash_table_init` ... 192
2.18.4.6 `bfd_hash_table_free` ... 192
2.18.4.7 `bfd_hash_lookup` ... 192
2.18.4.8 `bfd_hash_insert` ... 192
2.18.4.9 `bfd_hash_rename` ... 193
2.18.4.10 `bfd_hash_replace` ... 193
2.18.4.11 `bfd_hash_allocate` ... 193
2.18.4.12 `bfd_hash_newfunc` ... 193
2.18.4.13 `bfd_hash_traverse` ... 193
2.18.4.14 `bfd_hash_set_default_size` ... 193
2.18.4.15 `_bfd_stringtab_init` ... 193
2.18.4.16 `_bfd_xcoff_stringtab_init` ... 193
2.18.4.17 `_bfd_stringtab_free` ... 193
2.18.4.18 `_bfd_stringtab_add` ... 194
2.18.4.19 `_bfd_stringtab_size` ... 194
2.18.4.20 `_bfd_stringtab_emit` ... 194

3 BFD back ends ... 195

3.1 What to Put Where ... 195
3.2 a.out backends ... 195
3.2.1 Relocations ... 196
3.2.2 Internal entry points ... 196
3.2.2.1 `aout_size_swap_exec_header_in` ... 196
3.2.2.2 `aout_size_swap_exec_header_out` ... 196
3.2.2.3 `aout_size_some_aout_object_p` ... 196
3.2.2.4 `aout_size_mkobject` ... 197
3.2.2.5 `aout_size_machine_type` ... 197
3.2.2.6 `aout_size_set_arch_mach` ... 197
3.2.2.7 `aout_size_new_section_hook` ... 197
3.3 coff backends ... 197
3.3.1 Porting to a new version of coff ... 197
3.3.2 How the coff backend works ... 198
3.3.2.1 File layout ... 198
3.3.2.2 Coff long section names ... 198
3.3.2.3 Bit twiddling ... 199
3.3.2.4 Symbol reading ... 199
3.3.2.5 Symbol writing ... 200
3.3.2.6 `coff_symbol_type` ... 201
3.3.2.7 `bfd_coff_backend_data` ... 202
3.3.2.8 Writing relocations ... 205
3.3.2.9 Reading linenumbers ... 205
3.3.2.10 Reading relocations ... 205
3.4 ELF backends ... 206
3.5 mmo backend ... 206
3.5.1 File layout ... 206
3.5.2 Symbol table format ... 208

3.5.3 mmo section mapping 210

BFD Index 220

1 Introduction

BFD is a package which allows applications to use the same routines to operate on object files whatever the object file format. A new object file format can be supported simply by creating a new BFD back end and adding it to the library.

BFD is split into two parts: the front end, and the back ends (one for each object file format).

- The front end of BFD provides the interface to the user. It manages memory and various canonical data structures. The front end also decides which back end to use and when to call back end routines.
- The back ends provide BFD its view of the real world. Each back end provides a set of calls which the BFD front end can use to maintain its canonical form. The back ends also may keep around information for their own use, for greater efficiency.

1.1 History

One spur behind BFD was the desire, on the part of the GNU 960 team at Intel Oregon, for interoperability of applications on their COFF and b.out file formats. Cygnus was providing GNU support for the team, and was contracted to provide the required functionality.

The name came from a conversation David Wallace was having with Richard Stallman about the library: RMS said that it would be quite hard—David said "BFD". Stallman was right, but the name stuck.

At the same time, Ready Systems wanted much the same thing, but for different object file formats: IEEE-695, Oasys, Srecords, a.out and 68k coff.

BFD was first implemented by members of Cygnus Support; Steve Chamberlain (`sac@cygnus.com`), John Gilmore (`gnu@cygnus.com`), K. Richard Pixley (`rich@cygnus.com`) and David Henkel-Wallace (`gumby@cygnus.com`).

1.2 How To Use BFD

To use the library, include `bfd.h` and link with `libbfd.a`.

BFD provides a common interface to the parts of an object file for a calling application.

When an application successfully opens a target file (object, archive, or whatever), a pointer to an internal structure is returned. This pointer points to a structure called `bfd`, described in `bfd.h`. Our convention is to call this pointer a BFD, and instances of it within code `abfd`. All operations on the target object file are applied as methods to the BFD. The mapping is defined within `bfd.h` in a set of macros, all beginning with '`bfd_`' to reduce namespace pollution.

For example, this sequence does what you would probably expect: return the number of sections in an object file attached to a BFD `abfd`.

```
#include "bfd.h"

unsigned int number_of_sections (abfd)
bfd *abfd;
{
```

```
  return bfd_count_sections (abfd);
}
```

The abstraction used within BFD is that an object file has:

- a header,
- a number of sections containing raw data (see Section 2.6 [Sections], page 26),
- a set of relocations (see Section 2.10 [Relocations], page 51), and
- some symbol information (see Section 2.7 [Symbols], page 40).

Also, BFDs opened for archives have the additional attribute of an index and contain subordinate BFDs. This approach is fine for a.out and coff, but loses efficiency when applied to formats such as S-records and IEEE-695.

1.3 What BFD Version 2 Can Do

When an object file is opened, BFD subroutines automatically determine the format of the input object file. They then build a descriptor in memory with pointers to routines that will be used to access elements of the object file's data structures.

As different information from the object files is required, BFD reads from different sections of the file and processes them. For example, a very common operation for the linker is processing symbol tables. Each BFD back end provides a routine for converting between the object file's representation of symbols and an internal canonical format. When the linker asks for the symbol table of an object file, it calls through a memory pointer to the routine from the relevant BFD back end which reads and converts the table into a canonical form. The linker then operates upon the canonical form. When the link is finished and the linker writes the output file's symbol table, another BFD back end routine is called to take the newly created symbol table and convert it into the chosen output format.

1.3.1 Information Loss

Information can be lost during output. The output formats supported by BFD do not provide identical facilities, and information which can be described in one form has nowhere to go in another format. One example of this is alignment information in `b.out`. There is nowhere in an `a.out` format file to store alignment information on the contained data, so when a file is linked from `b.out` and an `a.out` image is produced, alignment information will not propagate to the output file. (The linker will still use the alignment information internally, so the link is performed correctly).

Another example is COFF section names. COFF files may contain an unlimited number of sections, each one with a textual section name. If the target of the link is a format which does not have many sections (e.g., `a.out`) or has sections without names (e.g., the Oasys format), the link cannot be done simply. You can circumvent this problem by describing the desired input-to-output section mapping with the linker command language.

Information can be lost during canonicalization. The BFD internal canonical form of the external formats is not exhaustive; there are structures in input formats for which there is no direct representation internally. This means that the BFD back ends cannot maintain all possible data richness through the transformation between external to internal and back to external formats.

This limitation is only a problem when an application reads one format and writes another. Each BFD back end is responsible for maintaining as much data as possible, and the internal BFD canonical form has structures which are opaque to the BFD core, and exported only to the back ends. When a file is read in one format, the canonical form is generated for BFD and the application. At the same time, the back end saves away any information which may otherwise be lost. If the data is then written back in the same format, the back end routine will be able to use the canonical form provided by the BFD core as well as the information it prepared earlier. Since there is a great deal of commonality between back ends, there is no information lost when linking or copying big endian COFF to little endian COFF, or `a.out` to `b.out`. When a mixture of formats is linked, the information is only lost from the files whose format differs from the destination.

1.3.2 The BFD canonical object-file format

The greatest potential for loss of information occurs when there is the least overlap between the information provided by the source format, that stored by the canonical format, and that needed by the destination format. A brief description of the canonical form may help you understand which kinds of data you can count on preserving across conversions.

files Information stored on a per-file basis includes target machine architecture, particular implementation format type, a demand pageable bit, and a write protected bit. Information like Unix magic numbers is not stored here—only the magic numbers' meaning, so a `ZMAGIC` file would have both the demand pageable bit and the write protected text bit set. The byte order of the target is stored on a per-file basis, so that big- and little-endian object files may be used with one another.

sections Each section in the input file contains the name of the section, the section's original address in the object file, size and alignment information, various flags, and pointers into other BFD data structures.

symbols Each symbol contains a pointer to the information for the object file which originally defined it, its name, its value, and various flag bits. When a BFD back end reads in a symbol table, it relocates all symbols to make them relative to the base of the section where they were defined. Doing this ensures that each symbol points to its containing section. Each symbol also has a varying amount of hidden private data for the BFD back end. Since the symbol points to the original file, the private data format for that symbol is accessible. `ld` can operate on a collection of symbols of wildly different formats without problems.

Normal global and simple local symbols are maintained on output, so an output file (no matter its format) will retain symbols pointing to functions and to global, static, and common variables. Some symbol information is not worth retaining; in `a.out`, type information is stored in the symbol table as long symbol names. This information would be useless to most COFF debuggers; the linker has command-line switches to allow users to throw it away.

There is one word of type information within the symbol, so if the format supports symbol type information within symbols (for example, COFF, Oasys) and the type is simple enough to fit within one word (nearly everything but aggregates), the information will be preserved.

relocation level

Each canonical BFD relocation record contains a pointer to the symbol to relocate to, the offset of the data to relocate, the section the data is in, and a pointer to a relocation type descriptor. Relocation is performed by passing messages through the relocation type descriptor and the symbol pointer. Therefore, relocations can be performed on output data using a relocation method that is only available in one of the input formats. For instance, Oasys provides a byte relocation format. A relocation record requesting this relocation type would point indirectly to a routine to perform this, so the relocation may be performed on a byte being written to a 68k COFF file, even though 68k COFF has no such relocation type.

line numbers

Object formats can contain, for debugging purposes, some form of mapping between symbols, source line numbers, and addresses in the output file. These addresses have to be relocated along with the symbol information. Each symbol with an associated list of line number records points to the first record of the list. The head of a line number list consists of a pointer to the symbol, which allows finding out the address of the function whose line number is being described. The rest of the list is made up of pairs: offsets into the section and line numbers. Any format which can simply derive this information can pass it successfully between formats.

2 BFD Front End

2.1 typedef bfd

A BFD has type `bfd`; objects of this type are the cornerstone of any application using BFD. Using BFD consists of making references though the BFD and to data in the BFD.

Here is the structure that defines the type `bfd`. It contains the major data about the file and pointers to the rest of the data.

```
struct bfd
{
  /* The filename the application opened the BFD with.  */
  const char *filename;

  /* A pointer to the target jump table.  */
  const struct bfd_target *xvec;

  /* The IOSTREAM, and corresponding IO vector that provide access
     to the file backing the BFD.  */
  void *iostream;
  const struct bfd_iovec *iovec;

  /* The caching routines use these to maintain a
     least-recently-used list of BFDs.  */
  struct bfd *lru_prev, *lru_next;

  /* Track current file position (or current buffer offset for
     in-memory BFDs).  When a file is closed by the caching routines,
     BFD retains state information on the file here.  */
  ufile_ptr where;

  /* File modified time, if mtime_set is TRUE.  */
  long mtime;

  /* A unique identifier of the BFD  */
  unsigned int id;

  /* Format_specific flags.  */
  flagword flags;

  /* Values that may appear in the flags field of a BFD.  These also
     appear in the object_flags field of the bfd_target structure, where
     they indicate the set of flags used by that backend (not all flags
     are meaningful for all object file formats) (FIXME: at the moment,
     the object_flags values have mostly just been copied from backend
     to another, and are not necessarily correct).  */
```

```
#define BFD_NO_FLAGS                0x0

  /* BFD contains relocation entries.  */
#define HAS_RELOC                   0x1

  /* BFD is directly executable.  */
#define EXEC_P                      0x2

  /* BFD has line number information (basically used for F_LNNO in a
     COFF header).  */
#define HAS_LINENO                  0x4

  /* BFD has debugging information.  */
#define HAS_DEBUG                  0x08

  /* BFD has symbols.  */
#define HAS_SYMS                   0x10

  /* BFD has local symbols (basically used for F_LSYMS in a COFF
     header).  */
#define HAS_LOCALS                 0x20

  /* BFD is a dynamic object.  */
#define DYNAMIC                    0x40

  /* Text section is write protected (if D_PAGED is not set, this is
     like an a.out NMAGIC file) (the linker sets this by default, but
     clears it for -r or -N).  */
#define WP_TEXT                    0x80

  /* BFD is dynamically paged (this is like an a.out ZMAGIC file) (the
     linker sets this by default, but clears it for -r or -n or -N).  */
#define D_PAGED                   0x100

  /* BFD is relaxable (this means that bfd_relax_section may be able to
     do something) (sometimes bfd_relax_section can do something even if
     this is not set).  */
#define BFD_IS_RELAXABLE          0x200

  /* This may be set before writing out a BFD to request using a
     traditional format.  For example, this is used to request that when
     writing out an a.out object the symbols not be hashed to eliminate
     duplicates.  */
#define BFD_TRADITIONAL_FORMAT    0x400

  /* This flag indicates that the BFD contents are actually cached
     in memory.  If this is set, iostream points to a malloc'd
```

```
     bfd_in_memory struct.  */
#define BFD_IN_MEMORY              0x800

  /* This BFD has been created by the linker and doesn't correspond
     to any input file.  */
#define BFD_LINKER_CREATED       0x1000

  /* This may be set before writing out a BFD to request that it
     be written using values for UIDs, GIDs, timestamps, etc. that
     will be consistent from run to run.  */
#define BFD_DETERMINISTIC_OUTPUT 0x2000

  /* Compress sections in this BFD.  */
#define BFD_COMPRESS             0x4000

  /* Decompress sections in this BFD.  */
#define BFD_DECOMPRESS           0x8000

  /* BFD is a dummy, for plugins.  */
#define BFD_PLUGIN              0x10000

  /* Compress sections in this BFD with SHF_COMPRESSED from gABI.  */
#define BFD_COMPRESS_GABI       0x20000

  /* Convert ELF common symbol type to STT_COMMON or STT_OBJECT in this
     BFD.  */
#define BFD_CONVERT_ELF_COMMON  0x40000

  /* Use the ELF STT_COMMON type in this BFD.  */
#define BFD_USE_ELF_STT_COMMON  0x80000

  /* Put pathnames into archives (non-POSIX).  */
#define BFD_ARCHIVE_FULL_PATH  0x100000

#define BFD_CLOSED_BY_CACHE    0x200000
  /* Compress sections in this BFD with SHF_COMPRESSED zstd.  */
#define BFD_COMPRESS_ZSTD      0x400000

  /* Don't generate ELF section header.  */
#define BFD_NO_SECTION_HEADER  0x800000

  /* Flags bits which are for BFD use only.  */
#define BFD_FLAGS_FOR_BFD_USE_MASK \
  (BFD_IN_MEMORY | BFD_COMPRESS | BFD_DECOMPRESS | BFD_LINKER_CREATED \
   | BFD_PLUGIN | BFD_TRADITIONAL_FORMAT | BFD_DETERMINISTIC_OUTPUT \
   | BFD_COMPRESS_GABI | BFD_CONVERT_ELF_COMMON | BFD_USE_ELF_STT_COMMON \
   | BFD_NO_SECTION_HEADER)
```

```
/* The format which belongs to the BFD. (object, core, etc.)  */
ENUM_BITFIELD (bfd_format) format : 3;

/* The direction with which the BFD was opened.  */
ENUM_BITFIELD (bfd_direction) direction : 2;

/* POSIX.1-2017 (IEEE Std 1003.1) says of fopen : "When a file is
   opened with update mode ('+' as the second or third character in
   the mode argument), both input and output may be performed on
   the associated stream.  However, the application shall ensure
   that output is not directly followed by input without an
   intervening call to fflush() or to a file positioning function
   (fseek(), fsetpos(), or rewind()), and input is not directly
   followed by output without an intervening call to a file
   positioning function, unless the input operation encounters
   end-of-file."
   This field tracks the last IO operation, so that bfd can insert
   a seek when IO direction changes.  */
ENUM_BITFIELD (bfd_last_io) last_io : 2;

/* Is the file descriptor being cached?  That is, can it be closed as
   needed, and re-opened when accessed later?  */
unsigned int cacheable : 1;

/* Marks whether there was a default target specified when the
   BFD was opened. This is used to select which matching algorithm
   to use to choose the back end.  */
unsigned int target_defaulted : 1;

/* ... and here: (``once'' means at least once).  */
unsigned int opened_once : 1;

/* Set if we have a locally maintained mtime value, rather than
   getting it from the file each time.  */
unsigned int mtime_set : 1;

/* Flag set if symbols from this BFD should not be exported.  */
unsigned int no_export : 1;

/* Remember when output has begun, to stop strange things
   from happening.  */
unsigned int output_has_begun : 1;

/* Have archive map.  */
unsigned int has_armap : 1;
```

```
/* Set if this is a thin archive.  */
unsigned int is_thin_archive : 1;

/* Set if this archive should not cache element positions.  */
unsigned int no_element_cache : 1;

/* Set if only required symbols should be added in the link hash table for
   this object.  Used by VMS linkers.  */
unsigned int selective_search : 1;

/* Set if this is the linker output BFD.  */
unsigned int is_linker_output : 1;

/* Set if this is the linker input BFD.  */
unsigned int is_linker_input : 1;

/* If this is an input for a compiler plug-in library.  */
ENUM_BITFIELD (bfd_plugin_format) plugin_format : 2;

/* Set if this is a plugin output file.  */
unsigned int lto_output : 1;

/* Do not attempt to modify this file.  Set when detecting errors
   that BFD is not prepared to handle for objcopy/strip.  */
unsigned int read_only : 1;

/* LTO object type.  */
ENUM_BITFIELD (bfd_lto_object_type) lto_type : 3;

/* Set if this BFD is currently being processed by
   bfd_check_format_matches.  This is checked by the cache to
   avoid closing the BFD in this case.  This should only be
   examined or modified while the BFD lock is held.  */
unsigned int in_format_matches : 1;

/* Set to dummy BFD created when claimed by a compiler plug-in
   library.  */
bfd *plugin_dummy_bfd;

/* The offset of this bfd in the file, typically 0 if it is not
   contained in an archive.  */
ufile_ptr origin;

/* The origin in the archive of the proxy entry.  This will
   normally be the same as origin, except for thin archives,
   when it will contain the current offset of the proxy in the
   thin archive rather than the offset of the bfd in its actual
```

```
   container.  */
ufile_ptr proxy_origin;

/* A hash table for section names.  */
struct bfd_hash_table section_htab;

/* Pointer to linked list of sections.  */
struct bfd_section *sections;

/* The last section on the section list.  */
struct bfd_section *section_last;

/* The object-only section on the section list.  */
struct bfd_section *object_only_section;

/* The number of sections.  */
unsigned int section_count;

/* The archive plugin file descriptor.  */
int archive_plugin_fd;

/* The number of opens on the archive plugin file descriptor.  */
unsigned int archive_plugin_fd_open_count;

/* A field used by _bfd_generic_link_add_archive_symbols.  This will
   be used only for archive elements.  */
int archive_pass;

/* The total size of memory from bfd_alloc.  */
bfd_size_type alloc_size;

/* Stuff only useful for object files:
   The start address.  */
bfd_vma start_address;

/* Symbol table for output BFD (with symcount entries).
   Also used by the linker to cache input BFD symbols.  */
struct bfd_symbol **outsymbols;

/* Used for input and output.  */
unsigned int symcount;

/* Used for slurped dynamic symbol tables.  */
unsigned int dynsymcount;

/* Pointer to structure which contains architecture information.  */
const struct bfd_arch_info *arch_info;
```

```
/* Cached length of file for bfd_get_size.  0 until bfd_get_size is
   called, 1 if stat returns an error or the file size is too large to
   return in ufile_ptr.  Both 0 and 1 should be treated as "unknown".  */
ufile_ptr size;

/* Stuff only useful for archives.  */
void *arelt_data;
struct bfd *my_archive;      /* The containing archive BFD.  */
struct bfd *archive_next;    /* The next BFD in the archive.  */
struct bfd *archive_head;    /* The first BFD in the archive.  */
struct bfd *nested_archives; /* List of nested archive in a flattened
                                thin archive.  */

union {
  /* For input BFDs, a chain of BFDs involved in a link.  */
  struct bfd *next;
  /* For output BFD, the linker hash table.  */
  struct bfd_link_hash_table *hash;
} link;

/* Used by the back end to hold private data.  */
union
  {
    struct aout_data_struct *aout_data;
    struct artdata *aout_ar_data;
    struct coff_tdata *coff_obj_data;
    struct pe_tdata *pe_obj_data;
    struct xcoff_tdata *xcoff_obj_data;
    struct ecoff_tdata *ecoff_obj_data;
    struct srec_data_struct *srec_data;
    struct verilog_data_struct *verilog_data;
    struct ihex_data_struct *ihex_data;
    struct tekhex_data_struct *tekhex_data;
    struct elf_obj_tdata *elf_obj_data;
    struct mmo_data_struct *mmo_data;
    struct trad_core_struct *trad_core_data;
    struct som_data_struct *som_data;
    struct hpux_core_struct *hpux_core_data;
    struct hppabsd_core_struct *hppabsd_core_data;
    struct sgi_core_struct *sgi_core_data;
    struct lynx_core_struct *lynx_core_data;
    struct osf_core_struct *osf_core_data;
    struct cisco_core_struct *cisco_core_data;
    struct netbsd_core_struct *netbsd_core_data;
    struct mach_o_data_struct *mach_o_data;
    struct mach_o_fat_data_struct *mach_o_fat_data;
```

```
      struct plugin_data_struct *plugin_data;
      struct bfd_pef_data_struct *pef_data;
      struct bfd_pef_xlib_data_struct *pef_xlib_data;
      struct bfd_sym_data_struct *sym_data;
      void *any;
    }
  tdata;

  /* Used by the application to hold private data.  */
  void *usrdata;

  /* Where all the allocated stuff under this BFD goes.  This is a
     struct objalloc *, but we use void * to avoid requiring the inclusion
     of objalloc.h.  */
  void *memory;

  /* For input BFDs, the build ID, if the object has one. */
  const struct bfd_build_id *build_id;

  /* For input BFDs, mmapped entries. */
  struct bfd_mmapped *mmapped;
};
```

2.2 Error reporting

Most BFD functions return nonzero on success (check their individual documentation for precise semantics). On an error, they call `bfd_set_error` to set an error condition that callers can check by calling `bfd_get_error`. If that returns `bfd_error_system_call`, then check `errno`.

The easiest way to report a BFD error to the user is to use `bfd_perror`.

The BFD error is thread-local.

2.2.1 Type `bfd_error_type`

The values returned by `bfd_get_error` are defined by the enumerated type `bfd_error_type`.

```
typedef enum bfd_error
{
  bfd_error_no_error = 0,
  bfd_error_system_call,
  bfd_error_invalid_target,
  bfd_error_wrong_format,
  bfd_error_wrong_object_format,
  bfd_error_invalid_operation,
  bfd_error_no_memory,
  bfd_error_no_symbols,
```

```
  bfd_error_no_armap,
  bfd_error_no_more_archived_files,
  bfd_error_malformed_archive,
  bfd_error_missing_dso,
  bfd_error_file_not_recognized,
  bfd_error_file_ambiguously_recognized,
  bfd_error_no_contents,
  bfd_error_nonrepresentable_section,
  bfd_error_no_debug_section,
  bfd_error_bad_value,
  bfd_error_file_truncated,
  bfd_error_file_too_big,
  bfd_error_sorry,
  bfd_error_on_input,
  bfd_error_invalid_error_code
}
bfd_error_type;
```

2.2.1.1 bfd_get_error

`bfd_error_type bfd_get_error (void);` [Function]

Return the current BFD error condition.

2.2.1.2 bfd_set_error

`void bfd_set_error (bfd_error_type error_tag);` [Function]

Set the BFD error condition to be *error_tag*.

error_tag must not be bfd_error_on_input. Use bfd_set_input_error for input errors instead.

2.2.1.3 bfd_set_input_error

`void bfd_set_input_error (bfd *input, bfd_error_type error_tag);` [Function]

Set the BFD error condition to be bfd_error_on_input. *input* is the input bfd where the error occurred, and *error_tag* the bfd_error_type error.

2.2.1.4 bfd_errmsg

`const char *bfd_errmsg (bfd_error_type error_tag);` [Function]

Return a string describing the error *error_tag*, or the system error if *error_tag* is `bfd_error_system_call`.

2.2.1.5 bfd_perror

`void bfd_perror (const char *message);` [Function]

Print to the standard error stream a string describing the last BFD error that occurred, or the last system error if the last BFD error was a system call failure. If

message is non-NULL and non-empty, the error string printed is preceded by *message*, a colon, and a space. It is followed by a newline.

2.2.1.6 bfd_asprintf

`char *bfd_asprintf (const char *fmt, ...);` [Function]

Primarily for error reporting, this function is like libiberty's xasprintf except that it can return NULL on no memory and the returned string should not be freed. Uses a thread-local malloc'd buffer managed by libbfd, _bfd_error_buf. Be aware that a call to this function frees the result of any previous call. bfd_errmsg (bfd_error_on_input) also calls this function.

2.2.2 BFD error handler

Some BFD functions want to print messages describing the problem. They call a BFD error handler function. This function may be overridden by the program.

The BFD error handler acts like vprintf.

```
typedef void (*bfd_error_handler_type) (const char *, va_list);


typedef int (*bfd_print_callback) (void *, const char *, ...);
```

2.2.2.1 bfd_print_error

`void bfd_print_error (bfd_print_callback print_func, void *stream, const char *fmt, va_list ap);` [Function]

This formats FMT and AP according to BFD "printf" rules, sending the output to STREAM by repeated calls to PRINT_FUNC. PRINT_FUNC is a printf-like function; it does not need to implement the BFD printf format extensions. This can be used in a callback that is set via bfd_set_error_handler to turn the error into ordinary output.

2.2.2.2 _bfd_error_handler

`void _bfd_error_handler (const char *fmt, ...) ATTRIBUTE_PRINTF_1;` [Function]

This is the default routine to handle BFD error messages. Like fprintf (stderr, ...), but also handles some extra format specifiers.

%pA section name from section. For group components, prints group name too. %pB file name from bfd. For archive components, prints archive too.

Beware: Only supports a maximum of 9 format arguments.

2.2.2.3 bfd_set_error_handler

`bfd_error_handler_type bfd_set_error_handler (bfd_error_handler_type);` [Function]

Set the BFD error handler function. Returns the previous function.

2.2.2.4 _bfd_set_error_handler_caching

struct per_xvec_messages *_bfd_set_error_handler_caching (struct per_xvec_messages *); [Function]

Set the BFD error handler function to one that stores messages to the per_xvec_messages object. Returns the previous object to which messages are stored. Note that two sequential calls to this with a non-NULL argument will cause output to be dropped, rather than gathered.

2.2.2.5 _bfd_restore_error_handler_caching

void _bfd_restore_error_handler_caching (struct per_xvec_messages *); [Function]

Reset the BFD error handler object to an earlier value.

2.2.2.6 bfd_set_error_program_name

void bfd_set_error_program_name (const char *); [Function]

Set the program name to use when printing a BFD error. This is printed before the error message followed by a colon and space. The string must not be changed after it is passed to this function.

2.2.2.7 _bfd_get_error_program_name

const char *_bfd_get_error_program_name (void); [Function]

Get the program name used when printing a BFD error.

2.2.3 BFD assert handler

If BFD finds an internal inconsistency, the bfd assert handler is called with information on the BFD version, BFD source file and line. If this happens, most programs linked against BFD are expected to want to exit with an error, or mark the current BFD operation as failed, so it is recommended to override the default handler, which just calls _bfd_error_handler and continues.

```
typedef void (*bfd_assert_handler_type) (const char *bfd_formatmsg,
                                         const char *bfd_version,
                                         const char *bfd_file,
                                         int bfd_line);
```

2.2.3.1 bfd_set_assert_handler

bfd_assert_handler_type bfd_set_assert_handler (bfd_assert_handler_type); [Function]

Set the BFD assert handler function. Returns the previous function.

2.2.3.2 bfd_init

`unsigned int bfd_init (void);` [Function]

This routine must be called before any other BFD function to initialize magical internal data structures. Returns a magic number, which may be used to check that the bfd library is configured as expected by users.

```
/* Value returned by bfd_init.  */
#define BFD_INIT_MAGIC (sizeof (struct bfd_section))
```

2.3 Threading

BFD has limited support for thread-safety. Most BFD globals are protected by locks, while the error-related globals are thread-local. A given BFD cannot safely be used from two threads at the same time; it is up to the application to do any needed locking. However, it is ok for different threads to work on different BFD objects at the same time.

2.3.1 Thread functions.

```
typedef bool (*bfd_lock_unlock_fn_type) (void *);
```

2.3.1.1 _bfd_threading_enabled

`bool _bfd_threading_enabled (void);` [Function]

Return true if threading is enabled, false if not.

2.3.1.2 bfd_thread_init

`bool bfd_thread_init (bfd_lock_unlock_fn_type lock, bfd_lock_unlock_fn_type unlock, void *data);` [Function]

Initialize BFD threading. The functions passed in will be used to lock and unlock global data structures. This may only be called a single time in a given process. Returns true on success and false on error. On error, the caller should assume that BFD cannot be used by multiple threads. DATA is passed verbatim to the lock and unlock functions. The lock and unlock functions should return true on success, or set the BFD error and return false on failure. Note also that the lock must be a recursive lock: BFD may attempt to acquire the lock when it is already held by the current thread.

2.3.1.3 bfd_thread_cleanup

`void bfd_thread_cleanup (void);` [Function]

Clean up any thread-local state. This should be called by a thread that uses any BFD functions, before the thread exits. It is fine to call this multiple times, or to call it and then later call BFD functions on the same thread again.

2.3.1.4 bfd_lock

`bool bfd_lock (void);` [Function]

Acquire the global BFD lock, if needed. Returns true on success, false on error.

2.3.1.5 bfd_unlock

`bool bfd_unlock (void);` [Function]
Release the global BFD lock, if needed. Returns true on success, false on error.

2.4 Miscellaneous

2.4.1 Miscellaneous functions

2.4.1.1 bfd_get_reloc_upper_bound

`long bfd_get_reloc_upper_bound (bfd *abfd, asection *sect);` [Function]
Return the number of bytes required to store the relocation information associated with section *sect* attached to bfd *abfd*. If an error occurs, return -1.

2.4.1.2 bfd_canonicalize_reloc

`long bfd_canonicalize_reloc (bfd *abfd, asection *sec, arelent **loc, asymbol **syms);` [Function]
Call the back end associated with the open BFD *abfd* and translate the external form of the relocation information attached to *sec* into the internal canonical form. Place the table into memory at *loc*, which has been preallocated, usually by a call to `bfd_get_reloc_upper_bound`. Returns the number of relocs, or -1 on error.

The *syms* table is also needed for horrible internal magic reasons.

2.4.1.3 bfd_set_reloc

`void bfd_set_reloc (bfd *abfd, asection *sec, arelent **rel, unsigned int count);` [Function]
Set the relocation pointer and count within section *sec* to the values *rel* and *count*. The argument *abfd* is ignored.

```
#define bfd_set_reloc(abfd, asect, location, count) \
       BFD_SEND (abfd, _bfd_set_reloc, (abfd, asect, location, count))
```

2.4.1.4 bfd_set_file_flags

`bool bfd_set_file_flags (bfd *abfd, flagword flags);` [Function]
Set the flag word in the BFD *abfd* to the value *flags*.

Possible errors are:

- `bfd_error_wrong_format` - The target bfd was not of object format.
- `bfd_error_invalid_operation` - The target bfd was open for reading.
- `bfd_error_invalid_operation` - The flag word contained a bit which was not applicable to the type of file. E.g., an attempt was made to set the `D_PAGED` bit on a BFD format which does not support demand paging.

2.4.1.5 bfd_get_arch_size

`int bfd_get_arch_size (bfd *abfd);` [Function]

Returns the normalized architecture address size, in bits, as determined by the object file's format. By normalized, we mean either 32 or 64. For ELF, this information is included in the header. Use bfd_arch_bits_per_address for number of bits in the architecture address.

Returns the arch size in bits if known, `-1` otherwise.

2.4.1.6 bfd_get_sign_extend_vma

`int bfd_get_sign_extend_vma (bfd *abfd);` [Function]

Indicates if the target architecture "naturally" sign extends an address. Some architectures implicitly sign extend address values when they are converted to types larger than the size of an address. For instance, bfd_get_start_address() will return an address sign extended to fill a bfd_vma when this is the case.

Returns `1` if the target architecture is known to sign extend addresses, `0` if the target architecture is known to not sign extend addresses, and `-1` otherwise.

2.4.1.7 bfd_set_start_address

`bool bfd_set_start_address (bfd *abfd, bfd_vma vma);` [Function]

Make *vma* the entry point of output BFD *abfd*.

Returns `TRUE` on success, `FALSE` otherwise.

2.4.1.8 bfd_get_gp_size

`unsigned int bfd_get_gp_size (bfd *abfd);` [Function]

Return the maximum size of objects to be optimized using the GP register under MIPS ECOFF. This is typically set by the `-G` argument to the compiler, assembler or linker.

2.4.1.9 bfd_set_gp_size

`void bfd_set_gp_size (bfd *abfd, unsigned int i);` [Function]

Set the maximum size of objects to be optimized using the GP register under ECOFF or MIPS ELF. This is typically set by the `-G` argument to the compiler, assembler or linker.

2.4.1.10 bfd_set_gp_value

`void bfd_set_gp_value (bfd *abfd, bfd_vma v);` [Function]

Allow external access to the fucntion to set the GP value. This is specifically added for gdb-compile support.

2.4.1.11 bfd_scan_vma

`bfd_vma bfd_scan_vma (const char *string, const char **end, int base);` [Function]

Convert, like `strtoul` or `stdtoull`depending on the size of a `bfd_vma`, a numerical expression *string* into a `bfd_vma` integer, and return that integer.

2.4.1.12 bfd_copy_private_header_data

`bool bfd_copy_private_header_data (bfd *ibfd, bfd *obfd);` [Function]
Copy private BFD header information from the BFD *ibfd* to the the BFD *obfd*. This copies information that may require sections to exist, but does not require symbol tables. Return `true` on success, `false` on error. Possible error returns are:

- `bfd_error_no_memory` - Not enough memory exists to create private data for *obfd*.

```
#define bfd_copy_private_header_data(ibfd, obfd) \
       BFD_SEND (obfd, _bfd_copy_private_header_data, \
                 (ibfd, obfd))
```

2.4.1.13 bfd_copy_private_bfd_data

`bool bfd_copy_private_bfd_data (bfd *ibfd, bfd *obfd);` [Function]
Copy private BFD information from the BFD *ibfd* to the the BFD *obfd*. Return `TRUE` on success, `FALSE` on error. Possible error returns are:

- `bfd_error_no_memory` - Not enough memory exists to create private data for *obfd*.

```
#define bfd_copy_private_bfd_data(ibfd, obfd) \
       BFD_SEND (obfd, _bfd_copy_private_bfd_data, \
                 (ibfd, obfd))
```

2.4.1.14 bfd_set_private_flags

`bool bfd_set_private_flags (bfd *abfd, flagword flags);` [Function]
Set private BFD flag information in the BFD *abfd*. Return `TRUE` on success, `FALSE` on error. Possible error returns are:

- `bfd_error_no_memory` - Not enough memory exists to create private data for *obfd*.

```
#define bfd_set_private_flags(abfd, flags) \
       BFD_SEND (abfd, _bfd_set_private_flags, (abfd, flags))
```

2.4.1.15 Other functions

The following functions exist but have not yet been documented.

```
#define bfd_sizeof_headers(abfd, info) \
       BFD_SEND (abfd, _bfd_sizeof_headers, (abfd, info))

#define bfd_find_nearest_line(abfd, sec, syms, off, file, func, line) \
       BFD_SEND (abfd, _bfd_find_nearest_line, \
                 (abfd, syms, sec, off, file, func, line, NULL))

#define bfd_find_nearest_line_with_alt(abfd, alt_filename, sec, syms, off, \
                                       file, func, line, disc) \
       BFD_SEND (abfd, _bfd_find_nearest_line_with_alt, \
                 (abfd, alt_filename, syms, sec, off, file, func, line, disc))
```

```
#define bfd_find_nearest_line_discriminator(abfd, sec, syms, off, file, func, \
                                            line, disc) \
       BFD_SEND (abfd, _bfd_find_nearest_line, \
                 (abfd, syms, sec, off, file, func, line, disc))

#define bfd_find_line(abfd, syms, sym, file, line) \
       BFD_SEND (abfd, _bfd_find_line, \
                 (abfd, syms, sym, file, line))

#define bfd_find_inliner_info(abfd, file, func, line) \
       BFD_SEND (abfd, _bfd_find_inliner_info, \
                 (abfd, file, func, line))

#define bfd_debug_info_start(abfd) \
       BFD_SEND (abfd, _bfd_debug_info_start, (abfd))

#define bfd_debug_info_end(abfd) \
       BFD_SEND (abfd, _bfd_debug_info_end, (abfd))

#define bfd_debug_info_accumulate(abfd, section) \
       BFD_SEND (abfd, _bfd_debug_info_accumulate, (abfd, section))

#define bfd_stat_arch_elt(abfd, stat) \
       BFD_SEND (abfd->my_archive ? abfd->my_archive : abfd, \
                 _bfd_stat_arch_elt, (abfd, stat))

#define bfd_update_armap_timestamp(abfd) \
       BFD_SEND (abfd, _bfd_update_armap_timestamp, (abfd))

#define bfd_set_arch_mach(abfd, arch, mach)\
       BFD_SEND ( abfd, _bfd_set_arch_mach, (abfd, arch, mach))

#define bfd_relax_section(abfd, section, link_info, again) \
       BFD_SEND (abfd, _bfd_relax_section, (abfd, section, link_info, again))

#define bfd_gc_sections(abfd, link_info) \
       BFD_SEND (abfd, _bfd_gc_sections, (abfd, link_info))

#define bfd_lookup_section_flags(link_info, flag_info, section) \
       BFD_SEND (abfd, _bfd_lookup_section_flags, (link_info, flag_info, section))

#define bfd_merge_sections(abfd, link_info) \
       BFD_SEND (abfd, _bfd_merge_sections, (abfd, link_info))

#define bfd_is_group_section(abfd, sec) \
       BFD_SEND (abfd, _bfd_is_group_section, (abfd, sec))
```

```
#define bfd_group_name(abfd, sec) \
       BFD_SEND (abfd, _bfd_group_name, (abfd, sec))

#define bfd_discard_group(abfd, sec) \
       BFD_SEND (abfd, _bfd_discard_group, (abfd, sec))

#define bfd_link_hash_table_create(abfd) \
       BFD_SEND (abfd, _bfd_link_hash_table_create, (abfd))

#define bfd_link_add_symbols(abfd, info) \
       BFD_SEND (abfd, _bfd_link_add_symbols, (abfd, info))

#define bfd_link_just_syms(abfd, sec, info) \
       BFD_SEND (abfd, _bfd_link_just_syms, (sec, info))

#define bfd_final_link(abfd, info) \
       BFD_SEND (abfd, _bfd_final_link, (abfd, info))

#define bfd_free_cached_info(abfd) \
       BFD_SEND (abfd, _bfd_free_cached_info, (abfd))

#define bfd_get_dynamic_symtab_upper_bound(abfd) \
       BFD_SEND (abfd, _bfd_get_dynamic_symtab_upper_bound, (abfd))

#define bfd_print_private_bfd_data(abfd, file)\
       BFD_SEND (abfd, _bfd_print_private_bfd_data, (abfd, file))

#define bfd_canonicalize_dynamic_symtab(abfd, asymbols) \
       BFD_SEND (abfd, _bfd_canonicalize_dynamic_symtab, (abfd, asymbols))

#define bfd_get_synthetic_symtab(abfd, count, syms, dyncount, dynsyms, ret) \
       BFD_SEND (abfd, _bfd_get_synthetic_symtab, (abfd, count, syms, \
                                                   dyncount, dynsyms, ret))

#define bfd_get_dynamic_reloc_upper_bound(abfd) \
       BFD_SEND (abfd, _bfd_get_dynamic_reloc_upper_bound, (abfd))

#define bfd_canonicalize_dynamic_reloc(abfd, arels, asyms) \
       BFD_SEND (abfd, _bfd_canonicalize_dynamic_reloc, (abfd, arels, asyms))
```

2.4.1.16 bfd_get_relocated_section_contents

`bfd_byte *bfd_get_relocated_section_contents (bfd *, struct bfd_link_info *, struct bfd_link_order *, bfd_byte *, bool, asymbol **);` [Function]

Read and relocate the indirect link_order section, into DATA (if non-NULL) or to a malloc'd buffer. Return the buffer, or NULL on errors.

2.4.1.17 bfd_record_phdr

`bool bfd_record_phdr (bfd *, unsigned long, bool, flagword, bool, bfd_vma, bool, bool, unsigned int, struct bfd_section **);` [Function]

Record information about an ELF program header.

2.4.1.18 bfd_sprintf_vma

`void bfd_sprintf_vma (bfd *, char *, bfd_vma); void bfd_fprintf_vma (bfd *, void *, bfd_vma);` [Function]

bfd_sprintf_vma and bfd_fprintf_vma display an address in the target's address size.

2.4.1.19 bfd_alt_mach_code

`bool bfd_alt_mach_code (bfd *abfd, int alternative);` [Function]

When more than one machine code number is available for the same machine type, this function can be used to switch between the preferred one (alternative == 0) and any others. Currently, only ELF supports this feature, with up to two alternate machine codes.

2.4.1.20 bfd_emul_get_maxpagesize

`bfd_vma bfd_emul_get_maxpagesize (const char *);` [Function]

Returns the maximum page size, in bytes, as determined by emulation.

2.4.1.21 bfd_emul_get_commonpagesize

`bfd_vma bfd_emul_get_commonpagesize (const char *);` [Function]

Returns the common page size, in bytes, as determined by emulation.

2.4.1.22 bfd_demangle

`char *bfd_demangle (bfd *, const char *, int);` [Function]

Wrapper around cplus_demangle. Strips leading underscores and other such chars that would otherwise confuse the demangler. If passed a g++ v3 ABI mangled name, returns a buffer allocated with malloc holding the demangled name. Returns NULL otherwise and on memory alloc failure.

2.4.1.23 bfd_group_signature

`asymbol *bfd_group_signature (asection *group, asymbol **isympp);` [Function]

Return a pointer to the symbol used as a signature for GROUP.

2.4.1.24 struct bfd_iovec

The struct bfd_iovec contains the internal file I/O class. Each BFD has an instance of this class and all file I/O is routed through it (it is assumed that the instance implements all methods listed below).

```
struct bfd_iovec
{
  /* To avoid problems with macros, a "b" rather than "f"
     prefix is prepended to each method name.  */
  /* Attempt to read/write NBYTES on ABFD's IOSTREAM storing/fetching
     bytes starting at PTR.  Return the number of bytes actually
     transfered (a read past end-of-file returns less than NBYTES),
     or -1 (setting bfd_error) if an error occurs.  */
  file_ptr (*bread) (struct bfd *abfd, void *ptr, file_ptr nbytes);
  file_ptr (*bwrite) (struct bfd *abfd, const void *ptr,
                      file_ptr nbytes);
  /* Return the current IOSTREAM file offset, or -1 (setting bfd_error
     if an error occurs.  */
  file_ptr (*btell) (struct bfd *abfd);
  /* For the following, on successful completion a value of 0 is returned.
     Otherwise, a value of -1 is returned (and bfd_error is set).  */
  int (*bseek) (struct bfd *abfd, file_ptr offset, int whence);
  int (*bclose) (struct bfd *abfd);
  int (*bflush) (struct bfd *abfd);
  int (*bstat) (struct bfd *abfd, struct stat *sb);
  /* Mmap a part of the files. ADDR, LEN, PROT, FLAGS and OFFSET are the usual
     mmap parameter, except that LEN and OFFSET do not need to be page
     aligned.  Returns (void *)-1 on failure, mmapped address on success.
     Also write in MAP_ADDR the address of the page aligned buffer and in
     MAP_LEN the size mapped (a page multiple).  Use unmap with MAP_ADDR and
     MAP_LEN to unmap.  */
  void *(*bmmap) (struct bfd *abfd, void *addr, size_t len,
                  int prot, int flags, file_ptr offset,
                  void **map_addr, size_t *map_len);
};
extern const struct bfd_iovec _bfd_memory_iovec;
```

2.4.1.25 bfd_read

bfd_size_type bfd_read (void *, bfd_size_type, bfd *) [Function]
ATTRIBUTE_WARN_UNUSED_RESULT;

Attempt to read SIZE bytes from ABFD's iostream to PTR. Return the amount read.

2.4.1.26 bfd_write

`bfd_size_type bfd_write (const void *, bfd_size_type, bfd *) ATTRIBUTE_WARN_UNUSED_RESULT;` [Function]

Attempt to write SIZE bytes to ABFD's iostream from PTR. Return the amount written.

2.4.1.27 bfd_tell

`file_ptr bfd_tell (bfd *) ATTRIBUTE_WARN_UNUSED_RESULT;` [Function]

Return ABFD's iostream file position.

2.4.1.28 bfd_flush

`int bfd_flush (bfd *);` [Function]

Flush ABFD's iostream pending IO.

2.4.1.29 bfd_stat

`int bfd_stat (bfd *, struct stat *) ATTRIBUTE_WARN_UNUSED_RESULT;` [Function]

Call fstat on ABFD's iostream. Return 0 on success, and a negative value on failure.

2.4.1.30 bfd_seek

`int bfd_seek (bfd *, file_ptr, int) ATTRIBUTE_WARN_UNUSED_RESULT;` [Function]

Call fseek on ABFD's iostream. Return 0 on success, and a negative value on failure.

2.4.1.31 bfd_get_mtime

`long bfd_get_mtime (bfd *abfd);` [Function]

Return the file modification time (as read from the file system, or from the archive header for archive members).

2.4.1.32 bfd_get_size

`ufile_ptr bfd_get_size (bfd *abfd);` [Function]

Return the file size (as read from file system) for the file associated with BFD *abfd*.

The initial motivation for, and use of, this routine is not so we can get the exact size of the object the BFD applies to, since that might not be generally possible (archive members for example). It would be ideal if someone could eventually modify it so that such results were guaranteed.

Instead, we want to ask questions like "is this NNN byte sized object I'm about to try read from file offset YYY reasonable?" As as example of where we might do this, some object formats use string tables for which the first `sizeof (long)` bytes of the table contain the size of the table itself, including the size bytes. If an application tries to read what it thinks is one of these string tables, without some way to validate the size, and for some reason the size is wrong (byte swapping error, wrong location

for the string table, etc.), the only clue is likely to be a read error when it tries to read the table, or a "virtual memory exhausted" error when it tries to allocate 15 bazillon bytes of space for the 15 bazillon byte table it is about to read. This function at least allows us to answer the question, "is the size reasonable?".

A return value of zero indicates the file size is unknown.

2.4.1.33 bfd_get_file_size

`ufile_ptr bfd_get_file_size (bfd *abfd);` [Function]

Return the file size (as read from file system) for the file associated with BFD *abfd*. It supports both normal files and archive elements.

2.4.1.34 bfd_mmap

```
void *bfd_mmap (bfd *abfd, void *addr, size_t len, int        [Function]
    prot, int flags, file_ptr offset, void **map_addr, size_t
    *map_len) ATTRIBUTE_WARN_UNUSED_RESULT;
```

Return mmap()ed region of the file, if possible and implemented. LEN and OFFSET do not need to be page aligned. The page aligned address and length are written to MAP_ADDR and MAP_LEN.

2.4.1.35 bfd_get_current_time

`time_t bfd_get_current_time (time_t now);` [Function]

Returns the current time.

If the environment variable SOURCE_DATE_EPOCH is defined then this is parsed and its value is returned. Otherwise if the paramter NOW is non-zero, then that is returned. Otherwise the result of the system call "time(NULL)" is returned.

2.5 Memory Usage

BFD keeps all of its internal structures in obstacks. There is one obstack per open BFD file, into which the current state is stored. When a BFD is closed, the obstack is deleted, and so everything which has been allocated by BFD for the closing file is thrown away.

BFD does not free anything created by an application, but pointers into `bfd` structures become invalid on a `bfd_close`; for example, after a `bfd_close` the vector passed to `bfd_canonicalize_symtab` is still around, since it has been allocated by the application, but the data that it pointed to are lost.

The general rule is to not close a BFD until all operations dependent upon data from the BFD have been completed, or all the data from within the file has been copied. To help with the management of memory, there is a function (`bfd_alloc_size`) which returns the number of bytes in obstacks associated with the supplied BFD. This could be used to select the greediest open BFD, close it to reclaim the memory, perform some operation and reopen the BFD again, to get a fresh copy of the data structures.

2.6 Sections

The raw data contained within a BFD is maintained through the section abstraction. A single BFD may have any number of sections. It keeps hold of them by pointing to the first; each one points to the next in the list.

Sections are supported in BFD in `section.c`.

2.6.1 Section input

When a BFD is opened for reading, the section structures are created and attached to the BFD.

Each section has a name which describes the section in the outside world—for example, `a.out` would contain at least three sections, called `.text`, `.data` and `.bss`.

Names need not be unique; for example a COFF file may have several sections named `.data`.

Sometimes a BFD will contain more than the "natural" number of sections. A back end may attach other sections containing constructor data, or an application may add a section (using `bfd_make_section`) to the sections attached to an already open BFD. For example, the linker creates an extra section `COMMON` for each input file's BFD to hold information about common storage.

The raw data is not necessarily read in when the section descriptor is created. Some targets may leave the data in place until a `bfd_get_section_contents` call is made. Other back ends may read in all the data at once. For example, an S-record file has to be read once to determine the size of the data.

2.6.2 Section output

To write a new object style BFD, the various sections to be written have to be created. They are attached to the BFD in the same way as input sections; data is written to the sections using `bfd_set_section_contents`.

Any program that creates or combines sections (e.g., the assembler and linker) must use the `asection` fields `output_section` and `output_offset` to indicate the file sections to which each section must be written. (If the section is being created from scratch, `output_section` should probably point to the section itself and `output_offset` should probably be zero.)

The data to be written comes from input sections attached (via `output_section` pointers) to the output sections. The output section structure can be considered a filter for the input section: the output section determines the vma of the output data and the name, but the input section determines the offset into the output section of the data to be written.

E.g., to create a section "O", starting at 0x100, 0x123 long, containing two subsections, "A" at offset 0x0 (i.e., at vma 0x100) and "B" at offset 0x20 (i.e., at vma 0x120) the `asection` structures would look like:

```
section name          "A"
  output_offset   0x00
  size            0x20
  output_section ----------->  section name    "O"
                          |    vma             0x100
section name          "B" |    size            0x123
  output_offset   0x20    |
```

```
   size            0x103   |
   output_section  --------|
```

2.6.3 Link orders

The data within a section is stored in a *link_order*. These are much like the fixups in `gas`. The link_order abstraction allows a section to grow and shrink within itself.

A link_order knows how big it is, and which is the next link_order and where the raw data for it is; it also points to a list of relocations which apply to it.

The link_order is used by the linker to perform relaxing on final code. The compiler creates code which is as big as necessary to make it work without relaxing, and the user can select whether to relax. Sometimes relaxing takes a lot of time. The linker runs around the relocations to see if any are attached to data which can be shrunk, if so it does it on a link_order by link_order basis.

2.6.4 typedef asection

Here is the section structure:

```
typedef struct bfd_section
{
  /* The name of the section; the name isn't a copy, the pointer is
     the same as that passed to bfd_make_section.  */
  const char *name;

  /* The next section in the list belonging to the BFD, or NULL.  */
  struct bfd_section *next;

  /* The previous section in the list belonging to the BFD, or NULL.  */
  struct bfd_section *prev;

  /* A unique sequence number.  */
  unsigned int id;

  /* A unique section number which can be used by assembler to
     distinguish different sections with the same section name.  */
  unsigned int section_id;

  /* Which section in the bfd; 0..n-1 as sections are created in a bfd.  */
  unsigned int index;

  /* The field flags contains attributes of the section. Some
     flags are read in from the object file, and some are
     synthesized from other information.  */
  flagword flags;

#define SEC_NO_FLAGS                    0x0

  /* Tells the OS to allocate space for this section when loading.
```

```
     This is clear for a section containing debug information only.  */
#define SEC_ALLOC                         0x1

  /* Tells the OS to load the section from the file when loading.
     This is clear for a .bss section.  */
#define SEC_LOAD                          0x2

  /* The section contains data still to be relocated, so there is
     some relocation information too.  */
#define SEC_RELOC                         0x4

  /* A signal to the OS that the section contains read only data.  */
#define SEC_READONLY                      0x8

  /* The section contains code only.  */
#define SEC_CODE                         0x10

  /* The section contains data only.  */
#define SEC_DATA                         0x20

  /* The section will reside in ROM.  */
#define SEC_ROM                          0x40

  /* The section contains constructor information. This section
     type is used by the linker to create lists of constructors and
     destructors used by g++. When a back end sees a symbol
     which should be used in a constructor list, it creates a new
     section for the type of name (e.g., __CTOR_LIST__), attaches
     the symbol to it, and builds a relocation. To build the lists
     of constructors, all the linker has to do is catenate all the
     sections called __CTOR_LIST__ and relocate the data
     contained within - exactly the operations it would peform on
     standard data.  */
#define SEC_CONSTRUCTOR                  0x80

  /* The section has contents - a data section could be
     SEC_ALLOC | SEC_HAS_CONTENTS; a debug section could be
     SEC_HAS_CONTENTS  */
#define SEC_HAS_CONTENTS                0x100

  /* An instruction to the linker to not output the section
     even if it has information which would normally be written.  */
#define SEC_NEVER_LOAD                  0x200

  /* The section contains thread local data.  */
#define SEC_THREAD_LOCAL                0x400
```

```
  /* The section's size is fixed.  Generic linker code will not
     recalculate it and it is up to whoever has set this flag to
     get the size right.  */
#define SEC_FIXED_SIZE                  0x800

  /* The section contains common symbols (symbols may be defined
     multiple times, the value of a symbol is the amount of
     space it requires, and the largest symbol value is the one
     used).  Most targets have exactly one of these (which we
     translate to bfd_com_section_ptr), but ECOFF has two.  */
#define SEC_IS_COMMON                   0x1000

  /* The section contains only debugging information.  For
     example, this is set for ELF .debug and .stab sections.
     strip tests this flag to see if a section can be
     discarded.  */
#define SEC_DEBUGGING                   0x2000

  /* The contents of this section are held in memory pointed to
     by the contents field.  This is checked by bfd_get_section_contents,
     and the data is retrieved from memory if appropriate.  */
#define SEC_IN_MEMORY                   0x4000

  /* The contents of this section are to be excluded by the
     linker for executable and shared objects unless those
     objects are to be further relocated.  */
#define SEC_EXCLUDE                     0x8000

  /* The contents of this section are to be sorted based on the sum of
     the symbol and addend values specified by the associated relocation
     entries.  Entries without associated relocation entries will be
     appended to the end of the section in an unspecified order.  */
#define SEC_SORT_ENTRIES                0x10000

  /* When linking, duplicate sections of the same name should be
     discarded, rather than being combined into a single section as
     is usually done.  This is similar to how common symbols are
     handled.  See SEC_LINK_DUPLICATES below.  */
#define SEC_LINK_ONCE                   0x20000

  /* If SEC_LINK_ONCE is set, this bitfield describes how the linker
     should handle duplicate sections.  */
#define SEC_LINK_DUPLICATES             0xc0000

  /* This value for SEC_LINK_DUPLICATES means that duplicate
     sections with the same name should simply be discarded.  */
#define SEC_LINK_DUPLICATES_DISCARD       0x0
```

```
  /* This value for SEC_LINK_DUPLICATES means that the linker
     should warn if there are any duplicate sections, although
     it should still only link one copy.  */
#define SEC_LINK_DUPLICATES_ONE_ONLY  0x40000

  /* This value for SEC_LINK_DUPLICATES means that the linker
     should warn if any duplicate sections are a different size.  */
#define SEC_LINK_DUPLICATES_SAME_SIZE 0x80000

  /* This value for SEC_LINK_DUPLICATES means that the linker
     should warn if any duplicate sections contain different
     contents.  */
#define SEC_LINK_DUPLICATES_SAME_CONTENTS \
  (SEC_LINK_DUPLICATES_ONE_ONLY | SEC_LINK_DUPLICATES_SAME_SIZE)

  /* This section was created by the linker as part of dynamic
     relocation or other arcane processing.  It is skipped when
     going through the first-pass output, trusting that someone
     else up the line will take care of it later.  */
#define SEC_LINKER_CREATED           0x100000

  /* This section contains a section ID to distinguish different
     sections with the same section name.  */
#define SEC_ASSEMBLER_SECTION_ID     0x100000

  /* This section should not be subject to garbage collection.
     Also set to inform the linker that this section should not be
     listed in the link map as discarded.  */
#define SEC_KEEP                     0x200000

  /* This section contains "short" data, and should be placed
     "near" the GP.  */
#define SEC_SMALL_DATA               0x400000

  /* Attempt to merge identical entities in the section.
     Entity size is given in the entsize field.  */
#define SEC_MERGE                    0x800000

  /* If given with SEC_MERGE, entities to merge are zero terminated
     strings where entsize specifies character size instead of fixed
     size entries.  */
#define SEC_STRINGS                 0x1000000

  /* This section contains data about section groups.  */
#define SEC_GROUP                   0x2000000
```

```
  /* The section is a COFF shared library section.  This flag is
     only for the linker.  If this type of section appears in
     the input file, the linker must copy it to the output file
     without changing the vma or size.  FIXME: Although this
     was originally intended to be general, it really is COFF
     specific (and the flag was renamed to indicate this).  It
     might be cleaner to have some more general mechanism to
     allow the back end to control what the linker does with
     sections.  */
#define SEC_COFF_SHARED_LIBRARY     0x4000000

  /* This input section should be copied to output in reverse order
     as an array of pointers.  This is for ELF linker internal use
     only.  */
#define SEC_ELF_REVERSE_COPY        0x4000000

  /* This section contains data which may be shared with other
     executables or shared objects. This is for COFF only.  */
#define SEC_COFF_SHARED             0x8000000

  /* Indicate that section has the purecode flag set.  */
#define SEC_ELF_PURECODE            0x8000000

  /* When a section with this flag is being linked, then if the size of
     the input section is less than a page, it should not cross a page
     boundary.  If the size of the input section is one page or more,
     it should be aligned on a page boundary.  This is for TI
     TMS320C54X only.  */
#define SEC_TIC54X_BLOCK            0x10000000

  /* This section has the SHF_X86_64_LARGE flag.  This is ELF x86-64 only.  */
#define SEC_ELF_LARGE               0x10000000

  /* Conditionally link this section; do not link if there are no
     references found to any symbol in the section.  This is for TI
     TMS320C54X only.  */
#define SEC_TIC54X_CLINK            0x20000000

  /* This section contains vliw code.  This is for Toshiba MeP only.  */
#define SEC_MEP_VLIW                0x20000000

  /* All symbols, sizes and relocations in this section are octets
     instead of bytes.  Required for DWARF debug sections as DWARF
     information is organized in octets, not bytes.  */
#define SEC_ELF_OCTETS              0x40000000

  /* Indicate that section has the no read flag set. This happens
```

```
     when memory read flag isn't set. */
#define SEC_COFF_NOREAD            0x40000000

  /*  End of section flags.  */

  /* Some internal packed boolean fields.  */

  /* See the vma field.  */
  unsigned int user_set_vma : 1;

  /* A mark flag used by some of the linker backends.  */
  unsigned int linker_mark : 1;

  /* Another mark flag used by some of the linker backends.  Set for
     output sections that have an input section.  */
  unsigned int linker_has_input : 1;

  /* Mark flag used by some linker backends for garbage collection.  */
  unsigned int gc_mark : 1;

  /* Section compression status.  */
  unsigned int compress_status : 2;
#define COMPRESS_SECTION_NONE    0
#define COMPRESS_SECTION_DONE    1
#define DECOMPRESS_SECTION_ZLIB  2
#define DECOMPRESS_SECTION_ZSTD  3

  /* The following flags are used by the ELF linker. */

  /* Mark sections which have been allocated to segments.  */
  unsigned int segment_mark : 1;

  /* Type of sec_info information.  */
  unsigned int sec_info_type:3;
#define SEC_INFO_TYPE_NONE      0
#define SEC_INFO_TYPE_STABS     1
#define SEC_INFO_TYPE_MERGE     2
#define SEC_INFO_TYPE_EH_FRAME  3
#define SEC_INFO_TYPE_JUST_SYMS 4
#define SEC_INFO_TYPE_TARGET    5
#define SEC_INFO_TYPE_EH_FRAME_ENTRY 6
#define SEC_INFO_TYPE_SFRAME  7

  /* Nonzero if this section uses RELA relocations, rather than REL.  */
  unsigned int use_rela_p:1;

  /* Nonzero if section contents are mmapped.  */
```

```
unsigned int mmapped_p:1;

/* Nonzero if section contents should not be freed.  */
unsigned int alloced:1;

/* Bits used by various backends.  The generic code doesn't touch
   these fields.  */

unsigned int sec_flg0:1;
unsigned int sec_flg1:1;
unsigned int sec_flg2:1;
unsigned int sec_flg3:1;
unsigned int sec_flg4:1;
unsigned int sec_flg5:1;

/* End of internal packed boolean fields.  */

/*  The virtual memory address of the section - where it will be
    at run time.  The symbols are relocated against this.  The
    user_set_vma flag is maintained by bfd; if it's not set, the
    backend can assign addresses (for example, in a.out, where
    the default address for .data is dependent on the specific
    target and various flags).  */
bfd_vma vma;

/*  The load address of the section - where it would be in a
    rom image; really only used for writing section header
    information.  */
bfd_vma lma;

/* The size of the section in *octets*, as it will be output.
   Contains a value even if the section has no contents (e.g., the
   size of .bss).  */
bfd_size_type size;

/* For input sections, the original size on disk of the section, in
   octets.  This field should be set for any section whose size is
   changed by linker relaxation.  It is required for sections where
   the linker relaxation scheme doesn't cache altered section and
   reloc contents (stabs, eh_frame, SEC_MERGE, some coff relaxing
   targets), and thus the original size needs to be kept to read the
   section multiple times.  For output sections, rawsize holds the
   section size calculated on a previous linker relaxation pass.  */
bfd_size_type rawsize;

/* The compressed size of the section in octets.  */
bfd_size_type compressed_size;
```

```
/* If this section is going to be output, then this value is the
   offset in *bytes* into the output section of the first byte in the
   input section (byte ==> smallest addressable unit on the
   target).  In most cases, if this was going to start at the
   100th octet (8-bit quantity) in the output section, this value
   would be 100.  However, if the target byte size is 16 bits
   (bfd_octets_per_byte is "2"), this value would be 50.  */
bfd_vma output_offset;

/* The output section through which to map on output.  */
struct bfd_section *output_section;

/* If an input section, a pointer to a vector of relocation
   records for the data in this section.  */
struct reloc_cache_entry *relocation;

/* If an output section, a pointer to a vector of pointers to
   relocation records for the data in this section.  */
struct reloc_cache_entry **orelocation;

/* The number of relocation records in one of the above.  */
unsigned reloc_count;

/* The alignment requirement of the section, as an exponent of 2 -
   e.g., 3 aligns to 2^3 (or 8).  */
unsigned int alignment_power;

/* Information below is back end specific - and not always used
   or updated.  */

/* File position of section data.  */
file_ptr filepos;

/* File position of relocation info.  */
file_ptr rel_filepos;

/* File position of line data.  */
file_ptr line_filepos;

/* Pointer to data for applications.  */
void *userdata;

/* If the SEC_IN_MEMORY flag is set, this points to the actual
   contents.  */
bfd_byte *contents;
```

```
/* Attached line number information.  */
alent *lineno;

/* Number of line number records.  */
unsigned int lineno_count;

/* Entity size for merging purposes.  */
unsigned int entsize;

/* Points to the kept section if this section is a link-once section,
   and is discarded.  */
struct bfd_section *kept_section;

/* When a section is being output, this value changes as more
   linenumbers are written out.  */
file_ptr moving_line_filepos;

/* What the section number is in the target world.  */
int target_index;

void *used_by_bfd;

/* If this is a constructor section then here is a list of the
   relocations created to relocate items within it.  */
struct relent_chain *constructor_chain;

/* The BFD which owns the section.  */
bfd *owner;

/* A symbol which points at this section only.  */
struct bfd_symbol *symbol;

/* Early in the link process, map_head and map_tail are used to build
   a list of input sections attached to an output section.  Later,
   output sections use these fields for a list of bfd_link_order
   structs.  The linked_to_symbol_name field is for ELF assembler
   internal use.  */
union {
  struct bfd_link_order *link_order;
  struct bfd_section *s;
  const char *linked_to_symbol_name;
} map_head, map_tail;

/* Points to the output section this section is already assigned to,
   if any.  This is used when support for non-contiguous memory
   regions is enabled.  */
struct bfd_section *already_assigned;
```

```
  /* Explicitly specified section type, if non-zero.  */
  unsigned int type;

} asection;
```

2.6.5 Section prototypes

These are the functions exported by the section handling part of BFD.

2.6.5.1 bfd_section_list_clear

`void bfd_section_list_clear (bfd *);` [Function]

Clears the section list, and also resets the section count and hash table entries.

2.6.5.2 bfd_get_section_by_name

`asection *bfd_get_section_by_name (bfd *abfd, const char *name);` [Function]

Return the most recently created section attached to *abfd* named *name*. Return NULL if no such section exists.

2.6.5.3 bfd_get_next_section_by_name

`asection *bfd_get_next_section_by_name (bfd *ibfd, asection *sec);` [Function]

Given *sec* is a section returned by `bfd_get_section_by_name`, return the next most recently created section attached to the same BFD with the same name, or if no such section exists in the same BFD and IBFD is non-NULL, the next section with the same name in any input BFD following IBFD. Return NULL on finding no section.

2.6.5.4 bfd_get_linker_section

`asection *bfd_get_linker_section (bfd *abfd, const char *name);` [Function]

Return the linker created section attached to *abfd* named *name*. Return NULL if no such section exists.

2.6.5.5 bfd_get_section_by_name_if

`asection *bfd_get_section_by_name_if (bfd *abfd, const char *name, bool (*func) (bfd *abfd, asection *sect, void *obj), void *obj);` [Function]

Call the provided function *func* for each section attached to the BFD *abfd* whose name matches *name*, passing *obj* as an argument. The function will be called as if by

```
func (abfd, the_section, obj);
```

It returns the first section for which *func* returns true, otherwise `NULL`.

2.6.5.6 bfd_get_unique_section_name

`char *bfd_get_unique_section_name (bfd *abfd, const char *templat, int *count);` [Function]

Invent a section name that is unique in *abfd* by tacking a dot and a digit suffix onto the original *templat*. If *count* is non-NULL, then it specifies the first number tried as a suffix to generate a unique name. The value pointed to by *count* will be incremented in this case.

2.6.5.7 bfd_make_section_old_way

`asection *bfd_make_section_old_way (bfd *abfd, const char *name);` [Function]

Create a new empty section called *name* and attach it to the end of the chain of sections for the BFD *abfd*. An attempt to create a section with a name which is already in use returns its pointer without changing the section chain.

It has the funny name since this is the way it used to be before it was rewritten....

Possible errors are:

- `bfd_error_invalid_operation` - If output has already started for this BFD.
- `bfd_error_no_memory` - If memory allocation fails.

2.6.5.8 bfd_make_section_anyway_with_flags

`asection *bfd_make_section_anyway_with_flags (bfd *abfd, const char *name, flagword flags);` [Function]

Create a new empty section called *name* and attach it to the end of the chain of sections for *abfd*. Create a new section even if there is already a section with that name. Also set the attributes of the new section to the value *flags*.

Return `NULL` and set `bfd_error` on error; possible errors are:

- `bfd_error_invalid_operation` - If output has already started for *abfd*.
- `bfd_error_no_memory` - If memory allocation fails.

2.6.5.9 bfd_make_section_anyway

`asection *bfd_make_section_anyway (bfd *abfd, const char *name);` [Function]

Create a new empty section called *name* and attach it to the end of the chain of sections for *abfd*. Create a new section even if there is already a section with that name.

Return `NULL` and set `bfd_error` on error; possible errors are:

- `bfd_error_invalid_operation` - If output has already started for *abfd*.
- `bfd_error_no_memory` - If memory allocation fails.

2.6.5.10 bfd_make_section_with_flags

`asection *bfd_make_section_with_flags (bfd *, const char *name, flagword flags);` [Function]

Like `bfd_make_section_anyway`, but return `NULL` (without calling bfd_set_error ()) without changing the section chain if there is already a section named *name*. Also set the attributes of the new section to the value *flags*. If there is an error, return `NULL` and set `bfd_error`.

2.6.5.11 bfd_make_section

`asection *bfd_make_section (bfd *, const char *name);` [Function]

Like `bfd_make_section_anyway`, but return `NULL` (without calling bfd_set_error ()) without changing the section chain if there is already a section named *name*. If there is an error, return `NULL` and set `bfd_error`.

2.6.5.12 bfd_set_section_flags

`bool bfd_set_section_flags (asection *sec, flagword flags);` [Function]

Set the attributes of the section *sec* to the value *flags*. Return `TRUE` on success, `FALSE` on error. Possible error returns are:

- `bfd_error_invalid_operation` - The section cannot have one or more of the attributes requested. For example, a .bss section in `a.out` may not have the `SEC_HAS_CONTENTS` field set.

2.6.5.13 bfd_rename_section

`void bfd_rename_section (asection *sec, const char *newname);` [Function]

Rename section *sec* to *newname*.

2.6.5.14 bfd_map_over_sections

`void bfd_map_over_sections (bfd *abfd, void (*func) (bfd *abfd, asection *sect, void *obj), void *obj);` [Function]

Call the provided function *func* for each section attached to the BFD *abfd*, passing *obj* as an argument. The function will be called as if by

```
func (abfd, the_section, obj);
```

This is the preferred method for iterating over sections; an alternative would be to use a loop:

```
asection *p;
for (p = abfd->sections; p != NULL; p = p->next)
   func (abfd, p, ...)
```

2.6.5.15 bfd_sections_find_if

`asection *bfd_sections_find_if (bfd *abfd, bool (*operation) (bfd *abfd, asection *sect, void *obj), void *obj);` [Function]

Call the provided function *operation* for each section attached to the BFD *abfd*, passing *obj* as an argument. The function will be called as if by

```
operation (abfd, the_section, obj);
```

It returns the first section for which *operation* returns true.

2.6.5.16 bfd_set_section_size

`bool bfd_set_section_size (asection *sec, bfd_size_type val);` [Function]

Set *sec* to the size *val*. If the operation is ok, then `TRUE` is returned, else `FALSE`.

Possible error returns:

- `bfd_error_invalid_operation` - Writing has started to the BFD, so setting the size is invalid.

2.6.5.17 bfd_set_section_contents

`bool bfd_set_section_contents (bfd *abfd, asection *section, const void *data, file_ptr offset, bfd_size_type count);` [Function]

Sets the contents of the section *section* in BFD *abfd* to the data starting in memory at *location*. The data is written to the output section starting at offset *offset* for *count* octets.

Normally `TRUE` is returned, but `FALSE` is returned if there was an error. Possible error returns are:

- `bfd_error_no_contents` - The output section does not have the `SEC_HAS_CONTENTS` attribute, so nothing can be written to it.
- `bfd_error_bad_value` - The section is unable to contain all of the data.
- `bfd_error_invalid_operation` - The BFD is not writeable.
- and some more too.

This routine is front end to the back end function `_bfd_set_section_contents`.

2.6.5.18 bfd_get_section_contents

`bool bfd_get_section_contents (bfd *abfd, asection *section, void *location, file_ptr offset, bfd_size_type count);` [Function]

Read data from *section* in BFD *abfd* into memory starting at *location*. The data is read at an offset of *offset* from the start of the input section, and is read for *count* bytes.

If the contents of a constructor with the `SEC_CONSTRUCTOR` flag set are requested or if the section does not have the `SEC_HAS_CONTENTS` flag set, then the *location* is filled with zeroes. If no errors occur, `TRUE` is returned, else `FALSE`.

2.6.5.19 bfd_malloc_and_get_section

`bool bfd_malloc_and_get_section (bfd *abfd, asection *section, bfd_byte **buf);` [Function]

Read all data from *section* in BFD *abfd* into a buffer, **buf*, malloc'd by this function. Return `true` on success, `false` on failure in which case **buf* will be NULL.

2.6.5.20 bfd_copy_private_section_data

`bool bfd_copy_private_section_data (bfd *ibfd, asection *isec, bfd *obfd, asection *osec, struct bfd_link_info *link_info);` [Function]

Copy private section information from *isec* in the BFD *ibfd* to the section *osec* in the BFD *obfd*. Return `TRUE` on success, `FALSE` on error. Possible error returns are:

- `bfd_error_no_memory` - Not enough memory exists to create private data for *osec*.

```
#define bfd_copy_private_section_data(ibfd, isec, obfd, osec, link_info) \
       BFD_SEND (obfd, _bfd_copy_private_section_data, \
                 (ibfd, isec, obfd, osec, link_info))
```

2.6.5.21 bfd_generic_is_group_section

`bool bfd_generic_is_group_section (bfd *, const asection *sec);` [Function]

Returns TRUE if *sec* is a member of a group.

2.6.5.22 bfd_generic_group_name

`const char *bfd_generic_group_name (bfd *, const asection *sec);` [Function]

Returns group name if *sec* is a member of a group.

2.6.5.23 bfd_generic_discard_group

`bool bfd_generic_discard_group (bfd *abfd, asection *group);` [Function]

Remove all members of *group* from the output.

2.6.5.24 bfd_section_size_insane

`bool bfd_section_size_insane (bfd *abfd, asection *sec);` [Function]

Returns true if the given section has a size that indicates it cannot be read from file. Return false if the size is OK or* this function can't say one way or the other.

2.7 Symbols

BFD tries to maintain as much symbol information as it can when it moves information from file to file. BFD passes information to applications though the `asymbol` structure. When the application requests the symbol table, BFD reads the table in the native form and

translates parts of it into the internal format. To maintain more than the information passed to applications, some targets keep some information "behind the scenes" in a structure only the particular back end knows about. For example, the coff back end keeps the original symbol table structure as well as the canonical structure when a BFD is read in. On output, the coff back end can reconstruct the output symbol table so that no information is lost, even information unique to coff which BFD doesn't know or understand. If a coff symbol table were read, but were written through an a.out back end, all the coff specific information would be lost. The symbol table of a BFD is not necessarily read in until a canonicalize request is made. Then the BFD back end fills in a table provided by the application with pointers to the canonical information. To output symbols, the application provides BFD with a table of pointers to pointers to `asymbol`s. This allows applications like the linker to output a symbol as it was read, since the "behind the scenes" information will be still available.

2.7.1 Reading symbols

There are two stages to reading a symbol table from a BFD: allocating storage, and the actual reading process. This is an excerpt from an application which reads the symbol table:

```
long storage_needed;
asymbol **symbol_table;
long number_of_symbols;
long i;

storage_needed = bfd_get_symtab_upper_bound (abfd);

if (storage_needed < 0)
  FAIL

if (storage_needed == 0)
  return;

symbol_table = xmalloc (storage_needed);
  ...
number_of_symbols =
   bfd_canonicalize_symtab (abfd, symbol_table);

if (number_of_symbols < 0)
  FAIL

for (i = 0; i < number_of_symbols; i++)
  process_symbol (symbol_table[i]);
```

All storage for the symbols themselves is in an objalloc connected to the BFD; it is freed when the BFD is closed.

2.7.2 Writing symbols

Writing of a symbol table is automatic when a BFD open for writing is closed. The application attaches a vector of pointers to pointers to symbols to the BFD being written, and

fills in the symbol count. The close and cleanup code reads through the table provided and performs all the necessary operations. The BFD output code must always be provided with an "owned" symbol: one which has come from another BFD, or one which has been created using `bfd_make_empty_symbol`. Here is an example showing the creation of a symbol table with only one element:

```
#include "sysdep.h"
#include "bfd.h"
int main (void)
{
  bfd *abfd;
  asymbol *ptrs[2];
  asymbol *new;

  abfd = bfd_openw ("foo","a.out-sunos-big");
  bfd_set_format (abfd, bfd_object);
  new = bfd_make_empty_symbol (abfd);
  new->name = "dummy_symbol";
  new->section = bfd_make_section_old_way (abfd, ".text");
  new->flags = BSF_GLOBAL;
  new->value = 0x12345;

  ptrs[0] = new;
  ptrs[1] = 0;

  bfd_set_symtab (abfd, ptrs, 1);
  bfd_close (abfd);
  return 0;
}

./makesym
nm foo
00012345 A dummy_symbol
```

Many formats cannot represent arbitrary symbol information; for instance, the `a.out` object format does not allow an arbitrary number of sections. A symbol pointing to a section which is not one of `.text`, `.data` or `.bss` cannot be described.

2.7.3 Mini Symbols

Mini symbols provide read-only access to the symbol table. They use less memory space, but require more time to access. They can be useful for tools like nm or objdump, which may have to handle symbol tables of extremely large executables.

The `bfd_read_minisymbols` function will read the symbols into memory in an internal form. It will return a `void *` pointer to a block of memory, a symbol count, and the size of each symbol. The pointer is allocated using `malloc`, and should be freed by the caller when it is no longer needed.

The function `bfd_minisymbol_to_symbol` will take a pointer to a minisymbol, and a pointer to a structure returned by `bfd_make_empty_symbol`, and return a `asymbol` structure. The

return value may or may not be the same as the value from `bfd_make_empty_symbol` which was passed in.

2.7.4 typedef asymbol

An `asymbol` has the form:

```
typedef struct bfd_symbol
{
  /* A pointer to the BFD which owns the symbol. This information
     is necessary so that a back end can work out what additional
     information (invisible to the application writer) is carried
     with the symbol.

     This field is *almost* redundant, since you can use section->owner
     instead, except that some symbols point to the global sections
     bfd_{abs,com,und}_section.  This could be fixed by making
     these globals be per-bfd (or per-target-flavor).  FIXME.  */
  struct bfd *the_bfd; /* Use bfd_asymbol_bfd(sym) to access this field.  */

  /* The text of the symbol. The name is left alone, and not copied; the
     application may not alter it.  */
  const char *name;

  /* The value of the symbol.  This really should be a union of a
     numeric value with a pointer, since some flags indicate that
     a pointer to another symbol is stored here.  */
  symvalue value;

  /* Attributes of a symbol.  */
#define BSF_NO_FLAGS            0

  /* The symbol has local scope; static in C. The value
     is the offset into the section of the data.  */
#define BSF_LOCAL               (1 << 0)

  /* The symbol has global scope; initialized data in C. The
     value is the offset into the section of the data.  */
#define BSF_GLOBAL              (1 << 1)

  /* The symbol has global scope and is exported. The value is
     the offset into the section of the data.  */
#define BSF_EXPORT              BSF_GLOBAL /* No real difference.  */

  /* A normal C symbol would be one of:
     BSF_LOCAL, BSF_UNDEFINED or BSF_GLOBAL.  */

  /* The symbol is a debugging record. The value has an arbitrary
```

```
     meaning, unless BSF_DEBUGGING_RELOC is also set.  */
#define BSF_DEBUGGING           (1 << 2)

  /* The symbol denotes a function entry point.  Used in ELF,
     perhaps others someday.  */
#define BSF_FUNCTION            (1 << 3)

  /* Used by the linker.  */
#define BSF_KEEP                (1 << 5)

  /* An ELF common symbol.  */
#define BSF_ELF_COMMON          (1 << 6)

  /* A weak global symbol, overridable without warnings by
     a regular global symbol of the same name.  */
#define BSF_WEAK                (1 << 7)

  /* This symbol was created to point to a section, e.g. ELF's
     STT_SECTION symbols.  */
#define BSF_SECTION_SYM         (1 << 8)

  /* The symbol used to be a common symbol, but now it is
     allocated.  */
#define BSF_OLD_COMMON          (1 << 9)

  /* In some files the type of a symbol sometimes alters its
     location in an output file - ie in coff a ISFCN symbol
     which is also C_EXT symbol appears where it was
     declared and not at the end of a section.  This bit is set
     by the target BFD part to convey this information.  */
#define BSF_NOT_AT_END          (1 << 10)

  /* Signal that the symbol is the label of constructor section.  */
#define BSF_CONSTRUCTOR         (1 << 11)

  /* Signal that the symbol is a warning symbol.  The name is a
     warning.  The name of the next symbol is the one to warn about;
     if a reference is made to a symbol with the same name as the next
     symbol, a warning is issued by the linker.  */
#define BSF_WARNING             (1 << 12)

  /* Signal that the symbol is indirect.  This symbol is an indirect
     pointer to the symbol with the same name as the next symbol.  */
#define BSF_INDIRECT            (1 << 13)

  /* BSF_FILE marks symbols that contain a file name.  This is used
     for ELF STT_FILE symbols.  */
```

```
#define BSF_FILE               (1 << 14)

  /* Symbol is from dynamic linking information.  */
#define BSF_DYNAMIC            (1 << 15)

  /* The symbol denotes a data object.  Used in ELF, and perhaps
     others someday.  */
#define BSF_OBJECT             (1 << 16)

  /* This symbol is a debugging symbol.  The value is the offset
     into the section of the data.  BSF_DEBUGGING should be set
     as well.  */
#define BSF_DEBUGGING_RELOC    (1 << 17)

  /* This symbol is thread local.  Used in ELF.  */
#define BSF_THREAD_LOCAL       (1 << 18)

  /* This symbol represents a complex relocation expression,
     with the expression tree serialized in the symbol name.  */
#define BSF_RELC               (1 << 19)

  /* This symbol represents a signed complex relocation expression,
     with the expression tree serialized in the symbol name.  */
#define BSF_SRELC              (1 << 20)

  /* This symbol was created by bfd_get_synthetic_symtab.  */
#define BSF_SYNTHETIC          (1 << 21)

  /* This symbol is an indirect code object.  Unrelated to BSF_INDIRECT.
     The dynamic linker will compute the value of this symbol by
     calling the function that it points to.  BSF_FUNCTION must
     also be also set.  */
#define BSF_GNU_INDIRECT_FUNCTION (1 << 22)
  /* This symbol is a globally unique data object.  The dynamic linker
     will make sure that in the entire process there is just one symbol
     with this name and type in use.  BSF_OBJECT must also be set.  */
#define BSF_GNU_UNIQUE         (1 << 23)

  /* This section symbol should be included in the symbol table.  */
#define BSF_SECTION_SYM_USED   (1 << 24)

  flagword flags;

  /* A pointer to the section to which this symbol is
     relative.  This will always be non NULL, there are special
     sections for undefined and absolute symbols.  */
  struct bfd_section *section;
```

```
  /* Back end special data.  */
  union
    {
      void *p;
      bfd_vma i;
    }
  udata;
}
asymbol;
```

2.7.5 Symbol handling functions

2.7.5.1 bfd_get_symtab_upper_bound

Return the number of bytes required to store a vector of pointers to `asymbols` for all the symbols in the BFD *abfd*, including a terminal NULL pointer. If there are no symbols in the BFD, then return 0. If an error occurs, return -1.

```
#define bfd_get_symtab_upper_bound(abfd) \
       BFD_SEND (abfd, _bfd_get_symtab_upper_bound, (abfd))
```

2.7.5.2 bfd_is_local_label

`bool bfd_is_local_label (bfd *abfd, asymbol *sym);` [Function]

Return TRUE if the given symbol *sym* in the BFD *abfd* is a compiler generated local label, else return FALSE.

2.7.5.3 bfd_is_local_label_name

`bool bfd_is_local_label_name (bfd *abfd, const char *name);` [Function]

Return TRUE if a symbol with the name *name* in the BFD *abfd* is a compiler generated local label, else return FALSE. This just checks whether the name has the form of a local label.

```
#define bfd_is_local_label_name(abfd, name) \
       BFD_SEND (abfd, _bfd_is_local_label_name, (abfd, name))
```

2.7.5.4 bfd_is_target_special_symbol

`bool bfd_is_target_special_symbol (bfd *abfd, asymbol *sym);` [Function]

Return TRUE iff a symbol *sym* in the BFD *abfd* is something special to the particular target represented by the BFD. Such symbols should normally not be mentioned to the user.

```
#define bfd_is_target_special_symbol(abfd, sym) \
       BFD_SEND (abfd, _bfd_is_target_special_symbol, (abfd, sym))
```

2.7.5.5 bfd_canonicalize_symtab

Read the symbols from the BFD *abfd*, and fills in the vector *location* with pointers to the symbols and a trailing NULL. Return the actual number of symbol pointers, not including the NULL.

```
#define bfd_canonicalize_symtab(abfd, location) \
       BFD_SEND (abfd, _bfd_canonicalize_symtab, (abfd, location))
```

2.7.5.6 bfd_set_symtab

`bool bfd_set_symtab (bfd *abfd, asymbol **location, unsigned int count);` [Function]

Arrange that when the output BFD *abfd* is closed, the table *location* of *count* pointers to symbols will be written.

2.7.5.7 bfd_print_symbol_vandf

`void bfd_print_symbol_vandf (bfd *abfd, void *file, asymbol *symbol);` [Function]

Print the value and flags of the *symbol* supplied to the stream *file*.

2.7.5.8 bfd_make_empty_symbol

Create a new `asymbol` structure for the BFD *abfd* and return a pointer to it.

This routine is necessary because each back end has private information surrounding the `asymbol`. Building your own `asymbol` and pointing to it will not create the private information, and will cause problems later on.

```
#define bfd_make_empty_symbol(abfd) \
       BFD_SEND (abfd, _bfd_make_empty_symbol, (abfd))
```

2.7.5.9 _bfd_generic_make_empty_symbol

`asymbol *_bfd_generic_make_empty_symbol (bfd *);` [Function]

Create a new `asymbol` structure for the BFD *abfd* and return a pointer to it. Used by core file routines, binary back-end and anywhere else where no private info is needed.

2.7.5.10 bfd_make_debug_symbol

Create a new `asymbol` structure for the BFD *abfd*, to be used as a debugging symbol.

```
#define bfd_make_debug_symbol(abfd) \
       BFD_SEND (abfd, _bfd_make_debug_symbol, (abfd))
```

2.7.5.11 bfd_decode_symclass

`int bfd_decode_symclass (asymbol *symbol);` [Function]

Return a character corresponding to the symbol class of *symbol*, or '?' for an unknown class.

2.7.5.12 bfd_is_undefined_symclass

`bool bfd_is_undefined_symclass (int symclass);` [Function]

Returns non-zero if the class symbol returned by bfd_decode_symclass represents an undefined symbol. Returns zero otherwise.

2.7.5.13 bfd_symbol_info

`void bfd_symbol_info (asymbol *symbol, symbol_info *ret);` [Function]

Fill in the basic info about symbol that nm needs. Additional info may be added by the back-ends after calling this function.

2.7.5.14 bfd_copy_private_symbol_data

`bool bfd_copy_private_symbol_data (bfd *ibfd, asymbol *isym, bfd *obfd, asymbol *osym);` [Function]

Copy private symbol information from *isym* in the BFD *ibfd* to the symbol *osym* in the BFD *obfd*. Return `TRUE` on success, `FALSE` on error. Possible error returns are:

- `bfd_error_no_memory` - Not enough memory exists to create private data for *osec*.

```
#define bfd_copy_private_symbol_data(ibfd, isymbol, obfd, osymbol) \
       BFD_SEND (obfd, _bfd_copy_private_symbol_data, \
                 (ibfd, isymbol, obfd, osymbol))
```

2.8 Archives

An archive (or library) is just another BFD. It has a symbol table, although there's not much a user program will do with it.

The big difference between an archive BFD and an ordinary BFD is that the archive doesn't have sections. Instead it has a chain of BFDs that are considered its contents. These BFDs can be manipulated like any other. The BFDs contained in an archive opened for reading will all be opened for reading. You may put either input or output BFDs into an archive opened for output; they will be handled correctly when the archive is closed.

Use `bfd_openr_next_archived_file` to step through the contents of an archive opened for input. You don't have to read the entire archive if you don't want to! Read it until you find what you want.

A BFD returned by `bfd_openr_next_archived_file` can be closed manually with `bfd_close`. If you do not close it, then a second iteration through the members of an archive may return the same BFD. If you close the archive BFD, then all the member BFDs will automatically be closed as well.

Archive contents of output BFDs are chained through the `archive_next` pointer in a BFD. The first one is findable through the `archive_head` slot of the archive. Set it with `bfd_set_archive_head` (q.v.). A given BFD may be in only one open output archive at a time.

As expected, the BFD archive code is more general than the archive code of any given environment. BFD archives may contain files of different formats (e.g., a.out and coff) and even different architectures. You may even place archives recursively into archives!

This can cause unexpected confusion, since some archive formats are more expressive than others. For instance, Intel COFF archives can preserve long filenames; SunOS a.out archives cannot. If you move a file from the first to the second format and back again, the filename may be truncated. Likewise, different a.out environments have different conventions as to how they truncate filenames, whether they preserve directory names in filenames, etc. When interoperating with native tools, be sure your files are homogeneous.

Beware: most of these formats do not react well to the presence of spaces in filenames. We do the best we can, but can't always handle this case due to restrictions in the format of archives. Many Unix utilities are braindead in regards to spaces and such in filenames anyway, so this shouldn't be much of a restriction.

Archives are supported in BFD in `archive.c`.

2.8.1 Archive functions

2.8.1.1 `bfd_get_next_mapent`

`symindex bfd_get_next_mapent (bfd *abfd, symindex previous, carsym **sym);` [Function]

Step through archive *abfd*'s symbol table (if it has one). Successively update *sym* with the next symbol's information, returning that symbol's (internal) index into the symbol table.

Supply `BFD_NO_MORE_SYMBOLS` as the *previous* entry to get the first one; returns `BFD_NO_MORE_SYMBOLS` when you've already got the last one.

A `carsym` is a canonical archive symbol. The only user-visible element is its name, a null-terminated string.

2.8.1.2 `bfd_set_archive_head`

`bool bfd_set_archive_head (bfd *output, bfd *new_head);` [Function]

Set the head of the chain of BFDs contained in the archive *output* to *new_head*.

2.8.1.3 `bfd_openr_next_archived_file`

`bfd *bfd_openr_next_archived_file (bfd *archive, bfd *previous);` [Function]

Provided a BFD, *archive*, containing an archive and NULL, open an input BFD on the first contained element and returns that. Subsequent calls should pass the archive and the previous return value to return a created BFD to the next contained element. NULL is returned when there are no more. Note - if you want to process the bfd returned by this call be sure to call bfd_check_format() on it first.

2.9 File formats

A format is a BFD concept of high level file contents type. The formats supported by BFD are:

- `bfd_object`

The BFD may contain data, symbols, relocations and debug info.

- `bfd_archive`

The BFD contains other BFDs and an optional index.

- `bfd_core`

The BFD contains the result of an executable core dump.

2.9.1 File format functions

2.9.1.1 `bfd_check_format_lto`

`bool bfd_check_format_lto (bfd *abfd, bfd_format format, bool lto_sections_removed);` [Function]

Verify if the file attached to the BFD *abfd* is compatible with the format *format* (i.e., one of `bfd_object`, `bfd_archive` or `bfd_core`).

If LTO_SECTION_REMOVED is true, ignore plugin target.

If the BFD has been set to a specific target before the call, only the named target and format combination is checked. If the target has not been set, or has been set to `default`, then all the known target backends is interrogated to determine a match. If the default target matches, it is used. If not, exactly one target must recognize the file, or an error results.

The function returns `TRUE` on success, otherwise `FALSE` with one of the following error codes:

- `bfd_error_invalid_operation` - if `format` is not one of `bfd_object`, `bfd_archive` or `bfd_core`.
- `bfd_error_system_call` - if an error occured during a read - even some file mismatches can cause bfd_error_system_calls.
- `file_not_recognised` - none of the backends recognised the file format.
- `bfd_error_file_ambiguously_recognized` - more than one backend recognised the file format.

When calling bfd_check_format (or bfd_check_format_matches), any underlying file descriptor will be kept open for the duration of the call. This is done to avoid races when another thread calls bfd_cache_close_all. In this scenario, the thread calling bfd_check_format must call bfd_cache_close itself.

2.9.1.2 `bfd_check_format`

`bool bfd_check_format (bfd *abfd, bfd_format format);` [Function]

Similar to bfd_check_format_plugin, except plugin target isn't ignored.

2.9.1.3 `bfd_check_format_matches_lto`

`bool bfd_check_format_matches_lto (bfd *abfd, bfd_format format, char ***matching, bool lto_sections_removed);` [Function]

Like `bfd_check_format`, except when it returns FALSE with `bfd_errno` set to `bfd_error_file_ambiguously_recognized`. In that case, if *matching* is not NULL, it will be filled in with a NULL-terminated list of the names of the formats that matched, allocated with `malloc`. Then the user may choose a format and try again.

When done with the list that *matching* points to, the caller should free it.

If LTO_SECTION_REMOVED is true, ignore plugin target.

2.9.1.4 bfd_check_format_matches

`bool bfd_check_format_matches (bfd *abfd, bfd_format format, char ***matching);` [Function]

Like `bfd_check_format`, except when it returns FALSE with `bfd_errno` set to `bfd_error_file_ambiguously_recognized`. In that case, if *matching* is not NULL, it will be filled in with a NULL-terminated list of the names of the formats that matched, allocated with `malloc`. Then the user may choose a format and try again.

When done with the list that *matching* points to, the caller should free it.

2.9.1.5 bfd_set_format

`bool bfd_set_format (bfd *abfd, bfd_format format);` [Function]

This function sets the file format of the BFD *abfd* to the format *format*. If the target set in the BFD does not support the format requested, the format is invalid, or the BFD is not open for writing, then an error occurs.

2.9.1.6 bfd_format_string

`const char *bfd_format_string (bfd_format format);` [Function]

Return a pointer to a const string `invalid`, `object`, `archive`, `core`, or `unknown`, depending upon the value of *format*.

2.10 Relocations

BFD maintains relocations in much the same way it maintains symbols: they are left alone until required, then read in en-masse and translated into an internal form. A common routine `bfd_perform_relocation` acts upon the canonical form to do the fixup.

Relocations are maintained on a per section basis, while symbols are maintained on a per BFD basis.

All that a back end has to do to fit the BFD interface is to create a `struct reloc_cache_entry` for each relocation in a particular section, and fill in the right bits of the structures.

2.10.1 typedef arelent

This is the structure of a relocation entry:

```
struct reloc_cache_entry
{
  /* A pointer into the canonical table of pointers.  */
  struct bfd_symbol **sym_ptr_ptr;

  /* offset in section.  */
  bfd_size_type address;

  /* addend for relocation value.  */
  bfd_vma addend;

  /* Pointer to how to perform the required relocation.  */
```

```
  reloc_howto_type *howto;

};
```

Here is a description of each of the fields within an `arelent`:

- `sym_ptr_ptr`

The symbol table pointer points to a pointer to the symbol associated with the relocation request. It is the pointer into the table returned by the back end's `canonicalize_symtab` action. See Section 2.7 [Symbols], page 40. The symbol is referenced through a pointer to a pointer so that tools like the linker can fix up all the symbols of the same name by modifying only one pointer. The relocation routine looks in the symbol and uses the base of the section the symbol is attached to and the value of the symbol as the initial relocation offset. If the symbol pointer is zero, then the section provided is looked up.

- `address`

The `address` field gives the offset in bytes from the base of the section data which owns the relocation record to the first byte of relocatable information. The actual data relocated will be relative to this point; for example, a relocation type which modifies the bottom two bytes of a four byte word would not touch the first byte pointed to in a big endian world.

- `addend`

The `addend` is a value provided by the back end to be added (!) to the relocation offset. Its interpretation is dependent upon the howto. For example, on the 68k the code:

```
char foo[];
main()
        {
        return foo[0x12345678];
        }
```

Could be compiled into:

```
linkw fp,#-4
moveb @#12345678,d0
extbl d0
unlk fp
rts
```

This could create a reloc pointing to `foo`, but leave the offset in the data, something like:

```
RELOCATION RECORDS FOR [.text]:
offset   type      value
00000006 32        _foo

00000000 4e56 fffc          ; linkw fp,#-4
00000004 1039 1234 5678     ; moveb @#12345678,d0
0000000a 49c0               ; extbl d0
0000000c 4e5e               ; unlk fp
0000000e 4e75               ; rts
```

Using coff and an 88k, some instructions don't have enough space in them to represent the full address range, and pointers have to be loaded in two parts. So you'd get something like:

```
or.u     r13,r0,hi16(_foo+0x12345678)
ld.b     r2,r13,lo16(_foo+0x12345678)
jmp      r1
```

This should create two relocs, both pointing to `_foo`, and with 0x12340000 in their addend field. The data would consist of:

```
RELOCATION RECORDS FOR [.text]:
offset   type      value
00000002 HVRT16    _foo+0x12340000
00000006 LVRT16    _foo+0x12340000

00000000 5da05678           ; or.u r13,r0,0x5678
00000004 1c4d5678           ; ld.b r2,r13,0x5678
00000008 f400c001           ; jmp r1
```

The relocation routine digs out the value from the data, adds it to the addend to get the original offset, and then adds the value of `_foo`. Note that all 32 bits have to be kept around somewhere, to cope with carry from bit 15 to bit 16.

One further example is the sparc and the a.out format. The sparc has a similar problem to the 88k, in that some instructions don't have room for an entire offset, but on the sparc the parts are created in odd sized lumps. The designers of the a.out format chose to not use the data within the section for storing part of the offset; all the offset is kept within the reloc. Anything in the data should be ignored.

```
save %sp,-112,%sp
sethi %hi(_foo+0x12345678),%g2
ldsb [%g2+%lo(_foo+0x12345678)],%i0
ret
restore
```

Both relocs contain a pointer to `foo`, and the offsets contain junk.

```
RELOCATION RECORDS FOR [.text]:
offset   type      value
00000004 HI22      _foo+0x12345678
00000008 LO10      _foo+0x12345678

00000000 9de3bf90     ; save %sp,-112,%sp
00000004 05000000     ; sethi %hi(_foo+0),%g2
00000008 f048a000     ; ldsb [%g2+%lo(_foo+0)],%i0
0000000c 81c7e008     ; ret
00000010 81e80000     ; restore
```

- `howto`

The `howto` field can be imagined as a relocation instruction. It is a pointer to a structure which contains information on what to do with all of the other information in the reloc record and data section. A back end would normally have a relocation instruction set and

turn relocations into pointers to the correct structure on input - but it would be possible to create each howto field on demand.

2.10.1.1 enum complain_overflow

Indicates what sort of overflow checking should be done when performing a relocation.

```
enum complain_overflow
{
  /* Do not complain on overflow.  */
  complain_overflow_dont,

  /* Complain if the value overflows when considered as a signed
     number one bit larger than the field.  ie. A bitfield of N bits
     is allowed to represent -2**n to 2**n-1.  */
  complain_overflow_bitfield,

  /* Complain if the value overflows when considered as a signed
     number.  */
  complain_overflow_signed,

  /* Complain if the value overflows when considered as an
     unsigned number.  */
  complain_overflow_unsigned
};
```

2.10.1.2 reloc_howto_type

The `reloc_howto_type` is a structure which contains all the information that libbfd needs to know to tie up a back end's data.

```
struct reloc_howto_struct
{
  /* The type field has mainly a documentary use - the back end can
     do what it wants with it, though normally the back end's idea of
     an external reloc number is stored in this field.  */
  unsigned int type;

  /* The size of the item to be relocated in bytes.  */
  unsigned int size:4;

  /* The number of bits in the field to be relocated.  This is used
     when doing overflow checking.  */
  unsigned int bitsize:7;

  /* The value the final relocation is shifted right by.  This drops
     unwanted data from the relocation.  */
  unsigned int rightshift:6;
```

```
/* The bit position of the reloc value in the destination.
   The relocated value is left shifted by this amount.  */
unsigned int bitpos:6;

/* What type of overflow error should be checked for when
   relocating.  */
ENUM_BITFIELD (complain_overflow) complain_on_overflow:2;

/* The relocation value should be negated before applying.  */
unsigned int negate:1;

/* The relocation is relative to the item being relocated.  */
unsigned int pc_relative:1;

/* Some formats record a relocation addend in the section contents
   rather than with the relocation.  For ELF formats this is the
   distinction between USE_REL and USE_RELA (though the code checks
   for USE_REL == 1/0).  The value of this field is TRUE if the
   addend is recorded with the section contents; when performing a
   partial link (ld -r) the section contents (the data) will be
   modified.  The value of this field is FALSE if addends are
   recorded with the relocation (in arelent.addend); when performing
   a partial link the relocation will be modified.
   All relocations for all ELF USE_RELA targets should set this field
   to FALSE (values of TRUE should be looked on with suspicion).
   However, the converse is not true: not all relocations of all ELF
   USE_REL targets set this field to TRUE.  Why this is so is peculiar
   to each particular target.  For relocs that aren't used in partial
   links (e.g. GOT stuff) it doesn't matter what this is set to.  */
unsigned int partial_inplace:1;

/* When some formats create PC relative instructions, they leave
   the value of the pc of the place being relocated in the offset
   slot of the instruction, so that a PC relative relocation can
   be made just by adding in an ordinary offset (e.g., sun3 a.out).
   Some formats leave the displacement part of an instruction
   empty (e.g., ELF); this flag signals the fact.  */
unsigned int pcrel_offset:1;

/* Whether bfd_install_relocation should just install the addend,
   or should follow the practice of some older object formats and
   install a value including the symbol.  */
unsigned int install_addend:1;

/* src_mask selects the part of the instruction (or data) to be used
   in the relocation sum.  If the target relocations don't have an
   addend in the reloc, eg. ELF USE_REL, src_mask will normally equal
```

```
     dst_mask to extract the addend from the section contents.  If
     relocations do have an addend in the reloc, eg. ELF USE_RELA, this
     field should normally be zero.  Non-zero values for ELF USE_RELA
     targets should be viewed with suspicion as normally the value in
     the dst_mask part of the section contents should be ignored.  */
  bfd_vma src_mask;

  /* dst_mask selects which parts of the instruction (or data) are
     replaced with a relocated value.  */
  bfd_vma dst_mask;

  /* If this field is non null, then the supplied function is
     called rather than the normal function.  This allows really
     strange relocation methods to be accommodated.  */
  bfd_reloc_status_type (*special_function)
    (bfd *, arelent *, struct bfd_symbol *, void *, asection *,
     bfd *, char **);

  /* The textual name of the relocation type.  */
  const char *name;
};
```

2.10.1.3 The HOWTO Macro

The HOWTO macro fills in a reloc_howto_type (a typedef for const struct reloc_howto_struct).

```
#define HOWTO_INSTALL_ADDEND 0
#define HOWTO_RSIZE(sz) ((sz) < 0 ? -(sz) : (sz))
#define HOWTO(type, right, size, bits, pcrel, left, ovf, func, name,   \
              inplace, src_mask, dst_mask, pcrel_off)                  \
  { (unsigned) type, HOWTO_RSIZE (size), bits, right, left, ovf,       \
    size < 0, pcrel, inplace, pcrel_off, HOWTO_INSTALL_ADDEND,         \
    src_mask, dst_mask, func, name }
```

This is used to fill in an empty howto entry in an array.

```
#define EMPTY_HOWTO(C) \
  HOWTO ((C), 0, 1, 0, false, 0, complain_overflow_dont, NULL, \
         NULL, false, 0, 0, false)

static inline unsigned int
bfd_get_reloc_size (reloc_howto_type *howto)
{
  return howto->size;
}
```

2.10.1.4 arelent_chain

How relocs are tied together in an `asection`:

```
typedef struct relent_chain
{
  arelent relent;
  struct relent_chain *next;
}
arelent_chain;
```

2.10.1.5 bfd_check_overflow

`bfd_reloc_status_type bfd_check_overflow (enum complain_overflow how, unsigned int bitsize, unsigned int rightshift, unsigned int addrsize, bfd_vma relocation);` [Function]

Perform overflow checking on *relocation* which has *bitsize* significant bits and will be shifted right by *rightshift* bits, on a machine with addresses containing *addrsize* significant bits. The result is either of `bfd_reloc_ok` or `bfd_reloc_overflow`.

2.10.1.6 bfd_reloc_offset_in_range

`bool bfd_reloc_offset_in_range (reloc_howto_type *howto, bfd *abfd, asection *section, bfd_size_type offset);` [Function]

Returns TRUE if the reloc described by *HOWTO* can be applied at *OFFSET* octets in *SECTION*.

2.10.1.7 bfd_perform_relocation

`bfd_reloc_status_type bfd_perform_relocation (bfd *abfd, arelent *reloc_entry, void *data, asection *input_section, bfd *output_bfd, char **error_message);` [Function]

If *output_bfd* is supplied to this function, the generated image will be relocatable; the relocations are copied to the output file after they have been changed to reflect the new state of the world. There are two ways of reflecting the results of partial linkage in an output file: by modifying the output data in place, and by modifying the relocation record. Some native formats (e.g., basic a.out and basic coff) have no way of specifying an addend in the relocation type, so the addend has to go in the output data. This is no big deal since in these formats the output data slot will always be big enough for the addend. Complex reloc types with addends were invented to solve just this problem. The *error_message* argument is set to an error message if this return `bfd_reloc_dangerous`.

2.10.1.8 bfd_install_relocation

`bfd_reloc_status_type bfd_install_relocation (bfd *abfd,` [Function]
`arelent *reloc_entry, void *data, bfd_vma data_start,`
`asection *input_section, char **error_message);`

This looks remarkably like `bfd_perform_relocation`, except it does not expect that the section contents have been filled in. I.e., it's suitable for use when creating, rather than applying a relocation.

For now, this function should be considered reserved for the assembler.

2.10.2 The howto manager

When an application wants to create a relocation, but doesn't know what the target machine might call it, it can find out by using this bit of code.

2.10.2.1 bfd_reloc_code_real_type

The insides of a reloc code. The idea is that, eventually, there will be one enumerator for every type of relocation we ever do. Pass one of these values to `bfd_reloc_type_lookup`, and it'll return a howto pointer.

This does mean that the application must determine the correct enumerator value; you can't get a howto pointer from a random set of attributes.

Here are the possible values for `enum bfd_reloc_code_real`:

`BFD_RELOC_64`
`BFD_RELOC_32`
`BFD_RELOC_26`
`BFD_RELOC_24`
`BFD_RELOC_16`
`BFD_RELOC_14`
`BFD_RELOC_8`

Basic absolute relocations of N bits.

`BFD_RELOC_64_PCREL`
`BFD_RELOC_32_PCREL`
`BFD_RELOC_24_PCREL`
`BFD_RELOC_16_PCREL`
`BFD_RELOC_12_PCREL`
`BFD_RELOC_8_PCREL`

PC-relative relocations. Sometimes these are relative to the address of the relocation itself; sometimes they are relative to the start of the section containing the relocation. It depends on the specific target.

`BFD_RELOC_32_SECREL`
`BFD_RELOC_16_SECIDX`

Section relative relocations. Some targets need this for DWARF2.

`BFD_RELOC_32_GOT_PCREL`
`BFD_RELOC_16_GOT_PCREL`
`BFD_RELOC_8_GOT_PCREL`

BFD_RELOC_32_GOTOFF
BFD_RELOC_16_GOTOFF
BFD_RELOC_LO16_GOTOFF
BFD_RELOC_HI16_GOTOFF
BFD_RELOC_HI16_S_GOTOFF
BFD_RELOC_8_GOTOFF
BFD_RELOC_64_PLT_PCREL
BFD_RELOC_32_PLT_PCREL
BFD_RELOC_24_PLT_PCREL
BFD_RELOC_16_PLT_PCREL
BFD_RELOC_8_PLT_PCREL
BFD_RELOC_64_PLTOFF
BFD_RELOC_32_PLTOFF
BFD_RELOC_16_PLTOFF
BFD_RELOC_LO16_PLTOFF
BFD_RELOC_HI16_PLTOFF
BFD_RELOC_HI16_S_PLTOFF
BFD_RELOC_8_PLTOFF
: For ELF.

BFD_RELOC_SIZE32
BFD_RELOC_SIZE64
: Size relocations.

BFD_RELOC_68K_GLOB_DAT
BFD_RELOC_68K_JMP_SLOT
BFD_RELOC_68K_RELATIVE
BFD_RELOC_68K_TLS_GD32
BFD_RELOC_68K_TLS_GD16
BFD_RELOC_68K_TLS_GD8
BFD_RELOC_68K_TLS_LDM32
BFD_RELOC_68K_TLS_LDM16
BFD_RELOC_68K_TLS_LDM8
BFD_RELOC_68K_TLS_LDO32
BFD_RELOC_68K_TLS_LDO16
BFD_RELOC_68K_TLS_LDO8
BFD_RELOC_68K_TLS_IE32
BFD_RELOC_68K_TLS_IE16
BFD_RELOC_68K_TLS_IE8
BFD_RELOC_68K_TLS_LE32
BFD_RELOC_68K_TLS_LE16
BFD_RELOC_68K_TLS_LE8
: Relocations used by 68K ELF.

BFD_RELOC_32_BASEREL
BFD_RELOC_16_BASEREL
BFD_RELOC_LO16_BASEREL
BFD_RELOC_HI16_BASEREL

`BFD_RELOC_HI16_S_BASEREL`
`BFD_RELOC_8_BASEREL`
`BFD_RELOC_RVA`
: Linkage-table relative.

`BFD_RELOC_8_FFnn`
: Absolute 8-bit relocation, but used to form an address like 0xFFnn.

`BFD_RELOC_32_PCREL_S2`
`BFD_RELOC_16_PCREL_S2`
`BFD_RELOC_23_PCREL_S2`
: These PC-relative relocations are stored as word displacements – i.e., byte displacements shifted right two bits. The 30-bit word displacement (<<32_PCREL_S2>> – 32 bits, shifted 2) is used on the SPARC. (SPARC tools generally refer to this as <<WDISP30>>.) The signed 16-bit displacement is used on the MIPS, and the 23-bit displacement is used on the Alpha.

`BFD_RELOC_HI22`
`BFD_RELOC_LO10`
: High 22 bits and low 10 bits of 32-bit value, placed into lower bits of the target word. These are used on the SPARC.

`BFD_RELOC_GPREL16`
`BFD_RELOC_GPREL32`
: For systems that allocate a Global Pointer register, these are displacements off that register. These relocation types are handled specially, because the value the register will have is decided relatively late.

`BFD_RELOC_NONE`
`BFD_RELOC_SPARC_WDISP22`
`BFD_RELOC_SPARC22`
`BFD_RELOC_SPARC13`
`BFD_RELOC_SPARC_GOT10`
`BFD_RELOC_SPARC_GOT13`
`BFD_RELOC_SPARC_GOT22`
`BFD_RELOC_SPARC_PC10`
`BFD_RELOC_SPARC_PC22`
`BFD_RELOC_SPARC_WPLT30`
`BFD_RELOC_SPARC_COPY`
`BFD_RELOC_SPARC_GLOB_DAT`
`BFD_RELOC_SPARC_JMP_SLOT`
`BFD_RELOC_SPARC_RELATIVE`
`BFD_RELOC_SPARC_UA16`
`BFD_RELOC_SPARC_UA32`
`BFD_RELOC_SPARC_UA64`
`BFD_RELOC_SPARC_GOTDATA_HIX22`
`BFD_RELOC_SPARC_GOTDATA_LOX10`
`BFD_RELOC_SPARC_GOTDATA_OP_HIX22`
`BFD_RELOC_SPARC_GOTDATA_OP_LOX10`

BFD_RELOC_SPARC_GOTDATA_OP
BFD_RELOC_SPARC_JMP_IREL
BFD_RELOC_SPARC_IRELATIVE
: SPARC ELF relocations. There is probably some overlap with other relocation types already defined.

BFD_RELOC_SPARC_BASE13
BFD_RELOC_SPARC_BASE22
: I think these are specific to SPARC a.out (e.g., Sun 4).

BFD_RELOC_SPARC_64
BFD_RELOC_SPARC_10
BFD_RELOC_SPARC_11
BFD_RELOC_SPARC_OLO10
BFD_RELOC_SPARC_HH22
BFD_RELOC_SPARC_HM10
BFD_RELOC_SPARC_LM22
BFD_RELOC_SPARC_PC_HH22
BFD_RELOC_SPARC_PC_HM10
BFD_RELOC_SPARC_PC_LM22
BFD_RELOC_SPARC_WDISP16
BFD_RELOC_SPARC_WDISP19
BFD_RELOC_SPARC_7
BFD_RELOC_SPARC_6
BFD_RELOC_SPARC_5
BFD_RELOC_SPARC_DISP64
BFD_RELOC_SPARC_PLT32
BFD_RELOC_SPARC_PLT64
BFD_RELOC_SPARC_HIX22
BFD_RELOC_SPARC_LOX10
BFD_RELOC_SPARC_H44
BFD_RELOC_SPARC_M44
BFD_RELOC_SPARC_L44
BFD_RELOC_SPARC_REGISTER
BFD_RELOC_SPARC_H34
BFD_RELOC_SPARC_SIZE32
BFD_RELOC_SPARC_SIZE64
BFD_RELOC_SPARC_WDISP10
: SPARC64 relocations.

BFD_RELOC_SPARC_REV32
: SPARC little endian relocation.

BFD_RELOC_SPARC_TLS_GD_HI22
BFD_RELOC_SPARC_TLS_GD_LO10
BFD_RELOC_SPARC_TLS_GD_ADD
BFD_RELOC_SPARC_TLS_GD_CALL
BFD_RELOC_SPARC_TLS_LDM_HI22

BFD_RELOC_SPARC_TLS_LDM_LO10
BFD_RELOC_SPARC_TLS_LDM_ADD
BFD_RELOC_SPARC_TLS_LDM_CALL
BFD_RELOC_SPARC_TLS_LDO_HIX22
BFD_RELOC_SPARC_TLS_LDO_LOX10
BFD_RELOC_SPARC_TLS_LDO_ADD
BFD_RELOC_SPARC_TLS_IE_HI22
BFD_RELOC_SPARC_TLS_IE_LO10
BFD_RELOC_SPARC_TLS_IE_LD
BFD_RELOC_SPARC_TLS_IE_LDX
BFD_RELOC_SPARC_TLS_IE_ADD
BFD_RELOC_SPARC_TLS_LE_HIX22
BFD_RELOC_SPARC_TLS_LE_LOX10
BFD_RELOC_SPARC_TLS_DTPMOD32
BFD_RELOC_SPARC_TLS_DTPMOD64
BFD_RELOC_SPARC_TLS_DTPOFF32
BFD_RELOC_SPARC_TLS_DTPOFF64
BFD_RELOC_SPARC_TLS_TPOFF32
BFD_RELOC_SPARC_TLS_TPOFF64
: SPARC TLS relocations.

BFD_RELOC_SPU_IMM7
BFD_RELOC_SPU_IMM8
BFD_RELOC_SPU_IMM10
BFD_RELOC_SPU_IMM10W
BFD_RELOC_SPU_IMM16
BFD_RELOC_SPU_IMM16W
BFD_RELOC_SPU_IMM18
BFD_RELOC_SPU_PCREL9a
BFD_RELOC_SPU_PCREL9b
BFD_RELOC_SPU_PCREL16
BFD_RELOC_SPU_LO16
BFD_RELOC_SPU_HI16
BFD_RELOC_SPU_PPU32
BFD_RELOC_SPU_PPU64
BFD_RELOC_SPU_ADD_PIC
: SPU Relocations.

BFD_RELOC_ALPHA_GPDISP_HI16
: Alpha ECOFF and ELF relocations. Some of these treat the symbol or "addend" in some special way. For GPDISP_HI16 ("gpdisp") relocations, the symbol is ignored when writing; when reading, it will be the absolute section symbol. The addend is the displacement in bytes of the "lda" instruction from the "ldah" instruction (which is at the address of this reloc).

`BFD_RELOC_ALPHA_GPDISP_LO16`
: For GPDISP_LO16 ("ignore") relocations, the symbol is handled as with GPDISP_HI16 relocs. The addend is ignored when writing the relocations out, and is filled in with the file's GP value on reading, for convenience.

`BFD_RELOC_ALPHA_GPDISP`
: The ELF GPDISP relocation is exactly the same as the GPDISP_HI16 relocation except that there is no accompanying GPDISP_LO16 relocation.

`BFD_RELOC_ALPHA_LITERAL`
`BFD_RELOC_ALPHA_ELF_LITERAL`
`BFD_RELOC_ALPHA_LITUSE`
: The Alpha LITERAL/LITUSE relocs are produced by a symbol reference; the assembler turns it into a LDQ instruction to load the address of the symbol, and then fills in a register in the real instruction.

  The LITERAL reloc, at the LDQ instruction, refers to the .lita section symbol. The addend is ignored when writing, but is filled in with the file's GP value on reading, for convenience, as with the GPDISP_LO16 reloc.

  The ELF_LITERAL reloc is somewhere between 16_GOTOFF and GPDISP_LO16. It should refer to the symbol to be referenced, as with 16_GOTOFF, but it generates output not based on the position within the .got section, but relative to the GP value chosen for the file during the final link stage.

  The LITUSE reloc, on the instruction using the loaded address, gives information to the linker that it might be able to use to optimize away some literal section references. The symbol is ignored (read as the absolute section symbol), and the "addend" indicates the type of instruction using the register: 1 - "memory" fmt insn 2 - byte-manipulation (byte offset reg) 3 - jsr (target of branch)

`BFD_RELOC_ALPHA_HINT`
: The HINT relocation indicates a value that should be filled into the "hint" field of a jmp/jsr/ret instruction, for possible branch- prediction logic which may be provided on some processors.

`BFD_RELOC_ALPHA_LINKAGE`
: The LINKAGE relocation outputs a linkage pair in the object file, which is filled by the linker.

`BFD_RELOC_ALPHA_CODEADDR`
: The CODEADDR relocation outputs a STO_CA in the object file, which is filled by the linker.

`BFD_RELOC_ALPHA_GPREL_HI16`
`BFD_RELOC_ALPHA_GPREL_LO16`
: The GPREL_HI/LO relocations together form a 32-bit offset from the GP register.

`BFD_RELOC_ALPHA_BRSGP`
: Like BFD_RELOC_23_PCREL_S2, except that the source and target must share a common GP, and the target address is adjusted for STO_ALPHA_STD_GPLOAD.

`BFD_RELOC_ALPHA_NOP`
: The NOP relocation outputs a NOP if the longword displacement between two procedure entry points is < 2^21.

`BFD_RELOC_ALPHA_BSR`
: The BSR relocation outputs a BSR if the longword displacement between two procedure entry points is < 2^21.

`BFD_RELOC_ALPHA_LDA`
: The LDA relocation outputs a LDA if the longword displacement between two procedure entry points is < 2^16.

`BFD_RELOC_ALPHA_BOH`
: The BOH relocation outputs a BSR if the longword displacement between two procedure entry points is < 2^21, or else a hint.

`BFD_RELOC_ALPHA_TLSGD`
`BFD_RELOC_ALPHA_TLSLDM`
`BFD_RELOC_ALPHA_DTPMOD64`
`BFD_RELOC_ALPHA_GOTDTPREL16`
`BFD_RELOC_ALPHA_DTPREL64`
`BFD_RELOC_ALPHA_DTPREL_HI16`
`BFD_RELOC_ALPHA_DTPREL_LO16`
`BFD_RELOC_ALPHA_DTPREL16`
`BFD_RELOC_ALPHA_GOTTPREL16`
`BFD_RELOC_ALPHA_TPREL64`
`BFD_RELOC_ALPHA_TPREL_HI16`
`BFD_RELOC_ALPHA_TPREL_LO16`
`BFD_RELOC_ALPHA_TPREL16`
: Alpha thread-local storage relocations.

`BFD_RELOC_MIPS_JMP`
`BFD_RELOC_MICROMIPS_JMP`
: The MIPS jump instruction.

`BFD_RELOC_MIPS16_JMP`
: The MIPS16 jump instruction.

`BFD_RELOC_MIPS16_GPREL`
: MIPS16 GP relative reloc.

`BFD_RELOC_HI16`
: High 16 bits of 32-bit value; simple reloc.

`BFD_RELOC_HI16_S`
: High 16 bits of 32-bit value but the low 16 bits will be sign extended and added to form the final result. If the low 16 bits form a negative number, we need to add one to the high value to compensate for the borrow when the low bits are added.

`BFD_RELOC_LO16`
: Low 16 bits.

`BFD_RELOC_HI16_PCREL`
: High 16 bits of 32-bit pc-relative value.

`BFD_RELOC_HI16_S_PCREL`
: High 16 bits of 32-bit pc-relative value, adjusted.

`BFD_RELOC_LO16_PCREL`
: Low 16 bits of pc-relative value.

`BFD_RELOC_MIPS16_GOT16`
`BFD_RELOC_MIPS16_CALL16`
: Equivalent of BFD_RELOC_MIPS_*, but with the MIPS16 layout of 16-bit immediate fields.

`BFD_RELOC_MIPS16_HI16`
: MIPS16 high 16 bits of 32-bit value.

`BFD_RELOC_MIPS16_HI16_S`
: MIPS16 high 16 bits of 32-bit value but the low 16 bits will be sign extended and added to form the final result. If the low 16 bits form a negative number, we need to add one to the high value to compensate for the borrow when the low bits are added.

`BFD_RELOC_MIPS16_LO16`
: MIPS16 low 16 bits.

`BFD_RELOC_MIPS16_TLS_GD`
`BFD_RELOC_MIPS16_TLS_LDM`
`BFD_RELOC_MIPS16_TLS_DTPREL_HI16`
`BFD_RELOC_MIPS16_TLS_DTPREL_LO16`
`BFD_RELOC_MIPS16_TLS_GOTTPREL`
`BFD_RELOC_MIPS16_TLS_TPREL_HI16`
`BFD_RELOC_MIPS16_TLS_TPREL_LO16`
: MIPS16 TLS relocations.

`BFD_RELOC_MIPS_LITERAL`
`BFD_RELOC_MICROMIPS_LITERAL`
: Relocation against a MIPS literal section.

`BFD_RELOC_MICROMIPS_7_PCREL_S1`
`BFD_RELOC_MICROMIPS_10_PCREL_S1`
`BFD_RELOC_MICROMIPS_16_PCREL_S1`
: microMIPS PC-relative relocations.

`BFD_RELOC_MIPS16_16_PCREL_S1`
: MIPS16 PC-relative relocation.

`BFD_RELOC_MIPS_21_PCREL_S2`
`BFD_RELOC_MIPS_26_PCREL_S2`
`BFD_RELOC_MIPS_18_PCREL_S3`
`BFD_RELOC_MIPS_19_PCREL_S2`
: MIPS PC-relative relocations.

BFD_RELOC_MICROMIPS_GPREL16
BFD_RELOC_MICROMIPS_HI16
BFD_RELOC_MICROMIPS_HI16_S
BFD_RELOC_MICROMIPS_LO16
microMIPS versions of generic BFD relocs.

BFD_RELOC_MIPS_GOT16
BFD_RELOC_MICROMIPS_GOT16
BFD_RELOC_MIPS_CALL16
BFD_RELOC_MICROMIPS_CALL16
BFD_RELOC_MIPS_GOT_HI16
BFD_RELOC_MICROMIPS_GOT_HI16
BFD_RELOC_MIPS_GOT_LO16
BFD_RELOC_MICROMIPS_GOT_LO16
BFD_RELOC_MIPS_CALL_HI16
BFD_RELOC_MICROMIPS_CALL_HI16
BFD_RELOC_MIPS_CALL_LO16
BFD_RELOC_MICROMIPS_CALL_LO16
BFD_RELOC_MIPS_SUB
BFD_RELOC_MICROMIPS_SUB
BFD_RELOC_MIPS_GOT_PAGE
BFD_RELOC_MICROMIPS_GOT_PAGE
BFD_RELOC_MIPS_GOT_OFST
BFD_RELOC_MICROMIPS_GOT_OFST
BFD_RELOC_MIPS_GOT_DISP
BFD_RELOC_MICROMIPS_GOT_DISP
BFD_RELOC_MIPS_SHIFT5
BFD_RELOC_MIPS_SHIFT6
BFD_RELOC_MIPS_INSERT_A
BFD_RELOC_MIPS_INSERT_B
BFD_RELOC_MIPS_DELETE
BFD_RELOC_MIPS_HIGHEST
BFD_RELOC_MICROMIPS_HIGHEST
BFD_RELOC_MIPS_HIGHER
BFD_RELOC_MICROMIPS_HIGHER
BFD_RELOC_MIPS_SCN_DISP
BFD_RELOC_MICROMIPS_SCN_DISP
BFD_RELOC_MIPS_16
BFD_RELOC_MIPS_RELGOT
BFD_RELOC_MIPS_JALR
BFD_RELOC_MICROMIPS_JALR
BFD_RELOC_MIPS_TLS_DTPMOD32
BFD_RELOC_MIPS_TLS_DTPREL32
BFD_RELOC_MIPS_TLS_DTPMOD64
BFD_RELOC_MIPS_TLS_DTPREL64
BFD_RELOC_MIPS_TLS_GD
BFD_RELOC_MICROMIPS_TLS_GD

BFD_RELOC_MIPS_TLS_LDM
BFD_RELOC_MICROMIPS_TLS_LDM
BFD_RELOC_MIPS_TLS_DTPREL_HI16
BFD_RELOC_MICROMIPS_TLS_DTPREL_HI16
BFD_RELOC_MIPS_TLS_DTPREL_LO16
BFD_RELOC_MICROMIPS_TLS_DTPREL_LO16
BFD_RELOC_MIPS_TLS_GOTTPREL
BFD_RELOC_MICROMIPS_TLS_GOTTPREL
BFD_RELOC_MIPS_TLS_TPREL32
BFD_RELOC_MIPS_TLS_TPREL64
BFD_RELOC_MIPS_TLS_TPREL_HI16
BFD_RELOC_MICROMIPS_TLS_TPREL_HI16
BFD_RELOC_MIPS_TLS_TPREL_LO16
BFD_RELOC_MICROMIPS_TLS_TPREL_LO16
BFD_RELOC_MIPS_EH
: MIPS ELF relocations.

BFD_RELOC_MIPS_COPY
BFD_RELOC_MIPS_JUMP_SLOT
: MIPS ELF relocations (VxWorks and PLT extensions).

BFD_RELOC_MOXIE_10_PCREL
: Moxie ELF relocations.

BFD_RELOC_FT32_10
BFD_RELOC_FT32_20
BFD_RELOC_FT32_17
BFD_RELOC_FT32_18
BFD_RELOC_FT32_RELAX
BFD_RELOC_FT32_SC0
BFD_RELOC_FT32_SC1
BFD_RELOC_FT32_15
BFD_RELOC_FT32_DIFF32
: FT32 ELF relocations.

BFD_RELOC_FRV_LABEL16
BFD_RELOC_FRV_LABEL24
BFD_RELOC_FRV_LO16
BFD_RELOC_FRV_HI16
BFD_RELOC_FRV_GPREL12
BFD_RELOC_FRV_GPRELU12
BFD_RELOC_FRV_GPREL32
BFD_RELOC_FRV_GPRELHI
BFD_RELOC_FRV_GPRELLO
BFD_RELOC_FRV_GOT12
BFD_RELOC_FRV_GOTHI
BFD_RELOC_FRV_GOTLO
BFD_RELOC_FRV_FUNCDESC

BFD_RELOC_FRV_FUNCDESC_GOT12
BFD_RELOC_FRV_FUNCDESC_GOTHI
BFD_RELOC_FRV_FUNCDESC_GOTLO
BFD_RELOC_FRV_FUNCDESC_VALUE
BFD_RELOC_FRV_FUNCDESC_GOTOFF12
BFD_RELOC_FRV_FUNCDESC_GOTOFFHI
BFD_RELOC_FRV_FUNCDESC_GOTOFFLO
BFD_RELOC_FRV_GOTOFF12
BFD_RELOC_FRV_GOTOFFHI
BFD_RELOC_FRV_GOTOFFLO
BFD_RELOC_FRV_GETTLSOFF
BFD_RELOC_FRV_TLSDESC_VALUE
BFD_RELOC_FRV_GOTTLSDESC12
BFD_RELOC_FRV_GOTTLSDESCHI
BFD_RELOC_FRV_GOTTLSDESCLO
BFD_RELOC_FRV_TLSMOFF12
BFD_RELOC_FRV_TLSMOFFHI
BFD_RELOC_FRV_TLSMOFFLO
BFD_RELOC_FRV_GOTTLSOFF12
BFD_RELOC_FRV_GOTTLSOFFHI
BFD_RELOC_FRV_GOTTLSOFFLO
BFD_RELOC_FRV_TLSOFF
BFD_RELOC_FRV_TLSDESC_RELAX
BFD_RELOC_FRV_GETTLSOFF_RELAX
BFD_RELOC_FRV_TLSOFF_RELAX
BFD_RELOC_FRV_TLSMOFF
: Fujitsu Frv Relocations.

BFD_RELOC_MN10300_GOTOFF24
: This is a 24bit GOT-relative reloc for the mn10300.

BFD_RELOC_MN10300_GOT32
: This is a 32bit GOT-relative reloc for the mn10300, offset by two bytes in the instruction.

BFD_RELOC_MN10300_GOT24
: This is a 24bit GOT-relative reloc for the mn10300, offset by two bytes in the instruction.

BFD_RELOC_MN10300_GOT16
: This is a 16bit GOT-relative reloc for the mn10300, offset by two bytes in the instruction.

BFD_RELOC_MN10300_COPY
: Copy symbol at runtime.

BFD_RELOC_MN10300_GLOB_DAT
: Create GOT entry.

`BFD_RELOC_MN10300_JMP_SLOT`
: Create PLT entry.

`BFD_RELOC_MN10300_RELATIVE`
: Adjust by program base.

`BFD_RELOC_MN10300_SYM_DIFF`
: Together with another reloc targeted at the same location, allows for a value that is the difference of two symbols in the same section.

`BFD_RELOC_MN10300_ALIGN`
: The addend of this reloc is an alignment power that must be honoured at the offset's location, regardless of linker relaxation.

`BFD_RELOC_MN10300_TLS_GD`
`BFD_RELOC_MN10300_TLS_LD`
`BFD_RELOC_MN10300_TLS_LDO`
`BFD_RELOC_MN10300_TLS_GOTIE`
`BFD_RELOC_MN10300_TLS_IE`
`BFD_RELOC_MN10300_TLS_LE`
`BFD_RELOC_MN10300_TLS_DTPMOD`
`BFD_RELOC_MN10300_TLS_DTPOFF`
`BFD_RELOC_MN10300_TLS_TPOFF`
: Various TLS-related relocations.

`BFD_RELOC_MN10300_32_PCREL`
: This is a 32bit pcrel reloc for the mn10300, offset by two bytes in the instruction.

`BFD_RELOC_MN10300_16_PCREL`
: This is a 16bit pcrel reloc for the mn10300, offset by two bytes in the instruction.

`BFD_RELOC_386_GOT32`
`BFD_RELOC_386_PLT32`
`BFD_RELOC_386_COPY`
`BFD_RELOC_386_GLOB_DAT`
`BFD_RELOC_386_JUMP_SLOT`
`BFD_RELOC_386_RELATIVE`
`BFD_RELOC_386_GOTOFF`
`BFD_RELOC_386_GOTPC`
`BFD_RELOC_386_TLS_TPOFF`
`BFD_RELOC_386_TLS_IE`
`BFD_RELOC_386_TLS_GOTIE`
`BFD_RELOC_386_TLS_LE`
`BFD_RELOC_386_TLS_GD`
`BFD_RELOC_386_TLS_LDM`
`BFD_RELOC_386_TLS_LDO_32`
`BFD_RELOC_386_TLS_IE_32`
`BFD_RELOC_386_TLS_LE_32`
`BFD_RELOC_386_TLS_DTPMOD32`

BFD_RELOC_386_TLS_DTPOFF32
BFD_RELOC_386_TLS_TPOFF32
BFD_RELOC_386_TLS_GOTDESC
BFD_RELOC_386_TLS_DESC_CALL
BFD_RELOC_386_TLS_DESC
BFD_RELOC_386_IRELATIVE
BFD_RELOC_386_GOT32X
i386/elf relocations.

BFD_RELOC_X86_64_GOT32
BFD_RELOC_X86_64_PLT32
BFD_RELOC_X86_64_COPY
BFD_RELOC_X86_64_GLOB_DAT
BFD_RELOC_X86_64_JUMP_SLOT
BFD_RELOC_X86_64_RELATIVE
BFD_RELOC_X86_64_GOTPCREL
BFD_RELOC_X86_64_32S
BFD_RELOC_X86_64_DTPMOD64
BFD_RELOC_X86_64_DTPOFF64
BFD_RELOC_X86_64_TPOFF64
BFD_RELOC_X86_64_TLSGD
BFD_RELOC_X86_64_TLSLD
BFD_RELOC_X86_64_DTPOFF32
BFD_RELOC_X86_64_GOTTPOFF
BFD_RELOC_X86_64_TPOFF32
BFD_RELOC_X86_64_GOTOFF64
BFD_RELOC_X86_64_GOTPC32
BFD_RELOC_X86_64_GOT64
BFD_RELOC_X86_64_GOTPCREL64
BFD_RELOC_X86_64_GOTPC64
BFD_RELOC_X86_64_GOTPLT64
BFD_RELOC_X86_64_PLTOFF64
BFD_RELOC_X86_64_GOTPC32_TLSDESC
BFD_RELOC_X86_64_TLSDESC_CALL
BFD_RELOC_X86_64_TLSDESC
BFD_RELOC_X86_64_IRELATIVE
BFD_RELOC_X86_64_PC32_BND
BFD_RELOC_X86_64_PLT32_BND
BFD_RELOC_X86_64_GOTPCRELX
BFD_RELOC_X86_64_REX_GOTPCRELX
BFD_RELOC_X86_64_CODE_4_GOTPCRELX
BFD_RELOC_X86_64_CODE_4_GOTTPOFF
BFD_RELOC_X86_64_CODE_4_GOTPC32_TLSDESC
BFD_RELOC_X86_64_CODE_5_GOTPCRELX
BFD_RELOC_X86_64_CODE_5_GOTTPOFF
BFD_RELOC_X86_64_CODE_5_GOTPC32_TLSDESC
BFD_RELOC_X86_64_CODE_6_GOTPCRELX

BFD_RELOC_X86_64_CODE_6_GOTTPOFF
BFD_RELOC_X86_64_CODE_6_GOTPC32_TLSDESC
x86-64/elf relocations.

BFD_RELOC_NS32K_IMM_8
BFD_RELOC_NS32K_IMM_16
BFD_RELOC_NS32K_IMM_32
BFD_RELOC_NS32K_IMM_8_PCREL
BFD_RELOC_NS32K_IMM_16_PCREL
BFD_RELOC_NS32K_IMM_32_PCREL
BFD_RELOC_NS32K_DISP_8
BFD_RELOC_NS32K_DISP_16
BFD_RELOC_NS32K_DISP_32
BFD_RELOC_NS32K_DISP_8_PCREL
BFD_RELOC_NS32K_DISP_16_PCREL
BFD_RELOC_NS32K_DISP_32_PCREL
ns32k relocations.

BFD_RELOC_PDP11_DISP_8_PCREL
BFD_RELOC_PDP11_DISP_6_PCREL
PDP11 relocations.

BFD_RELOC_PJ_CODE_HI16
BFD_RELOC_PJ_CODE_LO16
BFD_RELOC_PJ_CODE_DIR16
BFD_RELOC_PJ_CODE_DIR32
BFD_RELOC_PJ_CODE_REL16
BFD_RELOC_PJ_CODE_REL32
Picojava relocs. Not all of these appear in object files.

BFD_RELOC_PPC_B26
BFD_RELOC_PPC_BA26
BFD_RELOC_PPC_TOC16
BFD_RELOC_PPC_TOC16_LO
BFD_RELOC_PPC_TOC16_HI
BFD_RELOC_PPC_B16
BFD_RELOC_PPC_B16_BRTAKEN
BFD_RELOC_PPC_B16_BRNTAKEN
BFD_RELOC_PPC_BA16
BFD_RELOC_PPC_BA16_BRTAKEN
BFD_RELOC_PPC_BA16_BRNTAKEN
BFD_RELOC_PPC_COPY
BFD_RELOC_PPC_GLOB_DAT
BFD_RELOC_PPC_JMP_SLOT
BFD_RELOC_PPC_RELATIVE
BFD_RELOC_PPC_LOCAL24PC
BFD_RELOC_PPC_EMB_NADDR32
BFD_RELOC_PPC_EMB_NADDR16

BFD_RELOC_PPC_EMB_NADDR16_LO
BFD_RELOC_PPC_EMB_NADDR16_HI
BFD_RELOC_PPC_EMB_NADDR16_HA
BFD_RELOC_PPC_EMB_SDAI16
BFD_RELOC_PPC_EMB_SDA2I16
BFD_RELOC_PPC_EMB_SDA2REL
BFD_RELOC_PPC_EMB_SDA21
BFD_RELOC_PPC_EMB_MRKREF
BFD_RELOC_PPC_EMB_RELSEC16
BFD_RELOC_PPC_EMB_RELST_LO
BFD_RELOC_PPC_EMB_RELST_HI
BFD_RELOC_PPC_EMB_RELST_HA
BFD_RELOC_PPC_EMB_BIT_FLD
BFD_RELOC_PPC_EMB_RELSDA
BFD_RELOC_PPC_VLE_REL8
BFD_RELOC_PPC_VLE_REL15
BFD_RELOC_PPC_VLE_REL24
BFD_RELOC_PPC_VLE_LO16A
BFD_RELOC_PPC_VLE_LO16D
BFD_RELOC_PPC_VLE_HI16A
BFD_RELOC_PPC_VLE_HI16D
BFD_RELOC_PPC_VLE_HA16A
BFD_RELOC_PPC_VLE_HA16D
BFD_RELOC_PPC_VLE_SDA21
BFD_RELOC_PPC_VLE_SDA21_LO
BFD_RELOC_PPC_VLE_SDAREL_LO16A
BFD_RELOC_PPC_VLE_SDAREL_LO16D
BFD_RELOC_PPC_VLE_SDAREL_HI16A
BFD_RELOC_PPC_VLE_SDAREL_HI16D
BFD_RELOC_PPC_VLE_SDAREL_HA16A
BFD_RELOC_PPC_VLE_SDAREL_HA16D
BFD_RELOC_PPC_16DX_HA
BFD_RELOC_PPC_REL16DX_HA
BFD_RELOC_PPC_NEG
BFD_RELOC_PPC64_HIGHER
BFD_RELOC_PPC64_HIGHER_S
BFD_RELOC_PPC64_HIGHEST
BFD_RELOC_PPC64_HIGHEST_S
BFD_RELOC_PPC64_TOC16_LO
BFD_RELOC_PPC64_TOC16_HI
BFD_RELOC_PPC64_TOC16_HA
BFD_RELOC_PPC64_TOC
BFD_RELOC_PPC64_PLTGOT16
BFD_RELOC_PPC64_PLTGOT16_LO
BFD_RELOC_PPC64_PLTGOT16_HI
BFD_RELOC_PPC64_PLTGOT16_HA
BFD_RELOC_PPC64_ADDR16_DS

BFD_RELOC_PPC64_ADDR16_LO_DS
BFD_RELOC_PPC64_GOT16_DS
BFD_RELOC_PPC64_GOT16_LO_DS
BFD_RELOC_PPC64_PLT16_LO_DS
BFD_RELOC_PPC64_SECTOFF_DS
BFD_RELOC_PPC64_SECTOFF_LO_DS
BFD_RELOC_PPC64_TOC16_DS
BFD_RELOC_PPC64_TOC16_LO_DS
BFD_RELOC_PPC64_PLTGOT16_DS
BFD_RELOC_PPC64_PLTGOT16_LO_DS
BFD_RELOC_PPC64_ADDR16_HIGH
BFD_RELOC_PPC64_ADDR16_HIGHA
BFD_RELOC_PPC64_REL16_HIGH
BFD_RELOC_PPC64_REL16_HIGHA
BFD_RELOC_PPC64_REL16_HIGHER
BFD_RELOC_PPC64_REL16_HIGHERA
BFD_RELOC_PPC64_REL16_HIGHEST
BFD_RELOC_PPC64_REL16_HIGHESTA
BFD_RELOC_PPC64_ADDR64_LOCAL
BFD_RELOC_PPC64_ENTRY
BFD_RELOC_PPC64_REL24_NOTOC
BFD_RELOC_PPC64_REL24_P9NOTOC
BFD_RELOC_PPC64_D34
BFD_RELOC_PPC64_D34_LO
BFD_RELOC_PPC64_D34_HI30
BFD_RELOC_PPC64_D34_HA30
BFD_RELOC_PPC64_PCREL34
BFD_RELOC_PPC64_GOT_PCREL34
BFD_RELOC_PPC64_PLT_PCREL34
BFD_RELOC_PPC64_ADDR16_HIGHER34
BFD_RELOC_PPC64_ADDR16_HIGHERA34
BFD_RELOC_PPC64_ADDR16_HIGHEST34
BFD_RELOC_PPC64_ADDR16_HIGHESTA34
BFD_RELOC_PPC64_REL16_HIGHER34
BFD_RELOC_PPC64_REL16_HIGHERA34
BFD_RELOC_PPC64_REL16_HIGHEST34
BFD_RELOC_PPC64_REL16_HIGHESTA34
BFD_RELOC_PPC64_D28
BFD_RELOC_PPC64_PCREL28

Power(rs6000) and PowerPC relocations.

BFD_RELOC_PPC_TLS
BFD_RELOC_PPC_TLSGD
BFD_RELOC_PPC_TLSLD
BFD_RELOC_PPC_TLSLE
BFD_RELOC_PPC_TLSIE
BFD_RELOC_PPC_TLSM

BFD_RELOC_PPC_TLSML
BFD_RELOC_PPC_DTPMOD
BFD_RELOC_PPC_TPREL16
BFD_RELOC_PPC_TPREL16_LO
BFD_RELOC_PPC_TPREL16_HI
BFD_RELOC_PPC_TPREL16_HA
BFD_RELOC_PPC_TPREL
BFD_RELOC_PPC_DTPREL16
BFD_RELOC_PPC_DTPREL16_LO
BFD_RELOC_PPC_DTPREL16_HI
BFD_RELOC_PPC_DTPREL16_HA
BFD_RELOC_PPC_DTPREL
BFD_RELOC_PPC_GOT_TLSGD16
BFD_RELOC_PPC_GOT_TLSGD16_LO
BFD_RELOC_PPC_GOT_TLSGD16_HI
BFD_RELOC_PPC_GOT_TLSGD16_HA
BFD_RELOC_PPC_GOT_TLSLD16
BFD_RELOC_PPC_GOT_TLSLD16_LO
BFD_RELOC_PPC_GOT_TLSLD16_HI
BFD_RELOC_PPC_GOT_TLSLD16_HA
BFD_RELOC_PPC_GOT_TPREL16
BFD_RELOC_PPC_GOT_TPREL16_LO
BFD_RELOC_PPC_GOT_TPREL16_HI
BFD_RELOC_PPC_GOT_TPREL16_HA
BFD_RELOC_PPC_GOT_DTPREL16
BFD_RELOC_PPC_GOT_DTPREL16_LO
BFD_RELOC_PPC_GOT_DTPREL16_HI
BFD_RELOC_PPC_GOT_DTPREL16_HA
BFD_RELOC_PPC64_TLSGD
BFD_RELOC_PPC64_TLSLD
BFD_RELOC_PPC64_TLSLE
BFD_RELOC_PPC64_TLSIE
BFD_RELOC_PPC64_TLSM
BFD_RELOC_PPC64_TLSML
BFD_RELOC_PPC64_TPREL16_DS
BFD_RELOC_PPC64_TPREL16_LO_DS
BFD_RELOC_PPC64_TPREL16_HIGH
BFD_RELOC_PPC64_TPREL16_HIGHA
BFD_RELOC_PPC64_TPREL16_HIGHER
BFD_RELOC_PPC64_TPREL16_HIGHERA
BFD_RELOC_PPC64_TPREL16_HIGHEST
BFD_RELOC_PPC64_TPREL16_HIGHESTA
BFD_RELOC_PPC64_DTPREL16_DS
BFD_RELOC_PPC64_DTPREL16_LO_DS
BFD_RELOC_PPC64_DTPREL16_HIGH
BFD_RELOC_PPC64_DTPREL16_HIGHA
BFD_RELOC_PPC64_DTPREL16_HIGHER

BFD_RELOC_PPC64_DTPREL16_HIGHERA
BFD_RELOC_PPC64_DTPREL16_HIGHEST
BFD_RELOC_PPC64_DTPREL16_HIGHESTA
BFD_RELOC_PPC64_TPREL34
BFD_RELOC_PPC64_DTPREL34
BFD_RELOC_PPC64_GOT_TLSGD_PCREL34
BFD_RELOC_PPC64_GOT_TLSLD_PCREL34
BFD_RELOC_PPC64_GOT_TPREL_PCREL34
BFD_RELOC_PPC64_GOT_DTPREL_PCREL34
BFD_RELOC_PPC64_TLS_PCREL
: PowerPC and PowerPC64 thread-local storage relocations.

BFD_RELOC_I370_D12
: IBM 370/390 relocations.

BFD_RELOC_CTOR
: The type of reloc used to build a constructor table - at the moment probably a 32 bit wide absolute relocation, but the target can choose. It generally does map to one of the other relocation types.

BFD_RELOC_ARM_PCREL_BRANCH
: ARM 26 bit pc-relative branch. The lowest two bits must be zero and are not stored in the instruction.

BFD_RELOC_ARM_PCREL_BLX
: ARM 26 bit pc-relative branch. The lowest bit must be zero and is not stored in the instruction. The 2nd lowest bit comes from a 1 bit field in the instruction.

BFD_RELOC_THUMB_PCREL_BLX
: Thumb 22 bit pc-relative branch. The lowest bit must be zero and is not stored in the instruction. The 2nd lowest bit comes from a 1 bit field in the instruction.

BFD_RELOC_ARM_PCREL_CALL
: ARM 26-bit pc-relative branch for an unconditional BL or BLX instruction.

BFD_RELOC_ARM_PCREL_JUMP
: ARM 26-bit pc-relative branch for B or conditional BL instruction.

BFD_RELOC_THUMB_PCREL_BRANCH5
: ARM 5-bit pc-relative branch for Branch Future instructions.

BFD_RELOC_THUMB_PCREL_BFCSEL
: ARM 6-bit pc-relative branch for BFCSEL instruction.

BFD_RELOC_ARM_THUMB_BF17
: ARM 17-bit pc-relative branch for Branch Future instructions.

BFD_RELOC_ARM_THUMB_BF13
: ARM 13-bit pc-relative branch for BFCSEL instruction.

BFD_RELOC_ARM_THUMB_BF19
: ARM 19-bit pc-relative branch for Branch Future Link instruction.

BFD_RELOC_ARM_THUMB_LOOP12
: ARM 12-bit pc-relative branch for Low Overhead Loop instructions.

BFD_RELOC_THUMB_PCREL_BRANCH7
BFD_RELOC_THUMB_PCREL_BRANCH9
BFD_RELOC_THUMB_PCREL_BRANCH12
BFD_RELOC_THUMB_PCREL_BRANCH20
BFD_RELOC_THUMB_PCREL_BRANCH23
BFD_RELOC_THUMB_PCREL_BRANCH25
: Thumb 7-, 9-, 12-, 20-, 23-, and 25-bit pc-relative branches. The lowest bit must be zero and is not stored in the instruction. Note that the corresponding ELF R_ARM_THM_JUMPnn constant has an "nn" one smaller in all cases. Note further that BRANCH23 corresponds to R_ARM_THM_CALL.

BFD_RELOC_ARM_OFFSET_IMM
: 12-bit immediate offset, used in ARM-format ldr and str instructions.

BFD_RELOC_ARM_THUMB_OFFSET
: 5-bit immediate offset, used in Thumb-format ldr and str instructions.

BFD_RELOC_ARM_TARGET1
: Pc-relative or absolute relocation depending on target. Used for entries in .init_array sections.

BFD_RELOC_ARM_ROSEGREL32
: Read-only segment base relative address.

BFD_RELOC_ARM_SBREL32
: Data segment base relative address.

BFD_RELOC_ARM_TARGET2
: This reloc is used for references to RTTI data from exception handling tables. The actual definition depends on the target. It may be a pc-relative or some form of GOT-indirect relocation.

BFD_RELOC_ARM_PREL31
: 31-bit PC relative address.

BFD_RELOC_ARM_MOVW
BFD_RELOC_ARM_MOVT
BFD_RELOC_ARM_MOVW_PCREL
BFD_RELOC_ARM_MOVT_PCREL
BFD_RELOC_ARM_THUMB_MOVW
BFD_RELOC_ARM_THUMB_MOVT
BFD_RELOC_ARM_THUMB_MOVW_PCREL
BFD_RELOC_ARM_THUMB_MOVT_PCREL
: Low and High halfword relocations for MOVW and MOVT instructions.

BFD_RELOC_ARM_GOTFUNCDESC
BFD_RELOC_ARM_GOTOFFFUNCDESC

BFD_RELOC_ARM_FUNCDESC
BFD_RELOC_ARM_FUNCDESC_VALUE
BFD_RELOC_ARM_TLS_GD32_FDPIC
BFD_RELOC_ARM_TLS_LDM32_FDPIC
BFD_RELOC_ARM_TLS_IE32_FDPIC
ARM FDPIC specific relocations.

BFD_RELOC_ARM_JUMP_SLOT
BFD_RELOC_ARM_GLOB_DAT
BFD_RELOC_ARM_GOT32
BFD_RELOC_ARM_PLT32
BFD_RELOC_ARM_RELATIVE
BFD_RELOC_ARM_GOTOFF
BFD_RELOC_ARM_GOTPC
BFD_RELOC_ARM_GOT_PREL
Relocations for setting up GOTs and PLTs for shared libraries.

BFD_RELOC_ARM_TLS_GD32
BFD_RELOC_ARM_TLS_LDO32
BFD_RELOC_ARM_TLS_LDM32
BFD_RELOC_ARM_TLS_DTPOFF32
BFD_RELOC_ARM_TLS_DTPMOD32
BFD_RELOC_ARM_TLS_TPOFF32
BFD_RELOC_ARM_TLS_IE32
BFD_RELOC_ARM_TLS_LE32
BFD_RELOC_ARM_TLS_GOTDESC
BFD_RELOC_ARM_TLS_CALL
BFD_RELOC_ARM_THM_TLS_CALL
BFD_RELOC_ARM_TLS_DESCSEQ
BFD_RELOC_ARM_THM_TLS_DESCSEQ
BFD_RELOC_ARM_TLS_DESC
ARM thread-local storage relocations.

BFD_RELOC_ARM_ALU_PC_G0_NC
BFD_RELOC_ARM_ALU_PC_G0
BFD_RELOC_ARM_ALU_PC_G1_NC
BFD_RELOC_ARM_ALU_PC_G1
BFD_RELOC_ARM_ALU_PC_G2
BFD_RELOC_ARM_LDR_PC_G0
BFD_RELOC_ARM_LDR_PC_G1
BFD_RELOC_ARM_LDR_PC_G2
BFD_RELOC_ARM_LDRS_PC_G0
BFD_RELOC_ARM_LDRS_PC_G1
BFD_RELOC_ARM_LDRS_PC_G2
BFD_RELOC_ARM_LDC_PC_G0
BFD_RELOC_ARM_LDC_PC_G1
BFD_RELOC_ARM_LDC_PC_G2
BFD_RELOC_ARM_ALU_SB_G0_NC

BFD_RELOC_ARM_ALU_SB_G0
BFD_RELOC_ARM_ALU_SB_G1_NC
BFD_RELOC_ARM_ALU_SB_G1
BFD_RELOC_ARM_ALU_SB_G2
BFD_RELOC_ARM_LDR_SB_G0
BFD_RELOC_ARM_LDR_SB_G1
BFD_RELOC_ARM_LDR_SB_G2
BFD_RELOC_ARM_LDRS_SB_G0
BFD_RELOC_ARM_LDRS_SB_G1
BFD_RELOC_ARM_LDRS_SB_G2
BFD_RELOC_ARM_LDC_SB_G0
BFD_RELOC_ARM_LDC_SB_G1
BFD_RELOC_ARM_LDC_SB_G2
: ARM group relocations.

BFD_RELOC_ARM_V4BX
: Annotation of BX instructions.

BFD_RELOC_ARM_IRELATIVE
: ARM support for STT_GNU_IFUNC.

BFD_RELOC_ARM_THUMB_ALU_ABS_G0_NC
BFD_RELOC_ARM_THUMB_ALU_ABS_G1_NC
BFD_RELOC_ARM_THUMB_ALU_ABS_G2_NC
BFD_RELOC_ARM_THUMB_ALU_ABS_G3_NC
: Thumb1 relocations to support execute-only code.

BFD_RELOC_ARM_IMMEDIATE
BFD_RELOC_ARM_ADRL_IMMEDIATE
BFD_RELOC_ARM_T32_IMMEDIATE
BFD_RELOC_ARM_T32_ADD_IMM
BFD_RELOC_ARM_T32_IMM12
BFD_RELOC_ARM_T32_ADD_PC12
BFD_RELOC_ARM_SHIFT_IMM
BFD_RELOC_ARM_SMC
BFD_RELOC_ARM_HVC
BFD_RELOC_ARM_SWI
BFD_RELOC_ARM_MULTI
BFD_RELOC_ARM_CP_OFF_IMM
BFD_RELOC_ARM_CP_OFF_IMM_S2
BFD_RELOC_ARM_T32_CP_OFF_IMM
BFD_RELOC_ARM_T32_CP_OFF_IMM_S2
BFD_RELOC_ARM_T32_VLDR_VSTR_OFF_IMM
BFD_RELOC_ARM_ADR_IMM
BFD_RELOC_ARM_LDR_IMM
BFD_RELOC_ARM_LITERAL
BFD_RELOC_ARM_IN_POOL
BFD_RELOC_ARM_OFFSET_IMM8

BFD_RELOC_ARM_T32_OFFSET_U8
BFD_RELOC_ARM_T32_OFFSET_IMM
BFD_RELOC_ARM_HWLITERAL
BFD_RELOC_ARM_THUMB_ADD
BFD_RELOC_ARM_THUMB_IMM
BFD_RELOC_ARM_THUMB_SHIFT

These relocs are only used within the ARM assembler. They are not (at present) written to any object files.

BFD_RELOC_SH_PCDISP8BY2
BFD_RELOC_SH_PCDISP12BY2
BFD_RELOC_SH_IMM3
BFD_RELOC_SH_IMM3U
BFD_RELOC_SH_DISP12
BFD_RELOC_SH_DISP12BY2
BFD_RELOC_SH_DISP12BY4
BFD_RELOC_SH_DISP12BY8
BFD_RELOC_SH_DISP20
BFD_RELOC_SH_DISP20BY8
BFD_RELOC_SH_IMM4
BFD_RELOC_SH_IMM4BY2
BFD_RELOC_SH_IMM4BY4
BFD_RELOC_SH_IMM8
BFD_RELOC_SH_IMM8BY2
BFD_RELOC_SH_IMM8BY4
BFD_RELOC_SH_PCRELIMM8BY2
BFD_RELOC_SH_PCRELIMM8BY4
BFD_RELOC_SH_SWITCH16
BFD_RELOC_SH_SWITCH32
BFD_RELOC_SH_USES
BFD_RELOC_SH_COUNT
BFD_RELOC_SH_ALIGN
BFD_RELOC_SH_CODE
BFD_RELOC_SH_DATA
BFD_RELOC_SH_LABEL
BFD_RELOC_SH_LOOP_START
BFD_RELOC_SH_LOOP_END
BFD_RELOC_SH_COPY
BFD_RELOC_SH_GLOB_DAT
BFD_RELOC_SH_JMP_SLOT
BFD_RELOC_SH_RELATIVE
BFD_RELOC_SH_GOTPC
BFD_RELOC_SH_GOT_LOW16
BFD_RELOC_SH_GOT_MEDLOW16
BFD_RELOC_SH_GOT_MEDHI16
BFD_RELOC_SH_GOT_HI16
BFD_RELOC_SH_GOTPLT_LOW16

BFD_RELOC_SH_GOTPLT_MEDLOW16
BFD_RELOC_SH_GOTPLT_MEDHI16
BFD_RELOC_SH_GOTPLT_HI16
BFD_RELOC_SH_PLT_LOW16
BFD_RELOC_SH_PLT_MEDLOW16
BFD_RELOC_SH_PLT_MEDHI16
BFD_RELOC_SH_PLT_HI16
BFD_RELOC_SH_GOTOFF_LOW16
BFD_RELOC_SH_GOTOFF_MEDLOW16
BFD_RELOC_SH_GOTOFF_MEDHI16
BFD_RELOC_SH_GOTOFF_HI16
BFD_RELOC_SH_GOTPC_LOW16
BFD_RELOC_SH_GOTPC_MEDLOW16
BFD_RELOC_SH_GOTPC_MEDHI16
BFD_RELOC_SH_GOTPC_HI16
BFD_RELOC_SH_COPY64
BFD_RELOC_SH_GLOB_DAT64
BFD_RELOC_SH_JMP_SLOT64
BFD_RELOC_SH_RELATIVE64
BFD_RELOC_SH_GOT10BY4
BFD_RELOC_SH_GOT10BY8
BFD_RELOC_SH_GOTPLT10BY4
BFD_RELOC_SH_GOTPLT10BY8
BFD_RELOC_SH_GOTPLT32
BFD_RELOC_SH_SHMEDIA_CODE
BFD_RELOC_SH_IMMU5
BFD_RELOC_SH_IMMS6
BFD_RELOC_SH_IMMS6BY32
BFD_RELOC_SH_IMMU6
BFD_RELOC_SH_IMMS10
BFD_RELOC_SH_IMMS10BY2
BFD_RELOC_SH_IMMS10BY4
BFD_RELOC_SH_IMMS10BY8
BFD_RELOC_SH_IMMS16
BFD_RELOC_SH_IMMU16
BFD_RELOC_SH_IMM_LOW16
BFD_RELOC_SH_IMM_LOW16_PCREL
BFD_RELOC_SH_IMM_MEDLOW16
BFD_RELOC_SH_IMM_MEDLOW16_PCREL
BFD_RELOC_SH_IMM_MEDHI16
BFD_RELOC_SH_IMM_MEDHI16_PCREL
BFD_RELOC_SH_IMM_HI16
BFD_RELOC_SH_IMM_HI16_PCREL
BFD_RELOC_SH_PT_16
BFD_RELOC_SH_TLS_GD_32
BFD_RELOC_SH_TLS_LD_32
BFD_RELOC_SH_TLS_LDO_32

BFD_RELOC_SH_TLS_IE_32
BFD_RELOC_SH_TLS_LE_32
BFD_RELOC_SH_TLS_DTPMOD32
BFD_RELOC_SH_TLS_DTPOFF32
BFD_RELOC_SH_TLS_TPOFF32
BFD_RELOC_SH_GOT20
BFD_RELOC_SH_GOTOFF20
BFD_RELOC_SH_GOTFUNCDESC
BFD_RELOC_SH_GOTFUNCDESC20
BFD_RELOC_SH_GOTOFFFUNCDESC
BFD_RELOC_SH_GOTOFFFUNCDESC20
BFD_RELOC_SH_FUNCDESC
Renesas / SuperH SH relocs. Not all of these appear in object files.

BFD_RELOC_ARC_NONE
BFD_RELOC_ARC_8
BFD_RELOC_ARC_16
BFD_RELOC_ARC_24
BFD_RELOC_ARC_32
BFD_RELOC_ARC_N8
BFD_RELOC_ARC_N16
BFD_RELOC_ARC_N24
BFD_RELOC_ARC_N32
BFD_RELOC_ARC_SDA
BFD_RELOC_ARC_SECTOFF
BFD_RELOC_ARC_S21H_PCREL
BFD_RELOC_ARC_S21W_PCREL
BFD_RELOC_ARC_S25H_PCREL
BFD_RELOC_ARC_S25W_PCREL
BFD_RELOC_ARC_SDA32
BFD_RELOC_ARC_SDA_LDST
BFD_RELOC_ARC_SDA_LDST1
BFD_RELOC_ARC_SDA_LDST2
BFD_RELOC_ARC_SDA16_LD
BFD_RELOC_ARC_SDA16_LD1
BFD_RELOC_ARC_SDA16_LD2
BFD_RELOC_ARC_S13_PCREL
BFD_RELOC_ARC_W
BFD_RELOC_ARC_32_ME
BFD_RELOC_ARC_32_ME_S
BFD_RELOC_ARC_N32_ME
BFD_RELOC_ARC_SECTOFF_ME
BFD_RELOC_ARC_SDA32_ME
BFD_RELOC_ARC_W_ME
BFD_RELOC_AC_SECTOFF_U8
BFD_RELOC_AC_SECTOFF_U8_1
BFD_RELOC_AC_SECTOFF_U8_2

BFD_RELOC_AC_SECTOFF_S9
BFD_RELOC_AC_SECTOFF_S9_1
BFD_RELOC_AC_SECTOFF_S9_2
BFD_RELOC_ARC_SECTOFF_ME_1
BFD_RELOC_ARC_SECTOFF_ME_2
BFD_RELOC_ARC_SECTOFF_1
BFD_RELOC_ARC_SECTOFF_2
BFD_RELOC_ARC_SDA_12
BFD_RELOC_ARC_SDA16_ST2
BFD_RELOC_ARC_32_PCREL
BFD_RELOC_ARC_PC32
BFD_RELOC_ARC_GOT32
BFD_RELOC_ARC_GOTPC32
BFD_RELOC_ARC_PLT32
BFD_RELOC_ARC_COPY
BFD_RELOC_ARC_GLOB_DAT
BFD_RELOC_ARC_JMP_SLOT
BFD_RELOC_ARC_RELATIVE
BFD_RELOC_ARC_GOTOFF
BFD_RELOC_ARC_GOTPC
BFD_RELOC_ARC_S21W_PCREL_PLT
BFD_RELOC_ARC_S25H_PCREL_PLT
BFD_RELOC_ARC_TLS_DTPMOD
BFD_RELOC_ARC_TLS_TPOFF
BFD_RELOC_ARC_TLS_GD_GOT
BFD_RELOC_ARC_TLS_GD_LD
BFD_RELOC_ARC_TLS_GD_CALL
BFD_RELOC_ARC_TLS_IE_GOT
BFD_RELOC_ARC_TLS_DTPOFF
BFD_RELOC_ARC_TLS_DTPOFF_S9
BFD_RELOC_ARC_TLS_LE_S9
BFD_RELOC_ARC_TLS_LE_32
BFD_RELOC_ARC_S25W_PCREL_PLT
BFD_RELOC_ARC_S21H_PCREL_PLT
BFD_RELOC_ARC_NPS_CMEM16
BFD_RELOC_ARC_JLI_SECTOFF
: ARC relocs.

BFD_RELOC_BFIN_16_IMM
: ADI Blackfin 16 bit immediate absolute reloc.

BFD_RELOC_BFIN_16_HIGH
: ADI Blackfin 16 bit immediate absolute reloc higher 16 bits.

BFD_RELOC_BFIN_4_PCREL
: ADI Blackfin 'a' part of LSETUP.

BFD_RELOC_BFIN_5_PCREL
: ADI Blackfin.

`BFD_RELOC_BFIN_16_LOW`
: ADI Blackfin 16 bit immediate absolute reloc lower 16 bits.

`BFD_RELOC_BFIN_10_PCREL`
: ADI Blackfin.

`BFD_RELOC_BFIN_11_PCREL`
: ADI Blackfin 'b' part of LSETUP.

`BFD_RELOC_BFIN_12_PCREL_JUMP`
: ADI Blackfin.

`BFD_RELOC_BFIN_12_PCREL_JUMP_S`
: ADI Blackfin Short jump, pcrel.

`BFD_RELOC_BFIN_24_PCREL_CALL_X`
: ADI Blackfin Call.x not implemented.

`BFD_RELOC_BFIN_24_PCREL_JUMP_L`
: ADI Blackfin Long Jump pcrel.

`BFD_RELOC_BFIN_GOT17M4`
`BFD_RELOC_BFIN_GOTHI`
`BFD_RELOC_BFIN_GOTLO`
`BFD_RELOC_BFIN_FUNCDESC`
`BFD_RELOC_BFIN_FUNCDESC_GOT17M4`
`BFD_RELOC_BFIN_FUNCDESC_GOTHI`
`BFD_RELOC_BFIN_FUNCDESC_GOTLO`
`BFD_RELOC_BFIN_FUNCDESC_VALUE`
`BFD_RELOC_BFIN_FUNCDESC_GOTOFF17M4`
`BFD_RELOC_BFIN_FUNCDESC_GOTOFFHI`
`BFD_RELOC_BFIN_FUNCDESC_GOTOFFLO`
`BFD_RELOC_BFIN_GOTOFF17M4`
`BFD_RELOC_BFIN_GOTOFFHI`
`BFD_RELOC_BFIN_GOTOFFLO`
: ADI Blackfin FD-PIC relocations.

`BFD_RELOC_BFIN_GOT`
: ADI Blackfin GOT relocation.

`BFD_RELOC_BFIN_PLTPC`
: ADI Blackfin PLTPC relocation.

`BFD_ARELOC_BFIN_PUSH`
: ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_CONST`
: ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_ADD`
: ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_SUB`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_MULT`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_DIV`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_MOD`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_LSHIFT`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_RSHIFT`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_AND`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_OR`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_XOR`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_LAND`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_LOR`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_LEN`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_NEG`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_COMP`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_PAGE`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_HWPAGE`
ADI Blackfin arithmetic relocation.

`BFD_ARELOC_BFIN_ADDR`
ADI Blackfin arithmetic relocation.

`BFD_RELOC_D10V_10_PCREL_R`
Mitsubishi D10V relocs. This is a 10-bit reloc with the right 2 bits assumed to be 0.

`BFD_RELOC_D10V_10_PCREL_L`
: Mitsubishi D10V relocs. This is a 10-bit reloc with the right 2 bits assumed to be 0. This is the same as the previous reloc except it is in the left container, i.e., shifted left 15 bits.

`BFD_RELOC_D10V_18`
: This is an 18-bit reloc with the right 2 bits assumed to be 0.

`BFD_RELOC_D10V_18_PCREL`
: This is an 18-bit reloc with the right 2 bits assumed to be 0.

`BFD_RELOC_D30V_6`
: Mitsubishi D30V relocs. This is a 6-bit absolute reloc.

`BFD_RELOC_D30V_9_PCREL`
: This is a 6-bit pc-relative reloc with the right 3 bits assumed to be 0.

`BFD_RELOC_D30V_9_PCREL_R`
: This is a 6-bit pc-relative reloc with the right 3 bits assumed to be 0. Same as the previous reloc but on the right side of the container.

`BFD_RELOC_D30V_15`
: This is a 12-bit absolute reloc with the right 3 bitsassumed to be 0.

`BFD_RELOC_D30V_15_PCREL`
: This is a 12-bit pc-relative reloc with the right 3 bits assumed to be 0.

`BFD_RELOC_D30V_15_PCREL_R`
: This is a 12-bit pc-relative reloc with the right 3 bits assumed to be 0. Same as the previous reloc but on the right side of the container.

`BFD_RELOC_D30V_21`
: This is an 18-bit absolute reloc with the right 3 bits assumed to be 0.

`BFD_RELOC_D30V_21_PCREL`
: This is an 18-bit pc-relative reloc with the right 3 bits assumed to be 0.

`BFD_RELOC_D30V_21_PCREL_R`
: This is an 18-bit pc-relative reloc with the right 3 bits assumed to be 0. Same as the previous reloc but on the right side of the container.

`BFD_RELOC_D30V_32`
: This is a 32-bit absolute reloc.

`BFD_RELOC_D30V_32_PCREL`
: This is a 32-bit pc-relative reloc.

`BFD_RELOC_DLX_HI16_S`
`BFD_RELOC_DLX_LO16`
`BFD_RELOC_DLX_JMP26`
: DLX relocs.

BFD_RELOC_M32C_HI8
BFD_RELOC_M32C_RL_JUMP
BFD_RELOC_M32C_RL_1ADDR
BFD_RELOC_M32C_RL_2ADDR
: Renesas M16C/M32C Relocations.

BFD_RELOC_M32R_24
: Renesas M32R (formerly Mitsubishi M32R) relocs. This is a 24 bit absolute address.

BFD_RELOC_M32R_10_PCREL
: This is a 10-bit pc-relative reloc with the right 2 bits assumed to be 0.

BFD_RELOC_M32R_18_PCREL
: This is an 18-bit reloc with the right 2 bits assumed to be 0.

BFD_RELOC_M32R_26_PCREL
: This is a 26-bit reloc with the right 2 bits assumed to be 0.

BFD_RELOC_M32R_HI16_ULO
: This is a 16-bit reloc containing the high 16 bits of an address used when the lower 16 bits are treated as unsigned.

BFD_RELOC_M32R_HI16_SLO
: This is a 16-bit reloc containing the high 16 bits of an address used when the lower 16 bits are treated as signed.

BFD_RELOC_M32R_LO16
: This is a 16-bit reloc containing the lower 16 bits of an address.

BFD_RELOC_M32R_SDA16
: This is a 16-bit reloc containing the small data area offset for use in add3, load, and store instructions.

BFD_RELOC_M32R_GOT24
BFD_RELOC_M32R_26_PLTREL
BFD_RELOC_M32R_COPY
BFD_RELOC_M32R_GLOB_DAT
BFD_RELOC_M32R_JMP_SLOT
BFD_RELOC_M32R_RELATIVE
BFD_RELOC_M32R_GOTOFF
BFD_RELOC_M32R_GOTOFF_HI_ULO
BFD_RELOC_M32R_GOTOFF_HI_SLO
BFD_RELOC_M32R_GOTOFF_LO
BFD_RELOC_M32R_GOTPC24
BFD_RELOC_M32R_GOT16_HI_ULO
BFD_RELOC_M32R_GOT16_HI_SLO
BFD_RELOC_M32R_GOT16_LO
BFD_RELOC_M32R_GOTPC_HI_ULO
BFD_RELOC_M32R_GOTPC_HI_SLO
BFD_RELOC_M32R_GOTPC_LO
: For PIC.

`BFD_RELOC_NDS32_20`
: NDS32 relocs. This is a 20 bit absolute address.

`BFD_RELOC_NDS32_9_PCREL`
: This is a 9-bit pc-relative reloc with the right 1 bit assumed to be 0.

`BFD_RELOC_NDS32_WORD_9_PCREL`
: This is a 9-bit pc-relative reloc with the right 1 bit assumed to be 0.

`BFD_RELOC_NDS32_15_PCREL`
: This is an 15-bit reloc with the right 1 bit assumed to be 0.

`BFD_RELOC_NDS32_17_PCREL`
: This is an 17-bit reloc with the right 1 bit assumed to be 0.

`BFD_RELOC_NDS32_25_PCREL`
: This is a 25-bit reloc with the right 1 bit assumed to be 0.

`BFD_RELOC_NDS32_HI20`
: This is a 20-bit reloc containing the high 20 bits of an address used with the lower 12 bits.

`BFD_RELOC_NDS32_LO12S3`
: This is a 12-bit reloc containing the lower 12 bits of an address then shift right by 3. This is used with ldi,sdi.

`BFD_RELOC_NDS32_LO12S2`
: This is a 12-bit reloc containing the lower 12 bits of an address then shift left by 2. This is used with lwi,swi.

`BFD_RELOC_NDS32_LO12S1`
: This is a 12-bit reloc containing the lower 12 bits of an address then shift left by 1. This is used with lhi,shi.

`BFD_RELOC_NDS32_LO12S0`
: This is a 12-bit reloc containing the lower 12 bits of an address then shift left by 0. This is used with lbisbi.

`BFD_RELOC_NDS32_LO12S0_ORI`
: This is a 12-bit reloc containing the lower 12 bits of an address then shift left by 0. This is only used with branch relaxations.

`BFD_RELOC_NDS32_SDA15S3`
: This is a 15-bit reloc containing the small data area 18-bit signed offset and shift left by 3 for use in ldi, sdi.

`BFD_RELOC_NDS32_SDA15S2`
: This is a 15-bit reloc containing the small data area 17-bit signed offset and shift left by 2 for use in lwi, swi.

`BFD_RELOC_NDS32_SDA15S1`
: This is a 15-bit reloc containing the small data area 16-bit signed offset and shift left by 1 for use in lhi, shi.

`BFD_RELOC_NDS32_SDA15S0`
: This is a 15-bit reloc containing the small data area 15-bit signed offset and shift left by 0 for use in lbi, sbi.

`BFD_RELOC_NDS32_SDA16S3`
: This is a 16-bit reloc containing the small data area 16-bit signed offset and shift left by 3.

`BFD_RELOC_NDS32_SDA17S2`
: This is a 17-bit reloc containing the small data area 17-bit signed offset and shift left by 2 for use in lwi.gp, swi.gp.

`BFD_RELOC_NDS32_SDA18S1`
: This is a 18-bit reloc containing the small data area 18-bit signed offset and shift left by 1 for use in lhi.gp, shi.gp.

`BFD_RELOC_NDS32_SDA19S0`
: This is a 19-bit reloc containing the small data area 19-bit signed offset and shift left by 0 for use in lbi.gp, sbi.gp.

`BFD_RELOC_NDS32_GOT20`
`BFD_RELOC_NDS32_9_PLTREL`
`BFD_RELOC_NDS32_25_PLTREL`
`BFD_RELOC_NDS32_COPY`
`BFD_RELOC_NDS32_GLOB_DAT`
`BFD_RELOC_NDS32_JMP_SLOT`
`BFD_RELOC_NDS32_RELATIVE`
`BFD_RELOC_NDS32_GOTOFF`
`BFD_RELOC_NDS32_GOTOFF_HI20`
`BFD_RELOC_NDS32_GOTOFF_LO12`
`BFD_RELOC_NDS32_GOTPC20`
`BFD_RELOC_NDS32_GOT_HI20`
`BFD_RELOC_NDS32_GOT_LO12`
`BFD_RELOC_NDS32_GOTPC_HI20`
`BFD_RELOC_NDS32_GOTPC_LO12`
: For PIC.

`BFD_RELOC_NDS32_INSN16`
`BFD_RELOC_NDS32_LABEL`
`BFD_RELOC_NDS32_LONGCALL1`
`BFD_RELOC_NDS32_LONGCALL2`
`BFD_RELOC_NDS32_LONGCALL3`
`BFD_RELOC_NDS32_LONGJUMP1`
`BFD_RELOC_NDS32_LONGJUMP2`
`BFD_RELOC_NDS32_LONGJUMP3`
`BFD_RELOC_NDS32_LOADSTORE`
`BFD_RELOC_NDS32_9_FIXED`
`BFD_RELOC_NDS32_15_FIXED`
`BFD_RELOC_NDS32_17_FIXED`

BFD_RELOC_NDS32_25_FIXED
BFD_RELOC_NDS32_LONGCALL4
BFD_RELOC_NDS32_LONGCALL5
BFD_RELOC_NDS32_LONGCALL6
BFD_RELOC_NDS32_LONGJUMP4
BFD_RELOC_NDS32_LONGJUMP5
BFD_RELOC_NDS32_LONGJUMP6
BFD_RELOC_NDS32_LONGJUMP7
: For relax.

BFD_RELOC_NDS32_PLTREL_HI20
BFD_RELOC_NDS32_PLTREL_LO12
BFD_RELOC_NDS32_PLT_GOTREL_HI20
BFD_RELOC_NDS32_PLT_GOTREL_LO12
: For PIC.

BFD_RELOC_NDS32_SDA12S2_DP
BFD_RELOC_NDS32_SDA12S2_SP
BFD_RELOC_NDS32_LO12S2_DP
BFD_RELOC_NDS32_LO12S2_SP
: For floating point.

BFD_RELOC_NDS32_DWARF2_OP1
BFD_RELOC_NDS32_DWARF2_OP2
BFD_RELOC_NDS32_DWARF2_LEB
: For dwarf2 debug_line.

BFD_RELOC_NDS32_UPDATE_TA
: For eliminating 16-bit instructions.

BFD_RELOC_NDS32_PLT_GOTREL_LO20
BFD_RELOC_NDS32_PLT_GOTREL_LO15
BFD_RELOC_NDS32_PLT_GOTREL_LO19
BFD_RELOC_NDS32_GOT_LO15
BFD_RELOC_NDS32_GOT_LO19
BFD_RELOC_NDS32_GOTOFF_LO15
BFD_RELOC_NDS32_GOTOFF_LO19
BFD_RELOC_NDS32_GOT15S2
BFD_RELOC_NDS32_GOT17S2
: For PIC object relaxation.

BFD_RELOC_NDS32_5
: NDS32 relocs. This is a 5 bit absolute address.

BFD_RELOC_NDS32_10_UPCREL
: This is a 10-bit unsigned pc-relative reloc with the right 1 bit assumed to be 0.

BFD_RELOC_NDS32_SDA_FP7U2_RELA
: If fp were omitted, fp can used as another gp.

BFD_RELOC_NDS32_RELAX_ENTRY
BFD_RELOC_NDS32_GOT_SUFF
BFD_RELOC_NDS32_GOTOFF_SUFF
BFD_RELOC_NDS32_PLT_GOT_SUFF
BFD_RELOC_NDS32_MULCALL_SUFF
BFD_RELOC_NDS32_PTR
BFD_RELOC_NDS32_PTR_COUNT
BFD_RELOC_NDS32_PTR_RESOLVED
BFD_RELOC_NDS32_PLTBLOCK
BFD_RELOC_NDS32_RELAX_REGION_BEGIN
BFD_RELOC_NDS32_RELAX_REGION_END
BFD_RELOC_NDS32_MINUEND
BFD_RELOC_NDS32_SUBTRAHEND
BFD_RELOC_NDS32_DIFF8
BFD_RELOC_NDS32_DIFF16
BFD_RELOC_NDS32_DIFF32
BFD_RELOC_NDS32_DIFF_ULEB128
BFD_RELOC_NDS32_EMPTY
: Relaxation relative relocation types.

BFD_RELOC_NDS32_25_ABS
: This is a 25 bit absolute address.

BFD_RELOC_NDS32_DATA
BFD_RELOC_NDS32_TRAN
BFD_RELOC_NDS32_17IFC_PCREL
BFD_RELOC_NDS32_10IFCU_PCREL
: For ex9 and ifc using.

BFD_RELOC_NDS32_TPOFF
BFD_RELOC_NDS32_GOTTPOFF
BFD_RELOC_NDS32_TLS_LE_HI20
BFD_RELOC_NDS32_TLS_LE_LO12
BFD_RELOC_NDS32_TLS_LE_20
BFD_RELOC_NDS32_TLS_LE_15S0
BFD_RELOC_NDS32_TLS_LE_15S1
BFD_RELOC_NDS32_TLS_LE_15S2
BFD_RELOC_NDS32_TLS_LE_ADD
BFD_RELOC_NDS32_TLS_LE_LS
BFD_RELOC_NDS32_TLS_IE_HI20
BFD_RELOC_NDS32_TLS_IE_LO12
BFD_RELOC_NDS32_TLS_IE_LO12S2
BFD_RELOC_NDS32_TLS_IEGP_HI20
BFD_RELOC_NDS32_TLS_IEGP_LO12
BFD_RELOC_NDS32_TLS_IEGP_LO12S2
BFD_RELOC_NDS32_TLS_IEGP_LW
BFD_RELOC_NDS32_TLS_DESC
BFD_RELOC_NDS32_TLS_DESC_HI20

BFD_RELOC_NDS32_TLS_DESC_LO12
BFD_RELOC_NDS32_TLS_DESC_20
BFD_RELOC_NDS32_TLS_DESC_SDA17S2
BFD_RELOC_NDS32_TLS_DESC_ADD
BFD_RELOC_NDS32_TLS_DESC_FUNC
BFD_RELOC_NDS32_TLS_DESC_CALL
BFD_RELOC_NDS32_TLS_DESC_MEM
BFD_RELOC_NDS32_REMOVE
BFD_RELOC_NDS32_GROUP
: For TLS.

BFD_RELOC_NDS32_LSI
: For floating load store relaxation.

BFD_RELOC_V850_9_PCREL
: This is a 9-bit reloc.

BFD_RELOC_V850_22_PCREL
: This is a 22-bit reloc.

BFD_RELOC_V850_SDA_16_16_OFFSET
: This is a 16 bit offset from the short data area pointer.

BFD_RELOC_V850_SDA_15_16_OFFSET
: This is a 16 bit offset (of which only 15 bits are used) from the short data area pointer.

BFD_RELOC_V850_ZDA_16_16_OFFSET
: This is a 16 bit offset from the zero data area pointer.

BFD_RELOC_V850_ZDA_15_16_OFFSET
: This is a 16 bit offset (of which only 15 bits are used) from the zero data area pointer.

BFD_RELOC_V850_TDA_6_8_OFFSET
: This is an 8 bit offset (of which only 6 bits are used) from the tiny data area pointer.

BFD_RELOC_V850_TDA_7_8_OFFSET
: This is an 8bit offset (of which only 7 bits are used) from the tiny data area pointer.

BFD_RELOC_V850_TDA_7_7_OFFSET
: This is a 7 bit offset from the tiny data area pointer.

BFD_RELOC_V850_TDA_16_16_OFFSET
: This is a 16 bit offset from the tiny data area pointer.

BFD_RELOC_V850_TDA_4_5_OFFSET
: This is a 5 bit offset (of which only 4 bits are used) from the tiny data area pointer.

BFD_RELOC_V850_TDA_4_4_OFFSET
: This is a 4 bit offset from the tiny data area pointer.

BFD_RELOC_V850_SDA_16_16_SPLIT_OFFSET
: This is a 16 bit offset from the short data area pointer, with the bits placed non-contiguously in the instruction.

`BFD_RELOC_V850_ZDA_16_16_SPLIT_OFFSET`
: This is a 16 bit offset from the zero data area pointer, with the bits placed non-contiguously in the instruction.

`BFD_RELOC_V850_CALLT_6_7_OFFSET`
: This is a 6 bit offset from the call table base pointer.

`BFD_RELOC_V850_CALLT_16_16_OFFSET`
: This is a 16 bit offset from the call table base pointer.

`BFD_RELOC_V850_LONGCALL`
: Used for relaxing indirect function calls.

`BFD_RELOC_V850_LONGJUMP`
: Used for relaxing indirect jumps.

`BFD_RELOC_V850_ALIGN`
: Used to maintain alignment whilst relaxing.

`BFD_RELOC_V850_LO16_SPLIT_OFFSET`
: This is a variation of BFD_RELOC_LO16 that can be used in v850e ld.bu instructions.

`BFD_RELOC_V850_16_PCREL`
: This is a 16-bit reloc.

`BFD_RELOC_V850_17_PCREL`
: This is a 17-bit reloc.

`BFD_RELOC_V850_23`
: This is a 23-bit reloc.

`BFD_RELOC_V850_32_PCREL`
: This is a 32-bit reloc.

`BFD_RELOC_V850_32_ABS`
: This is a 32-bit reloc.

`BFD_RELOC_V850_16_SPLIT_OFFSET`
: This is a 16-bit reloc.

`BFD_RELOC_V850_16_S1`
: This is a 16-bit reloc.

`BFD_RELOC_V850_LO16_S1`
: Low 16 bits. 16 bit shifted by 1.

`BFD_RELOC_V850_CALLT_15_16_OFFSET`
: This is a 16 bit offset from the call table base pointer.

BFD_RELOC_V850_32_GOTPCREL
BFD_RELOC_V850_16_GOT
BFD_RELOC_V850_32_GOT
BFD_RELOC_V850_22_PLT_PCREL
BFD_RELOC_V850_32_PLT_PCREL
BFD_RELOC_V850_COPY
BFD_RELOC_V850_GLOB_DAT
BFD_RELOC_V850_JMP_SLOT
BFD_RELOC_V850_RELATIVE
BFD_RELOC_V850_16_GOTOFF
BFD_RELOC_V850_32_GOTOFF
: DSO relocations.

BFD_RELOC_V850_CODE
: Start code.

BFD_RELOC_V850_DATA
: Start data in text.

BFD_RELOC_TIC30_LDP
: This is a 8bit DP reloc for the tms320c30, where the most significant 8 bits of a 24 bit word are placed into the least significant 8 bits of the opcode.

BFD_RELOC_TIC54X_PARTLS7
: This is a 7bit reloc for the tms320c54x, where the least significant 7 bits of a 16 bit word are placed into the least significant 7 bits of the opcode.

BFD_RELOC_TIC54X_PARTMS9
: This is a 9bit DP reloc for the tms320c54x, where the most significant 9 bits of a 16 bit word are placed into the least significant 9 bits of the opcode.

BFD_RELOC_TIC54X_23
: This is an extended address 23-bit reloc for the tms320c54x.

BFD_RELOC_TIC54X_16_OF_23
: This is a 16-bit reloc for the tms320c54x, where the least significant 16 bits of a 23-bit extended address are placed into the opcode.

BFD_RELOC_TIC54X_MS7_OF_23
: This is a reloc for the tms320c54x, where the most significant 7 bits of a 23-bit extended address are placed into the opcode.

BFD_RELOC_C6000_PCR_S21
BFD_RELOC_C6000_PCR_S12
BFD_RELOC_C6000_PCR_S10
BFD_RELOC_C6000_PCR_S7
BFD_RELOC_C6000_ABS_S16
BFD_RELOC_C6000_ABS_L16
BFD_RELOC_C6000_ABS_H16
BFD_RELOC_C6000_SBR_U15_B

BFD_RELOC_C6000_SBR_U15_H
BFD_RELOC_C6000_SBR_U15_W
BFD_RELOC_C6000_SBR_S16
BFD_RELOC_C6000_SBR_L16_B
BFD_RELOC_C6000_SBR_L16_H
BFD_RELOC_C6000_SBR_L16_W
BFD_RELOC_C6000_SBR_H16_B
BFD_RELOC_C6000_SBR_H16_H
BFD_RELOC_C6000_SBR_H16_W
BFD_RELOC_C6000_SBR_GOT_U15_W
BFD_RELOC_C6000_SBR_GOT_L16_W
BFD_RELOC_C6000_SBR_GOT_H16_W
BFD_RELOC_C6000_DSBT_INDEX
BFD_RELOC_C6000_PREL31
BFD_RELOC_C6000_COPY
BFD_RELOC_C6000_JUMP_SLOT
BFD_RELOC_C6000_EHTYPE
BFD_RELOC_C6000_PCR_H16
BFD_RELOC_C6000_PCR_L16
BFD_RELOC_C6000_ALIGN
BFD_RELOC_C6000_FPHEAD
BFD_RELOC_C6000_NOCMP
: TMS320C6000 relocations.

BFD_RELOC_FR30_48
: This is a 48 bit reloc for the FR30 that stores 32 bits.

BFD_RELOC_FR30_20
: This is a 32 bit reloc for the FR30 that stores 20 bits split up into two sections.

BFD_RELOC_FR30_6_IN_4
: This is a 16 bit reloc for the FR30 that stores a 6 bit word offset in 4 bits.

BFD_RELOC_FR30_8_IN_8
: This is a 16 bit reloc for the FR30 that stores an 8 bit byte offset into 8 bits.

BFD_RELOC_FR30_9_IN_8
: This is a 16 bit reloc for the FR30 that stores a 9 bit short offset into 8 bits.

BFD_RELOC_FR30_10_IN_8
: This is a 16 bit reloc for the FR30 that stores a 10 bit word offset into 8 bits.

BFD_RELOC_FR30_9_PCREL
: This is a 16 bit reloc for the FR30 that stores a 9 bit pc relative short offset into 8 bits.

BFD_RELOC_FR30_12_PCREL
: This is a 16 bit reloc for the FR30 that stores a 12 bit pc relative short offset into 11 bits.

BFD_RELOC_MCORE_PCREL_IMM8BY4
BFD_RELOC_MCORE_PCREL_IMM11BY2
BFD_RELOC_MCORE_PCREL_IMM4BY2
BFD_RELOC_MCORE_PCREL_32
BFD_RELOC_MCORE_PCREL_JSR_IMM11BY2
BFD_RELOC_MCORE_RVA
Motorola Mcore relocations.

BFD_RELOC_MEP_8
BFD_RELOC_MEP_16
BFD_RELOC_MEP_32
BFD_RELOC_MEP_PCREL8A2
BFD_RELOC_MEP_PCREL12A2
BFD_RELOC_MEP_PCREL17A2
BFD_RELOC_MEP_PCREL24A2
BFD_RELOC_MEP_PCABS24A2
BFD_RELOC_MEP_LOW16
BFD_RELOC_MEP_HI16U
BFD_RELOC_MEP_HI16S
BFD_RELOC_MEP_GPREL
BFD_RELOC_MEP_TPREL
BFD_RELOC_MEP_TPREL7
BFD_RELOC_MEP_TPREL7A2
BFD_RELOC_MEP_TPREL7A4
BFD_RELOC_MEP_UIMM24
BFD_RELOC_MEP_ADDR24A4
BFD_RELOC_MEP_GNU_VTINHERIT
BFD_RELOC_MEP_GNU_VTENTRY
Toshiba Media Processor Relocations.

BFD_RELOC_METAG_HIADDR16
BFD_RELOC_METAG_LOADDR16
BFD_RELOC_METAG_RELBRANCH
BFD_RELOC_METAG_GETSETOFF
BFD_RELOC_METAG_HIOG
BFD_RELOC_METAG_LOOG
BFD_RELOC_METAG_REL8
BFD_RELOC_METAG_REL16
BFD_RELOC_METAG_HI16_GOTOFF
BFD_RELOC_METAG_LO16_GOTOFF
BFD_RELOC_METAG_GETSET_GOTOFF
BFD_RELOC_METAG_GETSET_GOT
BFD_RELOC_METAG_HI16_GOTPC
BFD_RELOC_METAG_LO16_GOTPC
BFD_RELOC_METAG_HI16_PLT
BFD_RELOC_METAG_LO16_PLT
BFD_RELOC_METAG_RELBRANCH_PLT
BFD_RELOC_METAG_GOTOFF

BFD_RELOC_METAG_PLT
BFD_RELOC_METAG_COPY
BFD_RELOC_METAG_JMP_SLOT
BFD_RELOC_METAG_RELATIVE
BFD_RELOC_METAG_GLOB_DAT
BFD_RELOC_METAG_TLS_GD
BFD_RELOC_METAG_TLS_LDM
BFD_RELOC_METAG_TLS_LDO_HI16
BFD_RELOC_METAG_TLS_LDO_LO16
BFD_RELOC_METAG_TLS_LDO
BFD_RELOC_METAG_TLS_IE
BFD_RELOC_METAG_TLS_IENONPIC
BFD_RELOC_METAG_TLS_IENONPIC_HI16
BFD_RELOC_METAG_TLS_IENONPIC_LO16
BFD_RELOC_METAG_TLS_TPOFF
BFD_RELOC_METAG_TLS_DTPMOD
BFD_RELOC_METAG_TLS_DTPOFF
BFD_RELOC_METAG_TLS_LE
BFD_RELOC_METAG_TLS_LE_HI16
BFD_RELOC_METAG_TLS_LE_LO16
: Imagination Technologies Meta relocations.

BFD_RELOC_MMIX_GETA
BFD_RELOC_MMIX_GETA_1
BFD_RELOC_MMIX_GETA_2
BFD_RELOC_MMIX_GETA_3
: These are relocations for the GETA instruction.

BFD_RELOC_MMIX_CBRANCH
BFD_RELOC_MMIX_CBRANCH_J
BFD_RELOC_MMIX_CBRANCH_1
BFD_RELOC_MMIX_CBRANCH_2
BFD_RELOC_MMIX_CBRANCH_3
: These are relocations for a conditional branch instruction.

BFD_RELOC_MMIX_PUSHJ
BFD_RELOC_MMIX_PUSHJ_1
BFD_RELOC_MMIX_PUSHJ_2
BFD_RELOC_MMIX_PUSHJ_3
BFD_RELOC_MMIX_PUSHJ_STUBBABLE
: These are relocations for the PUSHJ instruction.

BFD_RELOC_MMIX_JMP
BFD_RELOC_MMIX_JMP_1
BFD_RELOC_MMIX_JMP_2
BFD_RELOC_MMIX_JMP_3
: These are relocations for the JMP instruction.

`BFD_RELOC_MMIX_ADDR19`
: This is a relocation for a relative address as in a GETA instruction or a branch.

`BFD_RELOC_MMIX_ADDR27`
: This is a relocation for a relative address as in a JMP instruction.

`BFD_RELOC_MMIX_REG_OR_BYTE`
: This is a relocation for an instruction field that may be a general register or a value 0..255.

`BFD_RELOC_MMIX_REG`
: This is a relocation for an instruction field that may be a general register.

`BFD_RELOC_MMIX_BASE_PLUS_OFFSET`
: This is a relocation for two instruction fields holding a register and an offset, the equivalent of the relocation.

`BFD_RELOC_MMIX_LOCAL`
: This relocation is an assertion that the expression is not allocated as a global register. It does not modify contents.

`BFD_RELOC_AVR_7_PCREL`
: This is a 16 bit reloc for the AVR that stores 8 bit pc relative short offset into 7 bits.

`BFD_RELOC_AVR_13_PCREL`
: This is a 16 bit reloc for the AVR that stores 13 bit pc relative short offset into 12 bits.

`BFD_RELOC_AVR_16_PM`
: This is a 16 bit reloc for the AVR that stores 17 bit value (usually program memory address) into 16 bits.

`BFD_RELOC_AVR_LO8_LDI`
: This is a 16 bit reloc for the AVR that stores 8 bit value (usually data memory address) into 8 bit immediate value of LDI insn.

`BFD_RELOC_AVR_HI8_LDI`
: This is a 16 bit reloc for the AVR that stores 8 bit value (high 8 bit of data memory address) into 8 bit immediate value of LDI insn.

`BFD_RELOC_AVR_HH8_LDI`
: This is a 16 bit reloc for the AVR that stores 8 bit value (most high 8 bit of program memory address) into 8 bit immediate value of LDI insn.

`BFD_RELOC_AVR_MS8_LDI`
: This is a 16 bit reloc for the AVR that stores 8 bit value (most high 8 bit of 32 bit value) into 8 bit immediate value of LDI insn.

`BFD_RELOC_AVR_LO8_LDI_NEG`
: This is a 16 bit reloc for the AVR that stores negated 8 bit value (usually data memory address) into 8 bit immediate value of SUBI insn.

`BFD_RELOC_AVR_HI8_LDI_NEG`
: This is a 16 bit reloc for the AVR that stores negated 8 bit value (high 8 bit of data memory address) into 8 bit immediate value of SUBI insn.

`BFD_RELOC_AVR_HH8_LDI_NEG`
: This is a 16 bit reloc for the AVR that stores negated 8 bit value (most high 8 bit of program memory address) into 8 bit immediate value of LDI or SUBI insn.

`BFD_RELOC_AVR_MS8_LDI_NEG`
: This is a 16 bit reloc for the AVR that stores negated 8 bit value (msb of 32 bit value) into 8 bit immediate value of LDI insn.

`BFD_RELOC_AVR_LO8_LDI_PM`
: This is a 16 bit reloc for the AVR that stores 8 bit value (usually command address) into 8 bit immediate value of LDI insn.

`BFD_RELOC_AVR_LO8_LDI_GS`
: This is a 16 bit reloc for the AVR that stores 8 bit value (command address) into 8 bit immediate value of LDI insn. If the address is beyond the 128k boundary, the linker inserts a jump stub for this reloc in the lower 128k.

`BFD_RELOC_AVR_HI8_LDI_PM`
: This is a 16 bit reloc for the AVR that stores 8 bit value (high 8 bit of command address) into 8 bit immediate value of LDI insn.

`BFD_RELOC_AVR_HI8_LDI_GS`
: This is a 16 bit reloc for the AVR that stores 8 bit value (high 8 bit of command address) into 8 bit immediate value of LDI insn. If the address is beyond the 128k boundary, the linker inserts a jump stub for this reloc below 128k.

`BFD_RELOC_AVR_HH8_LDI_PM`
: This is a 16 bit reloc for the AVR that stores 8 bit value (most high 8 bit of command address) into 8 bit immediate value of LDI insn.

`BFD_RELOC_AVR_LO8_LDI_PM_NEG`
: This is a 16 bit reloc for the AVR that stores negated 8 bit value (usually command address) into 8 bit immediate value of SUBI insn.

`BFD_RELOC_AVR_HI8_LDI_PM_NEG`
: This is a 16 bit reloc for the AVR that stores negated 8 bit value (high 8 bit of 16 bit command address) into 8 bit immediate value of SUBI insn.

`BFD_RELOC_AVR_HH8_LDI_PM_NEG`
: This is a 16 bit reloc for the AVR that stores negated 8 bit value (high 6 bit of 22 bit command address) into 8 bit immediate value of SUBI insn.

`BFD_RELOC_AVR_CALL`
: This is a 32 bit reloc for the AVR that stores 23 bit value into 22 bits.

`BFD_RELOC_AVR_LDI`
: This is a 16 bit reloc for the AVR that stores all needed bits for absolute addressing with ldi with overflow check to linktime.

`BFD_RELOC_AVR_6`
: This is a 6 bit reloc for the AVR that stores offset for ldd/std instructions.

`BFD_RELOC_AVR_6_ADIW`
: This is a 6 bit reloc for the AVR that stores offset for adiw/sbiw instructions.

`BFD_RELOC_AVR_8_LO`
: This is a 8 bit reloc for the AVR that stores bits 0..7 of a symbol in .byte lo8(symbol).

`BFD_RELOC_AVR_8_HI`
: This is a 8 bit reloc for the AVR that stores bits 8..15 of a symbol in .byte hi8(symbol).

`BFD_RELOC_AVR_8_HLO`
: This is a 8 bit reloc for the AVR that stores bits 16..23 of a symbol in .byte hlo8(symbol).

`BFD_RELOC_AVR_DIFF8`
`BFD_RELOC_AVR_DIFF16`
`BFD_RELOC_AVR_DIFF32`
: AVR relocations to mark the difference of two local symbols. These are only needed to support linker relaxation and can be ignored when not relaxing. The field is set to the value of the difference assuming no relaxation. The relocation encodes the position of the second symbol so the linker can determine whether to adjust the field value.

`BFD_RELOC_AVR_LDS_STS_16`
: This is a 7 bit reloc for the AVR that stores SRAM address for 16bit lds and sts instructions supported only tiny core.

`BFD_RELOC_AVR_PORT6`
: This is a 6 bit reloc for the AVR that stores an I/O register number for the IN and OUT instructions.

`BFD_RELOC_AVR_PORT5`
: This is a 5 bit reloc for the AVR that stores an I/O register number for the SBIC, SBIS, SBI and CBI instructions.

`BFD_RELOC_RISCV_HI20`
`BFD_RELOC_RISCV_PCREL_HI20`
`BFD_RELOC_RISCV_PCREL_LO12_I`
`BFD_RELOC_RISCV_PCREL_LO12_S`
`BFD_RELOC_RISCV_LO12_I`
`BFD_RELOC_RISCV_LO12_S`
`BFD_RELOC_RISCV_GPREL12_I`
`BFD_RELOC_RISCV_GPREL12_S`
`BFD_RELOC_RISCV_TPREL_HI20`
`BFD_RELOC_RISCV_TPREL_LO12_I`
`BFD_RELOC_RISCV_TPREL_LO12_S`
`BFD_RELOC_RISCV_TPREL_ADD`
`BFD_RELOC_RISCV_CALL`

BFD_RELOC_RISCV_CALL_PLT
BFD_RELOC_RISCV_ADD8
BFD_RELOC_RISCV_ADD16
BFD_RELOC_RISCV_ADD32
BFD_RELOC_RISCV_ADD64
BFD_RELOC_RISCV_SUB8
BFD_RELOC_RISCV_SUB16
BFD_RELOC_RISCV_SUB32
BFD_RELOC_RISCV_SUB64
BFD_RELOC_RISCV_GOT_HI20
BFD_RELOC_RISCV_TLS_GOT_HI20
BFD_RELOC_RISCV_TLS_GD_HI20
BFD_RELOC_RISCV_JMP
BFD_RELOC_RISCV_TLS_DTPMOD32
BFD_RELOC_RISCV_TLS_DTPREL32
BFD_RELOC_RISCV_TLS_DTPMOD64
BFD_RELOC_RISCV_TLS_DTPREL64
BFD_RELOC_RISCV_TLS_TPREL32
BFD_RELOC_RISCV_TLS_TPREL64
BFD_RELOC_RISCV_TLSDESC_HI20
BFD_RELOC_RISCV_TLSDESC_LOAD_LO12
BFD_RELOC_RISCV_TLSDESC_ADD_LO12
BFD_RELOC_RISCV_TLSDESC_CALL
BFD_RELOC_RISCV_ALIGN
BFD_RELOC_RISCV_RVC_BRANCH
BFD_RELOC_RISCV_RVC_JUMP
BFD_RELOC_RISCV_RELAX
BFD_RELOC_RISCV_CFA
BFD_RELOC_RISCV_SUB6
BFD_RELOC_RISCV_SET6
BFD_RELOC_RISCV_SET8
BFD_RELOC_RISCV_SET16
BFD_RELOC_RISCV_SET32
BFD_RELOC_RISCV_32_PCREL
BFD_RELOC_RISCV_SET_ULEB128
BFD_RELOC_RISCV_SUB_ULEB128
RISC-V relocations.

BFD_RELOC_RL78_NEG8
BFD_RELOC_RL78_NEG16
BFD_RELOC_RL78_NEG24
BFD_RELOC_RL78_NEG32
BFD_RELOC_RL78_16_OP
BFD_RELOC_RL78_24_OP
BFD_RELOC_RL78_32_OP
BFD_RELOC_RL78_8U
BFD_RELOC_RL78_16U

BFD_RELOC_RL78_24U
BFD_RELOC_RL78_DIR3U_PCREL
BFD_RELOC_RL78_DIFF
BFD_RELOC_RL78_GPRELB
BFD_RELOC_RL78_GPRELW
BFD_RELOC_RL78_GPRELL
BFD_RELOC_RL78_SYM
BFD_RELOC_RL78_OP_SUBTRACT
BFD_RELOC_RL78_OP_NEG
BFD_RELOC_RL78_OP_AND
BFD_RELOC_RL78_OP_SHRA
BFD_RELOC_RL78_ABS8
BFD_RELOC_RL78_ABS16
BFD_RELOC_RL78_ABS16_REV
BFD_RELOC_RL78_ABS32
BFD_RELOC_RL78_ABS32_REV
BFD_RELOC_RL78_ABS16U
BFD_RELOC_RL78_ABS16UW
BFD_RELOC_RL78_ABS16UL
BFD_RELOC_RL78_RELAX
BFD_RELOC_RL78_HI16
BFD_RELOC_RL78_HI8
BFD_RELOC_RL78_LO16
BFD_RELOC_RL78_CODE
BFD_RELOC_RL78_SADDR

Renesas RL78 Relocations.

BFD_RELOC_RX_NEG8
BFD_RELOC_RX_NEG16
BFD_RELOC_RX_NEG24
BFD_RELOC_RX_NEG32
BFD_RELOC_RX_16_OP
BFD_RELOC_RX_24_OP
BFD_RELOC_RX_32_OP
BFD_RELOC_RX_8U
BFD_RELOC_RX_16U
BFD_RELOC_RX_24U
BFD_RELOC_RX_DIR3U_PCREL
BFD_RELOC_RX_DIFF
BFD_RELOC_RX_GPRELB
BFD_RELOC_RX_GPRELW
BFD_RELOC_RX_GPRELL
BFD_RELOC_RX_SYM
BFD_RELOC_RX_OP_SUBTRACT
BFD_RELOC_RX_OP_NEG
BFD_RELOC_RX_ABS8
BFD_RELOC_RX_ABS16

`BFD_RELOC_RX_ABS16_REV`
`BFD_RELOC_RX_ABS32`
`BFD_RELOC_RX_ABS32_REV`
`BFD_RELOC_RX_ABS16U`
`BFD_RELOC_RX_ABS16UW`
`BFD_RELOC_RX_ABS16UL`
`BFD_RELOC_RX_RELAX`
: Renesas RX Relocations.

`BFD_RELOC_390_12`
: Direct 12 bit.

`BFD_RELOC_390_GOT12`
: 12 bit GOT offset.

`BFD_RELOC_390_PLT32`
: 32 bit PC relative PLT address.

`BFD_RELOC_390_COPY`
: Copy symbol at runtime.

`BFD_RELOC_390_GLOB_DAT`
: Create GOT entry.

`BFD_RELOC_390_JMP_SLOT`
: Create PLT entry.

`BFD_RELOC_390_RELATIVE`
: Adjust by program base.

`BFD_RELOC_390_GOTPC`
: 32 bit PC relative offset to GOT.

`BFD_RELOC_390_GOT16`
: 16 bit GOT offset.

`BFD_RELOC_390_PC12DBL`
: PC relative 12 bit shifted by 1.

`BFD_RELOC_390_PLT12DBL`
: 12 bit PC rel. PLT shifted by 1.

`BFD_RELOC_390_PC16DBL`
: PC relative 16 bit shifted by 1.

`BFD_RELOC_390_PLT16DBL`
: 16 bit PC rel. PLT shifted by 1.

`BFD_RELOC_390_PC24DBL`
: PC relative 24 bit shifted by 1.

`BFD_RELOC_390_PLT24DBL`
: 24 bit PC rel. PLT shifted by 1.

`BFD_RELOC_390_PC32DBL`
: PC relative 32 bit shifted by 1.

`BFD_RELOC_390_PLT32DBL`
: 32 bit PC rel. PLT shifted by 1.

`BFD_RELOC_390_GOTPCDBL`
: 32 bit PC rel. GOT shifted by 1.

`BFD_RELOC_390_GOT64`
: 64 bit GOT offset.

`BFD_RELOC_390_PLT64`
: 64 bit PC relative PLT address.

`BFD_RELOC_390_GOTENT`
: 32 bit rel. offset to GOT entry.

`BFD_RELOC_390_GOTOFF64`
: 64 bit offset to GOT.

`BFD_RELOC_390_GOTPLT12`
: 12-bit offset to symbol-entry within GOT, with PLT handling.

`BFD_RELOC_390_GOTPLT16`
: 16-bit offset to symbol-entry within GOT, with PLT handling.

`BFD_RELOC_390_GOTPLT32`
: 32-bit offset to symbol-entry within GOT, with PLT handling.

`BFD_RELOC_390_GOTPLT64`
: 64-bit offset to symbol-entry within GOT, with PLT handling.

`BFD_RELOC_390_GOTPLTENT`
: 32-bit rel. offset to symbol-entry within GOT, with PLT handling.

`BFD_RELOC_390_PLTOFF16`
: 16-bit rel. offset from the GOT to a PLT entry.

`BFD_RELOC_390_PLTOFF32`
: 32-bit rel. offset from the GOT to a PLT entry.

`BFD_RELOC_390_PLTOFF64`
: 64-bit rel. offset from the GOT to a PLT entry.

`BFD_RELOC_390_TLS_LOAD`
`BFD_RELOC_390_TLS_GDCALL`
`BFD_RELOC_390_TLS_LDCALL`
`BFD_RELOC_390_TLS_GD32`

`BFD_RELOC_390_TLS_GD64`
`BFD_RELOC_390_TLS_GOTIE12`
`BFD_RELOC_390_TLS_GOTIE32`
`BFD_RELOC_390_TLS_GOTIE64`
`BFD_RELOC_390_TLS_LDM32`
`BFD_RELOC_390_TLS_LDM64`
`BFD_RELOC_390_TLS_IE32`
`BFD_RELOC_390_TLS_IE64`
`BFD_RELOC_390_TLS_IEENT`
`BFD_RELOC_390_TLS_LE32`
`BFD_RELOC_390_TLS_LE64`
`BFD_RELOC_390_TLS_LDO32`
`BFD_RELOC_390_TLS_LDO64`
`BFD_RELOC_390_TLS_DTPMOD`
`BFD_RELOC_390_TLS_DTPOFF`
`BFD_RELOC_390_TLS_TPOFF`
: s390 tls relocations.

`BFD_RELOC_390_20`
`BFD_RELOC_390_GOT20`
`BFD_RELOC_390_GOTPLT20`
`BFD_RELOC_390_TLS_GOTIE20`
: Long displacement extension.

`BFD_RELOC_390_IRELATIVE`
: STT_GNU_IFUNC relocation.

`BFD_RELOC_SCORE_GPREL15`
: Score relocations. Low 16 bit for load/store.

`BFD_RELOC_SCORE_DUMMY2`
`BFD_RELOC_SCORE_JMP`
: This is a 24-bit reloc with the right 1 bit assumed to be 0.

`BFD_RELOC_SCORE_BRANCH`
: This is a 19-bit reloc with the right 1 bit assumed to be 0.

`BFD_RELOC_SCORE_IMM30`
: This is a 32-bit reloc for 48-bit instructions.

`BFD_RELOC_SCORE_IMM32`
: This is a 32-bit reloc for 48-bit instructions.

`BFD_RELOC_SCORE16_JMP`
: This is a 11-bit reloc with the right 1 bit assumed to be 0.

`BFD_RELOC_SCORE16_BRANCH`
: This is a 8-bit reloc with the right 1 bit assumed to be 0.

`BFD_RELOC_SCORE_BCMP`
: This is a 9-bit reloc with the right 1 bit assumed to be 0.

`BFD_RELOC_SCORE_GOT15`
`BFD_RELOC_SCORE_GOT_LO16`
`BFD_RELOC_SCORE_CALL15`
`BFD_RELOC_SCORE_DUMMY_HI16`
Undocumented Score relocs.

`BFD_RELOC_IP2K_FR9`
Scenix IP2K - 9-bit register number / data address.

`BFD_RELOC_IP2K_BANK`
Scenix IP2K - 4-bit register/data bank number.

`BFD_RELOC_IP2K_ADDR16CJP`
Scenix IP2K - low 13 bits of instruction word address.

`BFD_RELOC_IP2K_PAGE3`
Scenix IP2K - high 3 bits of instruction word address.

`BFD_RELOC_IP2K_LO8DATA`
`BFD_RELOC_IP2K_HI8DATA`
`BFD_RELOC_IP2K_EX8DATA`
Scenix IP2K - ext/low/high 8 bits of data address.

`BFD_RELOC_IP2K_LO8INSN`
`BFD_RELOC_IP2K_HI8INSN`
Scenix IP2K - low/high 8 bits of instruction word address.

`BFD_RELOC_IP2K_PC_SKIP`
Scenix IP2K - even/odd PC modifier to modify snb pcl.0.

`BFD_RELOC_IP2K_TEXT`
Scenix IP2K - 16 bit word address in text section.

`BFD_RELOC_IP2K_FR_OFFSET`
Scenix IP2K - 7-bit sp or dp offset.

`BFD_RELOC_VPE4KMATH_DATA`
`BFD_RELOC_VPE4KMATH_INSN`
Scenix VPE4K coprocessor - data/insn-space addressing.

`BFD_RELOC_VTABLE_INHERIT`
`BFD_RELOC_VTABLE_ENTRY`
These two relocations are used by the linker to determine which of the entries in a C++ virtual function table are actually used. When the –gc-sections option is given, the linker will zero out the entries that are not used, so that the code for those functions need not be included in the output.

VTABLE_INHERIT is a zero-space relocation used to describe to the linker the inheritance tree of a C++ virtual function table. The relocation's symbol should be the parent class' vtable, and the relocation should be located at the child vtable.

VTABLE_ENTRY is a zero-space relocation that describes the use of a virtual function table entry. The reloc's symbol should refer to the table of the class mentioned

in the code. Off of that base, an offset describes the entry that is being used. For Rela hosts, this offset is stored in the reloc's addend. For Rel hosts, we are forced to put this offset in the reloc's section offset.

```
BFD_RELOC_IA64_IMM14
BFD_RELOC_IA64_IMM22
BFD_RELOC_IA64_IMM64
BFD_RELOC_IA64_DIR32MSB
BFD_RELOC_IA64_DIR32LSB
BFD_RELOC_IA64_DIR64MSB
BFD_RELOC_IA64_DIR64LSB
BFD_RELOC_IA64_GPREL22
BFD_RELOC_IA64_GPREL64I
BFD_RELOC_IA64_GPREL32MSB
BFD_RELOC_IA64_GPREL32LSB
BFD_RELOC_IA64_GPREL64MSB
BFD_RELOC_IA64_GPREL64LSB
BFD_RELOC_IA64_LTOFF22
BFD_RELOC_IA64_LTOFF64I
BFD_RELOC_IA64_PLTOFF22
BFD_RELOC_IA64_PLTOFF64I
BFD_RELOC_IA64_PLTOFF64MSB
BFD_RELOC_IA64_PLTOFF64LSB
BFD_RELOC_IA64_FPTR64I
BFD_RELOC_IA64_FPTR32MSB
BFD_RELOC_IA64_FPTR32LSB
BFD_RELOC_IA64_FPTR64MSB
BFD_RELOC_IA64_FPTR64LSB
BFD_RELOC_IA64_PCREL21B
BFD_RELOC_IA64_PCREL21BI
BFD_RELOC_IA64_PCREL21M
BFD_RELOC_IA64_PCREL21F
BFD_RELOC_IA64_PCREL22
BFD_RELOC_IA64_PCREL60B
BFD_RELOC_IA64_PCREL64I
BFD_RELOC_IA64_PCREL32MSB
BFD_RELOC_IA64_PCREL32LSB
BFD_RELOC_IA64_PCREL64MSB
BFD_RELOC_IA64_PCREL64LSB
BFD_RELOC_IA64_LTOFF_FPTR22
BFD_RELOC_IA64_LTOFF_FPTR64I
BFD_RELOC_IA64_LTOFF_FPTR32MSB
BFD_RELOC_IA64_LTOFF_FPTR32LSB
BFD_RELOC_IA64_LTOFF_FPTR64MSB
BFD_RELOC_IA64_LTOFF_FPTR64LSB
BFD_RELOC_IA64_SEGREL32MSB
BFD_RELOC_IA64_SEGREL32LSB
```

BFD_RELOC_IA64_SEGREL64MSB
BFD_RELOC_IA64_SEGREL64LSB
BFD_RELOC_IA64_SECREL32MSB
BFD_RELOC_IA64_SECREL32LSB
BFD_RELOC_IA64_SECREL64MSB
BFD_RELOC_IA64_SECREL64LSB
BFD_RELOC_IA64_REL32MSB
BFD_RELOC_IA64_REL32LSB
BFD_RELOC_IA64_REL64MSB
BFD_RELOC_IA64_REL64LSB
BFD_RELOC_IA64_LTV32MSB
BFD_RELOC_IA64_LTV32LSB
BFD_RELOC_IA64_LTV64MSB
BFD_RELOC_IA64_LTV64LSB
BFD_RELOC_IA64_IPLTMSB
BFD_RELOC_IA64_IPLTLSB
BFD_RELOC_IA64_COPY
BFD_RELOC_IA64_LTOFF22X
BFD_RELOC_IA64_LDXMOV
BFD_RELOC_IA64_TPREL14
BFD_RELOC_IA64_TPREL22
BFD_RELOC_IA64_TPREL64I
BFD_RELOC_IA64_TPREL64MSB
BFD_RELOC_IA64_TPREL64LSB
BFD_RELOC_IA64_LTOFF_TPREL22
BFD_RELOC_IA64_DTPMOD64MSB
BFD_RELOC_IA64_DTPMOD64LSB
BFD_RELOC_IA64_LTOFF_DTPMOD22
BFD_RELOC_IA64_DTPREL14
BFD_RELOC_IA64_DTPREL22
BFD_RELOC_IA64_DTPREL64I
BFD_RELOC_IA64_DTPREL32MSB
BFD_RELOC_IA64_DTPREL32LSB
BFD_RELOC_IA64_DTPREL64MSB
BFD_RELOC_IA64_DTPREL64LSB
BFD_RELOC_IA64_LTOFF_DTPREL22
: Intel IA64 Relocations.

BFD_RELOC_M68HC11_HI8
: Motorola 68HC11 reloc. This is the 8 bit high part of an absolute address.

BFD_RELOC_M68HC11_LO8
: Motorola 68HC11 reloc. This is the 8 bit low part of an absolute address.

BFD_RELOC_M68HC11_3B
: Motorola 68HC11 reloc. This is the 3 bit of a value.

`BFD_RELOC_M68HC11_RL_JUMP`
: Motorola 68HC11 reloc. This reloc marks the beginning of a jump/call instruction. It is used for linker relaxation to correctly identify beginning of instruction and change some branches to use PC-relative addressing mode.

`BFD_RELOC_M68HC11_RL_GROUP`
: Motorola 68HC11 reloc. This reloc marks a group of several instructions that gcc generates and for which the linker relaxation pass can modify and/or remove some of them.

`BFD_RELOC_M68HC11_LO16`
: Motorola 68HC11 reloc. This is the 16-bit lower part of an address. It is used for 'call' instruction to specify the symbol address without any special transformation (due to memory bank window).

`BFD_RELOC_M68HC11_PAGE`
: Motorola 68HC11 reloc. This is a 8-bit reloc that specifies the page number of an address. It is used by 'call' instruction to specify the page number of the symbol.

`BFD_RELOC_M68HC11_24`
: Motorola 68HC11 reloc. This is a 24-bit reloc that represents the address with a 16-bit value and a 8-bit page number. The symbol address is transformed to follow the 16K memory bank of 68HC12 (seen as mapped in the window).

`BFD_RELOC_M68HC12_5B`
: Motorola 68HC12 reloc. This is the 5 bits of a value.

`BFD_RELOC_XGATE_RL_JUMP`
: Freescale XGATE reloc. This reloc marks the beginning of a bra/jal instruction.

`BFD_RELOC_XGATE_RL_GROUP`
: Freescale XGATE reloc. This reloc marks a group of several instructions that gcc generates and for which the linker relaxation pass can modify and/or remove some of them.

`BFD_RELOC_XGATE_LO16`
: Freescale XGATE reloc. This is the 16-bit lower part of an address. It is used for the '16-bit' instructions.

`BFD_RELOC_XGATE_GPAGE`
: Freescale XGATE reloc.

`BFD_RELOC_XGATE_24`
: Freescale XGATE reloc.

`BFD_RELOC_XGATE_PCREL_9`
: Freescale XGATE reloc. This is a 9-bit pc-relative reloc.

`BFD_RELOC_XGATE_PCREL_10`
: Freescale XGATE reloc. This is a 10-bit pc-relative reloc.

`BFD_RELOC_XGATE_IMM8_LO`
: Freescale XGATE reloc. This is the 16-bit lower part of an address. It is used for the '16-bit' instructions.

`BFD_RELOC_XGATE_IMM8_HI`
: Freescale XGATE reloc. This is the 16-bit higher part of an address. It is used for the '16-bit' instructions.

`BFD_RELOC_XGATE_IMM3`
: Freescale XGATE reloc. This is a 3-bit pc-relative reloc.

`BFD_RELOC_XGATE_IMM4`
: Freescale XGATE reloc. This is a 4-bit pc-relative reloc.

`BFD_RELOC_XGATE_IMM5`
: Freescale XGATE reloc. This is a 5-bit pc-relative reloc.

`BFD_RELOC_M68HC12_9B`
: Motorola 68HC12 reloc. This is the 9 bits of a value.

`BFD_RELOC_M68HC12_16B`
: Motorola 68HC12 reloc. This is the 16 bits of a value.

`BFD_RELOC_M68HC12_9_PCREL`
: Motorola 68HC12/XGATE reloc. This is a PCREL9 branch.

`BFD_RELOC_M68HC12_10_PCREL`
: Motorola 68HC12/XGATE reloc. This is a PCREL10 branch.

`BFD_RELOC_M68HC12_LO8XG`
: Motorola 68HC12/XGATE reloc. This is the 8 bit low part of an absolute address and immediately precedes a matching HI8XG part.

`BFD_RELOC_M68HC12_HI8XG`
: Motorola 68HC12/XGATE reloc. This is the 8 bit high part of an absolute address and immediately follows a matching LO8XG part.

`BFD_RELOC_S12Z_15_PCREL`
: Freescale S12Z reloc. This is a 15 bit relative address. If the most significant bits are all zero then it may be truncated to 8 bits.

`BFD_RELOC_CR16_NUM8`
`BFD_RELOC_CR16_NUM16`
`BFD_RELOC_CR16_NUM32`
`BFD_RELOC_CR16_NUM32a`
`BFD_RELOC_CR16_REGREL0`
`BFD_RELOC_CR16_REGREL4`
`BFD_RELOC_CR16_REGREL4a`
`BFD_RELOC_CR16_REGREL14`
`BFD_RELOC_CR16_REGREL14a`
`BFD_RELOC_CR16_REGREL16`

BFD_RELOC_CR16_REGREL20
BFD_RELOC_CR16_REGREL20a
BFD_RELOC_CR16_ABS20
BFD_RELOC_CR16_ABS24
BFD_RELOC_CR16_IMM4
BFD_RELOC_CR16_IMM8
BFD_RELOC_CR16_IMM16
BFD_RELOC_CR16_IMM20
BFD_RELOC_CR16_IMM24
BFD_RELOC_CR16_IMM32
BFD_RELOC_CR16_IMM32a
BFD_RELOC_CR16_DISP4
BFD_RELOC_CR16_DISP8
BFD_RELOC_CR16_DISP16
BFD_RELOC_CR16_DISP20
BFD_RELOC_CR16_DISP24
BFD_RELOC_CR16_DISP24a
BFD_RELOC_CR16_SWITCH8
BFD_RELOC_CR16_SWITCH16
BFD_RELOC_CR16_SWITCH32
BFD_RELOC_CR16_GOT_REGREL20
BFD_RELOC_CR16_GOTC_REGREL20
BFD_RELOC_CR16_GLOB_DAT
NS CR16 Relocations.

BFD_RELOC_CRX_REL4
BFD_RELOC_CRX_REL8
BFD_RELOC_CRX_REL8_CMP
BFD_RELOC_CRX_REL16
BFD_RELOC_CRX_REL24
BFD_RELOC_CRX_REL32
BFD_RELOC_CRX_REGREL12
BFD_RELOC_CRX_REGREL22
BFD_RELOC_CRX_REGREL28
BFD_RELOC_CRX_REGREL32
BFD_RELOC_CRX_ABS16
BFD_RELOC_CRX_ABS32
BFD_RELOC_CRX_NUM8
BFD_RELOC_CRX_NUM16
BFD_RELOC_CRX_NUM32
BFD_RELOC_CRX_IMM16
BFD_RELOC_CRX_IMM32
BFD_RELOC_CRX_SWITCH8
BFD_RELOC_CRX_SWITCH16
BFD_RELOC_CRX_SWITCH32
NS CRX Relocations.

`BFD_RELOC_CRIS_BDISP8`
`BFD_RELOC_CRIS_UNSIGNED_5`
`BFD_RELOC_CRIS_SIGNED_6`
`BFD_RELOC_CRIS_UNSIGNED_6`
`BFD_RELOC_CRIS_SIGNED_8`
`BFD_RELOC_CRIS_UNSIGNED_8`
`BFD_RELOC_CRIS_SIGNED_16`
`BFD_RELOC_CRIS_UNSIGNED_16`
`BFD_RELOC_CRIS_LAPCQ_OFFSET`
`BFD_RELOC_CRIS_UNSIGNED_4`
: These relocs are only used within the CRIS assembler. They are not (at present) written to any object files.

`BFD_RELOC_CRIS_COPY`
`BFD_RELOC_CRIS_GLOB_DAT`
`BFD_RELOC_CRIS_JUMP_SLOT`
`BFD_RELOC_CRIS_RELATIVE`
: Relocs used in ELF shared libraries for CRIS.

`BFD_RELOC_CRIS_32_GOT`
: 32-bit offset to symbol-entry within GOT.

`BFD_RELOC_CRIS_16_GOT`
: 16-bit offset to symbol-entry within GOT.

`BFD_RELOC_CRIS_32_GOTPLT`
: 32-bit offset to symbol-entry within GOT, with PLT handling.

`BFD_RELOC_CRIS_16_GOTPLT`
: 16-bit offset to symbol-entry within GOT, with PLT handling.

`BFD_RELOC_CRIS_32_GOTREL`
: 32-bit offset to symbol, relative to GOT.

`BFD_RELOC_CRIS_32_PLT_GOTREL`
: 32-bit offset to symbol with PLT entry, relative to GOT.

`BFD_RELOC_CRIS_32_PLT_PCREL`
: 32-bit offset to symbol with PLT entry, relative to this relocation.

`BFD_RELOC_CRIS_32_GOT_GD`
`BFD_RELOC_CRIS_16_GOT_GD`
`BFD_RELOC_CRIS_32_GD`
`BFD_RELOC_CRIS_DTP`
`BFD_RELOC_CRIS_32_DTPREL`
`BFD_RELOC_CRIS_16_DTPREL`
`BFD_RELOC_CRIS_32_GOT_TPREL`
`BFD_RELOC_CRIS_16_GOT_TPREL`
`BFD_RELOC_CRIS_32_TPREL`
`BFD_RELOC_CRIS_16_TPREL`

BFD_RELOC_CRIS_DTPMOD
BFD_RELOC_CRIS_32_IE
Relocs used in TLS code for CRIS.

BFD_RELOC_OR1K_REL_26
BFD_RELOC_OR1K_SLO16
BFD_RELOC_OR1K_PCREL_PG21
BFD_RELOC_OR1K_LO13
BFD_RELOC_OR1K_SLO13
BFD_RELOC_OR1K_GOTPC_HI16
BFD_RELOC_OR1K_GOTPC_LO16
BFD_RELOC_OR1K_GOT_AHI16
BFD_RELOC_OR1K_GOT16
BFD_RELOC_OR1K_GOT_PG21
BFD_RELOC_OR1K_GOT_LO13
BFD_RELOC_OR1K_PLT26
BFD_RELOC_OR1K_PLTA26
BFD_RELOC_OR1K_GOTOFF_SLO16
BFD_RELOC_OR1K_COPY
BFD_RELOC_OR1K_GLOB_DAT
BFD_RELOC_OR1K_JMP_SLOT
BFD_RELOC_OR1K_RELATIVE
BFD_RELOC_OR1K_TLS_GD_HI16
BFD_RELOC_OR1K_TLS_GD_LO16
BFD_RELOC_OR1K_TLS_GD_PG21
BFD_RELOC_OR1K_TLS_GD_LO13
BFD_RELOC_OR1K_TLS_LDM_HI16
BFD_RELOC_OR1K_TLS_LDM_LO16
BFD_RELOC_OR1K_TLS_LDM_PG21
BFD_RELOC_OR1K_TLS_LDM_LO13
BFD_RELOC_OR1K_TLS_LDO_HI16
BFD_RELOC_OR1K_TLS_LDO_LO16
BFD_RELOC_OR1K_TLS_IE_HI16
BFD_RELOC_OR1K_TLS_IE_AHI16
BFD_RELOC_OR1K_TLS_IE_LO16
BFD_RELOC_OR1K_TLS_IE_PG21
BFD_RELOC_OR1K_TLS_IE_LO13
BFD_RELOC_OR1K_TLS_LE_HI16
BFD_RELOC_OR1K_TLS_LE_AHI16
BFD_RELOC_OR1K_TLS_LE_LO16
BFD_RELOC_OR1K_TLS_LE_SLO16
BFD_RELOC_OR1K_TLS_TPOFF
BFD_RELOC_OR1K_TLS_DTPOFF
BFD_RELOC_OR1K_TLS_DTPMOD
OpenRISC 1000 Relocations.

BFD_RELOC_H8_DIR16A8
BFD_RELOC_H8_DIR16R8

`BFD_RELOC_H8_DIR24A8`
`BFD_RELOC_H8_DIR24R8`
`BFD_RELOC_H8_DIR32A16`
`BFD_RELOC_H8_DISP32A16`
: H8 elf Relocations.

`BFD_RELOC_XSTORMY16_REL_12`
`BFD_RELOC_XSTORMY16_12`
`BFD_RELOC_XSTORMY16_24`
`BFD_RELOC_XSTORMY16_FPTR16`
: Sony Xstormy16 Relocations.

`BFD_RELOC_RELC`
: Self-describing complex relocations.

`BFD_RELOC_VAX_GLOB_DAT`
`BFD_RELOC_VAX_JMP_SLOT`
`BFD_RELOC_VAX_RELATIVE`
: Relocations used by VAX ELF.

`BFD_RELOC_MT_PC16`
: Morpho MT - 16 bit immediate relocation.

`BFD_RELOC_MT_HI16`
: Morpho MT - Hi 16 bits of an address.

`BFD_RELOC_MT_LO16`
: Morpho MT - Low 16 bits of an address.

`BFD_RELOC_MT_GNU_VTINHERIT`
: Morpho MT - Used to tell the linker which vtable entries are used.

`BFD_RELOC_MT_GNU_VTENTRY`
: Morpho MT - Used to tell the linker which vtable entries are used.

`BFD_RELOC_MT_PCINSN8`
: Morpho MT - 8 bit immediate relocation.

`BFD_RELOC_MSP430_10_PCREL`
`BFD_RELOC_MSP430_16_PCREL`
`BFD_RELOC_MSP430_16`
`BFD_RELOC_MSP430_16_PCREL_BYTE`
`BFD_RELOC_MSP430_16_BYTE`
`BFD_RELOC_MSP430_2X_PCREL`
`BFD_RELOC_MSP430_RL_PCREL`
`BFD_RELOC_MSP430_ABS8`
`BFD_RELOC_MSP430X_PCR20_EXT_SRC`
`BFD_RELOC_MSP430X_PCR20_EXT_DST`
`BFD_RELOC_MSP430X_PCR20_EXT_ODST`
`BFD_RELOC_MSP430X_ABS20_EXT_SRC`

BFD_RELOC_MSP430X_ABS20_EXT_DST
BFD_RELOC_MSP430X_ABS20_EXT_ODST
BFD_RELOC_MSP430X_ABS20_ADR_SRC
BFD_RELOC_MSP430X_ABS20_ADR_DST
BFD_RELOC_MSP430X_PCR16
BFD_RELOC_MSP430X_PCR20_CALL
BFD_RELOC_MSP430X_ABS16
BFD_RELOC_MSP430_ABS_HI16
BFD_RELOC_MSP430_PREL31
BFD_RELOC_MSP430_SYM_DIFF
BFD_RELOC_MSP430_SET_ULEB128
BFD_RELOC_MSP430_SUB_ULEB128
: msp430 specific relocation codes.

BFD_RELOC_PRU_U16
: PRU LDI 16-bit unsigned data-memory relocation.

BFD_RELOC_PRU_U16_PMEMIMM
: PRU LDI 16-bit unsigned instruction-memory relocation.

BFD_RELOC_PRU_LDI32
: PRU relocation for two consecutive LDI load instructions that load a 32 bit value into a register. If the higher bits are all zero, then the second instruction may be relaxed.

BFD_RELOC_PRU_S10_PCREL
: PRU QBBx 10-bit signed PC-relative relocation.

BFD_RELOC_PRU_U8_PCREL
: PRU 8-bit unsigned relocation used for the LOOP instruction.

BFD_RELOC_PRU_32_PMEM
BFD_RELOC_PRU_16_PMEM
: PRU Program Memory relocations. Used to convert from byte addressing to 32-bit word addressing.

BFD_RELOC_PRU_GNU_DIFF8
BFD_RELOC_PRU_GNU_DIFF16
BFD_RELOC_PRU_GNU_DIFF32
BFD_RELOC_PRU_GNU_DIFF16_PMEM
BFD_RELOC_PRU_GNU_DIFF32_PMEM
: PRU relocations to mark the difference of two local symbols. These are only needed to support linker relaxation and can be ignored when not relaxing. The field is set to the value of the difference assuming no relaxation. The relocation encodes the position of the second symbol so the linker can determine whether to adjust the field value. The PMEM variants encode the word difference, instead of byte difference between symbols.

BFD_RELOC_IQ2000_OFFSET_16
BFD_RELOC_IQ2000_OFFSET_21
BFD_RELOC_IQ2000_UHI16
: IQ2000 Relocations.

`BFD_RELOC_XTENSA_RTLD`
: Special Xtensa relocation used only by PLT entries in ELF shared objects to indicate that the runtime linker should set the value to one of its own internal functions or data structures.

`BFD_RELOC_XTENSA_GLOB_DAT`
`BFD_RELOC_XTENSA_JMP_SLOT`
`BFD_RELOC_XTENSA_RELATIVE`
: Xtensa relocations for ELF shared objects.

`BFD_RELOC_XTENSA_PLT`
: Xtensa relocation used in ELF object files for symbols that may require PLT entries. Otherwise, this is just a generic 32-bit relocation.

`BFD_RELOC_XTENSA_DIFF8`
`BFD_RELOC_XTENSA_DIFF16`
`BFD_RELOC_XTENSA_DIFF32`
: Xtensa relocations for backward compatibility. These have been replaced by BFD_RELOC_XTENSA_PDIFF and BFD_RELOC_XTENSA_NDIFF. Xtensa relocations to mark the difference of two local symbols. These are only needed to support linker relaxation and can be ignored when not relaxing. The field is set to the value of the difference assuming no relaxation. The relocation encodes the position of the first symbol so the linker can determine whether to adjust the field value.

`BFD_RELOC_XTENSA_SLOT0_OP`
`BFD_RELOC_XTENSA_SLOT1_OP`
`BFD_RELOC_XTENSA_SLOT2_OP`
`BFD_RELOC_XTENSA_SLOT3_OP`
`BFD_RELOC_XTENSA_SLOT4_OP`
`BFD_RELOC_XTENSA_SLOT5_OP`
`BFD_RELOC_XTENSA_SLOT6_OP`
`BFD_RELOC_XTENSA_SLOT7_OP`
`BFD_RELOC_XTENSA_SLOT8_OP`
`BFD_RELOC_XTENSA_SLOT9_OP`
`BFD_RELOC_XTENSA_SLOT10_OP`
`BFD_RELOC_XTENSA_SLOT11_OP`
`BFD_RELOC_XTENSA_SLOT12_OP`
`BFD_RELOC_XTENSA_SLOT13_OP`
`BFD_RELOC_XTENSA_SLOT14_OP`
: Generic Xtensa relocations for instruction operands. Only the slot number is encoded in the relocation. The relocation applies to the last PC-relative immediate operand, or if there are no PC-relative immediates, to the last immediate operand.

`BFD_RELOC_XTENSA_SLOT0_ALT`
`BFD_RELOC_XTENSA_SLOT1_ALT`
`BFD_RELOC_XTENSA_SLOT2_ALT`
`BFD_RELOC_XTENSA_SLOT3_ALT`
`BFD_RELOC_XTENSA_SLOT4_ALT`

BFD_RELOC_XTENSA_SLOT5_ALT
BFD_RELOC_XTENSA_SLOT6_ALT
BFD_RELOC_XTENSA_SLOT7_ALT
BFD_RELOC_XTENSA_SLOT8_ALT
BFD_RELOC_XTENSA_SLOT9_ALT
BFD_RELOC_XTENSA_SLOT10_ALT
BFD_RELOC_XTENSA_SLOT11_ALT
BFD_RELOC_XTENSA_SLOT12_ALT
BFD_RELOC_XTENSA_SLOT13_ALT
BFD_RELOC_XTENSA_SLOT14_ALT

Alternate Xtensa relocations. Only the slot is encoded in the relocation. The meaning of these relocations is opcode-specific.

BFD_RELOC_XTENSA_OP0
BFD_RELOC_XTENSA_OP1
BFD_RELOC_XTENSA_OP2

Xtensa relocations for backward compatibility. These have all been replaced by BFD_RELOC_XTENSA_SLOT0_OP.

BFD_RELOC_XTENSA_ASM_EXPAND

Xtensa relocation to mark that the assembler expanded the instructions from an original target. The expansion size is encoded in the reloc size.

BFD_RELOC_XTENSA_ASM_SIMPLIFY

Xtensa relocation to mark that the linker should simplify assembler-expanded instructions. This is commonly used internally by the linker after analysis of a BFD_RELOC_XTENSA_ASM_EXPAND.

BFD_RELOC_XTENSA_TLSDESC_FN
BFD_RELOC_XTENSA_TLSDESC_ARG
BFD_RELOC_XTENSA_TLS_DTPOFF
BFD_RELOC_XTENSA_TLS_TPOFF
BFD_RELOC_XTENSA_TLS_FUNC
BFD_RELOC_XTENSA_TLS_ARG
BFD_RELOC_XTENSA_TLS_CALL

Xtensa TLS relocations.

BFD_RELOC_XTENSA_PDIFF8
BFD_RELOC_XTENSA_PDIFF16
BFD_RELOC_XTENSA_PDIFF32
BFD_RELOC_XTENSA_NDIFF8
BFD_RELOC_XTENSA_NDIFF16
BFD_RELOC_XTENSA_NDIFF32

Xtensa relocations to mark the difference of two local symbols. These are only needed to support linker relaxation and can be ignored when not relaxing. The field is set to the value of the difference assuming no relaxation. The relocation encodes the position of the subtracted symbol so the linker can determine whether to adjust the field value. PDIFF relocations are used for positive differences, NDIFF relocations

are used for negative differences. The difference value is treated as unsigned with these relocation types, giving full 8/16 value ranges.

`BFD_RELOC_Z80_DISP8`
8 bit signed offset in (ix+d) or (iy+d).

`BFD_RELOC_Z80_BYTE0`
First 8 bits of multibyte (32, 24 or 16 bit) value.

`BFD_RELOC_Z80_BYTE1`
Second 8 bits of multibyte (32, 24 or 16 bit) value.

`BFD_RELOC_Z80_BYTE2`
Third 8 bits of multibyte (32 or 24 bit) value.

`BFD_RELOC_Z80_BYTE3`
Fourth 8 bits of multibyte (32 bit) value.

`BFD_RELOC_Z80_WORD0`
Lowest 16 bits of multibyte (32 or 24 bit) value.

`BFD_RELOC_Z80_WORD1`
Highest 16 bits of multibyte (32 or 24 bit) value.

`BFD_RELOC_Z80_16_BE`
Like BFD_RELOC_16 but big-endian.

`BFD_RELOC_Z8K_DISP7`
DJNZ offset.

`BFD_RELOC_Z8K_CALLR`
CALR offset.

`BFD_RELOC_Z8K_IMM4L`
4 bit value.

`BFD_RELOC_LM32_CALL`
`BFD_RELOC_LM32_BRANCH`
`BFD_RELOC_LM32_16_GOT`
`BFD_RELOC_LM32_GOTOFF_HI16`
`BFD_RELOC_LM32_GOTOFF_LO16`
`BFD_RELOC_LM32_COPY`
`BFD_RELOC_LM32_GLOB_DAT`
`BFD_RELOC_LM32_JMP_SLOT`
`BFD_RELOC_LM32_RELATIVE`
Lattice Mico32 relocations.

`BFD_RELOC_MACH_O_SECTDIFF`
Difference between two section addreses. Must be followed by a BFD_RELOC_MACH_O_PAIR.

`BFD_RELOC_MACH_O_LOCAL_SECTDIFF`
: Like BFD_RELOC_MACH_O_SECTDIFF but with a local symbol.

`BFD_RELOC_MACH_O_PAIR`
: Pair of relocation. Contains the first symbol.

`BFD_RELOC_MACH_O_SUBTRACTOR32`
: Symbol will be substracted. Must be followed by a BFD_RELOC_32.

`BFD_RELOC_MACH_O_SUBTRACTOR64`
: Symbol will be substracted. Must be followed by a BFD_RELOC_64.

`BFD_RELOC_MACH_O_X86_64_BRANCH32`
`BFD_RELOC_MACH_O_X86_64_BRANCH8`
: PCREL relocations. They are marked as branch to create PLT entry if required.

`BFD_RELOC_MACH_O_X86_64_GOT`
: Used when referencing a GOT entry.

`BFD_RELOC_MACH_O_X86_64_GOT_LOAD`
: Used when loading a GOT entry with movq. It is specially marked so that the linker could optimize the movq to a leaq if possible.

`BFD_RELOC_MACH_O_X86_64_PCREL32_1`
: Same as BFD_RELOC_32_PCREL but with an implicit -1 addend.

`BFD_RELOC_MACH_O_X86_64_PCREL32_2`
: Same as BFD_RELOC_32_PCREL but with an implicit -2 addend.

`BFD_RELOC_MACH_O_X86_64_PCREL32_4`
: Same as BFD_RELOC_32_PCREL but with an implicit -4 addend.

`BFD_RELOC_MACH_O_X86_64_TLV`
: Used when referencing a TLV entry.

`BFD_RELOC_MACH_O_ARM64_ADDEND`
: Addend for PAGE or PAGEOFF.

`BFD_RELOC_MACH_O_ARM64_GOT_LOAD_PAGE21`
: Relative offset to page of GOT slot.

`BFD_RELOC_MACH_O_ARM64_GOT_LOAD_PAGEOFF12`
: Relative offset within page of GOT slot.

`BFD_RELOC_MACH_O_ARM64_POINTER_TO_GOT`
: Address of a GOT entry.

`BFD_RELOC_MICROBLAZE_32_LO`
: This is a 32 bit reloc for the microblaze that stores the low 16 bits of a value.

`BFD_RELOC_MICROBLAZE_32_LO_PCREL`
: This is a 32 bit pc-relative reloc for the microblaze that stores the low 16 bits of a value.

`BFD_RELOC_MICROBLAZE_32_ROSDA`
: This is a 32 bit reloc for the microblaze that stores a value relative to the read-only small data area anchor.

`BFD_RELOC_MICROBLAZE_32_RWSDA`
: This is a 32 bit reloc for the microblaze that stores a value relative to the read-write small data area anchor.

`BFD_RELOC_MICROBLAZE_32_SYM_OP_SYM`
: This is a 32 bit reloc for the microblaze to handle expressions of the form "Symbol Op Symbol".

`BFD_RELOC_MICROBLAZE_32_NONE`
: This is a 32 bit reloc that stores the 32 bit pc relative value in two words (with an imm instruction). No relocation is done here - only used for relaxing.

`BFD_RELOC_MICROBLAZE_64_NONE`
: This is a 64 bit reloc that stores the 32 bit pc relative value in two words (with an imm instruction). No relocation is done here - only used for relaxing.

`BFD_RELOC_MICROBLAZE_64_GOTPC`
: This is a 64 bit reloc that stores the 32 bit pc relative value in two words (with an imm instruction). The relocation is PC-relative GOT offset.

`BFD_RELOC_MICROBLAZE_64_GOT`
: This is a 64 bit reloc that stores the 32 bit pc relative value in two words (with an imm instruction). The relocation is GOT offset.

`BFD_RELOC_MICROBLAZE_64_PLT`
: This is a 64 bit reloc that stores the 32 bit pc relative value in two words (with an imm instruction). The relocation is PC-relative offset into PLT.

`BFD_RELOC_MICROBLAZE_64_GOTOFF`
: This is a 64 bit reloc that stores the 32 bit GOT relative value in two words (with an imm instruction). The relocation is relative offset from _GLOBAL_OFFSET_TABLE_.

`BFD_RELOC_MICROBLAZE_32_GOTOFF`
: This is a 32 bit reloc that stores the 32 bit GOT relative value in a word. The relocation is relative offset from _GLOBAL_OFFSET_TABLE_.

`BFD_RELOC_MICROBLAZE_COPY`
: This is used to tell the dynamic linker to copy the value out of the dynamic object into the runtime process image.

`BFD_RELOC_MICROBLAZE_64_TLS`
: Unused Reloc.

`BFD_RELOC_MICROBLAZE_64_TLSGD`
: This is a 64 bit reloc that stores the 32 bit GOT relative value of the GOT TLS GD info entry in two words (with an imm instruction). The relocation is GOT offset.

`BFD_RELOC_MICROBLAZE_64_TLSLD`
: This is a 64 bit reloc that stores the 32 bit GOT relative value of the GOT TLS LD info entry in two words (with an imm instruction). The relocation is GOT offset.

`BFD_RELOC_MICROBLAZE_32_TLSDTPMOD`
: This is a 32 bit reloc that stores the Module ID to GOT(n).

`BFD_RELOC_MICROBLAZE_32_TLSDTPREL`
: This is a 32 bit reloc that stores TLS offset to GOT(n+1).

`BFD_RELOC_MICROBLAZE_64_TLSDTPREL`
: This is a 32 bit reloc for storing TLS offset to two words (uses imm instruction).

`BFD_RELOC_MICROBLAZE_64_TLSGOTTPREL`
: This is a 64 bit reloc that stores 32-bit thread pointer relative offset to two words (uses imm instruction).

`BFD_RELOC_MICROBLAZE_64_TLSTPREL`
: This is a 64 bit reloc that stores 32-bit thread pointer relative offset to two words (uses imm instruction).

`BFD_RELOC_MICROBLAZE_64_TEXTPCREL`
: This is a 64 bit reloc that stores the 32 bit pc relative value in two words (with an imm instruction). The relocation is PC-relative offset from start of TEXT.

`BFD_RELOC_MICROBLAZE_64_TEXTREL`
: This is a 64 bit reloc that stores the 32 bit offset value in two words (with an imm instruction). The relocation is relative offset from start of TEXT.

`BFD_RELOC_KVX_RELOC_START`
: KVX pseudo relocation code to mark the start of the KVX relocation enumerators. N.B. the order of the enumerators is important as several tables in the KVX bfd backend are indexed by these enumerators; make sure they are all synced.

`BFD_RELOC_KVX_NONE`
: KVX null relocation code.

`BFD_RELOC_KVX_16`
`BFD_RELOC_KVX_32`
`BFD_RELOC_KVX_64`
`BFD_RELOC_KVX_S16_PCREL`
`BFD_RELOC_KVX_PCREL17`
`BFD_RELOC_KVX_PCREL27`
`BFD_RELOC_KVX_32_PCREL`
`BFD_RELOC_KVX_S37_PCREL_LO10`
`BFD_RELOC_KVX_S37_PCREL_UP27`
`BFD_RELOC_KVX_S43_PCREL_LO10`
`BFD_RELOC_KVX_S43_PCREL_UP27`
`BFD_RELOC_KVX_S43_PCREL_EX6`
`BFD_RELOC_KVX_S64_PCREL_LO10`

BFD_RELOC_KVX_S64_PCREL_UP27
BFD_RELOC_KVX_S64_PCREL_EX27
BFD_RELOC_KVX_64_PCREL
BFD_RELOC_KVX_S16
BFD_RELOC_KVX_S32_LO5
BFD_RELOC_KVX_S32_UP27
BFD_RELOC_KVX_S37_LO10
BFD_RELOC_KVX_S37_UP27
BFD_RELOC_KVX_S37_GOTOFF_LO10
BFD_RELOC_KVX_S37_GOTOFF_UP27
BFD_RELOC_KVX_S43_GOTOFF_LO10
BFD_RELOC_KVX_S43_GOTOFF_UP27
BFD_RELOC_KVX_S43_GOTOFF_EX6
BFD_RELOC_KVX_32_GOTOFF
BFD_RELOC_KVX_64_GOTOFF
BFD_RELOC_KVX_32_GOT
BFD_RELOC_KVX_S37_GOT_LO10
BFD_RELOC_KVX_S37_GOT_UP27
BFD_RELOC_KVX_S43_GOT_LO10
BFD_RELOC_KVX_S43_GOT_UP27
BFD_RELOC_KVX_S43_GOT_EX6
BFD_RELOC_KVX_64_GOT
BFD_RELOC_KVX_GLOB_DAT
BFD_RELOC_KVX_COPY
BFD_RELOC_KVX_JMP_SLOT
BFD_RELOC_KVX_RELATIVE
BFD_RELOC_KVX_S43_LO10
BFD_RELOC_KVX_S43_UP27
BFD_RELOC_KVX_S43_EX6
BFD_RELOC_KVX_S64_LO10
BFD_RELOC_KVX_S64_UP27
BFD_RELOC_KVX_S64_EX27
BFD_RELOC_KVX_S37_GOTADDR_LO10
BFD_RELOC_KVX_S37_GOTADDR_UP27
BFD_RELOC_KVX_S43_GOTADDR_LO10
BFD_RELOC_KVX_S43_GOTADDR_UP27
BFD_RELOC_KVX_S43_GOTADDR_EX6
BFD_RELOC_KVX_S64_GOTADDR_LO10
BFD_RELOC_KVX_S64_GOTADDR_UP27
BFD_RELOC_KVX_S64_GOTADDR_EX27
BFD_RELOC_KVX_64_DTPMOD
BFD_RELOC_KVX_64_DTPOFF
BFD_RELOC_KVX_S37_TLS_DTPOFF_LO10
BFD_RELOC_KVX_S37_TLS_DTPOFF_UP27
BFD_RELOC_KVX_S43_TLS_DTPOFF_LO10
BFD_RELOC_KVX_S43_TLS_DTPOFF_UP27
BFD_RELOC_KVX_S43_TLS_DTPOFF_EX6

BFD_RELOC_KVX_S37_TLS_GD_LO10
BFD_RELOC_KVX_S37_TLS_GD_UP27
BFD_RELOC_KVX_S43_TLS_GD_LO10
BFD_RELOC_KVX_S43_TLS_GD_UP27
BFD_RELOC_KVX_S43_TLS_GD_EX6
BFD_RELOC_KVX_S37_TLS_LD_LO10
BFD_RELOC_KVX_S37_TLS_LD_UP27
BFD_RELOC_KVX_S43_TLS_LD_LO10
BFD_RELOC_KVX_S43_TLS_LD_UP27
BFD_RELOC_KVX_S43_TLS_LD_EX6
BFD_RELOC_KVX_64_TPOFF
BFD_RELOC_KVX_S37_TLS_IE_LO10
BFD_RELOC_KVX_S37_TLS_IE_UP27
BFD_RELOC_KVX_S43_TLS_IE_LO10
BFD_RELOC_KVX_S43_TLS_IE_UP27
BFD_RELOC_KVX_S43_TLS_IE_EX6
BFD_RELOC_KVX_S37_TLS_LE_LO10
BFD_RELOC_KVX_S37_TLS_LE_UP27
BFD_RELOC_KVX_S43_TLS_LE_LO10
BFD_RELOC_KVX_S43_TLS_LE_UP27
BFD_RELOC_KVX_S43_TLS_LE_EX6
BFD_RELOC_KVX_8
: KVX Relocations.

BFD_RELOC_KVX_RELOC_END
: KVX pseudo relocation code to mark the end of the KVX relocation enumerators that have direct mapping to ELF reloc codes. There are a few more enumerators after this one; those are mainly used by the KVX assembler for the internal fixup or to select one of the above enumerators.

BFD_RELOC_AARCH64_RELOC_START
: AArch64 pseudo relocation code to mark the start of the AArch64 relocation enumerators. N.B. the order of the enumerators is important as several tables in the AArch64 bfd backend are indexed by these enumerators; make sure they are all synced.

BFD_RELOC_AARCH64_NULL
: Deprecated AArch64 null relocation code.

BFD_RELOC_AARCH64_NONE
: AArch64 null relocation code.

BFD_RELOC_AARCH64_64
BFD_RELOC_AARCH64_32
BFD_RELOC_AARCH64_16
: Basic absolute relocations of N bits. These are equivalent to BFD_RELOC_N and they were added to assist the indexing of the howto table.

BFD_RELOC_AARCH64_64_PCREL
BFD_RELOC_AARCH64_32_PCREL

`BFD_RELOC_AARCH64_16_PCREL`
: PC-relative relocations. These are equivalent to BFD_RELOC_N_PCREL and they were added to assist the indexing of the howto table.

`BFD_RELOC_AARCH64_MOVW_G0`
: AArch64 MOV[NZK] instruction with most significant bits 0 to 15 of an unsigned address/value.

`BFD_RELOC_AARCH64_MOVW_G0_NC`
: AArch64 MOV[NZK] instruction with less significant bits 0 to 15 of an address/value. No overflow checking.

`BFD_RELOC_AARCH64_MOVW_G1`
: AArch64 MOV[NZK] instruction with most significant bits 16 to 31 of an unsigned address/value.

`BFD_RELOC_AARCH64_MOVW_G1_NC`
: AArch64 MOV[NZK] instruction with less significant bits 16 to 31 of an address/value. No overflow checking.

`BFD_RELOC_AARCH64_MOVW_G2`
: AArch64 MOV[NZK] instruction with most significant bits 32 to 47 of an unsigned address/value.

`BFD_RELOC_AARCH64_MOVW_G2_NC`
: AArch64 MOV[NZK] instruction with less significant bits 32 to 47 of an address/value. No overflow checking.

`BFD_RELOC_AARCH64_MOVW_G3`
: AArch64 MOV[NZK] instruction with most signficant bits 48 to 64 of a signed or unsigned address/value.

`BFD_RELOC_AARCH64_MOVW_G0_S`
: AArch64 MOV[NZ] instruction with most significant bits 0 to 15 of a signed value. Changes instruction to MOVZ or MOVN depending on the value's sign.

`BFD_RELOC_AARCH64_MOVW_G1_S`
: AArch64 MOV[NZ] instruction with most significant bits 16 to 31 of a signed value. Changes instruction to MOVZ or MOVN depending on the value's sign.

`BFD_RELOC_AARCH64_MOVW_G2_S`
: AArch64 MOV[NZ] instruction with most significant bits 32 to 47 of a signed value. Changes instruction to MOVZ or MOVN depending on the value's sign.

`BFD_RELOC_AARCH64_MOVW_PREL_G0`
: AArch64 MOV[NZ] instruction with most significant bits 0 to 15 of a signed value. Changes instruction to MOVZ or MOVN depending on the value's sign.

`BFD_RELOC_AARCH64_MOVW_PREL_G0_NC`
: AArch64 MOV[NZ] instruction with most significant bits 0 to 15 of a signed value. Changes instruction to MOVZ or MOVN depending on the value's sign.

`BFD_RELOC_AARCH64_MOVW_PREL_G1`
: AArch64 MOVK instruction with most significant bits 16 to 31 of a signed value.

`BFD_RELOC_AARCH64_MOVW_PREL_G1_NC`
: AArch64 MOVK instruction with most significant bits 16 to 31 of a signed value.

`BFD_RELOC_AARCH64_MOVW_PREL_G2`
: AArch64 MOVK instruction with most significant bits 32 to 47 of a signed value.

`BFD_RELOC_AARCH64_MOVW_PREL_G2_NC`
: AArch64 MOVK instruction with most significant bits 32 to 47 of a signed value.

`BFD_RELOC_AARCH64_MOVW_PREL_G3`
: AArch64 MOVK instruction with most significant bits 47 to 63 of a signed value.

`BFD_RELOC_AARCH64_LD_LO19_PCREL`
: AArch64 Load Literal instruction, holding a 19 bit pc-relative word offset. The lowest two bits must be zero and are not stored in the instruction, giving a 21 bit signed byte offset.

`BFD_RELOC_AARCH64_ADR_LO21_PCREL`
: AArch64 ADR instruction, holding a simple 21 bit pc-relative byte offset.

`BFD_RELOC_AARCH64_ADR_HI21_PCREL`
: AArch64 ADRP instruction, with bits 12 to 32 of a pc-relative page offset, giving a 4KB aligned page base address.

`BFD_RELOC_AARCH64_ADR_HI21_NC_PCREL`
: AArch64 ADRP instruction, with bits 12 to 32 of a pc-relative page offset, giving a 4KB aligned page base address, but with no overflow checking.

`BFD_RELOC_AARCH64_ADD_LO12`
: AArch64 ADD immediate instruction, holding bits 0 to 11 of the address. Used in conjunction with BFD_RELOC_AARCH64_ADR_HI21_PCREL.

`BFD_RELOC_AARCH64_LDST8_LO12`
: AArch64 8-bit load/store instruction, holding bits 0 to 11 of the address. Used in conjunction with BFD_RELOC_AARCH64_ADR_HI21_PCREL.

`BFD_RELOC_AARCH64_TSTBR14`
: AArch64 14 bit pc-relative test bit and branch. The lowest two bits must be zero and are not stored in the instruction, giving a 16 bit signed byte offset.

`BFD_RELOC_AARCH64_BRANCH19`
: AArch64 19 bit pc-relative conditional branch and compare & branch. The lowest two bits must be zero and are not stored in the instruction, giving a 21 bit signed byte offset.

`BFD_RELOC_AARCH64_JUMP26`
: AArch64 26 bit pc-relative unconditional branch. The lowest two bits must be zero and are not stored in the instruction, giving a 28 bit signed byte offset.

`BFD_RELOC_AARCH64_CALL26`
: AArch64 26 bit pc-relative unconditional branch and link. The lowest two bits must be zero and are not stored in the instruction, giving a 28 bit signed byte offset.

`BFD_RELOC_AARCH64_LDST16_LO12`
: AArch64 16-bit load/store instruction, holding bits 0 to 11 of the address. Used in conjunction with BFD_RELOC_AARCH64_ADR_HI21_PCREL.

`BFD_RELOC_AARCH64_LDST32_LO12`
: AArch64 32-bit load/store instruction, holding bits 0 to 11 of the address. Used in conjunction with BFD_RELOC_AARCH64_ADR_HI21_PCREL.

`BFD_RELOC_AARCH64_LDST64_LO12`
: AArch64 64-bit load/store instruction, holding bits 0 to 11 of the address. Used in conjunction with BFD_RELOC_AARCH64_ADR_HI21_PCREL.

`BFD_RELOC_AARCH64_LDST128_LO12`
: AArch64 128-bit load/store instruction, holding bits 0 to 11 of the address. Used in conjunction with BFD_RELOC_AARCH64_ADR_HI21_PCREL.

`BFD_RELOC_AARCH64_GOT_LD_PREL19`
: AArch64 Load Literal instruction, holding a 19 bit PC relative word offset of the global offset table entry for a symbol. The lowest two bits must be zero and are not stored in the instruction, giving a 21 bit signed byte offset. This relocation type requires signed overflow checking.

`BFD_RELOC_AARCH64_ADR_GOT_PAGE`
: Get to the page base of the global offset table entry for a symbol as part of an ADRP instruction using a 21 bit PC relative value. Used in conjunction with BFD_RELOC_AARCH64_LD64_GOT_LO12_NC.

`BFD_RELOC_AARCH64_LD64_GOT_LO12_NC`
: Unsigned 12 bit byte offset for 64 bit load/store from the page of the GOT entry for this symbol. Used in conjunction with BFD_RELOC_AARCH64_ADR_GOT_PAGE. Valid in LP64 ABI only.

`BFD_RELOC_AARCH64_LD32_GOT_LO12_NC`
: Unsigned 12 bit byte offset for 32 bit load/store from the page of the GOT entry for this symbol. Used in conjunction with BFD_RELOC_AARCH64_ADR_GOT_PAGE. Valid in ILP32 ABI only.

`BFD_RELOC_AARCH64_MOVW_GOTOFF_G0_NC`
: Unsigned 16 bit byte offset for 64 bit load/store from the GOT entry for this symbol. Valid in LP64 ABI only.

`BFD_RELOC_AARCH64_MOVW_GOTOFF_G1`
: Unsigned 16 bit byte higher offset for 64 bit load/store from the GOT entry for this symbol. Valid in LP64 ABI only.

`BFD_RELOC_AARCH64_LD64_GOTOFF_LO15`
: Unsigned 15 bit byte offset for 64 bit load/store from the page of the GOT entry for this symbol. Valid in LP64 ABI only.

`BFD_RELOC_AARCH64_LD32_GOTPAGE_LO14`
Scaled 14 bit byte offset to the page base of the global offset table.

`BFD_RELOC_AARCH64_LD64_GOTPAGE_LO15`
Scaled 15 bit byte offset to the page base of the global offset table.

`BFD_RELOC_AARCH64_TLSGD_ADR_PAGE21`
Get to the page base of the global offset table entry for a symbols tls_index structure as part of an adrp instruction using a 21 bit PC relative value. Used in conjunction with BFD_RELOC_AARCH64_TLSGD_ADD_LO12_NC.

`BFD_RELOC_AARCH64_TLSGD_ADR_PREL21`
AArch64 TLS General Dynamic.

`BFD_RELOC_AARCH64_TLSGD_ADD_LO12_NC`
Unsigned 12 bit byte offset to global offset table entry for a symbol's tls_index structure. Used in conjunction with BFD_RELOC_AARCH64_TLSGD_ADR_PAGE21.

`BFD_RELOC_AARCH64_TLSGD_MOVW_G0_NC`
AArch64 TLS General Dynamic relocation.

`BFD_RELOC_AARCH64_TLSGD_MOVW_G1`
AArch64 TLS General Dynamic relocation.

`BFD_RELOC_AARCH64_TLSIE_ADR_GOTTPREL_PAGE21`
AArch64 TLS INITIAL EXEC relocation.

`BFD_RELOC_AARCH64_TLSIE_LD64_GOTTPREL_LO12_NC`
AArch64 TLS INITIAL EXEC relocation.

`BFD_RELOC_AARCH64_TLSIE_LD32_GOTTPREL_LO12_NC`
AArch64 TLS INITIAL EXEC relocation.

`BFD_RELOC_AARCH64_TLSIE_LD_GOTTPREL_PREL19`
AArch64 TLS INITIAL EXEC relocation.

`BFD_RELOC_AARCH64_TLSIE_MOVW_GOTTPREL_G0_NC`
AArch64 TLS INITIAL EXEC relocation.

`BFD_RELOC_AARCH64_TLSIE_MOVW_GOTTPREL_G1`
AArch64 TLS INITIAL EXEC relocation.

`BFD_RELOC_AARCH64_TLSLD_ADD_DTPREL_HI12`
bit[23:12] of byte offset to module TLS base address.

`BFD_RELOC_AARCH64_TLSLD_ADD_DTPREL_LO12`
Unsigned 12 bit byte offset to module TLS base address.

`BFD_RELOC_AARCH64_TLSLD_ADD_DTPREL_LO12_NC`
No overflow check version of BFD_RELOC_AARCH64_TLSLD_ADD_DTPREL_LO12.

`BFD_RELOC_AARCH64_TLSLD_ADD_LO12_NC`
: Unsigned 12 bit byte offset to global offset table entry for a symbol's tls_index structure. Used in conjunction with BFD_RELOC_AARCH64_TLSLD_ADR_PAGE21.

`BFD_RELOC_AARCH64_TLSLD_ADR_PAGE21`
: GOT entry page address for AArch64 TLS Local Dynamic, used with ADRP instruction.

`BFD_RELOC_AARCH64_TLSLD_ADR_PREL21`
: GOT entry address for AArch64 TLS Local Dynamic, used with ADR instruction.

`BFD_RELOC_AARCH64_TLSLD_LDST16_DTPREL_LO12`
: bit[11:1] of byte offset to module TLS base address, encoded in ldst instructions.

`BFD_RELOC_AARCH64_TLSLD_LDST16_DTPREL_LO12_NC`
: Similar to BFD_RELOC_AARCH64_TLSLD_LDST16_DTPREL_LO12, but no overflow check.

`BFD_RELOC_AARCH64_TLSLD_LDST32_DTPREL_LO12`
: bit[11:2] of byte offset to module TLS base address, encoded in ldst instructions.

`BFD_RELOC_AARCH64_TLSLD_LDST32_DTPREL_LO12_NC`
: Similar to BFD_RELOC_AARCH64_TLSLD_LDST32_DTPREL_LO12, but no overflow check.

`BFD_RELOC_AARCH64_TLSLD_LDST64_DTPREL_LO12`
: bit[11:3] of byte offset to module TLS base address, encoded in ldst instructions.

`BFD_RELOC_AARCH64_TLSLD_LDST64_DTPREL_LO12_NC`
: Similar to BFD_RELOC_AARCH64_TLSLD_LDST64_DTPREL_LO12, but no overflow check.

`BFD_RELOC_AARCH64_TLSLD_LDST8_DTPREL_LO12`
: bit[11:0] of byte offset to module TLS base address, encoded in ldst instructions.

`BFD_RELOC_AARCH64_TLSLD_LDST8_DTPREL_LO12_NC`
: Similar to BFD_RELOC_AARCH64_TLSLD_LDST8_DTPREL_LO12, but no overflow check.

`BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G0`
: bit[15:0] of byte offset to module TLS base address.

`BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G0_NC`
: No overflow check version of BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G0.

`BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G1`
: bit[31:16] of byte offset to module TLS base address.

`BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G1_NC`
: No overflow check version of BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G1.

BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G2
: bit[47:32] of byte offset to module TLS base address.

BFD_RELOC_AARCH64_TLSLE_MOVW_TPREL_G2
: AArch64 TLS LOCAL EXEC relocation.

BFD_RELOC_AARCH64_TLSLE_MOVW_TPREL_G1
: AArch64 TLS LOCAL EXEC relocation.

BFD_RELOC_AARCH64_TLSLE_MOVW_TPREL_G1_NC
: AArch64 TLS LOCAL EXEC relocation.

BFD_RELOC_AARCH64_TLSLE_MOVW_TPREL_G0
: AArch64 TLS LOCAL EXEC relocation.

BFD_RELOC_AARCH64_TLSLE_MOVW_TPREL_G0_NC
: AArch64 TLS LOCAL EXEC relocation.

BFD_RELOC_AARCH64_TLSLE_ADD_TPREL_HI12
: AArch64 TLS LOCAL EXEC relocation.

BFD_RELOC_AARCH64_TLSLE_ADD_TPREL_LO12
: AArch64 TLS LOCAL EXEC relocation.

BFD_RELOC_AARCH64_TLSLE_ADD_TPREL_LO12_NC
: AArch64 TLS LOCAL EXEC relocation.

BFD_RELOC_AARCH64_TLSLE_LDST16_TPREL_LO12
: bit[11:1] of byte offset to module TLS base address, encoded in ldst instructions.

BFD_RELOC_AARCH64_TLSLE_LDST16_TPREL_LO12_NC
: Similar to BFD_RELOC_AARCH64_TLSLE_LDST16_TPREL_LO12, but no overflow check.

BFD_RELOC_AARCH64_TLSLE_LDST32_TPREL_LO12
: bit[11:2] of byte offset to module TLS base address, encoded in ldst instructions.

BFD_RELOC_AARCH64_TLSLE_LDST32_TPREL_LO12_NC
: Similar to BFD_RELOC_AARCH64_TLSLE_LDST32_TPREL_LO12, but no overflow check.

BFD_RELOC_AARCH64_TLSLE_LDST64_TPREL_LO12
: bit[11:3] of byte offset to module TLS base address, encoded in ldst instructions.

BFD_RELOC_AARCH64_TLSLE_LDST64_TPREL_LO12_NC
: Similar to BFD_RELOC_AARCH64_TLSLE_LDST64_TPREL_LO12, but no overflow check.

BFD_RELOC_AARCH64_TLSLE_LDST8_TPREL_LO12
: bit[11:0] of byte offset to module TLS base address, encoded in ldst instructions.

`BFD_RELOC_AARCH64_TLSLE_LDST8_TPREL_LO12_NC`
: Similar to BFD_RELOC_AARCH64_TLSLE_LDST8_TPREL_LO12, but no overflow check.

`BFD_RELOC_AARCH64_TLSDESC_LD_PREL19`
`BFD_RELOC_AARCH64_TLSDESC_ADR_PREL21`
`BFD_RELOC_AARCH64_TLSDESC_ADR_PAGE21`
`BFD_RELOC_AARCH64_TLSDESC_LD64_LO12`
`BFD_RELOC_AARCH64_TLSDESC_LD32_LO12_NC`
`BFD_RELOC_AARCH64_TLSDESC_ADD_LO12`
`BFD_RELOC_AARCH64_TLSDESC_OFF_G1`
`BFD_RELOC_AARCH64_TLSDESC_OFF_G0_NC`
`BFD_RELOC_AARCH64_TLSDESC_LDR`
`BFD_RELOC_AARCH64_TLSDESC_ADD`
`BFD_RELOC_AARCH64_TLSDESC_CALL`
: AArch64 TLS DESC relocations.

`BFD_RELOC_AARCH64_COPY`
`BFD_RELOC_AARCH64_GLOB_DAT`
`BFD_RELOC_AARCH64_JUMP_SLOT`
`BFD_RELOC_AARCH64_RELATIVE`
: AArch64 DSO relocations.

`BFD_RELOC_AARCH64_TLS_DTPMOD`
`BFD_RELOC_AARCH64_TLS_DTPREL`
`BFD_RELOC_AARCH64_TLS_TPREL`
`BFD_RELOC_AARCH64_TLSDESC`
: AArch64 TLS relocations.

`BFD_RELOC_AARCH64_IRELATIVE`
: AArch64 support for STT_GNU_IFUNC.

`BFD_RELOC_AARCH64_RELOC_END`
: AArch64 pseudo relocation code to mark the end of the AArch64 relocation enumerators that have direct mapping to ELF reloc codes. There are a few more enumerators after this one; those are mainly used by the AArch64 assembler for the internal fixup or to select one of the above enumerators.

`BFD_RELOC_AARCH64_GAS_INTERNAL_FIXUP`
: AArch64 pseudo relocation code to be used internally by the AArch64 assembler and not (currently) written to any object files.

`BFD_RELOC_AARCH64_LDST_LO12`
: AArch64 unspecified load/store instruction, holding bits 0 to 11 of the address. Used in conjunction with BFD_RELOC_AARCH64_ADR_HI21_PCREL.

`BFD_RELOC_AARCH64_TLSLD_LDST_DTPREL_LO12`
: AArch64 pseudo relocation code for TLS local dynamic mode. It's to be used internally by the AArch64 assembler and not (currently) written to any object files.

BFD_RELOC_AARCH64_TLSLD_LDST_DTPREL_LO12_NC
: Similar to BFD_RELOC_AARCH64_TLSLD_LDST_DTPREL_LO12, but no overflow check.

BFD_RELOC_AARCH64_TLSLE_LDST_TPREL_LO12
: AArch64 pseudo relocation code for TLS local exec mode. It's to be used internally by the AArch64 assembler and not (currently) written to any object files.

BFD_RELOC_AARCH64_TLSLE_LDST_TPREL_LO12_NC
: Similar to BFD_RELOC_AARCH64_TLSLE_LDST_TPREL_LO12, but no overflow check.

BFD_RELOC_AARCH64_LD_GOT_LO12_NC
: AArch64 pseudo relocation code to be used internally by the AArch64 assembler and not (currently) written to any object files.

BFD_RELOC_AARCH64_TLSIE_LD_GOTTPREL_LO12_NC
: AArch64 pseudo relocation code to be used internally by the AArch64 assembler and not (currently) written to any object files.

BFD_RELOC_AARCH64_TLSDESC_LD_LO12_NC
: AArch64 pseudo relocation code to be used internally by the AArch64 assembler and not (currently) written to any object files.

BFD_RELOC_AARCH64_BRANCH9
: AArch64 9 bit pc-relative conditional branch and compare & branch. The lowest two bits must be zero and are not stored in the instruction, giving an 11 bit signed byte offset.

BFD_RELOC_TILEPRO_COPY
BFD_RELOC_TILEPRO_GLOB_DAT
BFD_RELOC_TILEPRO_JMP_SLOT
BFD_RELOC_TILEPRO_RELATIVE
BFD_RELOC_TILEPRO_BROFF_X1
BFD_RELOC_TILEPRO_JOFFLONG_X1
BFD_RELOC_TILEPRO_JOFFLONG_X1_PLT
BFD_RELOC_TILEPRO_IMM8_X0
BFD_RELOC_TILEPRO_IMM8_Y0
BFD_RELOC_TILEPRO_IMM8_X1
BFD_RELOC_TILEPRO_IMM8_Y1
BFD_RELOC_TILEPRO_DEST_IMM8_X1
BFD_RELOC_TILEPRO_MT_IMM15_X1
BFD_RELOC_TILEPRO_MF_IMM15_X1
BFD_RELOC_TILEPRO_IMM16_X0
BFD_RELOC_TILEPRO_IMM16_X1
BFD_RELOC_TILEPRO_IMM16_X0_LO
BFD_RELOC_TILEPRO_IMM16_X1_LO
BFD_RELOC_TILEPRO_IMM16_X0_HI
BFD_RELOC_TILEPRO_IMM16_X1_HI

BFD_RELOC_TILEPRO_IMM16_X0_HA
BFD_RELOC_TILEPRO_IMM16_X1_HA
BFD_RELOC_TILEPRO_IMM16_X0_PCREL
BFD_RELOC_TILEPRO_IMM16_X1_PCREL
BFD_RELOC_TILEPRO_IMM16_X0_LO_PCREL
BFD_RELOC_TILEPRO_IMM16_X1_LO_PCREL
BFD_RELOC_TILEPRO_IMM16_X0_HI_PCREL
BFD_RELOC_TILEPRO_IMM16_X1_HI_PCREL
BFD_RELOC_TILEPRO_IMM16_X0_HA_PCREL
BFD_RELOC_TILEPRO_IMM16_X1_HA_PCREL
BFD_RELOC_TILEPRO_IMM16_X0_GOT
BFD_RELOC_TILEPRO_IMM16_X1_GOT
BFD_RELOC_TILEPRO_IMM16_X0_GOT_LO
BFD_RELOC_TILEPRO_IMM16_X1_GOT_LO
BFD_RELOC_TILEPRO_IMM16_X0_GOT_HI
BFD_RELOC_TILEPRO_IMM16_X1_GOT_HI
BFD_RELOC_TILEPRO_IMM16_X0_GOT_HA
BFD_RELOC_TILEPRO_IMM16_X1_GOT_HA
BFD_RELOC_TILEPRO_MMSTART_X0
BFD_RELOC_TILEPRO_MMEND_X0
BFD_RELOC_TILEPRO_MMSTART_X1
BFD_RELOC_TILEPRO_MMEND_X1
BFD_RELOC_TILEPRO_SHAMT_X0
BFD_RELOC_TILEPRO_SHAMT_X1
BFD_RELOC_TILEPRO_SHAMT_Y0
BFD_RELOC_TILEPRO_SHAMT_Y1
BFD_RELOC_TILEPRO_TLS_GD_CALL
BFD_RELOC_TILEPRO_IMM8_X0_TLS_GD_ADD
BFD_RELOC_TILEPRO_IMM8_X1_TLS_GD_ADD
BFD_RELOC_TILEPRO_IMM8_Y0_TLS_GD_ADD
BFD_RELOC_TILEPRO_IMM8_Y1_TLS_GD_ADD
BFD_RELOC_TILEPRO_TLS_IE_LOAD
BFD_RELOC_TILEPRO_IMM16_X0_TLS_GD
BFD_RELOC_TILEPRO_IMM16_X1_TLS_GD
BFD_RELOC_TILEPRO_IMM16_X0_TLS_GD_LO
BFD_RELOC_TILEPRO_IMM16_X1_TLS_GD_LO
BFD_RELOC_TILEPRO_IMM16_X0_TLS_GD_HI
BFD_RELOC_TILEPRO_IMM16_X1_TLS_GD_HI
BFD_RELOC_TILEPRO_IMM16_X0_TLS_GD_HA
BFD_RELOC_TILEPRO_IMM16_X1_TLS_GD_HA
BFD_RELOC_TILEPRO_IMM16_X0_TLS_IE
BFD_RELOC_TILEPRO_IMM16_X1_TLS_IE
BFD_RELOC_TILEPRO_IMM16_X0_TLS_IE_LO
BFD_RELOC_TILEPRO_IMM16_X1_TLS_IE_LO
BFD_RELOC_TILEPRO_IMM16_X0_TLS_IE_HI
BFD_RELOC_TILEPRO_IMM16_X1_TLS_IE_HI
BFD_RELOC_TILEPRO_IMM16_X0_TLS_IE_HA

BFD_RELOC_TILEPRO_IMM16_X1_TLS_IE_HA
BFD_RELOC_TILEPRO_TLS_DTPMOD32
BFD_RELOC_TILEPRO_TLS_DTPOFF32
BFD_RELOC_TILEPRO_TLS_TPOFF32
BFD_RELOC_TILEPRO_IMM16_X0_TLS_LE
BFD_RELOC_TILEPRO_IMM16_X1_TLS_LE
BFD_RELOC_TILEPRO_IMM16_X0_TLS_LE_LO
BFD_RELOC_TILEPRO_IMM16_X1_TLS_LE_LO
BFD_RELOC_TILEPRO_IMM16_X0_TLS_LE_HI
BFD_RELOC_TILEPRO_IMM16_X1_TLS_LE_HI
BFD_RELOC_TILEPRO_IMM16_X0_TLS_LE_HA
BFD_RELOC_TILEPRO_IMM16_X1_TLS_LE_HA
Tilera TILEPro Relocations.

BFD_RELOC_TILEGX_HW0
BFD_RELOC_TILEGX_HW1
BFD_RELOC_TILEGX_HW2
BFD_RELOC_TILEGX_HW3
BFD_RELOC_TILEGX_HW0_LAST
BFD_RELOC_TILEGX_HW1_LAST
BFD_RELOC_TILEGX_HW2_LAST
BFD_RELOC_TILEGX_COPY
BFD_RELOC_TILEGX_GLOB_DAT
BFD_RELOC_TILEGX_JMP_SLOT
BFD_RELOC_TILEGX_RELATIVE
BFD_RELOC_TILEGX_BROFF_X1
BFD_RELOC_TILEGX_JUMPOFF_X1
BFD_RELOC_TILEGX_JUMPOFF_X1_PLT
BFD_RELOC_TILEGX_IMM8_X0
BFD_RELOC_TILEGX_IMM8_Y0
BFD_RELOC_TILEGX_IMM8_X1
BFD_RELOC_TILEGX_IMM8_Y1
BFD_RELOC_TILEGX_DEST_IMM8_X1
BFD_RELOC_TILEGX_MT_IMM14_X1
BFD_RELOC_TILEGX_MF_IMM14_X1
BFD_RELOC_TILEGX_MMSTART_X0
BFD_RELOC_TILEGX_MMEND_X0
BFD_RELOC_TILEGX_SHAMT_X0
BFD_RELOC_TILEGX_SHAMT_X1
BFD_RELOC_TILEGX_SHAMT_Y0
BFD_RELOC_TILEGX_SHAMT_Y1
BFD_RELOC_TILEGX_IMM16_X0_HW0
BFD_RELOC_TILEGX_IMM16_X1_HW0
BFD_RELOC_TILEGX_IMM16_X0_HW1
BFD_RELOC_TILEGX_IMM16_X1_HW1
BFD_RELOC_TILEGX_IMM16_X0_HW2
BFD_RELOC_TILEGX_IMM16_X1_HW2

BFD_RELOC_TILEGX_IMM16_X0_HW3
BFD_RELOC_TILEGX_IMM16_X1_HW3
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST
BFD_RELOC_TILEGX_IMM16_X0_HW2_LAST
BFD_RELOC_TILEGX_IMM16_X1_HW2_LAST
BFD_RELOC_TILEGX_IMM16_X0_HW0_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW0_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW1_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW1_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW2_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW2_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW3_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW3_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW2_LAST_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW2_LAST_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW0_GOT
BFD_RELOC_TILEGX_IMM16_X1_HW0_GOT
BFD_RELOC_TILEGX_IMM16_X0_HW0_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW0_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW1_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW1_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW2_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW2_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_GOT
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_GOT
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_GOT
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_GOT
BFD_RELOC_TILEGX_IMM16_X0_HW3_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW3_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW0_TLS_GD
BFD_RELOC_TILEGX_IMM16_X1_HW0_TLS_GD
BFD_RELOC_TILEGX_IMM16_X0_HW0_TLS_LE
BFD_RELOC_TILEGX_IMM16_X1_HW0_TLS_LE
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_TLS_LE
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_TLS_LE
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_TLS_LE
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_TLS_LE
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_TLS_GD
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_TLS_GD
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_TLS_GD

BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_TLS_GD
BFD_RELOC_TILEGX_IMM16_X0_HW0_TLS_IE
BFD_RELOC_TILEGX_IMM16_X1_HW0_TLS_IE
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW2_LAST_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X1_HW2_LAST_PLT_PCREL
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_TLS_IE
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_TLS_IE
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_TLS_IE
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_TLS_IE
BFD_RELOC_TILEGX_TLS_DTPMOD64
BFD_RELOC_TILEGX_TLS_DTPOFF64
BFD_RELOC_TILEGX_TLS_TPOFF64
BFD_RELOC_TILEGX_TLS_DTPMOD32
BFD_RELOC_TILEGX_TLS_DTPOFF32
BFD_RELOC_TILEGX_TLS_TPOFF32
BFD_RELOC_TILEGX_TLS_GD_CALL
BFD_RELOC_TILEGX_IMM8_X0_TLS_GD_ADD
BFD_RELOC_TILEGX_IMM8_X1_TLS_GD_ADD
BFD_RELOC_TILEGX_IMM8_Y0_TLS_GD_ADD
BFD_RELOC_TILEGX_IMM8_Y1_TLS_GD_ADD
BFD_RELOC_TILEGX_TLS_IE_LOAD
BFD_RELOC_TILEGX_IMM8_X0_TLS_ADD
BFD_RELOC_TILEGX_IMM8_X1_TLS_ADD
BFD_RELOC_TILEGX_IMM8_Y0_TLS_ADD
BFD_RELOC_TILEGX_IMM8_Y1_TLS_ADD
: Tilera TILE-Gx Relocations.

BFD_RELOC_BPF_64
BFD_RELOC_BPF_DISP32
BFD_RELOC_BPF_DISPCALL32
BFD_RELOC_BPF_DISP16
: Linux eBPF relocations.

BFD_RELOC_EPIPHANY_SIMM8
: Adapteva EPIPHANY - 8 bit signed pc-relative displacement.

BFD_RELOC_EPIPHANY_SIMM24
: Adapteva EPIPHANY - 24 bit signed pc-relative displacement.

BFD_RELOC_EPIPHANY_HIGH
: Adapteva EPIPHANY - 16 most-significant bits of absolute address.

BFD_RELOC_EPIPHANY_LOW
: Adapteva EPIPHANY - 16 least-significant bits of absolute address.

`BFD_RELOC_EPIPHANY_SIMM11`
: Adapteva EPIPHANY - 11 bit signed number - add/sub immediate.

`BFD_RELOC_EPIPHANY_IMM11`
: Adapteva EPIPHANY - 11 bit sign-magnitude number (ld/st displacement).

`BFD_RELOC_EPIPHANY_IMM8`
: Adapteva EPIPHANY - 8 bit immediate for 16 bit mov instruction.

`BFD_RELOC_VISIUM_HI16`
`BFD_RELOC_VISIUM_LO16`
`BFD_RELOC_VISIUM_IM16`
`BFD_RELOC_VISIUM_REL16`
`BFD_RELOC_VISIUM_HI16_PCREL`
`BFD_RELOC_VISIUM_LO16_PCREL`
`BFD_RELOC_VISIUM_IM16_PCREL`
: Visium Relocations.

`BFD_RELOC_WASM32_LEB128`
`BFD_RELOC_WASM32_LEB128_GOT`
`BFD_RELOC_WASM32_LEB128_GOT_CODE`
`BFD_RELOC_WASM32_LEB128_PLT`
`BFD_RELOC_WASM32_PLT_INDEX`
`BFD_RELOC_WASM32_ABS32_CODE`
`BFD_RELOC_WASM32_COPY`
`BFD_RELOC_WASM32_CODE_POINTER`
`BFD_RELOC_WASM32_INDEX`
`BFD_RELOC_WASM32_PLT_SIG`
: WebAssembly relocations.

`BFD_RELOC_CKCORE_NONE`
`BFD_RELOC_CKCORE_ADDR32`
`BFD_RELOC_CKCORE_PCREL_IMM8BY4`
`BFD_RELOC_CKCORE_PCREL_IMM11BY2`
`BFD_RELOC_CKCORE_PCREL_IMM4BY2`
`BFD_RELOC_CKCORE_PCREL32`
`BFD_RELOC_CKCORE_PCREL_JSR_IMM11BY2`
`BFD_RELOC_CKCORE_GNU_VTINHERIT`
`BFD_RELOC_CKCORE_GNU_VTENTRY`
`BFD_RELOC_CKCORE_RELATIVE`
`BFD_RELOC_CKCORE_COPY`
`BFD_RELOC_CKCORE_GLOB_DAT`
`BFD_RELOC_CKCORE_JUMP_SLOT`
`BFD_RELOC_CKCORE_GOTOFF`
`BFD_RELOC_CKCORE_GOTPC`
`BFD_RELOC_CKCORE_GOT32`
`BFD_RELOC_CKCORE_PLT32`
`BFD_RELOC_CKCORE_ADDRGOT`
`BFD_RELOC_CKCORE_ADDRPLT`

BFD_RELOC_CKCORE_PCREL_IMM26BY2
BFD_RELOC_CKCORE_PCREL_IMM16BY2
BFD_RELOC_CKCORE_PCREL_IMM16BY4
BFD_RELOC_CKCORE_PCREL_IMM10BY2
BFD_RELOC_CKCORE_PCREL_IMM10BY4
BFD_RELOC_CKCORE_ADDR_HI16
BFD_RELOC_CKCORE_ADDR_LO16
BFD_RELOC_CKCORE_GOTPC_HI16
BFD_RELOC_CKCORE_GOTPC_LO16
BFD_RELOC_CKCORE_GOTOFF_HI16
BFD_RELOC_CKCORE_GOTOFF_LO16
BFD_RELOC_CKCORE_GOT12
BFD_RELOC_CKCORE_GOT_HI16
BFD_RELOC_CKCORE_GOT_LO16
BFD_RELOC_CKCORE_PLT12
BFD_RELOC_CKCORE_PLT_HI16
BFD_RELOC_CKCORE_PLT_LO16
BFD_RELOC_CKCORE_ADDRGOT_HI16
BFD_RELOC_CKCORE_ADDRGOT_LO16
BFD_RELOC_CKCORE_ADDRPLT_HI16
BFD_RELOC_CKCORE_ADDRPLT_LO16
BFD_RELOC_CKCORE_PCREL_JSR_IMM26BY2
BFD_RELOC_CKCORE_TOFFSET_LO16
BFD_RELOC_CKCORE_DOFFSET_LO16
BFD_RELOC_CKCORE_PCREL_IMM18BY2
BFD_RELOC_CKCORE_DOFFSET_IMM18
BFD_RELOC_CKCORE_DOFFSET_IMM18BY2
BFD_RELOC_CKCORE_DOFFSET_IMM18BY4
BFD_RELOC_CKCORE_GOTOFF_IMM18
BFD_RELOC_CKCORE_GOT_IMM18BY4
BFD_RELOC_CKCORE_PLT_IMM18BY4
BFD_RELOC_CKCORE_PCREL_IMM7BY4
BFD_RELOC_CKCORE_TLS_LE32
BFD_RELOC_CKCORE_TLS_IE32
BFD_RELOC_CKCORE_TLS_GD32
BFD_RELOC_CKCORE_TLS_LDM32
BFD_RELOC_CKCORE_TLS_LDO32
BFD_RELOC_CKCORE_TLS_DTPMOD32
BFD_RELOC_CKCORE_TLS_DTPOFF32
BFD_RELOC_CKCORE_TLS_TPOFF32
BFD_RELOC_CKCORE_PCREL_FLRW_IMM8BY4
BFD_RELOC_CKCORE_NOJSRI
BFD_RELOC_CKCORE_CALLGRAPH
BFD_RELOC_CKCORE_IRELATIVE
BFD_RELOC_CKCORE_PCREL_BLOOP_IMM4BY4
BFD_RELOC_CKCORE_PCREL_BLOOP_IMM12BY4

C-SKY relocations.

BFD_RELOC_S12Z_OPR
S12Z relocations.

BFD_RELOC_LARCH_TLS_DTPMOD32
BFD_RELOC_LARCH_TLS_DTPREL32
BFD_RELOC_LARCH_TLS_DTPMOD64
BFD_RELOC_LARCH_TLS_DTPREL64
BFD_RELOC_LARCH_TLS_TPREL32
BFD_RELOC_LARCH_TLS_TPREL64
BFD_RELOC_LARCH_TLS_DESC32
BFD_RELOC_LARCH_TLS_DESC64
BFD_RELOC_LARCH_MARK_LA
BFD_RELOC_LARCH_MARK_PCREL
BFD_RELOC_LARCH_SOP_PUSH_PCREL
BFD_RELOC_LARCH_SOP_PUSH_ABSOLUTE
BFD_RELOC_LARCH_SOP_PUSH_DUP
BFD_RELOC_LARCH_SOP_PUSH_GPREL
BFD_RELOC_LARCH_SOP_PUSH_TLS_TPREL
BFD_RELOC_LARCH_SOP_PUSH_TLS_GOT
BFD_RELOC_LARCH_SOP_PUSH_TLS_GD
BFD_RELOC_LARCH_SOP_PUSH_PLT_PCREL
BFD_RELOC_LARCH_SOP_ASSERT
BFD_RELOC_LARCH_SOP_NOT
BFD_RELOC_LARCH_SOP_SUB
BFD_RELOC_LARCH_SOP_SL
BFD_RELOC_LARCH_SOP_SR
BFD_RELOC_LARCH_SOP_ADD
BFD_RELOC_LARCH_SOP_AND
BFD_RELOC_LARCH_SOP_IF_ELSE
BFD_RELOC_LARCH_SOP_POP_32_S_10_5
BFD_RELOC_LARCH_SOP_POP_32_U_10_12
BFD_RELOC_LARCH_SOP_POP_32_S_10_12
BFD_RELOC_LARCH_SOP_POP_32_S_10_16
BFD_RELOC_LARCH_SOP_POP_32_S_10_16_S2
BFD_RELOC_LARCH_SOP_POP_32_S_5_20
BFD_RELOC_LARCH_SOP_POP_32_S_0_5_10_16_S2
BFD_RELOC_LARCH_SOP_POP_32_S_0_10_10_16_S2
BFD_RELOC_LARCH_SOP_POP_32_U
BFD_RELOC_LARCH_ADD8
BFD_RELOC_LARCH_ADD16
BFD_RELOC_LARCH_ADD24
BFD_RELOC_LARCH_ADD32
BFD_RELOC_LARCH_ADD64
BFD_RELOC_LARCH_SUB8
BFD_RELOC_LARCH_SUB16
BFD_RELOC_LARCH_SUB24
BFD_RELOC_LARCH_SUB32

BFD_RELOC_LARCH_SUB64
BFD_RELOC_LARCH_B16
BFD_RELOC_LARCH_B21
BFD_RELOC_LARCH_B26
BFD_RELOC_LARCH_ABS_HI20
BFD_RELOC_LARCH_ABS_LO12
BFD_RELOC_LARCH_ABS64_LO20
BFD_RELOC_LARCH_ABS64_HI12
BFD_RELOC_LARCH_PCALA_HI20
BFD_RELOC_LARCH_PCALA_LO12
BFD_RELOC_LARCH_PCALA64_LO20
BFD_RELOC_LARCH_PCALA64_HI12
BFD_RELOC_LARCH_GOT_PC_HI20
BFD_RELOC_LARCH_GOT_PC_LO12
BFD_RELOC_LARCH_GOT64_PC_LO20
BFD_RELOC_LARCH_GOT64_PC_HI12
BFD_RELOC_LARCH_GOT_HI20
BFD_RELOC_LARCH_GOT_LO12
BFD_RELOC_LARCH_GOT64_LO20
BFD_RELOC_LARCH_GOT64_HI12
BFD_RELOC_LARCH_TLS_LE_HI20
BFD_RELOC_LARCH_TLS_LE_LO12
BFD_RELOC_LARCH_TLS_LE64_LO20
BFD_RELOC_LARCH_TLS_LE64_HI12
BFD_RELOC_LARCH_TLS_IE_PC_HI20
BFD_RELOC_LARCH_TLS_IE_PC_LO12
BFD_RELOC_LARCH_TLS_IE64_PC_LO20
BFD_RELOC_LARCH_TLS_IE64_PC_HI12
BFD_RELOC_LARCH_TLS_IE_HI20
BFD_RELOC_LARCH_TLS_IE_LO12
BFD_RELOC_LARCH_TLS_IE64_LO20
BFD_RELOC_LARCH_TLS_IE64_HI12
BFD_RELOC_LARCH_TLS_LD_PC_HI20
BFD_RELOC_LARCH_TLS_LD_HI20
BFD_RELOC_LARCH_TLS_GD_PC_HI20
BFD_RELOC_LARCH_TLS_GD_HI20
BFD_RELOC_LARCH_32_PCREL
BFD_RELOC_LARCH_RELAX
BFD_RELOC_LARCH_DELETE
BFD_RELOC_LARCH_ALIGN
BFD_RELOC_LARCH_PCREL20_S2
BFD_RELOC_LARCH_CFA
BFD_RELOC_LARCH_ADD6
BFD_RELOC_LARCH_SUB6
BFD_RELOC_LARCH_ADD_ULEB128
BFD_RELOC_LARCH_SUB_ULEB128
BFD_RELOC_LARCH_64_PCREL

BFD_RELOC_LARCH_CALL36
BFD_RELOC_LARCH_TLS_DESC_PC_HI20
BFD_RELOC_LARCH_TLS_DESC_PC_LO12
BFD_RELOC_LARCH_TLS_DESC64_PC_LO20
BFD_RELOC_LARCH_TLS_DESC64_PC_HI12
BFD_RELOC_LARCH_TLS_DESC_HI20
BFD_RELOC_LARCH_TLS_DESC_LO12
BFD_RELOC_LARCH_TLS_DESC64_LO20
BFD_RELOC_LARCH_TLS_DESC64_HI12
BFD_RELOC_LARCH_TLS_DESC_LD
BFD_RELOC_LARCH_TLS_DESC_CALL
BFD_RELOC_LARCH_TLS_LE_HI20_R
BFD_RELOC_LARCH_TLS_LE_ADD_R
BFD_RELOC_LARCH_TLS_LE_LO12_R
BFD_RELOC_LARCH_TLS_LD_PCREL20_S2
BFD_RELOC_LARCH_TLS_GD_PCREL20_S2
BFD_RELOC_LARCH_TLS_DESC_PCREL20_S2
: LARCH relocations.

```
typedef enum bfd_reloc_code_real bfd_reloc_code_real_type;
```

2.10.2.2 bfd_reloc_type_lookup

`reloc_howto_type *bfd_reloc_type_lookup (bfd *abfd, bfd_reloc_code_real_type code); reloc_howto_type *bfd_reloc_name_lookup (bfd *abfd, const char *reloc_name);` [Function]

Return a pointer to a howto structure which, when invoked, will perform the relocation *code* on data from the architecture noted.

2.10.2.3 bfd_default_reloc_type_lookup

`reloc_howto_type *bfd_default_reloc_type_lookup (bfd *abfd, bfd_reloc_code_real_type code);` [Function]

Provides a default relocation lookup routine for any architecture.

2.10.2.4 bfd_get_reloc_code_name

`const char *bfd_get_reloc_code_name (bfd_reloc_code_real_type code);` [Function]

Provides a printable name for the supplied relocation code. Useful mainly for printing error messages.

2.10.2.5 bfd_generic_relax_section

`bool bfd_generic_relax_section (bfd *abfd, asection *section, struct bfd_link_info *, bool *);` [Function]

Provides default handling for relaxing for back ends which don't do relaxing.

2.10.2.6 bfd_generic_gc_sections

`bool bfd_generic_gc_sections (bfd *, struct bfd_link_info *);` [Function]

Provides default handling for relaxing for back ends which don't do section gc – i.e., does nothing.

2.10.2.7 bfd_generic_lookup_section_flags

`bool bfd_generic_lookup_section_flags (struct bfd_link_info *, struct flag_info *, asection *);` [Function]

Provides default handling for section flags lookup – i.e., does nothing. Returns FALSE if the section should be omitted, otherwise TRUE.

2.10.2.8 bfd_generic_merge_sections

`bool bfd_generic_merge_sections (bfd *, struct bfd_link_info *);` [Function]

Provides default handling for SEC_MERGE section merging for back ends which don't have SEC_MERGE support – i.e., does nothing.

2.10.2.9 bfd_generic_get_relocated_section_contents

`bfd_byte *bfd_generic_get_relocated_section_contents (bfd *abfd, struct bfd_link_info *link_info, struct bfd_link_order *link_order, bfd_byte *data, bool relocatable, asymbol **symbols);` [Function]

Provides default handling of relocation effort for back ends which can't be bothered to do it efficiently.

2.10.2.10 _bfd_generic_set_reloc

`void _bfd_generic_set_reloc (bfd *abfd, sec_ptr section, arelent **relptr, unsigned int count);` [Function]

Installs a new set of internal relocations in SECTION.

2.10.2.11 _bfd_unrecognized_reloc

`bool _bfd_unrecognized_reloc (bfd * abfd, sec_ptr section, unsigned int r_type);` [Function]

Reports an unrecognized reloc. Written as a function in order to reduce code duplication. Returns FALSE so that it can be called from a return statement.

2.11 Core files

2.11.1 Core file functions

These are functions pertaining to core files.

2.11.1.1 bfd_core_file_failing_command

`const char *bfd_core_file_failing_command (bfd *abfd);` [Function]

Return a read-only string explaining which program was running when it failed and produced the core file *abfd*.

2.11.1.2 bfd_core_file_failing_signal

`int bfd_core_file_failing_signal (bfd *abfd);` [Function]

Returns the signal number which caused the core dump which generated the file the BFD *abfd* is attached to.

2.11.1.3 bfd_core_file_pid

`int bfd_core_file_pid (bfd *abfd);` [Function]

Returns the PID of the process the core dump the BFD *abfd* is attached to was generated from.

2.11.1.4 core_file_matches_executable_p

`bool core_file_matches_executable_p (bfd *core_bfd, bfd *exec_bfd);` [Function]

Return `TRUE` if the core file attached to *core_bfd* was generated by a run of the executable file attached to *exec_bfd*, `FALSE` otherwise.

2.11.1.5 generic_core_file_matches_executable_p

`bool generic_core_file_matches_executable_p (bfd *core_bfd, bfd *exec_bfd);` [Function]

Return TRUE if the core file attached to *core_bfd* was generated by a run of the executable file attached to *exec_bfd*. The match is based on executable basenames only.

Note: When not able to determine the core file failing command or the executable name, we still return TRUE even though we're not sure that core file and executable match. This is to avoid generating a false warning in situations where we really don't know whether they match or not.

2.12 Targets

Each port of BFD to a different machine requires the creation of a target back end. All the back end provides to the root part of BFD is a structure containing pointers to functions which perform certain low level operations on files. BFD translates the applications's requests through a pointer into calls to the back end routines.

When a file is opened with `bfd_openr`, its format and target are unknown. BFD uses various mechanisms to determine how to interpret the file. The operations performed are:

- Create a BFD by calling the internal routine `_bfd_new_bfd`, then call `bfd_find_target` with the target string supplied to `bfd_openr` and the new BFD pointer.
- If a null target string was provided to `bfd_find_target`, look up the environment variable `GNUTARGET` and use that as the target string.

- If the target string is still `NULL`, or the target string is `default`, then use the first item in the target vector as the target type, and set `target_defaulted` in the BFD to cause `bfd_check_format` to loop through all the targets. See Section 2.12.1 [bfd_target], page 142. See Section 2.9 [Formats], page 49.
- Otherwise, inspect the elements in the target vector one by one, until a match on target name is found. When found, use it.
- Otherwise return the error `bfd_error_invalid_target` to `bfd_openr`.
- `bfd_openr` attempts to open the file using `bfd_open_file`, and returns the BFD.

Once the BFD has been opened and the target selected, the file format may be determined. This is done by calling `bfd_check_format` on the BFD with a suggested format. If `target_defaulted` has been set, each possible target type is tried to see if it recognizes the specified format. `bfd_check_format` returns `TRUE` when the caller guesses right.

2.12.1 bfd_target

This structure contains everything that BFD knows about a target. It includes things like its byte order, name, and which routines to call to do various operations.

Every BFD points to a target structure with its `xvec` member.

The macros below are used to dispatch to functions through the `bfd_target` vector. They are used in a number of macros further down in `bfd.h`, and are also used when calling various routines by hand inside the BFD implementation. The *arglist* argument must be parenthesized; it contains all the arguments to the called function.

They make the documentation (more) unpleasant to read, so if someone wants to fix this and not break the above, please do.

```
#define BFD_SEND(bfd, message, arglist) \
  ((*((bfd)->xvec->message)) arglist)

#ifdef DEBUG_BFD_SEND
#undef BFD_SEND
#define BFD_SEND(bfd, message, arglist) \
  (((bfd) && (bfd)->xvec && (bfd)->xvec->message) ? \
    ((*((bfd)->xvec->message)) arglist) : \
    (bfd_assert (__FILE__,__LINE__), NULL))
#endif
```

For operations which index on the BFD format:

```
#define BFD_SEND_FMT(bfd, message, arglist) \
  (((bfd)->xvec->message[(int) ((bfd)->format)]) arglist)

#ifdef DEBUG_BFD_SEND
#undef BFD_SEND_FMT
#define BFD_SEND_FMT(bfd, message, arglist) \
  (((bfd) && (bfd)->xvec && (bfd)->xvec->message) ? \
   (((bfd)->xvec->message[(int) ((bfd)->format)]) arglist) : \
   (bfd_assert (__FILE__,__LINE__), NULL))
#endif
```

```
/* Defined to TRUE if unused section symbol should be kept.  */
#ifndef TARGET_KEEP_UNUSED_SECTION_SYMBOLS
#define TARGET_KEEP_UNUSED_SECTION_SYMBOLS true
#endif
```

This is the structure which defines the type of BFD this is. The `xvec` member of the struct `bfd` itself points here. Each module that implements access to a different target under BFD, defines one of these.

FIXME, these names should be rationalised with the names of the entry points which call them. Too bad we can't have one macro to define them both!

```
typedef struct bfd_target
{
  /* Identifies the kind of target, e.g., SunOS4, Ultrix, etc.  */
  const char *name;

 /* The "flavour" of a back end is a general indication about
    the contents of a file.  */
 enum bfd_flavour flavour;

 /* The order of bytes within the data area of a file.  */
 enum bfd_endian byteorder;

/* The order of bytes within the header parts of a file.  */
 enum bfd_endian header_byteorder;

 /* A mask of all the flags which an executable may have set -
    from the set BFD_NO_FLAGS, HAS_RELOC, ...D_PAGED.  */
 flagword object_flags;

/* A mask of all the flags which a section may have set - from
   the set SEC_NO_FLAGS, SEC_ALLOC, ...SET_NEVER_LOAD.  */
 flagword section_flags;

/* The character normally found at the front of a symbol.
   (if any), perhaps `_'.  */
 char symbol_leading_char;

/* The pad character for file names within an archive header.  */
 char ar_pad_char;

 /* The maximum number of characters in an archive header.  */
 unsigned char ar_max_namelen;

 /* How well this target matches, used to select between various
    possible targets when more than one target matches.  */
```

```
  unsigned char match_priority;

 /* TRUE if unused section symbols should be kept.  */
  bool keep_unused_section_symbols;

  /* Entries for byte swapping for data. These are different from the
     other entry points, since they don't take a BFD as the first argument.
     Certain other handlers could do the same.  */
  uint64_t       (*bfd_getx64) (const void *);
  int64_t        (*bfd_getx_signed_64) (const void *);
  void           (*bfd_putx64) (uint64_t, void *);
  bfd_vma        (*bfd_getx32) (const void *);
  bfd_signed_vma (*bfd_getx_signed_32) (const void *);
  void           (*bfd_putx32) (bfd_vma, void *);
  bfd_vma        (*bfd_getx16) (const void *);
  bfd_signed_vma (*bfd_getx_signed_16) (const void *);
  void           (*bfd_putx16) (bfd_vma, void *);

  /* Byte swapping for the headers.  */
  uint64_t       (*bfd_h_getx64) (const void *);
  int64_t        (*bfd_h_getx_signed_64) (const void *);
  void           (*bfd_h_putx64) (uint64_t, void *);
  bfd_vma        (*bfd_h_getx32) (const void *);
  bfd_signed_vma (*bfd_h_getx_signed_32) (const void *);
  void           (*bfd_h_putx32) (bfd_vma, void *);
  bfd_vma        (*bfd_h_getx16) (const void *);
  bfd_signed_vma (*bfd_h_getx_signed_16) (const void *);
  void           (*bfd_h_putx16) (bfd_vma, void *);

  /* Format dependent routines: these are vectors of entry points
     within the target vector structure, one for each format to check.  */

  /* Check the format of a file being read.  Return a bfd_cleanup on
     success or zero on failure.  */
  bfd_cleanup (*_bfd_check_format[bfd_type_end]) (bfd *);

  /* Set the format of a file being written.  */
  bool (*_bfd_set_format[bfd_type_end]) (bfd *);

  /* Write cached information into a file being written, at bfd_close.  */
  bool (*_bfd_write_contents[bfd_type_end]) (bfd *);
```

The general target vector. These vectors are initialized using the BFD_JUMP_TABLE macros.

```
  /* Generic entry points.  */
#define BFD_JUMP_TABLE_GENERIC(NAME) \
```

```
  NAME##_close_and_cleanup, \
  NAME##_bfd_free_cached_info, \
  NAME##_new_section_hook, \
  NAME##_get_section_contents

  /* Called when the BFD is being closed to do any necessary cleanup.  */
  bool (*_close_and_cleanup) (bfd *);
  /* Ask the BFD to free all cached information.  */
  bool (*_bfd_free_cached_info) (bfd *);
  /* Called when a new section is created.  */
  bool (*_new_section_hook) (bfd *, sec_ptr);
  /* Read the contents of a section.  */
  bool (*_bfd_get_section_contents) (bfd *, sec_ptr, void *, file_ptr,
                                     bfd_size_type);

  /* Entry points to copy private data.  */
#define BFD_JUMP_TABLE_COPY(NAME) \
  NAME##_bfd_copy_private_bfd_data, \
  NAME##_bfd_merge_private_bfd_data, \
  NAME##_bfd_copy_private_section_data, \
  NAME##_bfd_copy_private_symbol_data, \
  NAME##_bfd_copy_private_header_data, \
  NAME##_bfd_set_private_flags, \
  NAME##_bfd_print_private_bfd_data

  /* Called to copy BFD general private data from one object file
     to another.  */
  bool (*_bfd_copy_private_bfd_data) (bfd *, bfd *);
  /* Called to merge BFD general private data from one object file
     to a common output file when linking.  */
  bool (*_bfd_merge_private_bfd_data) (bfd *, struct bfd_link_info *);
  /* Called to copy BFD private section data from one object file
     to another.  */
  bool (*_bfd_copy_private_section_data) (bfd *, sec_ptr, bfd *, sec_ptr,
                                          struct bfd_link_info *);
  /* Called to copy BFD private symbol data from one symbol
     to another.  */
  bool (*_bfd_copy_private_symbol_data) (bfd *, asymbol *,
                                         bfd *, asymbol *);
  /* Called to copy BFD private header data from one object file
     to another.  */
  bool (*_bfd_copy_private_header_data) (bfd *, bfd *);
  /* Called to set private backend flags.  */
  bool (*_bfd_set_private_flags) (bfd *, flagword);

  /* Called to print private BFD data.  */
  bool (*_bfd_print_private_bfd_data) (bfd *, void *);
```

```
  /* Core file entry points.  */
#define BFD_JUMP_TABLE_CORE(NAME) \
  NAME##_core_file_failing_command, \
  NAME##_core_file_failing_signal, \
  NAME##_core_file_matches_executable_p, \
  NAME##_core_file_pid

  char *(*_core_file_failing_command) (bfd *);
  int   (*_core_file_failing_signal) (bfd *);
  bool  (*_core_file_matches_executable_p) (bfd *, bfd *);
  int   (*_core_file_pid) (bfd *);

  /* Archive entry points.  */
#define BFD_JUMP_TABLE_ARCHIVE(NAME) \
  NAME##_slurp_armap, \
  NAME##_slurp_extended_name_table, \
  NAME##_construct_extended_name_table, \
  NAME##_truncate_arname, \
  NAME##_write_armap, \
  NAME##_read_ar_hdr, \
  NAME##_write_ar_hdr, \
  NAME##_openr_next_archived_file, \
  NAME##_get_elt_at_index, \
  NAME##_generic_stat_arch_elt, \
  NAME##_update_armap_timestamp

  bool (*_bfd_slurp_armap) (bfd *);
  bool (*_bfd_slurp_extended_name_table) (bfd *);
  bool (*_bfd_construct_extended_name_table) (bfd *, char **,
                                              bfd_size_type *,
                                              const char **);
  void (*_bfd_truncate_arname) (bfd *, const char *, char *);
  bool (*write_armap) (bfd *, unsigned, struct orl *, unsigned, int);
  void *(*_bfd_read_ar_hdr_fn) (bfd *);
  bool (*_bfd_write_ar_hdr_fn) (bfd *, bfd *);
  bfd *(*openr_next_archived_file) (bfd *, bfd *);
#define bfd_get_elt_at_index(b,i) \
       BFD_SEND (b, _bfd_get_elt_at_index, (b,i))
  bfd *(*_bfd_get_elt_at_index) (bfd *, symindex);
  int  (*_bfd_stat_arch_elt) (bfd *, struct stat *);
  bool (*_bfd_update_armap_timestamp) (bfd *);

  /* Entry points used for symbols.  */
#define BFD_JUMP_TABLE_SYMBOLS(NAME) \
  NAME##_get_symtab_upper_bound, \
  NAME##_canonicalize_symtab, \
```

```
  NAME##_make_empty_symbol, \
  NAME##_print_symbol, \
  NAME##_get_symbol_info, \
  NAME##_get_symbol_version_string, \
  NAME##_bfd_is_local_label_name, \
  NAME##_bfd_is_target_special_symbol, \
  NAME##_get_lineno, \
  NAME##_find_nearest_line, \
  NAME##_find_nearest_line_with_alt, \
  NAME##_find_line, \
  NAME##_find_inliner_info, \
  NAME##_bfd_make_debug_symbol, \
  NAME##_read_minisymbols, \
  NAME##_minisymbol_to_symbol

  long (*_bfd_get_symtab_upper_bound) (bfd *);
  long (*_bfd_canonicalize_symtab) (bfd *, struct bfd_symbol **);
  struct bfd_symbol *
       (*_bfd_make_empty_symbol) (bfd *);
  void (*_bfd_print_symbol) (bfd *, void *, struct bfd_symbol *,
                             bfd_print_symbol_type);
#define bfd_print_symbol(b,p,s,e) \
       BFD_SEND (b, _bfd_print_symbol, (b,p,s,e))
  void  (*_bfd_get_symbol_info) (bfd *, struct bfd_symbol *, symbol_info *);
#define bfd_get_symbol_info(b,p,e) \
       BFD_SEND (b, _bfd_get_symbol_info, (b,p,e))
  const char *
       (*_bfd_get_symbol_version_string) (bfd *, struct bfd_symbol *,
                                          bool, bool *);
#define bfd_get_symbol_version_string(b,s,p,h) \
       BFD_SEND (b, _bfd_get_symbol_version_string, (b,s,p,h))
  bool (*_bfd_is_local_label_name) (bfd *, const char *);
  bool (*_bfd_is_target_special_symbol) (bfd *, asymbol *);
  alent *
       (*_get_lineno) (bfd *, struct bfd_symbol *);
  bool (*_bfd_find_nearest_line) (bfd *, struct bfd_symbol **,
                                  struct bfd_section *, bfd_vma,
                                  const char **, const char **,
                                  unsigned int *, unsigned int *);
  bool (*_bfd_find_nearest_line_with_alt) (bfd *, const char *,
                                           struct bfd_symbol **,
                                           struct bfd_section *, bfd_vma,
                                           const char **, const char **,
                                           unsigned int *, unsigned int *);
  bool (*_bfd_find_line) (bfd *, struct bfd_symbol **,
                          struct bfd_symbol *, const char **,
                          unsigned int *);
```

```
  bool (*_bfd_find_inliner_info)
    (bfd *, const char **, const char **, unsigned int *);
 /* Back-door to allow format-aware applications to create debug symbols
    while using BFD for everything else.  Currently used by the assembler
    when creating COFF files.  */
  asymbol *
       (*_bfd_make_debug_symbol) (bfd *);
#define bfd_read_minisymbols(b, d, m, s) \
       BFD_SEND (b, _read_minisymbols, (b, d, m, s))
  long (*_read_minisymbols) (bfd *, bool, void **, unsigned int *);
#define bfd_minisymbol_to_symbol(b, d, m, f) \
       BFD_SEND (b, _minisymbol_to_symbol, (b, d, m, f))
  asymbol *
       (*_minisymbol_to_symbol) (bfd *, bool, const void *, asymbol *);

  /* Routines for relocs.  */
#define BFD_JUMP_TABLE_RELOCS(NAME) \
  NAME##_get_reloc_upper_bound, \
  NAME##_canonicalize_reloc, \
  NAME##_set_reloc, \
  NAME##_bfd_reloc_type_lookup, \
  NAME##_bfd_reloc_name_lookup

  long (*_get_reloc_upper_bound) (bfd *, sec_ptr);
  long (*_bfd_canonicalize_reloc) (bfd *, sec_ptr, arelent **,
                                   struct bfd_symbol **);
  void (*_bfd_set_reloc) (bfd *, sec_ptr, arelent **, unsigned int);
  /* See documentation on reloc types.  */
  reloc_howto_type *
       (*reloc_type_lookup) (bfd *, bfd_reloc_code_real_type);
  reloc_howto_type *
       (*reloc_name_lookup) (bfd *, const char *);

  /* Routines used when writing an object file.  */
#define BFD_JUMP_TABLE_WRITE(NAME) \
  NAME##_set_arch_mach, \
  NAME##_set_section_contents

  bool (*_bfd_set_arch_mach) (bfd *, enum bfd_architecture,
                                   unsigned long);
  bool (*_bfd_set_section_contents) (bfd *, sec_ptr, const void *,
                                   file_ptr, bfd_size_type);

  /* Routines used by the linker.  */
#define BFD_JUMP_TABLE_LINK(NAME) \
  NAME##_sizeof_headers, \
  NAME##_bfd_get_relocated_section_contents, \
```

```
  NAME##_bfd_relax_section, \
  NAME##_bfd_link_hash_table_create, \
  NAME##_bfd_link_add_symbols, \
  NAME##_bfd_link_just_syms, \
  NAME##_bfd_copy_link_hash_symbol_type, \
  NAME##_bfd_final_link, \
  NAME##_bfd_link_split_section, \
  NAME##_bfd_link_check_relocs, \
  NAME##_bfd_gc_sections, \
  NAME##_bfd_lookup_section_flags, \
  NAME##_bfd_merge_sections, \
  NAME##_bfd_is_group_section, \
  NAME##_bfd_group_name, \
  NAME##_bfd_discard_group, \
  NAME##_section_already_linked, \
  NAME##_bfd_define_common_symbol, \
  NAME##_bfd_link_hide_symbol, \
  NAME##_bfd_define_start_stop

  int  (*_bfd_sizeof_headers) (bfd *, struct bfd_link_info *);
  bfd_byte *
       (*_bfd_get_relocated_section_contents) (bfd *,
                                               struct bfd_link_info *,
                                               struct bfd_link_order *,
                                               bfd_byte *, bool,
                                               struct bfd_symbol **);

  bool (*_bfd_relax_section) (bfd *, struct bfd_section *,
                              struct bfd_link_info *, bool *);

  /* Create a hash table for the linker.  Different backends store
     different information in this table.  */
  struct bfd_link_hash_table *
       (*_bfd_link_hash_table_create) (bfd *);

  /* Add symbols from this object file into the hash table.  */
  bool (*_bfd_link_add_symbols) (bfd *, struct bfd_link_info *);

  /* Indicate that we are only retrieving symbol values from this section.  */
  void (*_bfd_link_just_syms) (asection *, struct bfd_link_info *);

  /* Copy the symbol type and other attributes for a linker script
     assignment of one symbol to another.  */
#define bfd_copy_link_hash_symbol_type(b, t, f) \
       BFD_SEND (b, _bfd_copy_link_hash_symbol_type, (b, t, f))
  void (*_bfd_copy_link_hash_symbol_type) (bfd *,
                                           struct bfd_link_hash_entry *,
```

```
                                        struct bfd_link_hash_entry *);

/* Do a link based on the link_order structures attached to each
   section of the BFD.  */
bool (*_bfd_final_link) (bfd *, struct bfd_link_info *);

/* Should this section be split up into smaller pieces during linking.  */
bool (*_bfd_link_split_section) (bfd *, struct bfd_section *);

/* Check the relocations in the bfd for validity.  */
bool (* _bfd_link_check_relocs)(bfd *, struct bfd_link_info *);

/* Remove sections that are not referenced from the output.  */
bool (*_bfd_gc_sections) (bfd *, struct bfd_link_info *);

/* Sets the bitmask of allowed and disallowed section flags.  */
bool (*_bfd_lookup_section_flags) (struct bfd_link_info *,
                                   struct flag_info *, asection *);

/* Attempt to merge SEC_MERGE sections.  */
bool (*_bfd_merge_sections) (bfd *, struct bfd_link_info *);

/* Is this section a member of a group?  */
bool (*_bfd_is_group_section) (bfd *, const struct bfd_section *);

/* The group name, if section is a member of a group.  */
const char *(*_bfd_group_name) (bfd *, const struct bfd_section *);

/* Discard members of a group.  */
bool (*_bfd_discard_group) (bfd *, struct bfd_section *);

/* Check if SEC has been already linked during a reloceatable or
   final link.  */
bool (*_section_already_linked) (bfd *, asection *,
                                 struct bfd_link_info *);

/* Define a common symbol.  */
bool (*_bfd_define_common_symbol) (bfd *, struct bfd_link_info *,
                                   struct bfd_link_hash_entry *);

/* Hide a symbol.  */
void (*_bfd_link_hide_symbol) (bfd *, struct bfd_link_info *,
                               struct bfd_link_hash_entry *);

/* Define a __start, __stop, .startof. or .sizeof. symbol.  */
struct bfd_link_hash_entry *
     (*_bfd_define_start_stop) (struct bfd_link_info *, const char *,
```

```
                                    asection *);

  /* Routines to handle dynamic symbols and relocs.  */
#define BFD_JUMP_TABLE_DYNAMIC(NAME) \
  NAME##_get_dynamic_symtab_upper_bound, \
  NAME##_canonicalize_dynamic_symtab, \
  NAME##_get_synthetic_symtab, \
  NAME##_get_dynamic_reloc_upper_bound, \
  NAME##_canonicalize_dynamic_reloc

  /* Get the amount of memory required to hold the dynamic symbols.  */
  long (*_bfd_get_dynamic_symtab_upper_bound) (bfd *);
  /* Read in the dynamic symbols.  */
  long (*_bfd_canonicalize_dynamic_symtab) (bfd *, struct bfd_symbol **);
  /* Create synthetized symbols.  */
  long (*_bfd_get_synthetic_symtab) (bfd *, long, struct bfd_symbol **,
                                     long, struct bfd_symbol **,
                                     struct bfd_symbol **);
  /* Get the amount of memory required to hold the dynamic relocs.  */
  long (*_bfd_get_dynamic_reloc_upper_bound) (bfd *);
  /* Read in the dynamic relocs.  */
  long (*_bfd_canonicalize_dynamic_reloc) (bfd *, arelent **,
                                           struct bfd_symbol **);
```

A pointer to an alternative bfd_target in case the current one is not satisfactory. This can happen when the target cpu supports both big and little endian code, and target chosen by the linker has the wrong endianness. The function open_output() in ld/ldlang.c uses this field to find an alternative output format that is suitable.

```
  /* Opposite endian version of this target.  */
  const struct bfd_target *alternative_target;

  /* Data for use by back-end routines, which isn't
     generic enough to belong in this structure.  */
  const void *backend_data;

} bfd_target;

static inline const char *
bfd_get_target (const bfd *abfd)
{
  return abfd->xvec->name;
}

static inline enum bfd_flavour
bfd_get_flavour (const bfd *abfd)
{
```

```
  return abfd->xvec->flavour;
}

static inline flagword
bfd_applicable_file_flags (const bfd *abfd)
{
  return abfd->xvec->object_flags;
}

static inline bool
bfd_family_coff (const bfd *abfd)
{
  return (bfd_get_flavour (abfd) == bfd_target_coff_flavour
          || bfd_get_flavour (abfd) == bfd_target_xcoff_flavour);
}

static inline bool
bfd_big_endian (const bfd *abfd)
{
  return abfd->xvec->byteorder == BFD_ENDIAN_BIG;
}
static inline bool
bfd_little_endian (const bfd *abfd)
{
  return abfd->xvec->byteorder == BFD_ENDIAN_LITTLE;
}

static inline bool
bfd_header_big_endian (const bfd *abfd)
{
  return abfd->xvec->header_byteorder == BFD_ENDIAN_BIG;
}

static inline bool
bfd_header_little_endian (const bfd *abfd)
{
  return abfd->xvec->header_byteorder == BFD_ENDIAN_LITTLE;
}

static inline flagword
bfd_applicable_section_flags (const bfd *abfd)
{
  return abfd->xvec->section_flags;
}

static inline char
bfd_get_symbol_leading_char (const bfd *abfd)
```

```
{
  return abfd->xvec->symbol_leading_char;
}

static inline enum bfd_flavour
bfd_asymbol_flavour (const asymbol *sy)
{
  if ((sy->flags & BSF_SYNTHETIC) != 0)
    return bfd_target_unknown_flavour;
  return sy->the_bfd->xvec->flavour;
}

static inline bool
bfd_keep_unused_section_symbols (const bfd *abfd)
{
  return abfd->xvec->keep_unused_section_symbols;
}

static inline bool
bfd_target_supports_archives (const bfd *abfd)
{
  return (abfd->xvec->_bfd_check_format[bfd_archive]
          != abfd->xvec->_bfd_check_format[bfd_unknown]);
}
```

2.12.1.1 bfd_set_default_target

`bool bfd_set_default_target (const char *name);` [Function]

Set the default target vector to use when recognizing a BFD. This takes the name of the target, which may be a BFD target name or a configuration triplet.

2.12.1.2 bfd_find_target

`const bfd_target *bfd_find_target (const char *target_name, bfd *abfd);` [Function]

Return a pointer to the transfer vector for the object target named *target_name*. If *target_name* is `NULL`, choose the one in the environment variable `GNUTARGET`; if that is null or not defined, then choose the first entry in the target list. Passing in the string "default" or setting the environment variable to "default" will cause the first entry in the target list to be returned, and "target_defaulted" will be set in the BFD if *abfd* isn't `NULL`. This causes `bfd_check_format` to loop over all the targets to find the one that matches the file being read.

2.12.1.3 bfd_get_target_info

`const bfd_target *bfd_get_target_info (const char *target_name, bfd *abfd, bool *is_bigendian, int *underscoring, const char **def_target_arch);` [Function]

Return a pointer to the transfer vector for the object target named *target_name*. If *target_name* is `NULL`, choose the one in the environment variable `GNUTARGET`; if that is null or not defined, then choose the first entry in the target list. Passing in the string `"default"` or setting the environment variable to `"default"` will cause the first entry in the target list to be returned, and `"target_defaulted"` will be set in the BFD if *abfd* isn't `NULL`. This causes `bfd_check_format` to loop over all the targets to find the one that matches the file being read. If *is_bigendian* is not `NULL`, then set this value to target's endian mode. True for big-endian, FALSE for little-endian or for invalid target. If *underscoring* is not `NULL`, then set this value to target's underscoring mode. Zero for none-underscoring, -1 for invalid target, else the value of target vector's symbol underscoring. If *def_target_arch* is not `NULL`, then set it to the architecture string specified by the target_name.

2.12.1.4 bfd_target_list

`const char ** bfd_target_list (void);` [Function]

Return a freshly malloced NULL-terminated vector of the names of all the valid BFD targets. Do not modify the names.

2.12.1.5 bfd_iterate_over_targets

`const bfd_target *bfd_iterate_over_targets (int (*func) (const bfd_target *, void *), void *data);` [Function]

Call *func* for each target in the list of BFD target vectors, passing *data* to *func*. Stop iterating if *func* returns a non-zero result, and return that target vector. Return NULL if *func* always returns zero.

2.12.1.6 bfd_flavour_name

`const char *bfd_flavour_name (enum bfd_flavour flavour);` [Function]

Return the string form of *flavour*.

2.13 Architectures

BFD keeps one atom in a BFD describing the architecture of the data attached to the BFD: a pointer to a `bfd_arch_info_type`.

Pointers to structures can be requested independently of a BFD so that an architecture's information can be interrogated without access to an open BFD.

The architecture information is provided by each architecture package. The set of default architectures is selected by the macro `SELECT_ARCHITECTURES`. This is normally set up in the `config/target.mt` file of your choice. If the name is not defined, then all the architectures supported are included.

When BFD starts up, all the architectures are called with an initialize method. It is up to the architecture back end to insert as many items into the list of architectures as it wants

to; generally this would be one for each machine and one for the default case (an item with a machine field of 0).

BFD's idea of an architecture is implemented in `archures.c`.

2.13.1 bfd_architecture

This enum gives the object file's CPU architecture, in a global sense—i.e., what processor family does it belong to? Another field indicates which processor within the family is in use. The machine gives a number which distinguishes different versions of the architecture, containing, for example, 68020 for Motorola 68020.

```
enum bfd_architecture
{
  bfd_arch_unknown,   /* File arch not known.  */
  bfd_arch_obscure,   /* Arch known, not one of these.  */
  bfd_arch_m68k,      /* Motorola 68xxx.  */
#define bfd_mach_m68000               1
#define bfd_mach_m68008               2
#define bfd_mach_m68010               3
#define bfd_mach_m68020               4
#define bfd_mach_m68030               5
#define bfd_mach_m68040               6
#define bfd_mach_m68060               7
#define bfd_mach_cpu32                8
#define bfd_mach_fido                 9
#define bfd_mach_mcf_isa_a_nodiv      10
#define bfd_mach_mcf_isa_a            11
#define bfd_mach_mcf_isa_a_mac        12
#define bfd_mach_mcf_isa_a_emac       13
#define bfd_mach_mcf_isa_aplus        14
#define bfd_mach_mcf_isa_aplus_mac    15
#define bfd_mach_mcf_isa_aplus_emac   16
#define bfd_mach_mcf_isa_b_nousp      17
#define bfd_mach_mcf_isa_b_nousp_mac  18
#define bfd_mach_mcf_isa_b_nousp_emac 19
#define bfd_mach_mcf_isa_b            20
#define bfd_mach_mcf_isa_b_mac        21
#define bfd_mach_mcf_isa_b_emac       22
#define bfd_mach_mcf_isa_b_float      23
#define bfd_mach_mcf_isa_b_float_mac  24
#define bfd_mach_mcf_isa_b_float_emac 25
#define bfd_mach_mcf_isa_c            26
#define bfd_mach_mcf_isa_c_mac        27
#define bfd_mach_mcf_isa_c_emac       28
#define bfd_mach_mcf_isa_c_nodiv      29
#define bfd_mach_mcf_isa_c_nodiv_mac  30
#define bfd_mach_mcf_isa_c_nodiv_emac 31
  bfd_arch_vax,       /* DEC Vax.  */
```

```
  bfd_arch_or1k,      /* OpenRISC 1000.  */
#define bfd_mach_or1k          1
#define bfd_mach_or1knd        2

  bfd_arch_sparc,     /* SPARC.  */
#define bfd_mach_sparc                 1
/* The difference between v8plus and v9 is that v9 is a true 64 bit env.  */
#define bfd_mach_sparc_sparclet        2
#define bfd_mach_sparc_sparclite       3
#define bfd_mach_sparc_v8plus          4
#define bfd_mach_sparc_v8plusa         5 /* with ultrasparc add'ns.  */
#define bfd_mach_sparc_sparclite_le    6
#define bfd_mach_sparc_v9              7
#define bfd_mach_sparc_v9a             8 /* with ultrasparc add'ns.  */
#define bfd_mach_sparc_v8plusb         9 /* with cheetah add'ns.  */
#define bfd_mach_sparc_v9b             10 /* with cheetah add'ns.  */
#define bfd_mach_sparc_v8plusc         11 /* with UA2005 and T1 add'ns.  */
#define bfd_mach_sparc_v9c             12 /* with UA2005 and T1 add'ns.  */
#define bfd_mach_sparc_v8plusd         13 /* with UA2007 and T3 add'ns.  */
#define bfd_mach_sparc_v9d             14 /* with UA2007 and T3 add'ns.  */
#define bfd_mach_sparc_v8pluse         15 /* with OSA2001 and T4 add'ns (no IMA).  */
#define bfd_mach_sparc_v9e             16 /* with OSA2001 and T4 add'ns (no IMA).  */
#define bfd_mach_sparc_v8plusv         17 /* with OSA2011 and T4 and IMA and FJMAU add
#define bfd_mach_sparc_v9v             18 /* with OSA2011 and T4 and IMA and FJMAU add
#define bfd_mach_sparc_v8plusm         19 /* with OSA2015 and M7 add'ns.  */
#define bfd_mach_sparc_v9m             20 /* with OSA2015 and M7 add'ns.  */
#define bfd_mach_sparc_v8plusm8        21 /* with OSA2017 and M8 add'ns.  */
#define bfd_mach_sparc_v9m8            22 /* with OSA2017 and M8 add'ns.  */
/* Nonzero if MACH has the v9 instruction set.  */
#define bfd_mach_sparc_v9_p(mach) \
  ((mach) >= bfd_mach_sparc_v8plus && (mach) <= bfd_mach_sparc_v9m8 \
   && (mach) != bfd_mach_sparc_sparclite_le)
/* Nonzero if MACH is a 64 bit sparc architecture.  */
#define bfd_mach_sparc_64bit_p(mach) \
  ((mach) >= bfd_mach_sparc_v9 \
   && (mach) != bfd_mach_sparc_v8plusb \
   && (mach) != bfd_mach_sparc_v8plusc \
   && (mach) != bfd_mach_sparc_v8plusd \
   && (mach) != bfd_mach_sparc_v8pluse \
   && (mach) != bfd_mach_sparc_v8plusv \
   && (mach) != bfd_mach_sparc_v8plusm \
   && (mach) != bfd_mach_sparc_v8plusm8)
  bfd_arch_spu,       /* PowerPC SPU.  */
#define bfd_mach_spu           256
  bfd_arch_mips,      /* MIPS Rxxxx.  */
#define bfd_mach_mips3000              3000
```

```
#define bfd_mach_mips3900             3900
#define bfd_mach_mips4000             4000
#define bfd_mach_mips4010             4010
#define bfd_mach_mips4100             4100
#define bfd_mach_mips4111             4111
#define bfd_mach_mips4120             4120
#define bfd_mach_mips4300             4300
#define bfd_mach_mips4400             4400
#define bfd_mach_mips4600             4600
#define bfd_mach_mips4650             4650
#define bfd_mach_mips5000             5000
#define bfd_mach_mips5400             5400
#define bfd_mach_mips5500             5500
#define bfd_mach_mips5900             5900
#define bfd_mach_mips6000             6000
#define bfd_mach_mips7000             7000
#define bfd_mach_mips8000             8000
#define bfd_mach_mips9000             9000
#define bfd_mach_mips10000            10000
#define bfd_mach_mips12000            12000
#define bfd_mach_mips14000            14000
#define bfd_mach_mips16000            16000
#define bfd_mach_mips16               16
#define bfd_mach_mips5                5
#define bfd_mach_mips_allegrex        10111431 /* octal 'AL', 31.  */
#define bfd_mach_mips_loongson_2e     3001
#define bfd_mach_mips_loongson_2f     3002
#define bfd_mach_mips_gs464           3003
#define bfd_mach_mips_gs464e          3004
#define bfd_mach_mips_gs264e          3005
#define bfd_mach_mips_sb1             12310201 /* octal 'SB', 01.  */
#define bfd_mach_mips_octeon          6501
#define bfd_mach_mips_octeonp         6601
#define bfd_mach_mips_octeon2         6502
#define bfd_mach_mips_octeon3         6503
#define bfd_mach_mips_xlr             887682   /* decimal 'XLR'.  */
#define bfd_mach_mips_interaptiv_mr2  736550   /* decimal 'IA2'.  */
#define bfd_mach_mipsisa32            32
#define bfd_mach_mipsisa32r2          33
#define bfd_mach_mipsisa32r3          34
#define bfd_mach_mipsisa32r5          36
#define bfd_mach_mipsisa32r6          37
#define bfd_mach_mipsisa64            64
#define bfd_mach_mipsisa64r2          65
#define bfd_mach_mipsisa64r3          66
#define bfd_mach_mipsisa64r5          68
#define bfd_mach_mipsisa64r6          69
```

```
#define bfd_mach_mips_micromips        96
  bfd_arch_i386,      /* Intel 386.  */
#define bfd_mach_i386_intel_syntax     (1 << 0)
#define bfd_mach_i386_i8086            (1 << 1)
#define bfd_mach_i386_i386             (1 << 2)
#define bfd_mach_x86_64                (1 << 3)
#define bfd_mach_x64_32                (1 << 4)
#define bfd_mach_i386_i386_intel_syntax (bfd_mach_i386_i386 | bfd_mach_i386_intel_synt
#define bfd_mach_x86_64_intel_syntax   (bfd_mach_x86_64 | bfd_mach_i386_intel_syntax)
#define bfd_mach_x64_32_intel_syntax   (bfd_mach_x64_32 | bfd_mach_i386_intel_syntax)
  bfd_arch_iamcu,     /* Intel MCU.  */
#define bfd_mach_iamcu                 (1 << 8)
#define bfd_mach_i386_iamcu            (bfd_mach_i386_i386 | bfd_mach_iamcu)
#define bfd_mach_i386_iamcu_intel_syntax (bfd_mach_i386_iamcu | bfd_mach_i386_intel_sy
  bfd_arch_romp,      /* IBM ROMP PC/RT.  */
  bfd_arch_convex,    /* Convex.  */
  bfd_arch_m98k,      /* Motorola 98xxx.  */
  bfd_arch_pyramid,   /* Pyramid Technology.  */
  bfd_arch_h8300,     /* Renesas H8/300 (formerly Hitachi H8/300).  */
#define bfd_mach_h8300         1
#define bfd_mach_h8300h        2
#define bfd_mach_h8300s        3
#define bfd_mach_h8300hn       4
#define bfd_mach_h8300sn       5
#define bfd_mach_h8300sx       6
#define bfd_mach_h8300sxn      7
  bfd_arch_pdp11,     /* DEC PDP-11.  */
  bfd_arch_powerpc,   /* PowerPC.  */
#define bfd_mach_ppc           32
#define bfd_mach_ppc64         64
#define bfd_mach_ppc_403       403
#define bfd_mach_ppc_403gc     4030
#define bfd_mach_ppc_405       405
#define bfd_mach_ppc_505       505
#define bfd_mach_ppc_601       601
#define bfd_mach_ppc_602       602
#define bfd_mach_ppc_603       603
#define bfd_mach_ppc_ec603e    6031
#define bfd_mach_ppc_604       604
#define bfd_mach_ppc_620       620
#define bfd_mach_ppc_630       630
#define bfd_mach_ppc_750       750
#define bfd_mach_ppc_860       860
#define bfd_mach_ppc_a35       35
#define bfd_mach_ppc_rs64ii    642
#define bfd_mach_ppc_rs64iii   643
#define bfd_mach_ppc_7400      7400
```

```
#define bfd_mach_ppc_e500      500
#define bfd_mach_ppc_e500mc    5001
#define bfd_mach_ppc_e500mc64  5005
#define bfd_mach_ppc_e5500     5006
#define bfd_mach_ppc_e6500     5007
#define bfd_mach_ppc_titan     83
#define bfd_mach_ppc_vle       84
  bfd_arch_rs6000,    /* IBM RS/6000.  */
#define bfd_mach_rs6k          6000
#define bfd_mach_rs6k_rs1      6001
#define bfd_mach_rs6k_rsc      6003
#define bfd_mach_rs6k_rs2      6002
  bfd_arch_hppa,      /* HP PA RISC.  */
#define bfd_mach_hppa10        10
#define bfd_mach_hppa11        11
#define bfd_mach_hppa20        20
#define bfd_mach_hppa20w       25
  bfd_arch_d10v,      /* Mitsubishi D10V.  */
#define bfd_mach_d10v          1
#define bfd_mach_d10v_ts2      2
#define bfd_mach_d10v_ts3      3
  bfd_arch_d30v,      /* Mitsubishi D30V.  */
  bfd_arch_dlx,       /* DLX.  */
  bfd_arch_m68hc11,   /* Motorola 68HC11.  */
  bfd_arch_m68hc12,   /* Motorola 68HC12.  */
#define bfd_mach_m6812_default 0
#define bfd_mach_m6812         1
#define bfd_mach_m6812s        2
  bfd_arch_m9s12x,    /* Freescale S12X.  */
  bfd_arch_m9s12xg,   /* Freescale XGATE.  */
  bfd_arch_s12z,    /* Freescale S12Z.  */
#define bfd_mach_s12z_default 0
  bfd_arch_z8k,       /* Zilog Z8000.  */
#define bfd_mach_z8001         1
#define bfd_mach_z8002         2
  bfd_arch_sh,        /* Renesas / SuperH SH (formerly Hitachi SH).  */
#define bfd_mach_sh                             1
#define bfd_mach_sh2                            0x20
#define bfd_mach_sh_dsp                         0x2d
#define bfd_mach_sh2a                           0x2a
#define bfd_mach_sh2a_nofpu                     0x2b
#define bfd_mach_sh2a_nofpu_or_sh4_nommu_nofpu 0x2a1
#define bfd_mach_sh2a_nofpu_or_sh3_nommu       0x2a2
#define bfd_mach_sh2a_or_sh4                    0x2a3
#define bfd_mach_sh2a_or_sh3e                   0x2a4
#define bfd_mach_sh2e                           0x2e
#define bfd_mach_sh3                            0x30
```

```
#define bfd_mach_sh3_nommu                    0x31
#define bfd_mach_sh3_dsp                      0x3d
#define bfd_mach_sh3e                         0x3e
#define bfd_mach_sh4                          0x40
#define bfd_mach_sh4_nofpu                    0x41
#define bfd_mach_sh4_nommu_nofpu              0x42
#define bfd_mach_sh4a                         0x4a
#define bfd_mach_sh4a_nofpu                   0x4b
#define bfd_mach_sh4al_dsp                    0x4d
  bfd_arch_alpha,     /* Dec Alpha.  */
#define bfd_mach_alpha_ev4     0x10
#define bfd_mach_alpha_ev5     0x20
#define bfd_mach_alpha_ev6     0x30
  bfd_arch_arm,       /* Advanced Risc Machines ARM.  */
#define bfd_mach_arm_unknown   0
#define bfd_mach_arm_2         1
#define bfd_mach_arm_2a        2
#define bfd_mach_arm_3         3
#define bfd_mach_arm_3M        4
#define bfd_mach_arm_4         5
#define bfd_mach_arm_4T        6
#define bfd_mach_arm_5         7
#define bfd_mach_arm_5T        8
#define bfd_mach_arm_5TE       9
#define bfd_mach_arm_XScale    10
#define bfd_mach_arm_ep9312    11
#define bfd_mach_arm_iWMMXt    12
#define bfd_mach_arm_iWMMXt2   13
#define bfd_mach_arm_5TEJ      14
#define bfd_mach_arm_6         15
#define bfd_mach_arm_6KZ       16
#define bfd_mach_arm_6T2       17
#define bfd_mach_arm_6K        18
#define bfd_mach_arm_7         19
#define bfd_mach_arm_6M        20
#define bfd_mach_arm_6SM       21
#define bfd_mach_arm_7EM       22
#define bfd_mach_arm_8         23
#define bfd_mach_arm_8R        24
#define bfd_mach_arm_8M_BASE   25
#define bfd_mach_arm_8M_MAIN   26
#define bfd_mach_arm_8_1M_MAIN 27
#define bfd_mach_arm_9         28
  bfd_arch_nds32,     /* Andes NDS32.  */
#define bfd_mach_n1            1
#define bfd_mach_n1h           2
#define bfd_mach_n1h_v2        3
```

```
#define bfd_mach_n1h_v3        4
#define bfd_mach_n1h_v3m       5
  bfd_arch_ns32k,     /* National Semiconductors ns32000.  */
  bfd_arch_tic30,     /* Texas Instruments TMS320C30.  */
  bfd_arch_tic4x,     /* Texas Instruments TMS320C3X/4X.  */
#define bfd_mach_tic3x         30
#define bfd_mach_tic4x         40
  bfd_arch_tic54x,    /* Texas Instruments TMS320C54X.  */
  bfd_arch_tic6x,     /* Texas Instruments TMS320C6X.  */
  bfd_arch_v850,      /* NEC V850.  */
  bfd_arch_v850_rh850,/* NEC V850 (using RH850 ABI).  */
#define bfd_mach_v850          1
#define bfd_mach_v850e         'E'
#define bfd_mach_v850e1        '1'
#define bfd_mach_v850e2        0x4532
#define bfd_mach_v850e2v3      0x45325633
#define bfd_mach_v850e3v5      0x45335635 /* ('E'|'3'|'V'|'5').  */
  bfd_arch_arc,       /* ARC Cores.  */
#define bfd_mach_arc_a4        0
#define bfd_mach_arc_a5        1
#define bfd_mach_arc_arc600    2
#define bfd_mach_arc_arc601    4
#define bfd_mach_arc_arc700    3
#define bfd_mach_arc_arcv2     5
 bfd_arch_m32c,       /* Renesas M16C/M32C.  */
#define bfd_mach_m16c          0x75
#define bfd_mach_m32c          0x78
  bfd_arch_m32r,      /* Renesas M32R (formerly Mitsubishi M32R/D).  */
#define bfd_mach_m32r          1 /* For backwards compatibility.  */
#define bfd_mach_m32rx         'x'
#define bfd_mach_m32r2         '2'
  bfd_arch_mn10200,   /* Matsushita MN10200.  */
  bfd_arch_mn10300,   /* Matsushita MN10300.  */
#define bfd_mach_mn10300       300
#define bfd_mach_am33          330
#define bfd_mach_am33_2        332
  bfd_arch_fr30,
#define bfd_mach_fr30          0x46523330
  bfd_arch_frv,
#define bfd_mach_frv           1
#define bfd_mach_frvsimple     2
#define bfd_mach_fr300         300
#define bfd_mach_fr400         400
#define bfd_mach_fr450         450
#define bfd_mach_frvtomcat     499     /* fr500 prototype.  */
#define bfd_mach_fr500         500
#define bfd_mach_fr550         550
```

```
  bfd_arch_moxie,     /* The moxie processor.  */
#define bfd_mach_moxie         1
  bfd_arch_ft32,      /* The ft32 processor.  */
#define bfd_mach_ft32          1
#define bfd_mach_ft32b         2
  bfd_arch_mcore,
  bfd_arch_mep,
#define bfd_mach_mep           1
#define bfd_mach_mep_h1        0x6831
#define bfd_mach_mep_c5        0x6335
  bfd_arch_metag,
#define bfd_mach_metag         1
  bfd_arch_ia64,      /* HP/Intel ia64.  */
#define bfd_mach_ia64_elf64    64
#define bfd_mach_ia64_elf32    32
  bfd_arch_ip2k,      /* Ubicom IP2K microcontrollers. */
#define bfd_mach_ip2022        1
#define bfd_mach_ip2022ext     2
 bfd_arch_iq2000,     /* Vitesse IQ2000.  */
#define bfd_mach_iq2000        1
#define bfd_mach_iq10          2
  bfd_arch_bpf,       /* Linux eBPF.  */
#define bfd_mach_bpf           1
#define bfd_mach_xbpf          2
  bfd_arch_epiphany,  /* Adapteva EPIPHANY.  */
#define bfd_mach_epiphany16    1
#define bfd_mach_epiphany32    2
  bfd_arch_mt,
#define bfd_mach_ms1           1
#define bfd_mach_mrisc2        2
#define bfd_mach_ms2           3
  bfd_arch_pj,
  bfd_arch_avr,       /* Atmel AVR microcontrollers.  */
#define bfd_mach_avr1          1
#define bfd_mach_avr2          2
#define bfd_mach_avr25         25
#define bfd_mach_avr3          3
#define bfd_mach_avr31         31
#define bfd_mach_avr35         35
#define bfd_mach_avr4          4
#define bfd_mach_avr5          5
#define bfd_mach_avr51         51
#define bfd_mach_avr6          6
#define bfd_mach_avrtiny       100
#define bfd_mach_avrxmega1     101
#define bfd_mach_avrxmega2     102
#define bfd_mach_avrxmega3     103
```

```
#define bfd_mach_avrxmega4     104
#define bfd_mach_avrxmega5     105
#define bfd_mach_avrxmega6     106
#define bfd_mach_avrxmega7     107
  bfd_arch_bfin,      /* ADI Blackfin.  */
#define bfd_mach_bfin          1
  bfd_arch_cr16,      /* National Semiconductor CompactRISC (ie CR16).  */
#define bfd_mach_cr16          1
  bfd_arch_crx,       /*  National Semiconductor CRX.  */
#define bfd_mach_crx           1
  bfd_arch_cris,      /* Axis CRIS.  */
#define bfd_mach_cris_v0_v10   255
#define bfd_mach_cris_v32      32
#define bfd_mach_cris_v10_v32  1032
  bfd_arch_riscv,
#define bfd_mach_riscv32       132
#define bfd_mach_riscv64       164
  bfd_arch_rl78,
#define bfd_mach_rl78          0x75
  bfd_arch_rx,        /* Renesas RX.  */
#define bfd_mach_rx            0x75
#define bfd_mach_rx_v2         0x76
#define bfd_mach_rx_v3         0x77
  bfd_arch_s390,      /* IBM s390.  */
#define bfd_mach_s390_31       31
#define bfd_mach_s390_64       64
  bfd_arch_score,     /* Sunplus score.  */
#define bfd_mach_score3        3
#define bfd_mach_score7        7
  bfd_arch_mmix,      /* Donald Knuth's educational processor.  */
  bfd_arch_xstormy16,
#define bfd_mach_xstormy16     1
  bfd_arch_msp430,    /* Texas Instruments MSP430 architecture.  */
#define bfd_mach_msp11         11
#define bfd_mach_msp110        110
#define bfd_mach_msp12         12
#define bfd_mach_msp13         13
#define bfd_mach_msp14         14
#define bfd_mach_msp15         15
#define bfd_mach_msp16         16
#define bfd_mach_msp20         20
#define bfd_mach_msp21         21
#define bfd_mach_msp22         22
#define bfd_mach_msp23         23
#define bfd_mach_msp24         24
#define bfd_mach_msp26         26
#define bfd_mach_msp31         31
```

```
#define bfd_mach_msp32         32
#define bfd_mach_msp33         33
#define bfd_mach_msp41         41
#define bfd_mach_msp42         42
#define bfd_mach_msp43         43
#define bfd_mach_msp44         44
#define bfd_mach_msp430x       45
#define bfd_mach_msp46         46
#define bfd_mach_msp47         47
#define bfd_mach_msp54         54
  bfd_arch_xgate,     /* Freescale XGATE.  */
#define bfd_mach_xgate         1
  bfd_arch_xtensa,    /* Tensilica's Xtensa cores.  */
#define bfd_mach_xtensa        1
  bfd_arch_z80,
/* Zilog Z80 without undocumented opcodes.  */
#define bfd_mach_z80strict     1
/* Zilog Z180: successor with additional instructions, but without
 halves of ix and iy.  */
#define bfd_mach_z180          2
/* Zilog Z80 with ixl, ixh, iyl, and iyh.  */
#define bfd_mach_z80           3
/* Zilog eZ80 (successor of Z80 & Z180) in Z80 (16-bit address) mode.  */
#define bfd_mach_ez80_z80      4
/* Zilog eZ80 (successor of Z80 & Z180) in ADL (24-bit address) mode.  */
#define bfd_mach_ez80_adl      5
/* Z80N */
#define bfd_mach_z80n          6
/* Zilog Z80 with all undocumented instructions.  */
#define bfd_mach_z80full       7
/* GameBoy Z80 (reduced instruction set).  */
#define bfd_mach_gbz80         8
/* ASCII R800: successor with multiplication.  */
#define bfd_mach_r800          11
  bfd_arch_lm32,      /* Lattice Mico32.  */
#define bfd_mach_lm32          1
  bfd_arch_microblaze,/* Xilinx MicroBlaze.  */
  bfd_arch_kvx,        /* Kalray VLIW core of the MPPA processor family */
#define bfd_mach_kv3_unknown       0
#define bfd_mach_kv3_1             1
#define bfd_mach_kv3_1_64          2
#define bfd_mach_kv3_1_usr         3
#define bfd_mach_kv3_2             4
#define bfd_mach_kv3_2_64          5
#define bfd_mach_kv3_2_usr         6
#define bfd_mach_kv4_1             7
#define bfd_mach_kv4_1_64          8
```

```
#define bfd_mach_kv4_1_usr         9
  bfd_arch_tilepro,   /* Tilera TILEPro.  */
  bfd_arch_tilegx,    /* Tilera TILE-Gx.  */
#define bfd_mach_tilepro       1
#define bfd_mach_tilegx        1
#define bfd_mach_tilegx32      2
  bfd_arch_aarch64,   /* AArch64.  */
#define bfd_mach_aarch64 0
#define bfd_mach_aarch64_8R    1
#define bfd_mach_aarch64_ilp32 32
#define bfd_mach_aarch64_llp64 64
  bfd_arch_visium,    /* Visium.  */
#define bfd_mach_visium        1
  bfd_arch_wasm32,    /* WebAssembly.  */
#define bfd_mach_wasm32        1
  bfd_arch_pru,       /* PRU.  */
#define bfd_mach_pru           0
  bfd_arch_nfp,       /* Netronome Flow Processor */
#define bfd_mach_nfp3200       0x3200
#define bfd_mach_nfp6000       0x6000
  bfd_arch_csky,      /* C-SKY.  */
#define bfd_mach_ck_unknown    0
#define bfd_mach_ck510         1
#define bfd_mach_ck610         2
#define bfd_mach_ck801         3
#define bfd_mach_ck802         4
#define bfd_mach_ck803         5
#define bfd_mach_ck807         6
#define bfd_mach_ck810         7
#define bfd_mach_ck860         8
  bfd_arch_loongarch,       /* LoongArch */
#define bfd_mach_loongarch32   1
#define bfd_mach_loongarch64   2
  bfd_arch_amdgcn,     /* AMDGCN */
#define bfd_mach_amdgcn_unknown 0x000
#define bfd_mach_amdgcn_gfx900  0x02c
#define bfd_mach_amdgcn_gfx904  0x02e
#define bfd_mach_amdgcn_gfx906  0x02f
#define bfd_mach_amdgcn_gfx908  0x030
#define bfd_mach_amdgcn_gfx90a  0x03f
#define bfd_mach_amdgcn_gfx1010 0x033
#define bfd_mach_amdgcn_gfx1011 0x034
#define bfd_mach_amdgcn_gfx1012 0x035
#define bfd_mach_amdgcn_gfx1030 0x036
#define bfd_mach_amdgcn_gfx1031 0x037
#define bfd_mach_amdgcn_gfx1032 0x038
#define bfd_mach_amdgcn_gfx1100 0x041
```

```
#define bfd_mach_amdgcn_gfx1101 0x046
#define bfd_mach_amdgcn_gfx1102 0x047
  bfd_arch_last
  };
```

2.13.2 bfd_arch_info

This structure contains information on architectures for use within BFD.

```
typedef struct bfd_arch_info
{
  int bits_per_word;
  int bits_per_address;
  int bits_per_byte;
  enum bfd_architecture arch;
  unsigned long mach;
  const char *arch_name;
  const char *printable_name;
  unsigned int section_align_power;
  /* TRUE if this is the default machine for the architecture.
     The default arch should be the first entry for an arch so that
     all the entries for that arch can be accessed via next.  */
  bool the_default;
  const struct bfd_arch_info * (*compatible) (const struct bfd_arch_info *,
                                              const struct bfd_arch_info *);

  bool (*scan) (const struct bfd_arch_info *, const char *);

  /* Allocate via bfd_malloc and return a fill buffer of size COUNT.  If
     IS_BIGENDIAN is TRUE, the order of bytes is big endian.  If CODE is
     TRUE, the buffer contains code.  */
  void *(*fill) (bfd_size_type count, bool is_bigendian, bool code);

  const struct bfd_arch_info *next;

  /* On some architectures the offset for a relocation can point into
     the middle of an instruction.  This field specifies the maximum
     offset such a relocation can have (in octets).  This affects the
     behaviour of the disassembler, since a value greater than zero
     means that it may need to disassemble an instruction twice, once
     to get its length and then a second time to display it.  If the
     value is negative then this has to be done for every single
     instruction, regardless of the offset of the reloc.  */
  signed int max_reloc_offset_into_insn;
}
bfd_arch_info_type;
```

2.13.2.1 bfd_printable_name

`const char *bfd_printable_name (bfd *abfd);` [Function]

Return a printable string representing the architecture and machine from the pointer to the architecture info structure.

2.13.2.2 bfd_scan_arch

`const bfd_arch_info_type *bfd_scan_arch (const char *string);` [Function]

Figure out if BFD supports any cpu which could be described with the name *string*. Return a pointer to an `arch_info` structure if a machine is found, otherwise NULL.

2.13.2.3 bfd_arch_list

`const char **bfd_arch_list (void);` [Function]

Return a freshly malloced NULL-terminated vector of the names of all the valid BFD architectures. Do not modify the names.

2.13.2.4 bfd_arch_get_compatible

`const bfd_arch_info_type *bfd_arch_get_compatible (const bfd *abfd, const bfd *bbfd, bool accept_unknowns);` [Function]

Determine whether two BFDs' architectures and machine types are compatible. Calculates the lowest common denominator between the two architectures and machine types implied by the BFDs and returns a pointer to an `arch_info` structure describing the compatible machine.

2.13.2.5 bfd_default_arch_struct

The `bfd_default_arch_struct` is an item of `bfd_arch_info_type` which has been initialized to a fairly generic state. A BFD starts life by pointing to this structure, until the correct back end has determined the real architecture of the file.

```
extern const bfd_arch_info_type bfd_default_arch_struct;
```

2.13.2.6 bfd_set_arch_info

`void bfd_set_arch_info (bfd *abfd, const bfd_arch_info_type *arg);` [Function]

Set the architecture info of *abfd* to *arg*.

2.13.2.7 bfd_default_set_arch_mach

`bool bfd_default_set_arch_mach (bfd *abfd, enum bfd_architecture arch, unsigned long mach);` [Function]

Set the architecture and machine type in BFD *abfd* to *arch* and *mach*. Find the correct pointer to a structure and insert it into the `arch_info` pointer.

2.13.2.8 bfd_get_arch

`enum bfd_architecture bfd_get_arch (const bfd *abfd);` [Function]
Return the enumerated type which describes the BFD *abfd*'s architecture.

2.13.2.9 bfd_get_mach

`unsigned long bfd_get_mach (const bfd *abfd);` [Function]
Return the long type which describes the BFD *abfd*'s machine.

2.13.2.10 bfd_arch_bits_per_byte

`unsigned int bfd_arch_bits_per_byte (const bfd *abfd);` [Function]
Return the number of bits in one of the BFD *abfd*'s architecture's bytes.

2.13.2.11 bfd_arch_bits_per_address

`unsigned int bfd_arch_bits_per_address (const bfd *abfd);` [Function]
Return the number of bits in one of the BFD *abfd*'s architecture's addresses.

2.13.2.12 bfd_default_compatible

```
const bfd_arch_info_type *bfd_default_compatible (const
        bfd_arch_info_type *a, const bfd_arch_info_type *b);
```
[Function]
The default function for testing for compatibility.

2.13.2.13 bfd_default_scan

```
bool bfd_default_scan (const struct bfd_arch_info *info,
        const char *string);
```
[Function]
The default function for working out whether this is an architecture hit and a machine hit.

2.13.2.14 bfd_get_arch_info

`const bfd_arch_info_type *bfd_get_arch_info (bfd *abfd);` [Function]
Return the architecture info struct in *abfd*.

2.13.2.15 bfd_lookup_arch

```
const bfd_arch_info_type *bfd_lookup_arch (enum
        bfd_architecture arch, unsigned long machine);
```
[Function]
Look for the architecture info structure which matches the arguments *arch* and *machine*. A machine of 0 matches the machine/architecture structure which marks itself as the default.

2.13.2.16 bfd_printable_arch_mach

```
const char *bfd_printable_arch_mach (enum bfd_architecture
        arch, unsigned long machine);
```
[Function]
Return a printable string representing the architecture and machine type.

This routine is depreciated.

2.13.2.17 bfd_octets_per_byte

`unsigned int bfd_octets_per_byte (const bfd *abfd, const asection *sec);` [Function]

Return the number of octets (8-bit quantities) per target byte (minimum addressable unit). In most cases, this will be one, but some DSP targets have 16, 32, or even 48 bits per byte.

2.13.2.18 bfd_arch_mach_octets_per_byte

`unsigned int bfd_arch_mach_octets_per_byte (enum bfd_architecture arch, unsigned long machine);` [Function]

See bfd_octets_per_byte.

This routine is provided for those cases where a bfd * is not available

2.13.2.19 bfd_arch_default_fill

`void *bfd_arch_default_fill (bfd_size_type count, bool is_bigendian, bool code);` [Function]

Allocate via bfd_malloc and return a fill buffer of size COUNT. If IS_BIGENDIAN is TRUE, the order of bytes is big endian. If CODE is TRUE, the buffer contains code.

2.14 Opening and closing BFDs

2.14.1 Functions for opening and closing

2.14.1.1 _bfd_new_bfd

`bfd *_bfd_new_bfd (void);` [Function]

Return a new BFD. All BFD's are allocated through this routine.

2.14.1.2 _bfd_new_bfd_contained_in

`bfd *_bfd_new_bfd_contained_in (bfd *);` [Function]

Allocate a new BFD as a member of archive OBFD.

2.14.1.3 _bfd_free_cached_info

`bool _bfd_free_cached_info (bfd *);` [Function]

Free objalloc memory.

2.14.1.4 bfd_fopen

`bfd *bfd_fopen (const char *filename, const char *target, const char *mode, int fd);` [Function]

Open the file *filename* with the target *target*. Return a pointer to the created BFD. If *fd* is not -1, then `fdopen` is used to open the file; otherwise, `fopen` is used. *mode* is passed directly to `fopen` or `fdopen`.

Calls `bfd_find_target`, so *target* is interpreted as by that function.

The new BFD is marked as cacheable iff *fd* is -1.

If `NULL` is returned then an error has occured. Possible errors are `bfd_error_no_memory`, `bfd_error_invalid_target` or `system_call` error.

On error, *fd* is always closed.

A copy of the *filename* argument is stored in the newly created BFD. It can be accessed via the bfd_get_filename() macro.

2.14.1.5 `bfd_openr`

`bfd *bfd_openr (const char *filename, const char *target);` [Function]

Open the file *filename* (using `fopen`) with the target *target*. Return a pointer to the created BFD.

Calls `bfd_find_target`, so *target* is interpreted as by that function.

If `NULL` is returned then an error has occured. Possible errors are `bfd_error_no_memory`, `bfd_error_invalid_target` or `system_call` error.

A copy of the *filename* argument is stored in the newly created BFD. It can be accessed via the bfd_get_filename() macro.

2.14.1.6 `bfd_fdopenr`

`bfd *bfd_fdopenr (const char *filename, const char *target, int fd);` [Function]

`bfd_fdopenr` is to `bfd_fopenr` much like `fdopen` is to `fopen`. It opens a BFD on a file already described by the *fd* supplied.

When the file is later `bfd_close`d, the file descriptor will be closed. If the caller desires that this file descriptor be cached by BFD (opened as needed, closed as needed to free descriptors for other opens), with the supplied *fd* used as an initial file descriptor (but subject to closure at any time), call bfd_set_cacheable(bfd, 1) on the returned BFD. The default is to assume no caching; the file descriptor will remain open until `bfd_close`, and will not be affected by BFD operations on other files.

Possible errors are `bfd_error_no_memory`, `bfd_error_invalid_target` and `bfd_error_system_call`.

On error, *fd* is closed.

A copy of the *filename* argument is stored in the newly created BFD. It can be accessed via the bfd_get_filename() macro.

2.14.1.7 `bfd_fdopenw`

`bfd *bfd_fdopenw (const char *filename, const char *target, int fd);` [Function]

`bfd_fdopenw` is exactly like `bfd_fdopenr` with the exception that the resulting BFD is suitable for output.

2.14.1.8 bfd_openstreamr

`bfd *bfd_openstreamr (const char * filename, const char * target, void * stream);` [Function]

Open a BFD for read access on an existing stdio stream. When the BFD is passed to `bfd_close`, the stream will be closed.

A copy of the *filename* argument is stored in the newly created BFD. It can be accessed via the bfd_get_filename() macro.

2.14.1.9 bfd_openr_iovec

`bfd *bfd_openr_iovec (const char *filename, const char *target, void *(*open_func) (struct bfd *nbfd, void *open_closure), void *open_closure, file_ptr (*pread_func) (struct bfd *nbfd, void *stream, void *buf, file_ptr nbytes, file_ptr offset), int (*close_func) (struct bfd *nbfd, void *stream), int (*stat_func) (struct bfd *abfd, void *stream, struct stat *sb));` [Function]

Create and return a BFD backed by a read-only *stream*. The *stream* is created using *open_func*, accessed using *pread_func* and destroyed using *close_func*.

Calls `bfd_find_target`, so *target* is interpreted as by that function.

Calls *open_func* (which can call `bfd_zalloc` and `bfd_get_filename`) to obtain the read-only stream backing the BFD. *open_func* either succeeds returning the non-`NULL` *stream*, or fails returning `NULL` (setting `bfd_error`).

Calls *pread_func* to request *nbytes* of data from *stream* starting at *offset* (e.g., via a call to `bfd_read`). *pread_func* either succeeds returning the number of bytes read (which can be less than *nbytes* when end-of-file), or fails returning -1 (setting `bfd_error`).

Calls *close_func* when the BFD is later closed using `bfd_close`. *close_func* either succeeds returning 0, or fails returning -1 (setting `bfd_error`).

Calls *stat_func* to fill in a stat structure for bfd_stat, bfd_get_size, and bfd_get_mtime calls. *stat_func* returns 0 on success, or returns -1 on failure (setting `bfd_error`).

If `bfd_openr_iovec` returns `NULL` then an error has occurred. Possible errors are `bfd_error_no_memory`, `bfd_error_invalid_target` and `bfd_error_system_call`.

A copy of the *filename* argument is stored in the newly created BFD. It can be accessed via the bfd_get_filename() macro.

2.14.1.10 bfd_openw

`bfd *bfd_openw (const char *filename, const char *target);` [Function]

Create a BFD, associated with file *filename*, using the file format *target*, and return a pointer to it.

Possible errors are `bfd_error_system_call`, `bfd_error_no_memory`, `bfd_error_invalid_target`.

A copy of the *filename* argument is stored in the newly created BFD. It can be accessed via the bfd_get_filename() macro.

2.14.1.11 bfd_elf_bfd_from_remote_memory

bfd *bfd_elf_bfd_from_remote_memory (bfd *templ, bfd_vma ehdr_vma, bfd_size_type size, bfd_vma *loadbasep, int (*target_read_memory) (bfd_vma vma, bfd_byte *myaddr, bfd_size_type len)); [Function]

Create a new BFD as if by bfd_openr. Rather than opening a file, reconstruct an ELF file by reading the segments out of remote memory based on the ELF file header at EHDR_VMA and the ELF program headers it points to. If non-zero, SIZE is the known extent of the object. If not null, *LOADBASEP is filled in with the difference between the VMAs from which the segments were read, and the VMAs the file headers (and hence BFD's idea of each section's VMA) put them at.

The function TARGET_READ_MEMORY is called to copy LEN bytes from the remote memory at target address VMA into the local buffer at MYADDR; it should return zero on success or an errno code on failure. TEMPL must be a BFD for an ELF target with the word size and byte order found in the remote memory.

2.14.1.12 bfd_close

bool bfd_close (bfd *abfd); [Function]

Close a BFD. If the BFD was open for writing, then pending operations are completed and the file written out and closed. If the created file is executable, then `chmod` is called to mark it as such.

All memory attached to the BFD is released.

The file descriptor associated with the BFD is closed (even if it was passed in to BFD by `bfd_fdopenr`).

`TRUE` is returned if all is ok, otherwise `FALSE`.

2.14.1.13 bfd_close_all_done

bool bfd_close_all_done (bfd *); [Function]

Close a BFD. Differs from `bfd_close` since it does not complete any pending operations. This routine would be used if the application had just used BFD for swapping and didn't want to use any of the writing code.

If the created file is executable, then `chmod` is called to mark it as such.

All memory attached to the BFD is released.

`TRUE` is returned if all is ok, otherwise `FALSE`.

2.14.1.14 bfd_create

bfd *bfd_create (const char *filename, bfd *templ); [Function]

Create a new BFD in the manner of `bfd_openw`, but without opening a file. The new BFD takes the target from the target used by *templ*. The format is always set to `bfd_object`.

A copy of the *filename* argument is stored in the newly created BFD. It can be accessed via the bfd_get_filename() macro.

2.14.1.15 bfd_make_writable

`bool bfd_make_writable (bfd *abfd);` [Function]

Takes a BFD as created by `bfd_create` and converts it into one like as returned by `bfd_openw`. It does this by converting the BFD to BFD_IN_MEMORY. It's assumed that you will call `bfd_make_readable` on this bfd later.

`TRUE` is returned if all is ok, otherwise `FALSE`.

2.14.1.16 bfd_make_readable

`bool bfd_make_readable (bfd *abfd);` [Function]

Takes a BFD as created by `bfd_create` and `bfd_make_writable` and converts it into one like as returned by `bfd_openr`. It does this by writing the contents out to the memory buffer, then reversing the direction.

`TRUE` is returned if all is ok, otherwise `FALSE`.

2.14.1.17 bfd_calc_gnu_debuglink_crc32

`uint32_t bfd_calc_gnu_debuglink_crc32 (uint32_t crc, const bfd_byte *buf, bfd_size_type len);` [Function]

Computes a CRC value as used in the .gnu_debuglink section. Advances the previously computed *crc* value by computing and adding in the crc32 for *len* bytes of *buf*.

Return the updated CRC32 value.

2.14.1.18 bfd_get_debug_link_info

`char *bfd_get_debug_link_info (bfd *abfd, uint32_t *crc32_out);` [Function]

Extracts the filename and CRC32 value for any separate debug information file associated with *abfd*.

Returns the filename of the associated debug information file, or NULL if there is no such file. If the filename was found then the contents of *crc32_out* are updated to hold the corresponding CRC32 value for the file.

The returned filename is allocated with `malloc`; freeing it is the responsibility of the caller.

2.14.1.19 bfd_get_alt_debug_link_info

`char *bfd_get_alt_debug_link_info (bfd * abfd, bfd_size_type *buildid_len, bfd_byte **buildid_out);` [Function]

Fetch the filename and BuildID value for any alternate debuginfo associated with *abfd*. Return NULL if no such info found, otherwise return filename and update *buildid_len* and *buildid_out*. The returned filename and build_id are allocated with `malloc`; freeing them is the responsibility of the caller.

2.14.1.20 bfd_follow_gnu_debuglink

`char *bfd_follow_gnu_debuglink (bfd *abfd, const char *dir);` [Function]

Takes a BFD and searches it for a .gnu_debuglink section. If this section is found, it examines the section for the name and checksum of a '.debug' file containing auxiliary debugging information. It then searches the filesystem for this .debug file in some standard locations, including the directory tree rooted at *dir*, and if found returns the full filename.

If *dir* is NULL, the search will take place starting at the current directory.

Returns `NULL` on any errors or failure to locate the .debug file, otherwise a pointer to a heap-allocated string containing the filename. The caller is responsible for freeing this string.

2.14.1.21 bfd_follow_gnu_debugaltlink

`char *bfd_follow_gnu_debugaltlink (bfd *abfd, const char *dir);` [Function]

Takes a BFD and searches it for a .gnu_debugaltlink section. If this section is found, it examines the section for the name of a file containing auxiliary debugging information. It then searches the filesystem for this file in a set of standard locations, including the directory tree rooted at *dir*, and if found returns the full filename.

If *dir* is NULL, the search will take place starting at the current directory.

Returns `NULL` on any errors or failure to locate the debug file, otherwise a pointer to a heap-allocated string containing the filename. The caller is responsible for freeing this string.

2.14.1.22 bfd_create_gnu_debuglink_section

`struct bfd_section *bfd_create_gnu_debuglink_section (bfd *abfd, const char *filename);` [Function]

Takes a *BFD* and adds a .gnu_debuglink section to it. The section is sized to be big enough to contain a link to the specified *filename*.

A pointer to the new section is returned if all is ok. Otherwise `NULL` is returned and bfd_error is set.

2.14.1.23 bfd_fill_in_gnu_debuglink_section

`bool bfd_fill_in_gnu_debuglink_section (bfd *abfd, struct bfd_section *sect, const char *filename);` [Function]

Takes a *BFD* and containing a .gnu_debuglink section *SECT* and fills in the contents of the section to contain a link to the specified *filename*. The filename should be absolute or relative to the current directory.

`TRUE` is returned if all is ok. Otherwise `FALSE` is returned and bfd_error is set.

2.14.1.24 bfd_follow_build_id_debuglink

`char *bfd_follow_build_id_debuglink (bfd *abfd, const char *dir);` [Function]

Takes *abfd* and searches it for a .note.gnu.build-id section. If this section is found, it extracts the value of the NT_GNU_BUILD_ID note, which should be a hexadecimal value *NNNN+NN* (for 32+ hex digits). It then searches the filesystem for a file named *.build-id/NN/NN+NN.debug* in a set of standard locations, including the directory tree rooted at *dir*. The filename of the first matching file to be found is returned. A matching file should contain a .note.gnu.build-id section with the same *NNNN+NN* note as *abfd*, although this check is currently not implemented.

If *dir* is NULL, the search will take place starting at the current directory.

Returns `NULL` on any errors or failure to locate the debug file, otherwise a pointer to a heap-allocated string containing the filename. The caller is responsible for freeing this string.

2.14.1.25 bfd_set_filename

`const char *bfd_set_filename (bfd *abfd, const char *filename);` [Function]

Set the filename of *abfd*, copying the FILENAME parameter to bfd_alloc'd memory owned by *abfd*. Returns a pointer the newly allocated name, or NULL if the allocation failed.

2.14.1.26 bfd_extract_object_only_section

`const char *bfd_extract_object_only_section (bfd *abfd);` [Function]

Takes a *ABFD* and extract the .gnu_object_only section into a temporary file.

2.15 Implementation details

2.15.1 Internal functions

These routines are used within BFD. They are not intended for export, but are documented here for completeness.

2.15.1.1 bfd_malloc

`void *bfd_malloc (bfd_size_type *size*);` [Function]

Returns a pointer to an allocated block of memory that is at least SIZE bytes long. If SIZE is 0 then it will be treated as if it were 1. If SIZE is too big then NULL will be returned. Returns NULL upon error and sets bfd_error.

2.15.1.2 bfd_realloc

`void *bfd_realloc (void **mem*, bfd_size_type *size*);` [Function]

Returns a pointer to an allocated block of memory that is at least SIZE bytes long. If SIZE is 0 then it will be treated as if it were 1. If SIZE is too big then NULL will be returned. If MEM is not NULL then it must point to an allocated block of

memory. If this block is large enough then MEM may be used as the return value for this function, but this is not guaranteed.

If MEM is not returned then the first N bytes in the returned block will be identical to the first N bytes in region pointed to by MEM, where N is the lessor of SIZE and the length of the region of memory currently addressed by MEM.

Returns NULL upon error and sets bfd_error.

2.15.1.3 bfd_realloc_or_free

`void *bfd_realloc_or_free (void **mem*, bfd_size_type *size*);` [Function]

Returns a pointer to an allocated block of memory that is at least SIZE bytes long. If SIZE is 0 then no memory will be allocated, MEM will be freed, and NULL will be returned. This will not cause bfd_error to be set.

If SIZE is too big then NULL will be returned and bfd_error will be set. If MEM is not NULL then it must point to an allocated block of memory. If this block is large enough then MEM may be used as the return value for this function, but this is not guaranteed.

If MEM is not returned then the first N bytes in the returned block will be identical to the first N bytes in region pointed to by MEM, where N is the lessor of SIZE and the length of the region of memory currently addressed by MEM.

2.15.1.4 bfd_zmalloc

`void *bfd_zmalloc (bfd_size_type *size*);` [Function]

Returns a pointer to an allocated block of memory that is at least SIZE bytes long. If SIZE is 0 then it will be treated as if it were 1. If SIZE is too big then NULL will be returned. Returns NULL upon error and sets bfd_error.

If NULL is not returned then the allocated block of memory will have been cleared.

2.15.1.5 bfd_alloc

`void *bfd_alloc (bfd *abfd, bfd_size_type wanted);` [Function]

Allocate a block of *wanted* bytes of memory attached to `abfd` and return a pointer to it.

2.15.1.6 bfd_zalloc

`void *bfd_zalloc (bfd *abfd, bfd_size_type wanted);` [Function]

Allocate a block of *wanted* bytes of zeroed memory attached to `abfd` and return a pointer to it.

2.15.1.7 bfd_release

`void bfd_release (bfd *, void *);` [Function]

Free a block allocated for a BFD. Note: Also frees all more recently allocated blocks!

2.15.1.8 bfd_write_bigendian_4byte_int

`bool bfd_write_bigendian_4byte_int (bfd *, unsigned int);` [Function]
Write a 4 byte integer *i* to the output BFD *abfd*, in big endian order regardless of what else is going on. This is useful in archives.

2.15.1.9 bfd_put_size

2.15.1.10 bfd_get_size

These macros as used for reading and writing raw data in sections; each access (except for bytes) is vectored through the target format of the BFD and mangled accordingly. The mangling performs any necessary endian translations and removes alignment restrictions. Note that types accepted and returned by these macros are identical so they can be swapped around in macros—for example, `libaout.h` defines `GET_WORD` to either `bfd_get_32` or `bfd_get_64`.

In the put routines, *val* must be a `bfd_vma`. If we are on a system without prototypes, the caller is responsible for making sure that is true, with a cast if necessary. We don't cast them in the macro definitions because that would prevent `lint` or `gcc -Wall` from detecting sins such as passing a pointer. To detect calling these with less than a `bfd_vma`, use `gcc -Wconversion` on a host with 64 bit `bfd_vma`'s.

```
/* Byte swapping macros for user section data.  */

#define bfd_put_8(abfd, val, ptr) \
  ((void) (*((bfd_byte *) (ptr)) = (val) & 0xff))
#define bfd_put_signed_8 \
  bfd_put_8
#define bfd_get_8(abfd, ptr) \
  ((bfd_vma) *(const bfd_byte *) (ptr) & 0xff)
#define bfd_get_signed_8(abfd, ptr) \
  ((((bfd_signed_vma) *(const bfd_byte *) (ptr) & 0xff) ^ 0x80) - 0x80)

#define bfd_put_16(abfd, val, ptr) \
  BFD_SEND (abfd, bfd_putx16, ((val),(ptr)))
#define bfd_put_signed_16 \
  bfd_put_16
#define bfd_get_16(abfd, ptr) \
  BFD_SEND (abfd, bfd_getx16, (ptr))
#define bfd_get_signed_16(abfd, ptr) \
  BFD_SEND (abfd, bfd_getx_signed_16, (ptr))

#define bfd_put_24(abfd, val, ptr) \
  do                                \
    if (bfd_big_endian (abfd))      \
      bfd_putb24 ((val), (ptr));    \
    else                            \
      bfd_putl24 ((val), (ptr));    \
```

```
  while (0)

bfd_vma bfd_getb24 (const void *p);
bfd_vma bfd_getl24 (const void *p);

#define bfd_get_24(abfd, ptr) \
  (bfd_big_endian (abfd) ? bfd_getb24 (ptr) : bfd_getl24 (ptr))

#define bfd_put_32(abfd, val, ptr) \
  BFD_SEND (abfd, bfd_putx32, ((val),(ptr)))
#define bfd_put_signed_32 \
  bfd_put_32
#define bfd_get_32(abfd, ptr) \
  BFD_SEND (abfd, bfd_getx32, (ptr))
#define bfd_get_signed_32(abfd, ptr) \
  BFD_SEND (abfd, bfd_getx_signed_32, (ptr))

#define bfd_put_64(abfd, val, ptr) \
  BFD_SEND (abfd, bfd_putx64, ((val), (ptr)))
#define bfd_put_signed_64 \
  bfd_put_64
#define bfd_get_64(abfd, ptr) \
  BFD_SEND (abfd, bfd_getx64, (ptr))
#define bfd_get_signed_64(abfd, ptr) \
  BFD_SEND (abfd, bfd_getx_signed_64, (ptr))

#define bfd_get(bits, abfd, ptr)                       \
  ((bits) == 8 ? bfd_get_8 (abfd, ptr)                 \
   : (bits) == 16 ? bfd_get_16 (abfd, ptr)             \
   : (bits) == 32 ? bfd_get_32 (abfd, ptr)             \
   : (bits) == 64 ? bfd_get_64 (abfd, ptr)             \
   : (abort (), (bfd_vma) - 1))

#define bfd_put(bits, abfd, val, ptr)                  \
  ((bits) == 8 ? bfd_put_8  (abfd, val, ptr)           \
   : (bits) == 16 ? bfd_put_16 (abfd, val, ptr)        \
   : (bits) == 32 ? bfd_put_32 (abfd, val, ptr)        \
   : (bits) == 64 ? bfd_put_64 (abfd, val, ptr)        \
   : (abort (), (void) 0))
```

2.15.1.11 `bfd_h_put_size`

These macros have the same function as their `bfd_get_x` brethren, except that they are used for removing information for the header records of object files. Believe it or not, some object files keep their header records in big endian order and their data in little endian order.

```
/* Byte swapping macros for file header data.  */

#define bfd_h_put_8(abfd, val, ptr) \
  bfd_put_8 (abfd, val, ptr)
#define bfd_h_put_signed_8(abfd, val, ptr) \
  bfd_put_8 (abfd, val, ptr)
#define bfd_h_get_8(abfd, ptr) \
  bfd_get_8 (abfd, ptr)
#define bfd_h_get_signed_8(abfd, ptr) \
  bfd_get_signed_8 (abfd, ptr)

#define bfd_h_put_16(abfd, val, ptr) \
  BFD_SEND (abfd, bfd_h_putx16, (val, ptr))
#define bfd_h_put_signed_16 \
  bfd_h_put_16
#define bfd_h_get_16(abfd, ptr) \
  BFD_SEND (abfd, bfd_h_getx16, (ptr))
#define bfd_h_get_signed_16(abfd, ptr) \
  BFD_SEND (abfd, bfd_h_getx_signed_16, (ptr))

#define bfd_h_put_32(abfd, val, ptr) \
  BFD_SEND (abfd, bfd_h_putx32, (val, ptr))
#define bfd_h_put_signed_32 \
  bfd_h_put_32
#define bfd_h_get_32(abfd, ptr) \
  BFD_SEND (abfd, bfd_h_getx32, (ptr))
#define bfd_h_get_signed_32(abfd, ptr) \
  BFD_SEND (abfd, bfd_h_getx_signed_32, (ptr))

#define bfd_h_put_64(abfd, val, ptr) \
  BFD_SEND (abfd, bfd_h_putx64, (val, ptr))
#define bfd_h_put_signed_64 \
  bfd_h_put_64
#define bfd_h_get_64(abfd, ptr) \
  BFD_SEND (abfd, bfd_h_getx64, (ptr))
#define bfd_h_get_signed_64(abfd, ptr) \
  BFD_SEND (abfd, bfd_h_getx_signed_64, (ptr))

/* Aliases for the above, which should eventually go away.  */

#define H_PUT_64  bfd_h_put_64
#define H_PUT_32  bfd_h_put_32
#define H_PUT_16  bfd_h_put_16
#define H_PUT_8   bfd_h_put_8
#define H_PUT_S64 bfd_h_put_signed_64
#define H_PUT_S32 bfd_h_put_signed_32
```

```
#define H_PUT_S16 bfd_h_put_signed_16
#define H_PUT_S8  bfd_h_put_signed_8
#define H_GET_64  bfd_h_get_64
#define H_GET_32  bfd_h_get_32
#define H_GET_16  bfd_h_get_16
#define H_GET_8   bfd_h_get_8
#define H_GET_S64 bfd_h_get_signed_64
#define H_GET_S32 bfd_h_get_signed_32
#define H_GET_S16 bfd_h_get_signed_16
#define H_GET_S8  bfd_h_get_signed_8
```

2.15.1.12 Byte swapping routines.

`uint64_t bfd_getb64 (const void *); uint64_t bfd_getl64` [Function]
`(const void *); int64_t bfd_getb_signed_64 (const void *); int64_t bfd_getl_signed_64 (const void *); bfd_vma bfd_getb32 (const void *); bfd_vma bfd_getl32 (const void *); bfd_signed_vma bfd_getb_signed_32 (const void *); bfd_signed_vma bfd_getl_signed_32 (const void *); bfd_vma bfd_getb16 (const void *); bfd_vma bfd_getl16 (const void *); bfd_signed_vma bfd_getb_signed_16 (const void *); bfd_signed_vma bfd_getl_signed_16 (const void *); void bfd_putb64 (uint64_t, void *); void bfd_putl64 (uint64_t, void *); void bfd_putb32 (bfd_vma, void *); void bfd_putl32 (bfd_vma, void *); void bfd_putb24 (bfd_vma, void *); void bfd_putl24 (bfd_vma, void *); void bfd_putb16 (bfd_vma, void *); void bfd_putl16 (bfd_vma, void *); uint64_t bfd_get_bits (const void *, int, bool); void bfd_put_bits (uint64_t, void *, int, bool);`

Read and write integers in a particular endian order. getb and putb functions handle big-endian, getl and putl handle little-endian. bfd_get_bits and bfd_put_bits specify big-endian by passing TRUE in the last parameter, little-endian by passing FALSE.

2.15.1.13 bfd_log2

`unsigned int bfd_log2 (bfd_vma x);` [Function]

Return the log base 2 of the value supplied, rounded up. E.g., an x of 1025 returns 11. A x of 0 returns 0.

2.16 File caching

The file caching mechanism is embedded within BFD and allows the application to open as many BFDs as it wants without regard to the underlying operating system's file descriptor limit (often as low as 20 open files). The module in `cache.c` maintains a least recently used list of `bfd_cache_max_open` files, and exports the name `bfd_cache_lookup`, which

runs around and makes sure that the required BFD is open. If not, then it chooses a file to close, closes it and opens the one wanted, returning its file handle.

2.16.1 Caching functions

2.16.1.1 bfd_cache_init

`bool bfd_cache_init (bfd *abfd);` [Function]

Add a newly opened BFD to the cache.

2.16.1.2 bfd_cache_close

`bool bfd_cache_close (bfd *abfd);` [Function]

Remove the BFD *abfd* from the cache. If the attached file is open, then close it too.

`FALSE` is returned if closing the file fails, `TRUE` is returned if all is well.

2.16.1.3 bfd_cache_close_all

`bool bfd_cache_close_all (void);` [Function]

Remove all BFDs from the cache. If the attached file is open, then close it too. Note - despite its name this function will close a BFD even if it is not marked as being cacheable, ie even if bfd_get_cacheable() returns false.

`FALSE` is returned if closing one of the file fails, `TRUE` is returned if all is well.

2.16.1.4 bfd_cache_set_uncloseable

```
bool bfd_cache_set_uncloseable (bfd *abfd, bool value,
    bool *old);
```
[Function]

Internal function to mark ABFD as either closeable or not. This is used by bfd_check_format_matches to avoid races where bfd_cache_close_all is called in another thread. VALUE is true to mark the BFD as temporarily uncloseable by the cache; false to mark it as closeable once again. OLD, if non-NULL, is set to the previous value of the flag. Returns false on error, true on success.

2.16.1.5 bfd_cache_size

`unsigned bfd_cache_size (void);` [Function]

Return the number of open files in the cache.

2.16.1.6 bfd_open_file

`FILE* bfd_open_file (bfd *abfd);` [Function]

Call the OS to open a file for *abfd*. Return the `FILE *` (possibly `NULL`) that results from this operation. Set up the BFD so that future accesses know the file is open. If the `FILE *` returned is `NULL`, then it won't have been put in the cache, so it won't have to be removed from it.

2.17 Linker Functions

The linker uses three special entry points in the BFD target vector. It is not necessary to write special routines for these entry points when creating a new BFD back end, since generic versions are provided. However, writing them can speed up linking and make it use significantly less runtime memory.

The first routine creates a hash table used by the other routines. The second routine adds the symbols from an object file to the hash table. The third routine takes all the object files and links them together to create the output file. These routines are designed so that the linker proper does not need to know anything about the symbols in the object files that it is linking. The linker merely arranges the sections as directed by the linker script and lets BFD handle the details of symbols and relocs.

The second routine and third routines are passed a pointer to a `struct bfd_link_info` structure (defined in `bfdlink.h`) which holds information relevant to the link, including the linker hash table (which was created by the first routine) and a set of callback functions to the linker proper.

The generic linker routines are in `linker.c`, and use the header file `genlink.h`. As of this writing, the only back ends which have implemented versions of these routines are a.out (in `aoutx.h`) and ECOFF (in `ecoff.c`). The a.out routines are used as examples throughout this section.

2.17.1 Creating a linker hash table

The linker routines must create a hash table, which must be derived from `struct bfd_link_hash_table` described in `bfdlink.c`. See Section 2.18 [Hash Tables], page 189, for information on how to create a derived hash table. This entry point is called using the target vector of the linker output file.

The `_bfd_link_hash_table_create` entry point must allocate and initialize an instance of the desired hash table. If the back end does not require any additional information to be stored with the entries in the hash table, the entry point may simply create a `struct bfd_link_hash_table`. Most likely, however, some additional information will be needed.

For example, with each entry in the hash table the a.out linker keeps the index the symbol has in the final output file (this index number is used so that when doing a relocatable link the symbol index used in the output file can be quickly filled in when copying over a reloc). The a.out linker code defines the required structures and functions for a hash table derived from `struct bfd_link_hash_table`. The a.out linker hash table is created by the function `NAME(aout,link_hash_table_create)`; it simply allocates space for the hash table, initializes it, and returns a pointer to it.

When writing the linker routines for a new back end, you will generally not know exactly which fields will be required until you have finished. You should simply create a new hash table which defines no additional fields, and then simply add fields as they become necessary.

2.17.2 Adding symbols to the hash table

The linker proper will call the `_bfd_link_add_symbols` entry point for each object file or archive which is to be linked (typically these are the files named on the command line, but some may also come from the linker script). The entry point is responsible for examining the file. For an object file, BFD must add any relevant symbol information to the hash

table. For an archive, BFD must determine which elements of the archive should be used and adding them to the link.

The a.out version of this entry point is `NAME(aout,link_add_symbols)`.

2.17.2.1 Differing file formats

Normally all the files involved in a link will be of the same format, but it is also possible to link together different format object files, and the back end must support that. The `_bfd_link_add_symbols` entry point is called via the target vector of the file to be added. This has an important consequence: the function may not assume that the hash table is the type created by the corresponding `_bfd_link_hash_table_create` vector. All the `_bfd_link_add_symbols` function can assume about the hash table is that it is derived from `struct bfd_link_hash_table`.

Sometimes the `_bfd_link_add_symbols` function must store some information in the hash table entry to be used by the `_bfd_final_link` function. In such a case the output bfd xvec must be checked to make sure that the hash table was created by an object file of the same format.

The `_bfd_final_link` routine must be prepared to handle a hash entry without any extra information added by the `_bfd_link_add_symbols` function. A hash entry without extra information will also occur when the linker script directs the linker to create a symbol. Note that, regardless of how a hash table entry is added, all the fields will be initialized to some sort of null value by the hash table entry initialization function.

See `ecoff_link_add_externals` for an example of how to check the output bfd before saving information (in this case, the ECOFF external symbol debugging information) in a hash table entry.

2.17.2.2 Adding symbols from an object file

When the `_bfd_link_add_symbols` routine is passed an object file, it must add all externally visible symbols in that object file to the hash table. The actual work of adding the symbol to the hash table is normally handled by the function `_bfd_generic_link_add_one_symbol`. The `_bfd_link_add_symbols` routine is responsible for reading all the symbols from the object file and passing the correct information to `_bfd_generic_link_add_one_symbol`.

The `_bfd_link_add_symbols` routine should not use `bfd_canonicalize_symtab` to read the symbols. The point of providing this routine is to avoid the overhead of converting the symbols into generic `asymbol` structures.

`_bfd_generic_link_add_one_symbol` handles the details of combining common symbols, warning about multiple definitions, and so forth. It takes arguments which describe the symbol to add, notably symbol flags, a section, and an offset. The symbol flags include such things as `BSF_WEAK` or `BSF_INDIRECT`. The section is a section in the object file, or something like `bfd_und_section_ptr` for an undefined symbol or `bfd_com_section_ptr` for a common symbol.

If the `_bfd_final_link` routine is also going to need to read the symbol information, the `_bfd_link_add_symbols` routine should save it somewhere attached to the object file BFD. However, the information should only be saved if the `keep_memory` field of the `info` argument is TRUE, so that the `-no-keep-memory` linker switch is effective.

The a.out function which adds symbols from an object file is `aout_link_add_object_symbols`, and most of the interesting work is in `aout_link_add_symbols`. The latter saves pointers to the hash tables entries created by `_bfd_generic_link_add_one_symbol` indexed by symbol number, so that the `_bfd_final_link` routine does not have to call the hash table lookup routine to locate the entry.

2.17.2.3 Adding symbols from an archive

When the `_bfd_link_add_symbols` routine is passed an archive, it must look through the symbols defined by the archive and decide which elements of the archive should be included in the link. For each such element it must call the `add_archive_element` linker callback, and it must add the symbols from the object file to the linker hash table. (The callback may in fact indicate that a replacement BFD should be used, in which case the symbols from that BFD should be added to the linker hash table instead.)

In most cases the work of looking through the symbols in the archive should be done by the `_bfd_generic_link_add_archive_symbols` function. `_bfd_generic_link_add_archive_symbols` is passed a function to call to make the final decision about adding an archive element to the link and to do the actual work of adding the symbols to the linker hash table. If the element is to be included, the `add_archive_element` linker callback routine must be called with the element as an argument, and the element's symbols must be added to the linker hash table just as though the element had itself been passed to the `_bfd_link_add_symbols` function.

When the a.out `_bfd_link_add_symbols` function receives an archive, it calls `_bfd_generic_link_add_archive_symbols` passing `aout_link_check_archive_element` as the function argument. `aout_link_check_archive_element` calls `aout_link_check_ar_symbols`. If the latter decides to add the element (an element is only added if it provides a real, non-common, definition for a previously undefined or common symbol) it calls the `add_archive_element` callback and then `aout_link_check_archive_element` calls `aout_link_add_symbols` to actually add the symbols to the linker hash table - possibly those of a substitute BFD, if the `add_archive_element` callback avails itself of that option.

The ECOFF back end is unusual in that it does not normally call `_bfd_generic_link_add_archive_symbols`, because ECOFF archives already contain a hash table of symbols. The ECOFF back end searches the archive itself to avoid the overhead of creating a new hash table.

2.17.3 Performing the final link

When all the input files have been processed, the linker calls the `_bfd_final_link` entry point of the output BFD. This routine is responsible for producing the final output file, which has several aspects. It must relocate the contents of the input sections and copy the data into the output sections. It must build an output symbol table including any local symbols from the input files and the global symbols from the hash table. When producing relocatable output, it must modify the input relocs and write them into the output file. There may also be object format dependent work to be done.

The linker will also call the `write_object_contents` entry point when the BFD is closed. The two entry points must work together in order to produce the correct output file.

The details of how this works are inevitably dependent upon the specific object file format. The a.out `_bfd_final_link` routine is `NAME(aout,final_link)`.

2.17.3.1 Information provided by the linker

Before the linker calls the `_bfd_final_link` entry point, it sets up some data structures for the function to use.

The `input_bfds` field of the `bfd_link_info` structure will point to a list of all the input files included in the link. These files are linked through the `link.next` field of the `bfd` structure.

Each section in the output file will have a list of `link_order` structures attached to the `map_head.link_order` field (the `link_order` structure is defined in `bfdlink.h`). These structures describe how to create the contents of the output section in terms of the contents of various input sections, fill constants, and, eventually, other types of information. They also describe relocs that must be created by the BFD backend, but do not correspond to any input file; this is used to support -Ur, which builds constructors while generating a relocatable object file.

2.17.3.2 Relocating the section contents

The `_bfd_final_link` function should look through the `link_order` structures attached to each section of the output file. Each `link_order` structure should either be handled specially, or it should be passed to the function `_bfd_default_link_order` which will do the right thing (`_bfd_default_link_order` is defined in `linker.c`).

For efficiency, a `link_order` of type `bfd_indirect_link_order` whose associated section belongs to a BFD of the same format as the output BFD must be handled specially. This type of `link_order` describes part of an output section in terms of a section belonging to one of the input files. The `_bfd_final_link` function should read the contents of the section and any associated relocs, apply the relocs to the section contents, and write out the modified section contents. If performing a relocatable link, the relocs themselves must also be modified and written out.

The functions `_bfd_relocate_contents` and `_bfd_final_link_relocate` provide some general support for performing the actual relocations, notably overflow checking. Their arguments include information about the symbol the relocation is against and a `reloc_howto_type` argument which describes the relocation to perform. These functions are defined in `reloc.c`.

The a.out function which handles reading, relocating, and writing section contents is `aout_link_input_section`. The actual relocation is done in `aout_link_input_section_std` and `aout_link_input_section_ext`.

2.17.3.3 Writing the symbol table

The `_bfd_final_link` function must gather all the symbols in the input files and write them out. It must also write out all the symbols in the global hash table. This must be controlled by the `strip` and `discard` fields of the `bfd_link_info` structure.

The local symbols of the input files will not have been entered into the linker hash table. The `_bfd_final_link` routine must consider each input file and include the symbols in

the output file. It may be convenient to do this when looking through the `link_order` structures, or it may be done by stepping through the `input_bfds` list.

The `_bfd_final_link` routine must also traverse the global hash table to gather all the externally visible symbols. It is possible that most of the externally visible symbols may be written out when considering the symbols of each input file, but it is still necessary to traverse the hash table since the linker script may have defined some symbols that are not in any of the input files.

The `strip` field of the `bfd_link_info` structure controls which symbols are written out. The possible values are listed in `bfdlink.h`. If the value is `strip_some`, then the `keep_hash` field of the `bfd_link_info` structure is a hash table of symbols to keep; each symbol should be looked up in this hash table, and only symbols which are present should be included in the output file.

If the `strip` field of the `bfd_link_info` structure permits local symbols to be written out, the `discard` field is used to further controls which local symbols are included in the output file. If the value is `discard_l`, then all local symbols which begin with a certain prefix are discarded; this is controlled by the `bfd_is_local_label_name` entry point.

The a.out backend handles symbols by calling `aout_link_write_symbols` on each input BFD and then traversing the global hash table with the function `aout_link_write_other_symbol`. It builds a string table while writing out the symbols, which is written to the output file at the end of `NAME(aout,final_link)`.

2.17.3.4 _bfd_generic_link_add_one_symbol

`bool _bfd_generic_link_add_one_symbol (struct bfd_link_info *info, bfd *abfd, const char *name, flagword flags, asection *section, bfd_vma value, const char *string, bool copy, bool collect, struct bfd_link_hash_entry **hashp);` [Function]

Add a symbol to the global hash table. ABFD is the BFD the symbol comes from. NAME is the name of the symbol. FLAGS is the BSF_* bits associated with the symbol. SECTION is the section in which the symbol is defined; this may be bfd_und_section_ptr or bfd_com_section_ptr. VALUE is the value of the symbol, relative to the section. STRING is used for either an indirect symbol, in which case it is the name of the symbol to indirect to, or a warning symbol, in which case it is the warning string. COPY is TRUE if NAME or STRING must be copied into locally allocated memory if they need to be saved. COLLECT is TRUE if we should automatically collect gcc constructor or destructor names as collect2 does. HASHP, if not NULL, is a place to store the created hash table entry; if *HASHP is not NULL, the caller has already looked up the hash table entry, and stored it in *HASHP.

2.17.3.5 bfd_link_align_section

`bool bfd_link_align_section (asection *, unsigned int);` [Function]

Increase section alignment if the current section alignment is less than the requested value. Adjust output section alignment too, so that linker layout adjusts for alignment on the current lang_size_sections pass. This is important for lang_size_relro_segment. If the output section alignment isn't adjusted, the linker will place the output section at an address depending on its current alignment. When sizing the output section,

input sections attached transfer any increase in alignment to the output section, which will affect layout for the next sizing pass. Which is all well and good except that lang_size_relro_segment for the current sizing pass uses that possibly increased alignment with a layout that doesn't suit.

2.17.3.6 bfd_link_split_section

`bool bfd_link_split_section (bfd *abfd, asection *sec);` [Function]

Return nonzero if *sec* should be split during a reloceatable or final link.

```
#define bfd_link_split_section(abfd, sec) \
       BFD_SEND (abfd, _bfd_link_split_section, (abfd, sec))
```

2.17.3.7 bfd_section_already_linked

`bool bfd_section_already_linked (bfd *abfd, asection *sec, struct bfd_link_info *info);` [Function]

Check if *data* has been already linked during a reloceatable or final link. Return TRUE if it has.

```
#define bfd_section_already_linked(abfd, sec, info) \
       BFD_SEND (abfd, _section_already_linked, (abfd, sec, info))
```

2.17.3.8 bfd_generic_define_common_symbol

`bool bfd_generic_define_common_symbol (bfd *output_bfd, struct bfd_link_info *info, struct bfd_link_hash_entry *h);` [Function]

Convert common symbol *h* into a defined symbol. Return TRUE on success and FALSE on failure.

```
#define bfd_define_common_symbol(output_bfd, info, h) \
       BFD_SEND (output_bfd, _bfd_define_common_symbol, (output_bfd, info, h))
```

2.17.3.9 _bfd_generic_link_hide_symbol

`void _bfd_generic_link_hide_symbol (bfd *output_bfd, struct bfd_link_info *info, struct bfd_link_hash_entry *h);` [Function]

Hide symbol *h*. This is an internal function. It should not be called from outside the BFD library.

```
#define bfd_link_hide_symbol(output_bfd, info, h) \
       BFD_SEND (output_bfd, _bfd_link_hide_symbol, (output_bfd, info, h))
```

2.17.3.10 bfd_generic_define_start_stop

`struct bfd_link_hash_entry *bfd_generic_define_start_stop (struct bfd_link_info *info, const char *symbol, asection *sec);` [Function]

Define a __start, __stop, .startof. or .sizeof. symbol. Return the symbol or NULL if no such undefined symbol exists.

```
#define bfd_define_start_stop(output_bfd, info, symbol, sec) \
       BFD_SEND (output_bfd, _bfd_define_start_stop, (info, symbol, sec))
```

2.17.3.11 bfd_find_version_for_sym

`struct bfd_elf_version_tree * bfd_find_version_for_sym (struct bfd_elf_version_tree *verdefs, const char *sym_name, bool *hide);` [Function]

Search an elf version script tree for symbol versioning info and export / don't-export status for a given symbol. Return non-NULL on success and NULL on failure; also sets the output '`hide`' boolean parameter.

2.17.3.12 bfd_hide_sym_by_version

`bool bfd_hide_sym_by_version (struct bfd_elf_version_tree *verdefs, const char *sym_name);` [Function]

Search an elf version script tree for symbol versioning info for a given symbol. Return TRUE if the symbol is hidden.

2.17.3.13 bfd_link_check_relocs

`bool bfd_link_check_relocs (bfd *abfd, struct bfd_link_info *info);` [Function]

Checks the relocs in ABFD for validity. Does not execute the relocs. Return TRUE if everything is OK, FALSE otherwise. This is the external entry point to this code.

2.17.3.14 _bfd_generic_link_check_relocs

`bool _bfd_generic_link_check_relocs (bfd *abfd, struct bfd_link_info *info);` [Function]

Stub function for targets that do not implement reloc checking. Return TRUE. This is an internal function. It should not be called from outside the BFD library.

2.17.3.15 bfd_merge_private_bfd_data

`bool bfd_merge_private_bfd_data (bfd *ibfd, struct bfd_link_info *info);` [Function]

Merge private BFD information from the BFD *ibfd* to the the output file BFD when linking. Return `TRUE` on success, `FALSE` on error. Possible error returns are:

- `bfd_error_no_memory` - Not enough memory exists to create private data for *obfd*.

```
#define bfd_merge_private_bfd_data(ibfd, info) \
       BFD_SEND ((info)->output_bfd, _bfd_merge_private_bfd_data, \
                 (ibfd, info))
```

2.17.3.16 _bfd_generic_verify_endian_match

`bool _bfd_generic_verify_endian_match (bfd *ibfd, struct bfd_link_info *info);` [Function]

Can be used from / for bfd_merge_private_bfd_data to check that endianness matches between input and output file. Returns TRUE for a match, otherwise returns FALSE and emits an error.

2.18 Hash Tables

BFD provides a simple set of hash table functions. Routines are provided to initialize a hash table, to free a hash table, to look up a string in a hash table and optionally create an entry for it, and to traverse a hash table. There is currently no routine to delete an string from a hash table.

The basic hash table does not permit any data to be stored with a string. However, a hash table is designed to present a base class from which other types of hash tables may be derived. These derived types may store additional information with the string. Hash tables were implemented in this way, rather than simply providing a data pointer in a hash table entry, because they were designed for use by the linker back ends. The linker may create thousands of hash table entries, and the overhead of allocating private data and storing and following pointers becomes noticeable.

The basic hash table code is in `hash.c`.

2.18.1 Creating and freeing a hash table

To create a hash table, create an instance of a `struct bfd_hash_table` (defined in `bfd.h`) and call `bfd_hash_table_init` (if you know approximately how many entries you will need, the function `bfd_hash_table_init_n`, which takes a *size* argument, may be used). `bfd_hash_table_init` returns `FALSE` if some sort of error occurs.

The function `bfd_hash_table_init` take as an argument a function to use to create new entries. For a basic hash table, use the function `bfd_hash_newfunc`. See Section 2.18.4 [Deriving a New Hash Table Type], page 190, for why you would want to use a different value for this argument.

`bfd_hash_table_init` will create an objalloc which will be used to allocate new entries. You may allocate memory on this objalloc using `bfd_hash_allocate`.

Use `bfd_hash_table_free` to free up all the memory that has been allocated for a hash table. This will not free up the `struct bfd_hash_table` itself, which you must provide.

Use `bfd_hash_set_default_size` to set the default size of hash table to use.

2.18.2 Looking up or entering a string

The function `bfd_hash_lookup` is used both to look up a string in the hash table and to create a new entry.

If the *create* argument is `FALSE`, `bfd_hash_lookup` will look up a string. If the string is found, it will returns a pointer to a `struct bfd_hash_entry`. If the string is not found in the table `bfd_hash_lookup` will return `NULL`. You should not modify any of the fields in the returns `struct bfd_hash_entry`.

If the *create* argument is `TRUE`, the string will be entered into the hash table if it is not already there. Either way a pointer to a `struct bfd_hash_entry` will be returned, either to the existing structure or to a newly created one. In this case, a `NULL` return means that an error occurred.

If the *create* argument is `TRUE`, and a new entry is created, the *copy* argument is used to decide whether to copy the string onto the hash table objalloc or not. If *copy* is passed as `FALSE`, you must be careful not to deallocate or modify the string as long as the hash table exists.

2.18.3 Traversing a hash table

The function `bfd_hash_traverse` may be used to traverse a hash table, calling a function on each element. The traversal is done in a random order.

`bfd_hash_traverse` takes as arguments a function and a generic `void *` pointer. The function is called with a hash table entry (a `struct bfd_hash_entry *`) and the generic pointer passed to `bfd_hash_traverse`. The function must return a `boolean` value, which indicates whether to continue traversing the hash table. If the function returns `FALSE`, `bfd_hash_traverse` will stop the traversal and return immediately.

2.18.4 Deriving a new hash table type

Many uses of hash tables want to store additional information which each entry in the hash table. Some also find it convenient to store additional information with the hash table itself. This may be done using a derived hash table.

Since C is not an object oriented language, creating a derived hash table requires sticking together some boilerplate routines with a few differences specific to the type of hash table you want to create.

An example of a derived hash table is the linker hash table. The structures for this are defined in `bfdlink.h`. The functions are in `linker.c`.

You may also derive a hash table from an already derived hash table. For example, the a.out linker backend code uses a hash table derived from the linker hash table.

2.18.4.1 Define the derived structures

You must define a structure for an entry in the hash table, and a structure for the hash table itself.

The first field in the structure for an entry in the hash table must be of the type used for an entry in the hash table you are deriving from. If you are deriving from a basic hash table this is `struct bfd_hash_entry`, which is defined in `bfd.h`. The first field in the structure for the hash table itself must be of the type of the hash table you are deriving from itself. If you are deriving from a basic hash table, this is `struct bfd_hash_table`.

For example, the linker hash table defines `struct bfd_link_hash_entry` (in `bfdlink.h`). The first field, `root`, is of type `struct bfd_hash_entry`. Similarly, the first field in `struct bfd_link_hash_table`, `table`, is of type `struct bfd_hash_table`.

2.18.4.2 Write the derived creation routine

You must write a routine which will create and initialize an entry in the hash table. This routine is passed as the function argument to `bfd_hash_table_init`.

In order to permit other hash tables to be derived from the hash table you are creating, this routine must be written in a standard way.

The first argument to the creation routine is a pointer to a hash table entry. This may be `NULL`, in which case the routine should allocate the right amount of space. Otherwise the space has already been allocated by a hash table type derived from this one.

After allocating space, the creation routine must call the creation routine of the hash table type it is derived from, passing in a pointer to the space it just allocated. This will initialize any fields used by the base hash table.

Finally the creation routine must initialize any local fields for the new hash table type.

Here is a boilerplate example of a creation routine. *function_name* is the name of the routine. *entry_type* is the type of an entry in the hash table you are creating. *base_newfunc* is the name of the creation routine of the hash table type your hash table is derived from.

```
struct bfd_hash_entry *
function_name (struct bfd_hash_entry *entry,
                     struct bfd_hash_table *table,
                     const char *string)
{
  struct entry_type *ret = (entry_type *) entry;

 /* Allocate the structure if it has not already been allocated by a
    derived class.  */
  if (ret == NULL)
    {
      ret = bfd_hash_allocate (table, sizeof (* ret));
      if (ret == NULL)
        return NULL;
    }

 /* Call the allocation method of the base class.  */
  ret = ((entry_type *)
         base_newfunc ((struct bfd_hash_entry *) ret, table, string));

 /* Initialize the local fields here.  */

  return (struct bfd_hash_entry *) ret;
}
```

The creation routine for the linker hash table, which is in `linker.c`, looks just like this example. *function_name* is `_bfd_link_hash_newfunc`. *entry_type* is `struct bfd_link_hash_entry`. *base_newfunc* is `bfd_hash_newfunc`, the creation routine for a basic hash table.

`_bfd_link_hash_newfunc` also initializes the local fields in a linker hash table entry: `type`, `written` and `next`.

2.18.4.3 Write other derived routines

You will want to write other routines for your new hash table, as well.

You will want an initialization routine which calls the initialization routine of the hash table you are deriving from and initializes any other local fields. For the linker hash table, this is `_bfd_link_hash_table_init` in `linker.c`.

You will want a lookup routine which calls the lookup routine of the hash table you are deriving from and casts the result. The linker hash table uses `bfd_link_hash_lookup` in `linker.c` (this actually takes an additional argument which it uses to decide how to return the looked up value).

You may want a traversal routine. This should just call the traversal routine of the hash table you are deriving from with appropriate casts. The linker hash table uses `bfd_link_hash_traverse` in `linker.c`.

These routines may simply be defined as macros. For example, the a.out backend linker hash table, which is derived from the linker hash table, uses macros for the lookup and traversal routines. These are `aout_link_hash_lookup` and `aout_link_hash_traverse` in aoutx.h.

2.18.4.4 `bfd_hash_table_init_n`

```
bool bfd_hash_table_init_n (struct bfd_hash_table *,          [Function]
        struct bfd_hash_entry *(* *newfunc*) (struct bfd_hash_entry
        *, struct bfd_hash_table *, const char *), unsigned int
        *entsize*, unsigned int *size*);
```

Create a new hash table, given a number of entries.

2.18.4.5 `bfd_hash_table_init`

```
bool bfd_hash_table_init (struct bfd_hash_table *, struct     [Function]
        bfd_hash_entry *(* *newfunc*) (struct bfd_hash_entry *,
        struct bfd_hash_table *, const char *), unsigned int
        *entsize*);
```

Create a new hash table with the default number of entries.

2.18.4.6 `bfd_hash_table_free`

```
void bfd_hash_table_free (struct bfd_hash_table *);           [Function]
```

Free a hash table.

2.18.4.7 `bfd_hash_lookup`

```
struct bfd_hash_entry *bfd_hash_lookup (struct                [Function]
        bfd_hash_table *, const char *, bool *create*, bool *copy*);
```

Look up a string in a hash table.

2.18.4.8 `bfd_hash_insert`

```
struct bfd_hash_entry *bfd_hash_insert (struct                [Function]
        bfd_hash_table *, const char *, unsigned long *hash*);
```

Insert an entry in a hash table.

2.18.4.9 bfd_hash_rename

`void bfd_hash_rename (struct bfd_hash_table *, const char *, struct bfd_hash_entry *);` [Function]

Rename an entry in a hash table.

2.18.4.10 bfd_hash_replace

`void bfd_hash_replace (struct bfd_hash_table *, struct bfd_hash_entry * *old*, struct bfd_hash_entry * *new*);` [Function]

Replace an entry in a hash table.

2.18.4.11 bfd_hash_allocate

`void *bfd_hash_allocate (struct bfd_hash_table *, unsigned int *size*);` [Function]

Allocate space in a hash table.

2.18.4.12 bfd_hash_newfunc

`struct bfd_hash_entry *bfd_hash_newfunc (struct bfd_hash_entry *, struct bfd_hash_table *, const char *);` [Function]

Base method for creating a new hash table entry.

2.18.4.13 bfd_hash_traverse

`void bfd_hash_traverse (struct bfd_hash_table *, bool (*) (struct bfd_hash_entry *, void *), void *);` [Function]

Traverse a hash table.

2.18.4.14 bfd_hash_set_default_size

`unsigned int bfd_hash_set_default_size (unsigned int);` [Function]

Set hash table default size.

2.18.4.15 _bfd_stringtab_init

`struct bfd_strtab_hash *_bfd_stringtab_init (void);` [Function]

Create a new strtab.

2.18.4.16 _bfd_xcoff_stringtab_init

`struct bfd_strtab_hash *_bfd_xcoff_stringtab_init (bool *isxcoff64*);` [Function]

Create a new strtab in which the strings are output in the format used in the XCOFF .debug section: a two byte length precedes each string.

2.18.4.17 _bfd_stringtab_free

`void _bfd_stringtab_free (struct bfd_strtab_hash *);` [Function]

Free a strtab.

2.18.4.18 _bfd_stringtab_add

`bfd_size_type _bfd_stringtab_add (struct bfd_strtab_hash *, const char *, bool *hash*, bool *copy*);` [Function]

Get the index of a string in a strtab, adding it if it is not already present. If HASH is FALSE, we don't really use the hash table, and we don't eliminate duplicate strings. If COPY is true then store a copy of STR if creating a new entry.

2.18.4.19 _bfd_stringtab_size

`bfd_size_type _bfd_stringtab_size (struct bfd_strtab_hash *);` [Function]

Get the number of bytes in a strtab.

2.18.4.20 _bfd_stringtab_emit

`bool _bfd_stringtab_emit (bfd *, struct bfd_strtab_hash *);` [Function]

Write out a strtab. ABFD must already be at the right location in the file.

3 BFD back ends

3.1 What to Put Where

All of BFD lives in one directory.

3.2 a.out backends

BFD supports a number of different flavours of a.out format, though the major differences are only the sizes of the structures on disk, and the shape of the relocation information.

The support is split into a basic support file `aoutx.h` and other files which derive functions from the base. One derivation file is `aoutf1.h` (for a.out flavour 1), and adds to the basic a.out functions support for sun3, sun4, and 386 a.out files, to create a target jump vector for a specific target.

This information is further split out into more specific files for each machine, including `sunos.c` for sun3 and sun4, and `demo64.c` for a demonstration of a 64 bit a.out format.

The base file `aoutx.h` defines general mechanisms for reading and writing records to and from disk and various other methods which BFD requires. It is included by `aout32.c` and `aout64.c` to form the names `aout_32_swap_exec_header_in`, `aout_64_swap_exec_header_in`, etc.

As an example, this is what goes on to make the back end for a sun4, from `aout32.c`:

```
#define ARCH_SIZE 32
#include "aoutx.h"
```

Which exports names:

```
...
aout_32_canonicalize_reloc
aout_32_find_nearest_line
aout_32_get_lineno
aout_32_get_reloc_upper_bound
...
```

from `sunos.c`:

```
#define TARGET_NAME "a.out-sunos-big"
#define VECNAME    sparc_aout_sunos_be_vec
#include "aoutf1.h"
```

requires all the names from `aout32.c`, and produces the jump vector

```
sparc_aout_sunos_be_vec
```

The file `host-aout.c` is a special case. It is for a large set of hosts that use "more or less standard" a.out files, and for which cross-debugging is not interesting. It uses the standard 32-bit a.out support routines, but determines the file offsets and addresses of the text, data, and BSS sections, the machine architecture and machine type, and the entry point address, in a host-dependent manner. Once these values have been determined, generic code is used to handle the object file.

When porting it to run on a new system, you must supply:

```
HOST_PAGE_SIZE
```

```
HOST_SEGMENT_SIZE
HOST_MACHINE_ARCH       (optional)
HOST_MACHINE_MACHINE    (optional)
HOST_TEXT_START_ADDR
HOST_STACK_END_ADDR
```

in the file `../include/sys/h-XXX.h` (for your host). These values, plus the structures and macros defined in `a.out.h` on your host system, will produce a BFD target that will access ordinary a.out files on your host. To configure a new machine to use `host-aout.c`, specify:

```
TDEFAULTS = -DDEFAULT_VECTOR=host_aout_big_vec
TDEPFILES= host-aout.o trad-core.o
```

in the `config/XXX.mt` file, and modify `configure.ac` to use the `XXX.mt` file (by setting `"bfd_target=XXX"`) when your configuration is selected.

3.2.1 Relocations

The file `aoutx.h` provides for both the *standard* and *extended* forms of a.out relocation records.

The standard records contain only an address, a symbol index, and a type field. The extended records also have a full integer for an addend.

3.2.2 Internal entry points

`aoutx.h` exports several routines for accessing the contents of an a.out file, which are gathered and exported in turn by various format specific files (eg sunos.c).

3.2.2.1 aout_*size*_swap_exec_header_in

`void aout_size_swap_exec_header_in, (bfd *abfd, struct external_exec *bytes, struct internal_exec *execp);` [Function]

Swap the information in an executable header *raw_bytes* taken from a raw byte stream memory image into the internal exec header structure *execp*.

3.2.2.2 aout_*size*_swap_exec_header_out

`bool aout_size_swap_exec_header_out (bfd *abfd, struct internal_exec *execp, struct external_exec *raw_bytes);` [Function]

Swap the information in an internal exec header structure *execp* into the buffer *raw_bytes* ready for writing to disk.

3.2.2.3 aout_*size*_some_aout_object_p

`bfd_cleanup aout_size_some_aout_object_p (bfd *abfd, struct internal_exec *execp, bfd_cleanup (*callback_to_real_object_p) (bfd *));` [Function]

Some a.out variant thinks that the file open in *abfd* checking is an a.out file. Do some more checking, and set up for access if it really is. Call back to the calling environment's "finish up" function just before returning, to handle any last-minute setup.

3.2.2.4 aout_*size*_mkobject

`bool aout_size_mkobject, (bfd *abfd);` [Function]

Initialize BFD *abfd* for use with a.out files.

3.2.2.5 aout_*size*_machine_type

`enum machine_type aout_size_machine_type (enum bfd_architecture arch, unsigned long machine, bool *unknown);` [Function]

Keep track of machine architecture and machine type for a.out's. Return the `machine_type` for a particular architecture and machine, or `M_UNKNOWN` if that exact architecture and machine can't be represented in a.out format.

If the architecture is understood, machine type 0 (default) is always understood.

3.2.2.6 aout_*size*_set_arch_mach

`bool aout_size_set_arch_mach, (bfd *, enum bfd_architecture arch, unsigned long machine);` [Function]

Set the architecture and the machine of the BFD *abfd* to the values *arch* and *machine*. Verify that *abfd*'s format can support the architecture required.

3.2.2.7 aout_*size*_new_section_hook

`bool aout_size_new_section_hook, (bfd *abfd, asection *newsect);` [Function]

Called by the BFD in response to a `bfd_make_section` request.

3.3 coff backends

BFD supports a number of different flavours of coff format. The major differences between formats are the sizes and alignments of fields in structures on disk, and the occasional extra field.

Coff in all its varieties is implemented with a few common files and a number of implementation specific files. For example, the i386 coff format is implemented in the file `coff-i386.c`. This file `#includes` `coff/i386.h` which defines the external structure of the coff format for the i386, and `coff/internal.h` which defines the internal structure. `coff-i386.c` also defines the relocations used by the i386 coff format See Section 2.10 [Relocations], page 51.

3.3.1 Porting to a new version of coff

The recommended method is to select from the existing implementations the version of coff which is most like the one you want to use. For example, we'll say that i386 coff is the one you select, and that your coff flavour is called foo. Copy `i386coff.c` to `foocoff.c`, copy `../include/coff/i386.h` to `../include/coff/foo.h`, and add the lines to `targets.c` and `Makefile.in` so that your new back end is used. Alter the shapes of the structures in `../include/coff/foo.h` so that they match what you need. You will probably also have to add `#ifdef`s to the code in `coff/internal.h` and `coffcode.h` if your version of coff is too wild.

You can verify that your new BFD backend works quite simply by building `objdump` from the `binutils` directory, and making sure that its version of what's going on and your host system's idea (assuming it has the pretty standard coff dump utility, usually called `att-dump` or just `dump`) are the same. Then clean up your code, and send what you've done to Cygnus. Then your stuff will be in the next release, and you won't have to keep integrating it.

3.3.2 How the coff backend works

3.3.2.1 File layout

The Coff backend is split into generic routines that are applicable to any Coff target and routines that are specific to a particular target. The target-specific routines are further split into ones which are basically the same for all Coff targets except that they use the external symbol format or use different values for certain constants.

The generic routines are in `coffgen.c`. These routines work for any Coff target. They use some hooks into the target specific code; the hooks are in a `bfd_coff_backend_data` structure, one of which exists for each target.

The essentially similar target-specific routines are in `coffcode.h`. This header file includes executable C code. The various Coff targets first include the appropriate Coff header file, make any special defines that are needed, and then include `coffcode.h`.

Some of the Coff targets then also have additional routines in the target source file itself.

3.3.2.2 Coff long section names

In the standard Coff object format, section names are limited to the eight bytes available in the `s_name` field of the `SCNHDR` section header structure. The format requires the field to be NUL-padded, but not necessarily NUL-terminated, so the longest section names permitted are a full eight characters.

The Microsoft PE variants of the Coff object file format add an extension to support the use of long section names. This extension is defined in section 4 of the Microsoft PE/COFF specification (rev 8.1). If a section name is too long to fit into the section header's `s_name` field, it is instead placed into the string table, and the `s_name` field is filled with a slash (`"/"`) followed by the ASCII decimal representation of the offset of the full name relative to the string table base.

Note that this implies that the extension can only be used in object files, as executables do not contain a string table. The standard specifies that long section names from objects emitted into executable images are to be truncated.

However, as a GNU extension, BFD can generate executable images that contain a string table and long section names. This would appear to be technically valid, as the standard only says that Coff debugging information is deprecated, not forbidden, and in practice it works, although some tools that parse PE files expecting the MS standard format may become confused; `PEview` is one known example.

The functionality is supported in BFD by code implemented under the control of the macro `COFF_LONG_SECTION_NAMES`. If not defined, the format does not support long section names in any way. If defined, it is used to initialise a flag, `_bfd_coff_long_section_names`, and a hook function pointer, `_bfd_coff_set_long_section_names`, in the Coff backend data

structure. The flag controls the generation of long section names in output BFDs at runtime; if it is false, as it will be by default when generating an executable image, long section names are truncated; if true, the long section names extension is employed. The hook points to a function that allows the value of a copy of the flag in coff object tdata to be altered at runtime, on formats that support long section names at all; on other formats it points to a stub that returns an error indication.

With input BFDs, the flag is set according to whether any long section names are detected while reading the section headers. For a completely new BFD, the flag is set to the default for the target format. This information can be used by a client of the BFD library when deciding what output format to generate, and means that a BFD that is opened for read and subsequently converted to a writeable BFD and modified in-place will retain whatever format it had on input.

If `COFF_LONG_SECTION_NAMES` is simply defined (blank), or is defined to the value `"1"`, then long section names are enabled by default; if it is defined to the value zero, they are disabled by default (but still accepted in input BFDs). The header `coffcode.h` defines a macro, `COFF_DEFAULT_LONG_SECTION_NAMES`, which is used in the backends to initialise the backend data structure fields appropriately; see the comments for further detail.

3.3.2.3 Bit twiddling

Each flavour of coff supported in BFD has its own header file describing the external layout of the structures. There is also an internal description of the coff layout, in `coff/internal.h`. A major function of the coff backend is swapping the bytes and twiddling the bits to translate the external form of the structures into the normal internal form. This is all performed in the `bfd_swap_`*thing*`_`*direction* routines. Some elements are different sizes between different versions of coff; it is the duty of the coff version specific include file to override the definitions of various packing routines in `coffcode.h`. E.g., the size of line number entry in coff is sometimes 16 bits, and sometimes 32 bits. `#define`ing `PUT_LNSZ_LNNO` and `GET_LNSZ_LNNO` will select the correct one. No doubt, some day someone will find a version of coff which has a varying field size not catered to at the moment. To port BFD, that person will have to add more `#defines`. Three of the bit twiddling routines are exported to `gdb`; `coff_swap_aux_in`, `coff_swap_sym_in` and `coff_swap_lineno_in`. `GDB` reads the symbol table on its own, but uses BFD to fix things up. More of the bit twiddlers are exported for `gas`; `coff_swap_aux_out`, `coff_swap_sym_out`, `coff_swap_lineno_out`, `coff_swap_reloc_out`, `coff_swap_filehdr_out`, `coff_swap_aouthdr_out`, `coff_swap_scnhdr_out`. `Gas` currently keeps track of all the symbol table and reloc drudgery itself, thereby saving the internal BFD overhead, but uses BFD to swap things on the way out, making cross ports much safer. Doing so also allows BFD (and thus the linker) to use the same header files as `gas`, which makes one avenue to disaster disappear.

3.3.2.4 Symbol reading

The simple canonical form for symbols used by BFD is not rich enough to keep all the information available in a coff symbol table. The back end gets around this problem by keeping the original symbol table around, `"behind the scenes"`.

When a symbol table is requested (through a call to `bfd_canonicalize_symtab`), a request gets through to `coff_get_normalized_symtab`. This reads the symbol table from the coff file and swaps all the structures inside into the internal form. It also fixes up all the pointers

in the table (represented in the file by offsets from the first symbol in the table) into physical pointers to elements in the new internal table. This involves some work since the meanings of fields change depending upon context: a field that is a pointer to another structure in the symbol table at one moment may be the size in bytes of a structure at the next. Another pass is made over the table. All symbols which mark file names (`C_FILE` symbols) are modified so that the internal string points to the value in the auxent (the real filename) rather than the normal text associated with the symbol (`".file"`).

At this time the symbol names are moved around. Coff stores all symbols less than nine characters long physically within the symbol table; longer strings are kept at the end of the file in the string table. This pass moves all strings into memory and replaces them with pointers to the strings.

The symbol table is massaged once again, this time to create the canonical table used by the BFD application. Each symbol is inspected in turn, and a decision made (using the `sclass` field) about the various flags to set in the `asymbol`. See Section 2.7 [Symbols], page 40. The generated canonical table shares strings with the hidden internal symbol table.

Any linenumbers are read from the coff file too, and attached to the symbols which own the functions the linenumbers belong to.

3.3.2.5 Symbol writing

Writing a symbol to a coff file which didn't come from a coff file will lose any debugging information. The `asymbol` structure remembers the BFD from which the symbol was taken, and on output the back end makes sure that the same destination target as source target is present.

When the symbols have come from a coff file then all the debugging information is preserved.

Symbol tables are provided for writing to the back end in a vector of pointers to pointers. This allows applications like the linker to accumulate and output large symbol tables without having to do too much byte copying.

This function runs through the provided symbol table and patches each symbol marked as a file place holder (`C_FILE`) to point to the next file place holder in the list. It also marks each `offset` field in the list with the offset from the first symbol of the current symbol.

Another function of this procedure is to turn the canonical value form of BFD into the form used by coff. Internally, BFD expects symbol values to be offsets from a section base; so a symbol physically at 0x120, but in a section starting at 0x100, would have the value 0x20. Coff expects symbols to contain their final value, so symbols have their values changed at this point to reflect their sum with their owning section. This transformation uses the `output_section` field of the `asymbol`'s `asection` See Section 2.6 [Sections], page 26.

- `coff_mangle_symbols`

This routine runs though the provided symbol table and uses the offsets generated by the previous pass and the pointers generated when the symbol table was read in to create the structured hierarchy required by coff. It changes each pointer to a symbol into the index into the symbol table of the asymbol.

- `coff_write_symbols`

This routine runs through the symbol table and patches up the symbols from their internal form into the coff way, calls the bit twiddlers, and writes out the table to the file.

3.3.2.6 coff_symbol_type

The hidden information for an asymbol is described in a combined_entry_type:

```
typedef struct coff_ptr_struct
{
  /* Remembers the offset from the first symbol in the file for
     this symbol.  Generated by coff_renumber_symbols.  */
  unsigned int offset;

  /* Selects between the elements of the union below.  */
  unsigned int is_sym : 1;

  /* Selects between the elements of the x_sym.x_tagndx union.  If set,
     p is valid and the field will be renumbered.  */
  unsigned int fix_tag : 1;

  /* Selects between the elements of the x_sym.x_fcnary.x_fcn.x_endndx
     union.  If set, p is valid and the field will be renumbered.  */
  unsigned int fix_end : 1;

  /* Selects between the elements of the x_csect.x_scnlen union.  If set,
     p is valid and the field will be renumbered.  */
  unsigned int fix_scnlen : 1;

  /* If set, u.syment.n_value contains a pointer to a symbol.  The final
     value will be the offset field.  Used for XCOFF C_BSTAT symbols.  */
  unsigned int fix_value : 1;

  /* If set, u.syment.n_value is an index into the line number entries.
     Used for XCOFF C_BINCL/C_EINCL symbols.  */
  unsigned int fix_line : 1;

  /* The container for the symbol structure as read and translated
     from the file.  */
  union
  {
    union internal_auxent auxent;
    struct internal_syment syment;
  } u;

 /* An extra pointer which can used by format based on COFF (like XCOFF)
     to provide extra information to their backend.  */
 void *extrap;
} combined_entry_type;

/* Each canonical asymbol really looks like this: */
```

```
typedef struct coff_symbol_struct
{
  /* The actual symbol which the rest of BFD works with */
  asymbol symbol;

  /* A pointer to the hidden information for this symbol */
  combined_entry_type *native;

  /* A pointer to the linenumber information for this symbol */
  struct lineno_cache_entry *lineno;

  /* Have the line numbers been relocated yet ? */
  bool done_lineno;
} coff_symbol_type;
```

3.3.2.7 bfd_coff_backend_data

```
typedef struct
{
  void (*_bfd_coff_swap_aux_in)
    (bfd *, void *, int, int, int, int, void *);

  void (*_bfd_coff_swap_sym_in)
    (bfd *, void *, void *);

  void (*_bfd_coff_swap_lineno_in)
    (bfd *, void *, void *);

  unsigned int (*_bfd_coff_swap_aux_out)
    (bfd *, void *, int, int, int, int, void *);

  unsigned int (*_bfd_coff_swap_sym_out)
    (bfd *, void *, void *);

  unsigned int (*_bfd_coff_swap_lineno_out)
    (bfd *, void *, void *);

  unsigned int (*_bfd_coff_swap_reloc_out)
    (bfd *, void *, void *);

  unsigned int (*_bfd_coff_swap_filehdr_out)
    (bfd *, void *, void *);

  unsigned int (*_bfd_coff_swap_aouthdr_out)
    (bfd *, void *, void *);
```

```
unsigned int (*_bfd_coff_swap_scnhdr_out)
  (bfd *, void *, void *);

unsigned int _bfd_filhsz;
unsigned int _bfd_aoutsz;
unsigned int _bfd_scnhsz;
unsigned int _bfd_symesz;
unsigned int _bfd_auxesz;
unsigned int _bfd_relsz;
unsigned int _bfd_linesz;
unsigned int _bfd_filnmlen;
bool _bfd_coff_long_filenames;

bool _bfd_coff_long_section_names;
bool (*_bfd_coff_set_long_section_names)
  (bfd *, int);

unsigned int _bfd_coff_default_section_alignment_power;
bool _bfd_coff_force_symnames_in_strings;
unsigned int _bfd_coff_debug_string_prefix_length;
unsigned int _bfd_coff_max_nscns;

void (*_bfd_coff_swap_filehdr_in)
  (bfd *, void *, void *);

void (*_bfd_coff_swap_aouthdr_in)
  (bfd *, void *, void *);

void (*_bfd_coff_swap_scnhdr_in)
  (bfd *, void *, void *);

void (*_bfd_coff_swap_reloc_in)
  (bfd *abfd, void *, void *);

bool (*_bfd_coff_bad_format_hook)
  (bfd *, void *);

bool (*_bfd_coff_set_arch_mach_hook)
  (bfd *, void *);

void * (*_bfd_coff_mkobject_hook)
  (bfd *, void *, void *);

bool (*_bfd_styp_to_sec_flags_hook)
  (bfd *, void *, const char *, asection *, flagword *);

void (*_bfd_set_alignment_hook)
```

```
  (bfd *, asection *, void *);

bool (*_bfd_coff_slurp_symbol_table)
  (bfd *);

bool (*_bfd_coff_symname_in_debug)
  (bfd *, struct internal_syment *);

bool (*_bfd_coff_pointerize_aux_hook)
  (bfd *, combined_entry_type *, combined_entry_type *,
   unsigned int, combined_entry_type *);

bool (*_bfd_coff_print_aux)
  (bfd *, FILE *, combined_entry_type *, combined_entry_type *,
   combined_entry_type *, unsigned int);

bool (*_bfd_coff_reloc16_extra_cases)
  (bfd *, struct bfd_link_info *, struct bfd_link_order *, arelent *,
   bfd_byte *, size_t *, size_t *);

int (*_bfd_coff_reloc16_estimate)
  (bfd *, asection *, arelent *, unsigned int,
   struct bfd_link_info *);

enum coff_symbol_classification (*_bfd_coff_classify_symbol)
  (bfd *, struct internal_syment *);

bool (*_bfd_coff_compute_section_file_positions)
  (bfd *);

bool (*_bfd_coff_start_final_link)
  (bfd *, struct bfd_link_info *);

bool (*_bfd_coff_relocate_section)
  (bfd *, struct bfd_link_info *, bfd *, asection *, bfd_byte *,
   struct internal_reloc *, struct internal_syment *, asection **);

reloc_howto_type *(*_bfd_coff_rtype_to_howto)
  (bfd *, asection *, struct internal_reloc *,
   struct coff_link_hash_entry *, struct internal_syment *, bfd_vma *);

bool (*_bfd_coff_adjust_symndx)
  (bfd *, struct bfd_link_info *, bfd *, asection *,
   struct internal_reloc *, bool *);

bool (*_bfd_coff_link_output_has_begun)
  (bfd *, struct coff_final_link_info *);
```

```
  bool (*_bfd_coff_final_link_postscript)
    (bfd *, struct coff_final_link_info *);

  bool (*_bfd_coff_print_pdata)
    (bfd *, void *);

} bfd_coff_backend_data;
```

3.3.2.8 Writing relocations

To write relocations, the back end steps though the canonical relocation table and create an `internal_reloc`. The symbol index to use is removed from the `offset` field in the symbol table supplied. The address comes directly from the sum of the section base address and the relocation offset; the type is dug directly from the howto field. Then the `internal_reloc` is swapped into the shape of an `external_reloc` and written out to disk.

3.3.2.9 Reading linenumbers

Creating the linenumber table is done by reading in the entire coff linenumber table, and creating another table for internal use.

A coff linenumber table is structured so that each function is marked as having a line number of 0. Each line within the function is an offset from the first line in the function. The base of the line number information for the table is stored in the symbol associated with the function.

Note: The PE format uses line number 0 for a flag indicating a new source file.

The information is copied from the external to the internal table, and each symbol which marks a function is marked by pointing its...

How does this work ?

3.3.2.10 Reading relocations

Coff relocations are easily transformed into the internal BFD form (`arelent`).

Reading a coff relocation table is done in the following stages:

- Read the entire coff relocation table into memory.
- Process each relocation in turn; first swap it from the external to the internal form.
- Turn the symbol referenced in the relocation's symbol index into a pointer into the canonical symbol table. This table is the same as the one returned by a call to `bfd_canonicalize_symtab`. The back end will call that routine and save the result if a canonicalization hasn't been done.
- The reloc index is turned into a pointer to a howto structure, in a back end specific way. For instance, the 386 uses the `r_type` to directly produce an index into a howto table vector.
- Note that `arelent.addend` for COFF is often not what most people understand as a relocation addend, but rather an adjustment to the relocation addend stored in section contents of relocatable object files. The value found in section contents may also be

confusing, depending on both symbol value and addend somewhat similar to the field value for a final-linked object. See `CALC_ADDEND`.

3.4 ELF backends

BFD support for ELF formats is being worked on. Currently, the best supported back ends are for sparc and i386 (running svr4 or Solaris 2).

Documentation of the internals of the support code still needs to be written. The code is changing quickly enough that we haven't bothered yet.

3.5 mmo backend

The mmo object format is used exclusively together with Professor Donald E. Knuth's educational 64-bit processor MMIX. The simulator `mmix` which is available at `http://mmix.cs.hm.edu/src/index.html` understands this format. That package also includes a combined assembler and linker called `mmixal`. The mmo format has no advantages feature-wise compared to e.g. ELF. It is a simple non-relocatable object format with no support for archives or debugging information, except for symbol value information and line numbers (which is not yet implemented in BFD). See `http://mmix.cs.hm.edu/` for more information about MMIX. The ELF format is used for intermediate object files in the BFD implementation.

3.5.1 File layout

The mmo file contents is not partitioned into named sections as with e.g. ELF. Memory areas is formed by specifying the location of the data that follows. Only the memory area '`0x0000...00`' to '`0x01ff...ff`' is executable, so it is used for code (and constants) and the area '`0x2000...00`' to '`0x20ff...ff`' is used for writable data. See Section 3.5.3 [mmo section mapping], page 210.

There is provision for specifying "special data" of 65536 different types. We use type 80 (decimal), arbitrarily chosen the same as the ELF `e_machine` number for MMIX, filling it with section information normally found in ELF objects. See Section 3.5.3 [mmo section mapping], page 210.

Contents is entered as 32-bit words, xor:ed over previous contents, always zero-initialized. A word that starts with the byte '`0x98`' forms a command called a '`lopcode`', where the next byte distinguished between the thirteen lopcodes. The two remaining bytes, called the '`Y`' and '`Z`' fields, or the '`YZ`' field (a 16-bit big-endian number), are used for various purposes different for each lopcode. As documented in `http://mmix.cs.hm.edu/doc/mmixal.pdf`, the lopcodes are:

`lop_quote`
: 0x98000001. The next word is contents, regardless of whether it starts with 0x98 or not.

`lop_loc`
: 0x9801YYZZ, where '`Z`' is 1 or 2. This is a location directive, setting the location for the next data to the next 32-bit word (for $Z = 1$) or 64-bit word (for $Z = 2$), plus $Y * 2^5 6$. Normally '`Y`' is 0 for the text segment and 2 for the data segment. Beware that the low bits of non- tetrabyte-aligned values are silently discarded when being automatically incremented and when storing contents (in contrast

to e.g. its use as current location when followed by lop_fixo et al before the next possibly-quoted tetrabyte contents).

`lop_skip` 0x9802YYZZ. Increase the current location by '`YZ`' bytes.

`lop_fixo` 0x9803YYZZ, where '`Z`' is 1 or 2. Store the current location as 64 bits into the location pointed to by the next 32-bit ($Z = 1$) or 64-bit ($Z = 2$) word, plus $Y * 2^5 6$.

`lop_fixr` 0x9804YYZZ. '`YZ`' is stored into the current location plus $2 - 4 * YZ$.

`lop_fixrx`

0x980500ZZ. '`Z`' is 16 or 24. A value '`L`' derived from the following 32-bit word are used in a manner similar to '`YZ`' in lop_fixr: it is xor:ed into the current location minus $4 * L$. The first byte of the word is 0 or 1. If it is 1, then $L = (lowest24bitsofword) - 2^Z$, if 0, then $L = (lowest24bitsofword)$.

`lop_file` 0x9806YYZZ. '`Y`' is the file number, '`Z`' is count of 32-bit words. Set the file number to '`Y`' and the line counter to 0. The next $Z * 4$ bytes contain the file name, padded with zeros if the count is not a multiple of four. The same '`Y`' may occur multiple times, but '`Z`' must be 0 for all but the first occurrence.

`lop_line` 0x9807YYZZ. '`YZ`' is the line number. Together with lop_file, it forms the source location for the next 32-bit word. Note that for each non-lopcode 32-bit word, line numbers are assumed incremented by one.

`lop_spec` 0x9808YYZZ. '`YZ`' is the type number. Data until the next lopcode other than lop_quote forms special data of type '`YZ`'. See Section 3.5.3 [mmo section mapping], page 210.

Other types than 80, (or type 80 with a content that does not parse) is stored in sections named `.MMIX.spec_data.`*n* where *n* is the '`YZ`'-type. The flags for such a sections say not to allocate or load the data. The vma is 0. Contents of multiple occurrences of special data *n* is concatenated to the data of the previous lop_spec *n*s. The location in data or code at which the lop_spec occurred is lost.

`lop_pre` 0x980901ZZ. The first lopcode in a file. The '`Z`' field forms the length of header information in 32-bit words, where the first word tells the time in seconds since '`00:00:00 GMT Jan 1 1970`'.

`lop_post` 0x980a00ZZ. $Z > 32$. This lopcode follows after all content-generating lopcodes in a program. The '`Z`' field denotes the value of '`rG`' at the beginning of the program. The following $256 - Z$ big-endian 64-bit words are loaded into global registers '`$G`' ... '`$255`'.

`lop_stab` 0x980b0000. The next-to-last lopcode in a program. Must follow immediately after the lop_post lopcode and its data. After this lopcode follows all symbols in a compressed format (see Section 3.5.2 [Symbol-table], page 208).

`lop_end` 0x980cYYZZ. The last lopcode in a program. It must follow the lop_stab lopcode and its data. The '`YZ`' field contains the number of 32-bit words of symbol table information after the preceding lop_stab lopcode.

Note that the lopcode "fixups"; `lop_fixr`, `lop_fixrx` and `lop_fixo` are not generated by BFD, but are handled. They are generated by `mmixal`.

This trivial one-label, one-instruction file:

```
:Main TRAP 1,2,3
```

can be represented this way in mmo:

```
0x98090101 - lop_pre, one 32-bit word with timestamp.
<timestamp>
0x98010002 - lop_loc, text segment, using a 64-bit address.
             Note that mmixal does not emit this for the file above.
0x00000000 - Address, high 32 bits.
0x00000000 - Address, low 32 bits.
0x98060002 - lop_file, 2 32-bit words for file-name.
0x74657374 - "test"
0x2e730000 - ".s\0\0"
0x98070001 - lop_line, line 1.
0x00010203 - TRAP 1,2,3
0x980a00ff - lop_post, setting $255 to 0.
0x00000000
0x00000000
0x980b0000 - lop_stab for ":Main" = 0, serial 1.
0x203a4040   See Section 3.5.2 [Symbol-table], page 208.
0x10404020
0x4d206120
0x69016e00
0x81000000
0x980c0005 - lop_end; symbol table contained five 32-bit words.
```

3.5.2 Symbol table format

From mmixal.w (or really, the generated mmixal.tex) in the MMIXware package which also contains the `mmix` simulator: "Symbols are stored and retrieved by means of a '`ternary search trie`', following ideas of Bentley and Sedgewick. (See ACM–SIAM Symp. on Discrete Algorithms '`8`' (1997), 360–369; R.Sedgewick, '`Algorithms in C`' (Reading, Mass. Addison–Wesley, 1998), '`15.4`'.) Each trie node stores a character, and there are branches to subtries for the cases where a given character is less than, equal to, or greater than the character in the trie. There also is a pointer to a symbol table entry if a symbol ends at the current node."

So it's a tree encoded as a stream of bytes. The stream of bytes acts on a single virtual global symbol, adding and removing characters and signalling complete symbol points. Here, we read the stream and create symbols at the completion points.

First, there's a control byte `m`. If any of the listed bits in `m` is nonzero, we execute what stands at the right, in the listed order:

```
(MMO3_LEFT)
0x40 - Traverse left trie.
       (Read a new command byte and recurse.)

(MMO3_SYMBITS)
0x2f - Read the next byte as a character and store it in the
```

```
            current character position; increment character position.
            Test the bits of m:

            (MMO3_WCHAR)
            0x80 - The character is 16-bit (so read another byte,
                   merge into current character.

            (MMO3_TYPEBITS)
            0xf  - We have a complete symbol; parse the type, value
                   and serial number and do what should be done
                   with a symbol.  The type and length information
                   is in j = (m & 0xf).

                   (MMO3_REGQUAL_BITS)
                   j == 0xf: A register variable.  The following
                             byte tells which register.
                   j <= 8:   An absolute symbol.  Read j bytes as the
                             big-endian number the symbol equals.
                             A j = 2 with two zero bytes denotes an
                             unknown symbol.
                   j > 8:    As with j <= 8, but add (0x20 << 56)
                             to the value in the following j - 8
                             bytes.

                   Then comes the serial number, as a variant of
                   uleb128, but better named ubeb128:
                   Read bytes and shift the previous value left 7
                   (multiply by 128).  Add in the new byte, repeat
                   until a byte has bit 7 set.  The serial number
                   is the computed value minus 128.

            (MMO3_MIDDLE)
            0x20 - Traverse middle trie.  (Read a new command byte
                   and recurse.)  Decrement character position.

      (MMO3_RIGHT)
      0x10 - Traverse right trie.  (Read a new command byte and
             recurse.)
```

Let's look again at the `lop_stab` for the trivial file (see Section 3.5.1 [File layout], page 206).

```
      0x980b0000 - lop_stab for ":Main" = 0, serial 1.
      0x203a4040
      0x10404020
      0x4d206120
      0x69016e00
      0x81000000
```

This forms the trivial trie (note that the path between ":" and "M" is redundant):

```
203a     ":"
40        /
40       /
10       \
40       /
40      /
204d  "M"
2061  "a"
2069  "i"
016e  "n" is the last character in a full symbol, and
      with a value represented in one byte.
00    The value is 0.
81    The serial number is 1.
```

3.5.3 mmo section mapping

The implementation in BFD uses special data type 80 (decimal) to encapsulate and describe named sections, containing e.g. debug information. If needed, any datum in the encapsulation will be quoted using lop_quote. First comes a 32-bit word holding the number of 32-bit words containing the zero-terminated zero-padded segment name. After the name there's a 32-bit word holding flags describing the section type. Then comes a 64-bit big-endian word with the section length (in bytes), then another with the section start address. Depending on the type of section, the contents might follow, zero-padded to 32-bit boundary. For a loadable section (such as data or code), the contents might follow at some later point, not necessarily immediately, as a lop_loc with the same start address as in the section description, followed by the contents. This in effect forms a descriptor that must be emitted before the actual contents. Sections described this way must not overlap.

For areas that don't have such descriptors, synthetic sections are formed by BFD. Consecutive contents in the two memory areas '`0x0000...00`' to '`0x01ff...ff`' and '`0x2000...00`' to '`0x20ff...ff`' are entered in sections named `.text` and `.data` respectively. If an area is not otherwise described, but would together with a neighboring lower area be less than '`0x40000000`' bytes long, it is joined with the lower area and the gap is zero-filled. For other cases, a new section is formed, named `.MMIX.sec.`*n*. Here, *n* is a number, a running count through the mmo file, starting at 0.

A loadable section specified as:

```
.section secname,"ax"
TETRA 1,2,3,4,-1,-2009
BYTE 80
```

and linked to address '`0x4`', is represented by the sequence:

```
0x98080050 - lop_spec 80
0x00000002 - two 32-bit words for the section name
0x7365636e - "secn"
0x616d6500 - "ame\0"
0x00000033 - flags CODE, READONLY, LOAD, ALLOC
0x00000000 - high 32 bits of section length
0x0000001c - section length is 28 bytes; 6 * 4 + 1 + alignment to 32 bits
0x00000000 - high 32 bits of section address
```

```
0x00000004 - section address is 4
0x98010002 - 64 bits with address of following data
0x00000000 - high 32 bits of address
0x00000004 - low 32 bits: data starts at address 4
0x00000001 - 1
0x00000002 - 2
0x00000003 - 3
0x00000004 - 4
0xffffffff - -1
0xfffff827 - -2009
0x50000000 - 80 as a byte, padded with zeros.
```

Note that the lop_spec wrapping does not include the section contents. Compare this to a non-loaded section specified as:

```
.section thirdsec
TETRA 200001,100002
BYTE 38,40
```

This, when linked to address '`0x200000000000001c`', is represented by:

```
0x98080050 - lop_spec 80
0x00000002 - two 32-bit words for the section name
0x7365636e - "thir"
0x616d6500 - "dsec"
0x00000010 - flag READONLY
0x00000000 - high 32 bits of section length
0x0000000c - section length is 12 bytes; 2 * 4 + 2 + alignment to 32 bits
0x20000000 - high 32 bits of address
0x0000001c - low 32 bits of address 0x200000000000001c
0x00030d41 - 200001
0x000186a2 - 100002
0x26280000 - 38, 40 as bytes, padded with zeros
```

For the latter example, the section contents must not be loaded in memory, and is therefore specified as part of the special data. The address is usually unimportant but might provide information for e.g. the DWARF 2 debugging format.

Version 1.3, 3 November 2008

Copyright © 2000, 2001, 2002, 2007, 2008 Free Software Foundation, Inc.
`http://fsf.org/`

Everyone is permitted to copy and distribute verbatim copies
of this license document, but changing it is not allowed.

0. PREAMBLE

The purpose of this License is to make a manual, textbook, or other functional and useful document *free* in the sense of freedom: to assure everyone the effective freedom to copy and redistribute it, with or without modifying it, either commercially or non-commercially. Secondarily, this License preserves for the author and publisher a way to get credit for their work, while not being considered responsible for modifications made by others.

This License is a kind of "copyleft", which means that derivative works of the document must themselves be free in the same sense. It complements the GNU General Public License, which is a copyleft license designed for free software.

We have designed this License in order to use it for manuals for free software, because free software needs free documentation: a free program should come with manuals providing the same freedoms that the software does. But this License is not limited to software manuals; it can be used for any textual work, regardless of subject matter or whether it is published as a printed book. We recommend this License principally for works whose purpose is instruction or reference.

1. APPLICABILITY AND DEFINITIONS

   This License applies to any manual or other work, in any medium, that contains a notice placed by the copyright holder saying it can be distributed under the terms of this License. Such a notice grants a world-wide, royalty-free license, unlimited in duration, to use that work under the conditions stated herein. The "Document", below, refers to any such manual or work. Any member of the public is a licensee, and is addressed as "you". You accept the license if you copy, modify or distribute the work in a way requiring permission under copyright law.

   A "Modified Version" of the Document means any work containing the Document or a portion of it, either copied verbatim, or with modifications and/or translated into another language.

   A "Secondary Section" is a named appendix or a front-matter section of the Document that deals exclusively with the relationship of the publishers or authors of the Document to the Document's overall subject (or to related matters) and contains nothing that could fall directly within that overall subject. (Thus, if the Document is in part a textbook of mathematics, a Secondary Section may not explain any mathematics.) The relationship could be a matter of historical connection with the subject or with related matters, or of legal, commercial, philosophical, ethical or political position regarding them.

   The "Invariant Sections" are certain Secondary Sections whose titles are designated, as being those of Invariant Sections, in the notice that says that the Document is released under this License. If a section does not fit the above definition of Secondary then it is not allowed to be designated as Invariant. The Document may contain zero Invariant Sections. If the Document does not identify any Invariant Sections then there are none.

   The "Cover Texts" are certain short passages of text that are listed, as Front-Cover Texts or Back-Cover Texts, in the notice that says that the Document is released under this License. A Front-Cover Text may be at most 5 words, and a Back-Cover Text may be at most 25 words.

   A "Transparent" copy of the Document means a machine-readable copy, represented in a format whose specification is available to the general public, that is suitable for revising the document straightforwardly with generic text editors or (for images composed of pixels) generic paint programs or (for drawings) some widely available drawing editor, and that is suitable for input to text formatters or for automatic translation to a variety of formats suitable for input to text formatters. A copy made in an otherwise Transparent file format whose markup, or absence of markup, has been arranged to thwart or discourage subsequent modification by readers is not Transparent. An image

format is not Transparent if used for any substantial amount of text. A copy that is not "Transparent" is called "Opaque".

Examples of suitable formats for Transparent copies include plain ASCII without markup, Texinfo input format, LaTeX input format, SGML or XML using a publicly available DTD, and standard-conforming simple HTML, PostScript or PDF designed for human modification. Examples of transparent image formats include PNG, XCF and JPG. Opaque formats include proprietary formats that can be read and edited only by proprietary word processors, SGML or XML for which the DTD and/or processing tools are not generally available, and the machine-generated HTML, PostScript or PDF produced by some word processors for output purposes only.

The "Title Page" means, for a printed book, the title page itself, plus such following pages as are needed to hold, legibly, the material this License requires to appear in the title page. For works in formats which do not have any title page as such, "Title Page" means the text near the most prominent appearance of the work's title, preceding the beginning of the body of the text.

The "publisher" means any person or entity that distributes copies of the Document to the public.

A section "Entitled XYZ" means a named subunit of the Document whose title either is precisely XYZ or contains XYZ in parentheses following text that translates XYZ in another language. (Here XYZ stands for a specific section name mentioned below, such as "Acknowledgements", "Dedications", "Endorsements", or "History".) To "Preserve the Title" of such a section when you modify the Document means that it remains a section "Entitled XYZ" according to this definition.

The Document may include Warranty Disclaimers next to the notice which states that this License applies to the Document. These Warranty Disclaimers are considered to be included by reference in this License, but only as regards disclaiming warranties: any other implication that these Warranty Disclaimers may have is void and has no effect on the meaning of this License.

2. VERBATIM COPYING

   You may copy and distribute the Document in any medium, either commercially or noncommercially, provided that this License, the copyright notices, and the license notice saying this License applies to the Document are reproduced in all copies, and that you add no other conditions whatsoever to those of this License. You may not use technical measures to obstruct or control the reading or further copying of the copies you make or distribute. However, you may accept compensation in exchange for copies. If you distribute a large enough number of copies you must also follow the conditions in section 3.

   You may also lend copies, under the same conditions stated above, and you may publicly display copies.

3. COPYING IN QUANTITY

   If you publish printed copies (or copies in media that commonly have printed covers) of the Document, numbering more than 100, and the Document's license notice requires Cover Texts, you must enclose the copies in covers that carry, clearly and legibly, all these Cover Texts: Front-Cover Texts on the front cover, and Back-Cover Texts on the back cover. Both covers must also clearly and legibly identify you as the publisher

of these copies. The front cover must present the full title with all words of the title equally prominent and visible. You may add other material on the covers in addition. Copying with changes limited to the covers, as long as they preserve the title of the Document and satisfy these conditions, can be treated as verbatim copying in other respects.

If the required texts for either cover are too voluminous to fit legibly, you should put the first ones listed (as many as fit reasonably) on the actual cover, and continue the rest onto adjacent pages.

If you publish or distribute Opaque copies of the Document numbering more than 100, you must either include a machine-readable Transparent copy along with each Opaque copy, or state in or with each Opaque copy a computer-network location from which the general network-using public has access to download using public-standard network protocols a complete Transparent copy of the Document, free of added material. If you use the latter option, you must take reasonably prudent steps, when you begin distribution of Opaque copies in quantity, to ensure that this Transparent copy will remain thus accessible at the stated location until at least one year after the last time you distribute an Opaque copy (directly or through your agents or retailers) of that edition to the public.

It is requested, but not required, that you contact the authors of the Document well before redistributing any large number of copies, to give them a chance to provide you with an updated version of the Document.

4. MODIFICATIONS

   You may copy and distribute a Modified Version of the Document under the conditions of sections 2 and 3 above, provided that you release the Modified Version under precisely this License, with the Modified Version filling the role of the Document, thus licensing distribution and modification of the Modified Version to whoever possesses a copy of it. In addition, you must do these things in the Modified Version:

   A. Use in the Title Page (and on the covers, if any) a title distinct from that of the Document, and from those of previous versions (which should, if there were any, be listed in the History section of the Document). You may use the same title as a previous version if the original publisher of that version gives permission.

   B. List on the Title Page, as authors, one or more persons or entities responsible for authorship of the modifications in the Modified Version, together with at least five of the principal authors of the Document (all of its principal authors, if it has fewer than five), unless they release you from this requirement.

   C. State on the Title page the name of the publisher of the Modified Version, as the publisher.

   D. Preserve all the copyright notices of the Document.

   E. Add an appropriate copyright notice for your modifications adjacent to the other copyright notices.

   F. Include, immediately after the copyright notices, a license notice giving the public permission to use the Modified Version under the terms of this License, in the form shown in the Addendum below.

   G. Preserve in that license notice the full lists of Invariant Sections and required Cover Texts given in the Document's license notice.

H. Include an unaltered copy of this License.

I. Preserve the section Entitled "History", Preserve its Title, and add to it an item stating at least the title, year, new authors, and publisher of the Modified Version as given on the Title Page. If there is no section Entitled "History" in the Document, create one stating the title, year, authors, and publisher of the Document as given on its Title Page, then add an item describing the Modified Version as stated in the previous sentence.

J. Preserve the network location, if any, given in the Document for public access to a Transparent copy of the Document, and likewise the network locations given in the Document for previous versions it was based on. These may be placed in the "History" section. You may omit a network location for a work that was published at least four years before the Document itself, or if the original publisher of the version it refers to gives permission.

K. For any section Entitled "Acknowledgements" or "Dedications", Preserve the Title of the section, and preserve in the section all the substance and tone of each of the contributor acknowledgements and/or dedications given therein.

L. Preserve all the Invariant Sections of the Document, unaltered in their text and in their titles. Section numbers or the equivalent are not considered part of the section titles.

M. Delete any section Entitled "Endorsements". Such a section may not be included in the Modified Version.

N. Do not retitle any existing section to be Entitled "Endorsements" or to conflict in title with any Invariant Section.

O. Preserve any Warranty Disclaimers.

If the Modified Version includes new front-matter sections or appendices that qualify as Secondary Sections and contain no material copied from the Document, you may at your option designate some or all of these sections as invariant. To do this, add their titles to the list of Invariant Sections in the Modified Version's license notice. These titles must be distinct from any other section titles.

You may add a section Entitled "Endorsements", provided it contains nothing but endorsements of your Modified Version by various parties—for example, statements of peer review or that the text has been approved by an organization as the authoritative definition of a standard.

You may add a passage of up to five words as a Front-Cover Text, and a passage of up to 25 words as a Back-Cover Text, to the end of the list of Cover Texts in the Modified Version. Only one passage of Front-Cover Text and one of Back-Cover Text may be added by (or through arrangements made by) any one entity. If the Document already includes a cover text for the same cover, previously added by you or by arrangement made by the same entity you are acting on behalf of, you may not add another; but you may replace the old one, on explicit permission from the previous publisher that added the old one.

The author(s) and publisher(s) of the Document do not by this License give permission to use their names for publicity for or to assert or imply endorsement of any Modified Version.

5. COMBINING DOCUMENTS

   You may combine the Document with other documents released under this License, under the terms defined in section 4 above for modified versions, provided that you include in the combination all of the Invariant Sections of all of the original documents, unmodified, and list them all as Invariant Sections of your combined work in its license notice, and that you preserve all their Warranty Disclaimers.

   The combined work need only contain one copy of this License, and multiple identical Invariant Sections may be replaced with a single copy. If there are multiple Invariant Sections with the same name but different contents, make the title of each such section unique by adding at the end of it, in parentheses, the name of the original author or publisher of that section if known, or else a unique number. Make the same adjustment to the section titles in the list of Invariant Sections in the license notice of the combined work.

   In the combination, you must combine any sections Entitled "History" in the various original documents, forming one section Entitled "History"; likewise combine any sections Entitled "Acknowledgements", and any sections Entitled "Dedications". You must delete all sections Entitled "Endorsements."

6. COLLECTIONS OF DOCUMENTS

   You may make a collection consisting of the Document and other documents released under this License, and replace the individual copies of this License in the various documents with a single copy that is included in the collection, provided that you follow the rules of this License for verbatim copying of each of the documents in all other respects.

   You may extract a single document from such a collection, and distribute it individually under this License, provided you insert a copy of this License into the extracted document, and follow this License in all other respects regarding verbatim copying of that document.

7. AGGREGATION WITH INDEPENDENT WORKS

   A compilation of the Document or its derivatives with other separate and independent documents or works, in or on a volume of a storage or distribution medium, is called an "aggregate" if the copyright resulting from the compilation is not used to limit the legal rights of the compilation's users beyond what the individual works permit. When the Document is included in an aggregate, this License does not apply to the other works in the aggregate which are not themselves derivative works of the Document.

   If the Cover Text requirement of section 3 is applicable to these copies of the Document, then if the Document is less than one half of the entire aggregate, the Document's Cover Texts may be placed on covers that bracket the Document within the aggregate, or the electronic equivalent of covers if the Document is in electronic form. Otherwise they must appear on printed covers that bracket the whole aggregate.

8. TRANSLATION

   Translation is considered a kind of modification, so you may distribute translations of the Document under the terms of section 4. Replacing Invariant Sections with translations requires special permission from their copyright holders, but you may include translations of some or all Invariant Sections in addition to the original versions of these Invariant Sections. You may include a translation of this License, and all the

license notices in the Document, and any Warranty Disclaimers, provided that you also include the original English version of this License and the original versions of those notices and disclaimers. In case of a disagreement between the translation and the original version of this License or a notice or disclaimer, the original version will prevail.

If a section in the Document is Entitled "Acknowledgements", "Dedications", or "History", the requirement (section 4) to Preserve its Title (section 1) will typically require changing the actual title.

9. TERMINATION

   You may not copy, modify, sublicense, or distribute the Document except as expressly provided under this License. Any attempt otherwise to copy, modify, sublicense, or distribute it is void, and will automatically terminate your rights under this License.

   However, if you cease all violation of this License, then your license from a particular copyright holder is reinstated (a) provisionally, unless and until the copyright holder explicitly and finally terminates your license, and (b) permanently, if the copyright holder fails to notify you of the violation by some reasonable means prior to 60 days after the cessation.

   Moreover, your license from a particular copyright holder is reinstated permanently if the copyright holder notifies you of the violation by some reasonable means, this is the first time you have received notice of violation of this License (for any work) from that copyright holder, and you cure the violation prior to 30 days after your receipt of the notice.

   Termination of your rights under this section does not terminate the licenses of parties who have received copies or rights from you under this License. If your rights have been terminated and not permanently reinstated, receipt of a copy of some or all of the same material does not give you any rights to use it.

10. FUTURE REVISIONS OF THIS LICENSE

    The Free Software Foundation may publish new, revised versions of the GNU Free Documentation License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns. See `http://www.gnu.org/copyleft/`.

    Each version of the License is given a distinguishing version number. If the Document specifies that a particular numbered version of this License "or any later version" applies to it, you have the option of following the terms and conditions either of that specified version or of any later version that has been published (not as a draft) by the Free Software Foundation. If the Document does not specify a version number of this License, you may choose any version ever published (not as a draft) by the Free Software Foundation. If the Document specifies that a proxy can decide which future versions of this License can be used, that proxy's public statement of acceptance of a version permanently authorizes you to choose that version for the Document.

11. RELICENSING

    "Massive Multiauthor Collaboration Site" (or "MMC Site") means any World Wide Web server that publishes copyrightable works and also provides prominent facilities for anybody to edit those works. A public wiki that anybody can edit is an example of

such a server. A "Massive Multiauthor Collaboration" (or "MMC") contained in the site means any set of copyrightable works thus published on the MMC site.

"CC-BY-SA" means the Creative Commons Attribution-Share Alike 3.0 license published by Creative Commons Corporation, a not-for-profit corporation with a principal place of business in San Francisco, California, as well as future copyleft versions of that license published by that same organization.

"Incorporate" means to publish or republish a Document, in whole or in part, as part of another Document.

An MMC is "eligible for relicensing" if it is licensed under this License, and if all works that were first published under this License somewhere other than this MMC, and subsequently incorporated in whole or in part into the MMC, (1) had no cover texts or invariant sections, and (2) were thus incorporated prior to November 1, 2008.

The operator of an MMC Site may republish an MMC contained in the site under CC-BY-SA on the same site at any time before August 1, 2009, provided the MMC is eligible for relicensing.

ADDENDUM: How to use this License for your documents

To use this License in a document you have written, include a copy of the License in the document and put the following copyright and license notices just after the title page:

```
Copyright (C)  year  your name.
Permission is granted to copy, distribute and/or modify this document
under the terms of the GNU Free Documentation License, Version 1.3
or any later version published by the Free Software Foundation;
with no Invariant Sections, no Front-Cover Texts, and no Back-Cover
Texts.  A copy of the license is included in the section entitled ``GNU
Free Documentation License''.
```

If you have Invariant Sections, Front-Cover Texts and Back-Cover Texts, replace the "with. . . Texts." line with this:

```
with the Invariant Sections being list their titles, with
the Front-Cover Texts being list, and with the Back-Cover Texts
being list.
```

If you have Invariant Sections without Cover Texts, or some other combination of the three, merge those two alternatives to suit the situation.

If your document contains nontrivial examples of program code, we recommend releasing these examples in parallel under your choice of free software license, such as the GNU General Public License, to permit their use in free software.

BFD Index

*

*_bfd_generic_make_empty_symbol 47
*_bfd_new_bfd 169
*_bfd_new_bfd_contained_in 169
*bfd_alloc 176
*bfd_arch_default_fill 169
*bfd_asprintf 14
*bfd_create 172
*bfd_default_reloc_type_lookup 139
*bfd_demangle 22
*bfd_elf_bfd_from_remote_memory 172
*bfd_fdopenr 170
*bfd_fdopenw 170
*bfd_follow_build_id_debuglink 175
*bfd_follow_gnu_debugaltlink 174
*bfd_follow_gnu_debuglink 174
*bfd_fopen 169
*bfd_generic_get_relocated_section_contents 140
*bfd_get_alt_debug_link_info 173
*bfd_get_debug_link_info 173
*bfd_get_linker_section 36
*bfd_get_next_section_by_name 36
*bfd_get_relocated_section_contents 22
*bfd_get_section_by_name 36
*bfd_get_section_by_name_if 36
*bfd_get_unique_section_name 37
*bfd_group_signature 22
*bfd_hash_allocate 193
*bfd_make_section 38
*bfd_make_section_anyway 37
*bfd_make_section_anyway_with_flags 37
*bfd_make_section_old_way 37
*bfd_make_section_with_flags 38
*bfd_malloc 175
*bfd_mmap 25
*bfd_openr 170
*bfd_openr_iovec 171
*bfd_openr_next_archived_file 49
*bfd_openstreamr 171
*bfd_openw 171
*bfd_realloc 175
*bfd_realloc_or_free 176
*bfd_reloc_type_lookup 139
*bfd_sections_find_if 39
*bfd_zalloc 176
*bfd_zmalloc 176

_

_bfd_error_handler 14
_bfd_final_link_relocate 185
_bfd_free_cached_info 169
_bfd_generic_link_add_archive_symbols 184
_bfd_generic_link_add_one_symbol 183, 186
_bfd_generic_link_check_relocs 188
_bfd_generic_link_hide_symbol 187
_bfd_generic_make_empty_symbol 47
_bfd_generic_set_reloc 140
_bfd_generic_verify_endian_match 189
_bfd_get_error_program_name 15
_bfd_link_add_symbols in target vector 182
_bfd_link_final_link in target vector 184
_bfd_link_hash_table_create in target vector ... 182
_bfd_new_bfd 169
_bfd_new_bfd_contained_in 169
_bfd_relocate_contents 185
_bfd_restore_error_handler_caching 15
_bfd_set_error_handler_caching 14
_bfd_stringtab_add 193, 194
_bfd_stringtab_emit 194
_bfd_stringtab_free 193
_bfd_stringtab_init 193
_bfd_stringtab_size 194
_bfd_threading_enabled 16
_bfd_unrecognized_reloc 140
_bfd_xcoff_stringtab_init 193

A

aout_*size*_machine_type 197
aout_*size*_mkobject 196
aout_*size*_mkobject, ... 197
aout_*size*_new_section_hook 197
aout_*size*_new_section_hook, ... 197
aout_*size*_set_arch_mach 197
aout_*size*_set_arch_mach, ... 197
aout_*size*_some_aout_object_p 196
aout_*size*_swap_exec_header_in 196
aout_*size*_swap_exec_header_in, ... 196
aout_*size*_swap_exec_header_out 196
arelent_chain 56

B

bfd_alloc 176
bfd_alt_mach_code 22
bfd_arch_bits_per_address 168
bfd_arch_bits_per_byte 168
bfd_arch_default_fill 169
bfd_arch_get_compatible 167
bfd_arch_info_type 167, 168
bfd_arch_list 167

bfd_arch_mach_octets_per_byte 169
bfd_architecture 168
bfd_asprintf 14
bfd_cache_close 181
bfd_cache_close_all 181
bfd_cache_init 181
bfd_cache_set_uncloseable 181
bfd_cache_size 181
bfd_calc_gnu_debuglink_crc32 173
bfd_canonicalize_reloc 17
bfd_canonicalize_symtab 46
bfd_check_format 50
bfd_check_format_lto 50
bfd_check_format_matches 51
bfd_check_format_matches_lto 50
bfd_check_overflow 57
bfd_close 172
bfd_close_all_done 172
bfd_coff_backend_data 202
bfd_copy_private_bfd_data 19
bfd_copy_private_header_data 19
bfd_copy_private_section_data 40
bfd_copy_private_symbol_data 48
bfd_core_file_failing_command 140
bfd_core_file_failing_signal 141
bfd_core_file_pid 141
bfd_create 172
bfd_create_gnu_debuglink_section 174
bfd_decode_symclass 47
bfd_default_arch_struct 167
bfd_default_compatible 168
bfd_default_reloc_type_lookup 139
bfd_default_scan 168
bfd_default_set_arch_mach 167
bfd_demangle 22
bfd_elf_bfd_from_remote_memory 171
bfd_elf_version_tree 188
bfd_emul_get_commonpagesize 22
bfd_emul_get_maxpagesize 22
bfd_errmsg 13
bfd_extract_object_only_section 175
bfd_fdopenr 170
bfd_fdopenw 170
bfd_fill_in_gnu_debuglink_section 174
bfd_find_target 153
bfd_find_version_for_sym 188
bfd_flavour_name 154
bfd_flush 24
bfd_follow_build_id_debuglink 174
bfd_follow_gnu_debugaltlink 174
bfd_follow_gnu_debuglink 173
bfd_fopen 169
bfd_format_string 51
bfd_generic_define_common_symbol 187
bfd_generic_define_start_stop 187
bfd_generic_discard_group 40
bfd_generic_gc_sections 139, 140
bfd_generic_get_relocated_section_contents 140
bfd_generic_group_name 40
bfd_generic_is_group_section 40
bfd_generic_lookup_section_flags 140
bfd_generic_merge_sections 140
bfd_generic_relax_section 139
bfd_get_alt_debug_link_info 173
bfd_get_arch 167
bfd_get_arch_info 168
bfd_get_arch_size 17, 18
bfd_get_current_time 25
bfd_get_debug_link_info 173
bfd_get_error 13
bfd_get_file_size 25
bfd_get_gp_size 18
bfd_get_linker_section 36
bfd_get_mach 168
bfd_get_mtime 24
bfd_get_next_mapent 49
bfd_get_next_section_by_name 36
bfd_get_reloc_code_name 139
bfd_get_reloc_upper_bound 17
bfd_get_relocated_section_contents 21
bfd_get_section_by_name 36
bfd_get_section_by_name_if 36
bfd_get_section_contents 39
bfd_get_sign_extend_vma 18
bfd_get_size 24, 177
bfd_get_symtab_upper_bound 46
bfd_get_target_info 153
bfd_get_unique_section_name 36
bfd_getb64 180
bfd_group_signature 22
bfd_h_put_size 178
bfd_hash_allocate 189, 193
bfd_hash_entry 192, 193
bfd_hash_insert 192
bfd_hash_lookup 189, 192
bfd_hash_newfunc 189, 193
bfd_hash_rename 192, 193
bfd_hash_replace 193
bfd_hash_set_default_size 189, 193
bfd_hash_table_free 189, 192
bfd_hash_table_init 189, 192
bfd_hash_table_init_n 189, 192
bfd_hash_traverse 190, 193
bfd_hide_sym_by_version 188
bfd_init 15
bfd_install_relocation 57, 58
bfd_is_local_label 46
bfd_is_local_label_name 46
bfd_is_target_special_symbol 46
bfd_is_undefined_symclass 47, 48
bfd_iterate_over_targets 154
bfd_link_align_section 186
bfd_link_check_relocs 188
bfd_link_hash_entry 188
bfd_link_split_section 187
bfd_lock 16

bfd_log2 180
bfd_lookup_arch 168
bfd_make_debug_symbol 47
bfd_make_empty_symbol 47
bfd_make_readable 173
bfd_make_section 38
bfd_make_section_anyway 37
bfd_make_section_anyway_with_flags 37
bfd_make_section_old_way 37
bfd_make_section_with_flags 37
bfd_make_writable 172, 173
bfd_malloc 175
bfd_malloc_and_get_section 39, 40
bfd_map_over_sections 38
bfd_merge_private_bfd_data 188
bfd_mmap 25
bfd_octets_per_byte 168
bfd_open_file 181
bfd_openr 170
bfd_openr_iovec 171
bfd_openr_next_archived_file 49
bfd_openstreamr 170
bfd_openw 171
bfd_perform_relocation 57
bfd_perror 13
bfd_print_error 14
bfd_print_symbol_vandf 47
bfd_printable_arch_mach 168
bfd_printable_name 166
bfd_put_size 177
bfd_read 23
bfd_realloc 175
bfd_realloc_or_free 176
bfd_record_phdr 22
bfd_release 176
bfd_reloc_code_real_type 58
bfd_reloc_offset_in_range 57
bfd_reloc_type_lookup 139
bfd_rename_section 38
bfd_scan_arch 167
bfd_scan_vma 18
bfd_section 174
bfd_section_already_linked 187
bfd_section_list_clear 36
bfd_section_size_insane 40
bfd_sections_find_if 38
bfd_seek 24
bfd_set_arch_info 167
bfd_set_archive_head 49
bfd_set_assert_handler 15
bfd_set_default_target 153
bfd_set_error 13
bfd_set_error_handler 14
bfd_set_error_program_name 15
bfd_set_file_flags 17
bfd_set_filename 175
bfd_set_format 51
bfd_set_gp_size 18
bfd_set_gp_value 18
bfd_set_input_error 13
bfd_set_private_flags 19
bfd_set_reloc 17
bfd_set_section_contents 39
bfd_set_section_flags 38
bfd_set_section_size 39
bfd_set_start_address 18
bfd_set_symtab 47
bfd_sprintf_vma 22
bfd_stat 24
bfd_strtab_hash 193
bfd_symbol_info 48
bfd_target 153, 154
bfd_target_list 154
bfd_tell 24
bfd_thread_cleanup 16
bfd_thread_init 16
bfd_unlock 16, 17
bfd_write 23, 24
bfd_write_bigendian_4byte_int 176, 177
bfd_zalloc 176
bfd_zmalloc 176
BFD 1
BFD canonical format 3
BFD_ARELOC_BFIN_ADD 83
BFD_ARELOC_BFIN_ADDR 84
BFD_ARELOC_BFIN_AND 84
BFD_ARELOC_BFIN_COMP 84
BFD_ARELOC_BFIN_CONST 83
BFD_ARELOC_BFIN_DIV 84
BFD_ARELOC_BFIN_HWPAGE 84
BFD_ARELOC_BFIN_LAND 84
BFD_ARELOC_BFIN_LEN 84
BFD_ARELOC_BFIN_LOR 84
BFD_ARELOC_BFIN_LSHIFT 84
BFD_ARELOC_BFIN_MOD 84
BFD_ARELOC_BFIN_MULT 84
BFD_ARELOC_BFIN_NEG 84
BFD_ARELOC_BFIN_OR 84
BFD_ARELOC_BFIN_PAGE 84
BFD_ARELOC_BFIN_PUSH 83
BFD_ARELOC_BFIN_RSHIFT 84
BFD_ARELOC_BFIN_SUB 84
BFD_ARELOC_BFIN_XOR 84
BFD_RELOC_12_PCREL 58
BFD_RELOC_14 58
BFD_RELOC_16 58
BFD_RELOC_16_BASEREL 59
BFD_RELOC_16_GOT_PCREL 58
BFD_RELOC_16_GOTOFF 59
BFD_RELOC_16_PCREL 58
BFD_RELOC_16_PCREL_S2 60
BFD_RELOC_16_PLT_PCREL 59
BFD_RELOC_16_PLTOFF 59
BFD_RELOC_16_SECIDX 58
BFD_RELOC_23_PCREL_S2 60
BFD_RELOC_24 58

BFD_RELOC_24_PCREL ... 58
BFD_RELOC_24_PLT_PCREL ... 59
BFD_RELOC_26 ... 58
BFD_RELOC_32 ... 58
BFD_RELOC_32_BASEREL ... 59
BFD_RELOC_32_GOT_PCREL ... 58
BFD_RELOC_32_GOTOFF ... 58
BFD_RELOC_32_PCREL ... 58
BFD_RELOC_32_PCREL_S2 ... 60
BFD_RELOC_32_PLT_PCREL ... 59
BFD_RELOC_32_PLTOFF ... 59
BFD_RELOC_32_SECREL ... 58
BFD_RELOC_386_COPY ... 69
BFD_RELOC_386_GLOB_DAT ... 69
BFD_RELOC_386_GOT32 ... 69
BFD_RELOC_386_GOT32X ... 70
BFD_RELOC_386_GOTOFF ... 69
BFD_RELOC_386_GOTPC ... 69
BFD_RELOC_386_IRELATIVE ... 70
BFD_RELOC_386_JUMP_SLOT ... 69
BFD_RELOC_386_PLT32 ... 69
BFD_RELOC_386_RELATIVE ... 69
BFD_RELOC_386_TLS_DESC ... 70
BFD_RELOC_386_TLS_DESC_CALL ... 70
BFD_RELOC_386_TLS_DTPMOD32 ... 69
BFD_RELOC_386_TLS_DTPOFF32 ... 69
BFD_RELOC_386_TLS_GD ... 69
BFD_RELOC_386_TLS_GOTDESC ... 70
BFD_RELOC_386_TLS_GOTIE ... 69
BFD_RELOC_386_TLS_IE ... 69
BFD_RELOC_386_TLS_IE_32 ... 69
BFD_RELOC_386_TLS_LDM ... 69
BFD_RELOC_386_TLS_LDO_32 ... 69
BFD_RELOC_386_TLS_LE ... 69
BFD_RELOC_386_TLS_LE_32 ... 69
BFD_RELOC_386_TLS_TPOFF ... 69
BFD_RELOC_386_TLS_TPOFF32 ... 70
BFD_RELOC_390_12 ... 102
BFD_RELOC_390_20 ... 104
BFD_RELOC_390_COPY ... 102
BFD_RELOC_390_GLOB_DAT ... 102
BFD_RELOC_390_GOT12 ... 102
BFD_RELOC_390_GOT16 ... 102
BFD_RELOC_390_GOT20 ... 104
BFD_RELOC_390_GOT64 ... 103
BFD_RELOC_390_GOTENT ... 103
BFD_RELOC_390_GOTOFF64 ... 103
BFD_RELOC_390_GOTPC ... 102
BFD_RELOC_390_GOTPCDBL ... 103
BFD_RELOC_390_GOTPLT12 ... 103
BFD_RELOC_390_GOTPLT16 ... 103
BFD_RELOC_390_GOTPLT20 ... 104
BFD_RELOC_390_GOTPLT32 ... 103
BFD_RELOC_390_GOTPLT64 ... 103
BFD_RELOC_390_GOTPLTENT ... 103
BFD_RELOC_390_IRELATIVE ... 104
BFD_RELOC_390_JMP_SLOT ... 102
BFD_RELOC_390_PC12DBL ... 102
BFD_RELOC_390_PC16DBL ... 102
BFD_RELOC_390_PC24DBL ... 102
BFD_RELOC_390_PC32DBL ... 103
BFD_RELOC_390_PLT12DBL ... 102
BFD_RELOC_390_PLT16DBL ... 102
BFD_RELOC_390_PLT24DBL ... 103
BFD_RELOC_390_PLT32 ... 102
BFD_RELOC_390_PLT32DBL ... 103
BFD_RELOC_390_PLT64 ... 103
BFD_RELOC_390_PLTOFF16 ... 103
BFD_RELOC_390_PLTOFF32 ... 103
BFD_RELOC_390_PLTOFF64 ... 103
BFD_RELOC_390_RELATIVE ... 102
BFD_RELOC_390_TLS_DTPMOD ... 104
BFD_RELOC_390_TLS_DTPOFF ... 104
BFD_RELOC_390_TLS_GD32 ... 103
BFD_RELOC_390_TLS_GD64 ... 103
BFD_RELOC_390_TLS_GDCALL ... 103
BFD_RELOC_390_TLS_GOTIE12 ... 104
BFD_RELOC_390_TLS_GOTIE20 ... 104
BFD_RELOC_390_TLS_GOTIE32 ... 104
BFD_RELOC_390_TLS_GOTIE64 ... 104
BFD_RELOC_390_TLS_IE32 ... 104
BFD_RELOC_390_TLS_IE64 ... 104
BFD_RELOC_390_TLS_IEENT ... 104
BFD_RELOC_390_TLS_LDCALL ... 103
BFD_RELOC_390_TLS_LDM32 ... 104
BFD_RELOC_390_TLS_LDM64 ... 104
BFD_RELOC_390_TLS_LDO32 ... 104
BFD_RELOC_390_TLS_LDO64 ... 104
BFD_RELOC_390_TLS_LE32 ... 104
BFD_RELOC_390_TLS_LE64 ... 104
BFD_RELOC_390_TLS_LOAD ... 103
BFD_RELOC_390_TLS_TPOFF ... 104
BFD_RELOC_64 ... 58
BFD_RELOC_64_PCREL ... 58
BFD_RELOC_64_PLT_PCREL ... 59
BFD_RELOC_64_PLTOFF ... 59
BFD_RELOC_68K_GLOB_DAT ... 59
BFD_RELOC_68K_JMP_SLOT ... 59
BFD_RELOC_68K_RELATIVE ... 59
BFD_RELOC_68K_TLS_GD16 ... 59
BFD_RELOC_68K_TLS_GD32 ... 59
BFD_RELOC_68K_TLS_GD8 ... 59
BFD_RELOC_68K_TLS_IE16 ... 59
BFD_RELOC_68K_TLS_IE32 ... 59
BFD_RELOC_68K_TLS_IE8 ... 59
BFD_RELOC_68K_TLS_LDM16 ... 59
BFD_RELOC_68K_TLS_LDM32 ... 59
BFD_RELOC_68K_TLS_LDM8 ... 59
BFD_RELOC_68K_TLS_LDO16 ... 59
BFD_RELOC_68K_TLS_LDO32 ... 59
BFD_RELOC_68K_TLS_LDO8 ... 59
BFD_RELOC_68K_TLS_LE16 ... 59
BFD_RELOC_68K_TLS_LE32 ... 59
BFD_RELOC_68K_TLS_LE8 ... 59
BFD_RELOC_8 ... 58
BFD_RELOC_8_BASEREL ... 60

BFD_RELOC_8_FFnn ... 60
BFD_RELOC_8_GOT_PCREL ... 58
BFD_RELOC_8_GOTOFF ... 59
BFD_RELOC_8_PCREL ... 58
BFD_RELOC_8_PLT_PCREL ... 59
BFD_RELOC_8_PLTOFF ... 59
BFD_RELOC_AARCH64_16 ... 122
BFD_RELOC_AARCH64_16_PCREL ... 122
BFD_RELOC_AARCH64_32 ... 122
BFD_RELOC_AARCH64_32_PCREL ... 122
BFD_RELOC_AARCH64_64 ... 122
BFD_RELOC_AARCH64_64_PCREL ... 122
BFD_RELOC_AARCH64_ADD_LO12 ... 124
BFD_RELOC_AARCH64_ADR_GOT_PAGE ... 125
BFD_RELOC_AARCH64_ADR_HI21_NC_PCREL ... 124
BFD_RELOC_AARCH64_ADR_HI21_PCREL ... 124
BFD_RELOC_AARCH64_ADR_LO21_PCREL ... 124
BFD_RELOC_AARCH64_BRANCH19 ... 124
BFD_RELOC_AARCH64_BRANCH9 ... 130
BFD_RELOC_AARCH64_CALL26 ... 125
BFD_RELOC_AARCH64_COPY ... 129
BFD_RELOC_AARCH64_GAS_INTERNAL_FIXUP ... 129
BFD_RELOC_AARCH64_GLOB_DAT ... 129
BFD_RELOC_AARCH64_GOT_LD_PREL19 ... 125
BFD_RELOC_AARCH64_IRELATIVE ... 129
BFD_RELOC_AARCH64_JUMP_SLOT ... 129
BFD_RELOC_AARCH64_JUMP26 ... 124
BFD_RELOC_AARCH64_LD_GOT_LO12_NC ... 130
BFD_RELOC_AARCH64_LD_LO19_PCREL ... 124
BFD_RELOC_AARCH64_LD32_GOT_LO12_NC ... 125
BFD_RELOC_AARCH64_LD32_GOTPAGE_LO14 ... 126
BFD_RELOC_AARCH64_LD64_GOT_LO12_NC ... 125
BFD_RELOC_AARCH64_LD64_GOTOFF_LO15 ... 125
BFD_RELOC_AARCH64_LD64_GOTPAGE_LO15 ... 126
BFD_RELOC_AARCH64_LDST_LO12 ... 129
BFD_RELOC_AARCH64_LDST128_LO12 ... 125
BFD_RELOC_AARCH64_LDST16_LO12 ... 125
BFD_RELOC_AARCH64_LDST32_LO12 ... 125
BFD_RELOC_AARCH64_LDST64_LO12 ... 125
BFD_RELOC_AARCH64_LDST8_LO12 ... 124
BFD_RELOC_AARCH64_MOVW_G0 ... 123
BFD_RELOC_AARCH64_MOVW_G0_NC ... 123
BFD_RELOC_AARCH64_MOVW_G0_S ... 123
BFD_RELOC_AARCH64_MOVW_G1 ... 123
BFD_RELOC_AARCH64_MOVW_G1_NC ... 123
BFD_RELOC_AARCH64_MOVW_G1_S ... 123
BFD_RELOC_AARCH64_MOVW_G2 ... 123
BFD_RELOC_AARCH64_MOVW_G2_NC ... 123
BFD_RELOC_AARCH64_MOVW_G2_S ... 123
BFD_RELOC_AARCH64_MOVW_G3 ... 123
BFD_RELOC_AARCH64_MOVW_GOTOFF_G0_NC ... 125
BFD_RELOC_AARCH64_MOVW_GOTOFF_G1 ... 125
BFD_RELOC_AARCH64_MOVW_PREL_G0 ... 123
BFD_RELOC_AARCH64_MOVW_PREL_G0_NC ... 123
BFD_RELOC_AARCH64_MOVW_PREL_G1 ... 124
BFD_RELOC_AARCH64_MOVW_PREL_G1_NC ... 124
BFD_RELOC_AARCH64_MOVW_PREL_G2 ... 124
BFD_RELOC_AARCH64_MOVW_PREL_G2_NC ... 124
BFD_RELOC_AARCH64_MOVW_PREL_G3 ... 124
BFD_RELOC_AARCH64_NONE ... 122
BFD_RELOC_AARCH64_NULL ... 122
BFD_RELOC_AARCH64_RELATIVE ... 129
BFD_RELOC_AARCH64_RELOC_END ... 129
BFD_RELOC_AARCH64_RELOC_START ... 122
BFD_RELOC_AARCH64_TLS_DTPMOD ... 129
BFD_RELOC_AARCH64_TLS_DTPREL ... 129
BFD_RELOC_AARCH64_TLS_TPREL ... 129
BFD_RELOC_AARCH64_TLSDESC ... 129
BFD_RELOC_AARCH64_TLSDESC_ADD ... 129
BFD_RELOC_AARCH64_TLSDESC_ADD_LO12 ... 129
BFD_RELOC_AARCH64_TLSDESC_ADR_PAGE21 ... 129
BFD_RELOC_AARCH64_TLSDESC_ADR_PREL21 ... 129
BFD_RELOC_AARCH64_TLSDESC_CALL ... 129
BFD_RELOC_AARCH64_TLSDESC_LD_LO12_NC ... 130
BFD_RELOC_AARCH64_TLSDESC_LD_PREL19 ... 129
BFD_RELOC_AARCH64_TLSDESC_LD32_LO12_NC ... 129
BFD_RELOC_AARCH64_TLSDESC_LD64_LO12 ... 129
BFD_RELOC_AARCH64_TLSDESC_LDR ... 129
BFD_RELOC_AARCH64_TLSDESC_OFF_G0_NC ... 129
BFD_RELOC_AARCH64_TLSDESC_OFF_G1 ... 129
BFD_RELOC_AARCH64_TLSGD_ADD_LO12_NC ... 126
BFD_RELOC_AARCH64_TLSGD_ADR_PAGE21 ... 126
BFD_RELOC_AARCH64_TLSGD_ADR_PREL21 ... 126
BFD_RELOC_AARCH64_TLSGD_MOVW_G0_NC ... 126
BFD_RELOC_AARCH64_TLSGD_MOVW_G1 ... 126
BFD_RELOC_AARCH64_TLSIE_ADR_GOTTPREL_PAGE21 ... 126
BFD_RELOC_AARCH64_TLSIE_LD_GOTTPREL_LO12_NC ... 130
BFD_RELOC_AARCH64_TLSIE_LD_GOTTPREL_PREL19 ... 126
BFD_RELOC_AARCH64_TLSIE_LD32_GOTTPREL_LO12_NC ... 126
BFD_RELOC_AARCH64_TLSIE_LD64_GOTTPREL_LO12_NC ... 126
BFD_RELOC_AARCH64_TLSIE_MOVW_GOTTPREL_G0_NC ... 126
BFD_RELOC_AARCH64_TLSIE_MOVW_GOTTPREL_G1 ... 126
BFD_RELOC_AARCH64_TLSLD_ADD_DTPREL_HI12 ... 126
BFD_RELOC_AARCH64_TLSLD_ADD_DTPREL_LO12 ... 126
BFD_RELOC_AARCH64_TLSLD_ADD_DTPREL_LO12_NC ... 126
BFD_RELOC_AARCH64_TLSLD_ADD_LO12_NC ... 127
BFD_RELOC_AARCH64_TLSLD_ADR_PAGE21 ... 127
BFD_RELOC_AARCH64_TLSLD_ADR_PREL21 ... 127
BFD_RELOC_AARCH64_TLSLD_LDST_DTPREL_LO12 ... 129
BFD_RELOC_AARCH64_TLSLD_LDST_DTPREL_LO12_NC ... 130
BFD_RELOC_AARCH64_TLSLD_LDST16_DTPREL_LO12 ... 127
BFD_RELOC_AARCH64_TLSLD_LDST16_DTPREL_LO12_NC ... 127
BFD_RELOC_AARCH64_TLSLD_LDST32_DTPREL_LO12 ... 127
BFD_RELOC_AARCH64_TLSLD_LDST32_DTPREL_LO12_NC ... 127

BFD_RELOC_AARCH64_TLSLD_LDST64_DTPREL_LO12 . . . 127
BFD_RELOC_AARCH64_TLSLD_LDST64_DTPREL_LO12_NC . . . 127
BFD_RELOC_AARCH64_TLSLD_LDST8_DTPREL_LO12 . . . 127
BFD_RELOC_AARCH64_TLSLD_LDST8_DTPREL_LO12_NC . . . 127
BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G0 . . . 127
BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G0_NC . . . 127
BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G1 . . . 127
BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G1_NC . . . 127
BFD_RELOC_AARCH64_TLSLD_MOVW_DTPREL_G2 . . . 128
BFD_RELOC_AARCH64_TLSLE_ADD_TPREL_HI12 . . . 128
BFD_RELOC_AARCH64_TLSLE_ADD_TPREL_LO12 . . . 128
BFD_RELOC_AARCH64_TLSLE_ADD_TPREL_LO12_NC . . . 128
BFD_RELOC_AARCH64_TLSLE_LDST_TPREL_LO12 . 130
BFD_RELOC_AARCH64_TLSLE_LDST_TPREL_LO12_NC . . . 130
BFD_RELOC_AARCH64_TLSLE_LDST16_TPREL_LO12 . . . 128
BFD_RELOC_AARCH64_TLSLE_LDST16_TPREL_LO12_NC . . . 128
BFD_RELOC_AARCH64_TLSLE_LDST32_TPREL_LO12 . . . 128
BFD_RELOC_AARCH64_TLSLE_LDST32_TPREL_LO12_NC . . . 128
BFD_RELOC_AARCH64_TLSLE_LDST64_TPREL_LO12 . . . 128
BFD_RELOC_AARCH64_TLSLE_LDST64_TPREL_LO12_NC . . . 128
BFD_RELOC_AARCH64_TLSLE_LDST8_TPREL_LO12 . 128
BFD_RELOC_AARCH64_TLSLE_LDST8_TPREL_LO12_NC . . . 129
BFD_RELOC_AARCH64_TLSLE_MOVW_TPREL_G0 128
BFD_RELOC_AARCH64_TLSLE_MOVW_TPREL_G0_NC . 128
BFD_RELOC_AARCH64_TLSLE_MOVW_TPREL_G1 128
BFD_RELOC_AARCH64_TLSLE_MOVW_TPREL_G1_NC . 128
BFD_RELOC_AARCH64_TLSLE_MOVW_TPREL_G2 128
BFD_RELOC_AARCH64_TSTBR14 . . . 124
BFD_RELOC_AC_SECTOFF_S9 . . . 81
BFD_RELOC_AC_SECTOFF_S9_1 . . . 82
BFD_RELOC_AC_SECTOFF_S9_2 . . . 82
BFD_RELOC_AC_SECTOFF_U8 . . . 81
BFD_RELOC_AC_SECTOFF_U8_1 . . . 81
BFD_RELOC_AC_SECTOFF_U8_2 . . . 81
BFD_RELOC_ALPHA_BOH . . . 64
BFD_RELOC_ALPHA_BRSGP . . . 63
BFD_RELOC_ALPHA_BSR . . . 64
BFD_RELOC_ALPHA_CODEADDR . . . 63
BFD_RELOC_ALPHA_DTPMOD64 . . . 64
BFD_RELOC_ALPHA_DTPREL_HI16 . . . 64
BFD_RELOC_ALPHA_DTPREL_LO16 . . . 64
BFD_RELOC_ALPHA_DTPREL16 . . . 64
BFD_RELOC_ALPHA_DTPREL64 . . . 64
BFD_RELOC_ALPHA_ELF_LITERAL . . . 63
BFD_RELOC_ALPHA_GOTDTPREL16 . . . 64
BFD_RELOC_ALPHA_GOTTPREL16 . . . 64
BFD_RELOC_ALPHA_GPDISP . . . 63
BFD_RELOC_ALPHA_GPDISP_HI16 . . . 62
BFD_RELOC_ALPHA_GPDISP_LO16 . . . 63
BFD_RELOC_ALPHA_GPREL_HI16 . . . 63
BFD_RELOC_ALPHA_GPREL_LO16 . . . 63
BFD_RELOC_ALPHA_HINT . . . 63
BFD_RELOC_ALPHA_LDA . . . 64
BFD_RELOC_ALPHA_LINKAGE . . . 63
BFD_RELOC_ALPHA_LITERAL . . . 63
BFD_RELOC_ALPHA_LITUSE . . . 63
BFD_RELOC_ALPHA_NOP . . . 64
BFD_RELOC_ALPHA_TLSGD . . . 64
BFD_RELOC_ALPHA_TLSLDM . . . 64
BFD_RELOC_ALPHA_TPREL_HI16 . . . 64
BFD_RELOC_ALPHA_TPREL_LO16 . . . 64
BFD_RELOC_ALPHA_TPREL16 . . . 64
BFD_RELOC_ALPHA_TPREL64 . . . 64
BFD_RELOC_ARC_16 . . . 81
BFD_RELOC_ARC_24 . . . 81
BFD_RELOC_ARC_32 . . . 81
BFD_RELOC_ARC_32_ME . . . 81
BFD_RELOC_ARC_32_ME_S . . . 81
BFD_RELOC_ARC_32_PCREL . . . 82
BFD_RELOC_ARC_8 . . . 81
BFD_RELOC_ARC_COPY . . . 82
BFD_RELOC_ARC_GLOB_DAT . . . 82
BFD_RELOC_ARC_GOT32 . . . 82
BFD_RELOC_ARC_GOTOFF . . . 82
BFD_RELOC_ARC_GOTPC . . . 82
BFD_RELOC_ARC_GOTPC32 . . . 82
BFD_RELOC_ARC_JLI_SECTOFF . . . 82
BFD_RELOC_ARC_JMP_SLOT . . . 82
BFD_RELOC_ARC_N16 . . . 81
BFD_RELOC_ARC_N24 . . . 81
BFD_RELOC_ARC_N32 . . . 81
BFD_RELOC_ARC_N32_ME . . . 81
BFD_RELOC_ARC_N8 . . . 81
BFD_RELOC_ARC_NONE . . . 81
BFD_RELOC_ARC_NPS_CMEM16 . . . 82
BFD_RELOC_ARC_PC32 . . . 82
BFD_RELOC_ARC_PLT32 . . . 82
BFD_RELOC_ARC_RELATIVE . . . 82
BFD_RELOC_ARC_S13_PCREL . . . 81
BFD_RELOC_ARC_S21H_PCREL . . . 81
BFD_RELOC_ARC_S21H_PCREL_PLT . . . 82
BFD_RELOC_ARC_S21W_PCREL . . . 81
BFD_RELOC_ARC_S21W_PCREL_PLT . . . 82
BFD_RELOC_ARC_S25H_PCREL . . . 81
BFD_RELOC_ARC_S25H_PCREL_PLT . . . 82
BFD_RELOC_ARC_S25W_PCREL . . . 81
BFD_RELOC_ARC_S25W_PCREL_PLT . . . 82
BFD_RELOC_ARC_SDA . . . 81
BFD_RELOC_ARC_SDA_12 . . . 82
BFD_RELOC_ARC_SDA_LDST . . . 81
BFD_RELOC_ARC_SDA_LDST1 . . . 81

BFD_RELOC_ARC_SDA_LDST2 81
BFD_RELOC_ARC_SDA16_LD 81
BFD_RELOC_ARC_SDA16_LD1 81
BFD_RELOC_ARC_SDA16_LD2 81
BFD_RELOC_ARC_SDA16_ST2 82
BFD_RELOC_ARC_SDA32 81
BFD_RELOC_ARC_SDA32_ME 81
BFD_RELOC_ARC_SECTOFF 81
BFD_RELOC_ARC_SECTOFF_1 82
BFD_RELOC_ARC_SECTOFF_2 82
BFD_RELOC_ARC_SECTOFF_ME 81
BFD_RELOC_ARC_SECTOFF_ME_1 82
BFD_RELOC_ARC_SECTOFF_ME_2 82
BFD_RELOC_ARC_TLS_DTPMOD 82
BFD_RELOC_ARC_TLS_DTPOFF 82
BFD_RELOC_ARC_TLS_DTPOFF_S9 82
BFD_RELOC_ARC_TLS_GD_CALL 82
BFD_RELOC_ARC_TLS_GD_GOT 82
BFD_RELOC_ARC_TLS_GD_LD 82
BFD_RELOC_ARC_TLS_IE_GOT 82
BFD_RELOC_ARC_TLS_LE_32 82
BFD_RELOC_ARC_TLS_LE_S9 82
BFD_RELOC_ARC_TLS_TPOFF 82
BFD_RELOC_ARC_W 81
BFD_RELOC_ARC_W_ME 81
BFD_RELOC_ARM_ADR_IMM 78
BFD_RELOC_ARM_ADRL_IMMEDIATE 78
BFD_RELOC_ARM_ALU_PC_G0 77
BFD_RELOC_ARM_ALU_PC_G0_NC 77
BFD_RELOC_ARM_ALU_PC_G1 77
BFD_RELOC_ARM_ALU_PC_G1_NC 77
BFD_RELOC_ARM_ALU_PC_G2 77
BFD_RELOC_ARM_ALU_SB_G0 77
BFD_RELOC_ARM_ALU_SB_G0_NC 77
BFD_RELOC_ARM_ALU_SB_G1 78
BFD_RELOC_ARM_ALU_SB_G1_NC 78
BFD_RELOC_ARM_ALU_SB_G2 78
BFD_RELOC_ARM_CP_OFF_IMM 78
BFD_RELOC_ARM_CP_OFF_IMM_S2 78
BFD_RELOC_ARM_FUNCDESC 76
BFD_RELOC_ARM_FUNCDESC_VALUE 77
BFD_RELOC_ARM_GLOB_DAT 77
BFD_RELOC_ARM_GOT_PREL 77
BFD_RELOC_ARM_GOT32 77
BFD_RELOC_ARM_GOTFUNCDESC 76
BFD_RELOC_ARM_GOTOFF 77
BFD_RELOC_ARM_GOTOFFFUNCDESC 76
BFD_RELOC_ARM_GOTPC 77
BFD_RELOC_ARM_HVC 78
BFD_RELOC_ARM_HWLITERAL 79
BFD_RELOC_ARM_IMMEDIATE 78
BFD_RELOC_ARM_IN_POOL 78
BFD_RELOC_ARM_IRELATIVE 78
BFD_RELOC_ARM_JUMP_SLOT 77
BFD_RELOC_ARM_LDC_PC_G0 77
BFD_RELOC_ARM_LDC_PC_G1 77
BFD_RELOC_ARM_LDC_PC_G2 77
BFD_RELOC_ARM_LDC_SB_G0 78
BFD_RELOC_ARM_LDC_SB_G1 78
BFD_RELOC_ARM_LDC_SB_G2 78
BFD_RELOC_ARM_LDR_IMM 78
BFD_RELOC_ARM_LDR_PC_G0 77
BFD_RELOC_ARM_LDR_PC_G1 77
BFD_RELOC_ARM_LDR_PC_G2 77
BFD_RELOC_ARM_LDR_SB_G0 78
BFD_RELOC_ARM_LDR_SB_G1 78
BFD_RELOC_ARM_LDR_SB_G2 78
BFD_RELOC_ARM_LDRS_PC_G0 77
BFD_RELOC_ARM_LDRS_PC_G1 77
BFD_RELOC_ARM_LDRS_PC_G2 77
BFD_RELOC_ARM_LDRS_SB_G0 78
BFD_RELOC_ARM_LDRS_SB_G1 78
BFD_RELOC_ARM_LDRS_SB_G2 78
BFD_RELOC_ARM_LITERAL 78
BFD_RELOC_ARM_MOVT 76
BFD_RELOC_ARM_MOVT_PCREL 76
BFD_RELOC_ARM_MOVW 76
BFD_RELOC_ARM_MOVW_PCREL 76
BFD_RELOC_ARM_MULTI 78
BFD_RELOC_ARM_OFFSET_IMM 76
BFD_RELOC_ARM_OFFSET_IMM8 78
BFD_RELOC_ARM_PCREL_BLX 75
BFD_RELOC_ARM_PCREL_BRANCH 75
BFD_RELOC_ARM_PCREL_CALL 75
BFD_RELOC_ARM_PCREL_JUMP 75
BFD_RELOC_ARM_PLT32 77
BFD_RELOC_ARM_PREL31 76
BFD_RELOC_ARM_RELATIVE 77
BFD_RELOC_ARM_ROSEGREL32 76
BFD_RELOC_ARM_SBREL32 76
BFD_RELOC_ARM_SHIFT_IMM 78
BFD_RELOC_ARM_SMC 78
BFD_RELOC_ARM_SWI 78
BFD_RELOC_ARM_T32_ADD_IMM 78
BFD_RELOC_ARM_T32_ADD_PC12 78
BFD_RELOC_ARM_T32_CP_OFF_IMM 78
BFD_RELOC_ARM_T32_CP_OFF_IMM_S2 78
BFD_RELOC_ARM_T32_IMM12 78
BFD_RELOC_ARM_T32_IMMEDIATE 78
BFD_RELOC_ARM_T32_OFFSET_IMM 79
BFD_RELOC_ARM_T32_OFFSET_U8 78
BFD_RELOC_ARM_T32_VLDR_VSTR_OFF_IMM 78
BFD_RELOC_ARM_TARGET1 76
BFD_RELOC_ARM_TARGET2 76
BFD_RELOC_ARM_THM_TLS_CALL 77
BFD_RELOC_ARM_THM_TLS_DESCSEQ 77
BFD_RELOC_ARM_THUMB_ADD 79
BFD_RELOC_ARM_THUMB_ALU_ABS_G0_NC 78
BFD_RELOC_ARM_THUMB_ALU_ABS_G1_NC 78
BFD_RELOC_ARM_THUMB_ALU_ABS_G2_NC 78
BFD_RELOC_ARM_THUMB_ALU_ABS_G3_NC 78
BFD_RELOC_ARM_THUMB_BF13 75
BFD_RELOC_ARM_THUMB_BF17 75
BFD_RELOC_ARM_THUMB_BF19 75
BFD_RELOC_ARM_THUMB_IMM 79
BFD_RELOC_ARM_THUMB_LOOP12 76

BFD_RELOC_ARM_THUMB_MOVT ... 76
BFD_RELOC_ARM_THUMB_MOVT_PCREL ... 76
BFD_RELOC_ARM_THUMB_MOVW ... 76
BFD_RELOC_ARM_THUMB_MOVW_PCREL ... 76
BFD_RELOC_ARM_THUMB_OFFSET ... 76
BFD_RELOC_ARM_THUMB_SHIFT ... 79
BFD_RELOC_ARM_TLS_CALL ... 77
BFD_RELOC_ARM_TLS_DESC ... 77
BFD_RELOC_ARM_TLS_DESCSEQ ... 77
BFD_RELOC_ARM_TLS_DTPMOD32 ... 77
BFD_RELOC_ARM_TLS_DTPOFF32 ... 77
BFD_RELOC_ARM_TLS_GD32 ... 77
BFD_RELOC_ARM_TLS_GD32_FDPIC ... 77
BFD_RELOC_ARM_TLS_GOTDESC ... 77
BFD_RELOC_ARM_TLS_IE32 ... 77
BFD_RELOC_ARM_TLS_IE32_FDPIC ... 77
BFD_RELOC_ARM_TLS_LDM32 ... 77
BFD_RELOC_ARM_TLS_LDM32_FDPIC ... 77
BFD_RELOC_ARM_TLS_LDO32 ... 77
BFD_RELOC_ARM_TLS_LE32 ... 77
BFD_RELOC_ARM_TLS_TPOFF32 ... 77
BFD_RELOC_ARM_V4BX ... 78
BFD_RELOC_AVR_13_PCREL ... 97
BFD_RELOC_AVR_16_PM ... 97
BFD_RELOC_AVR_6 ... 99
BFD_RELOC_AVR_6_ADIW ... 99
BFD_RELOC_AVR_7_PCREL ... 97
BFD_RELOC_AVR_8_HI ... 99
BFD_RELOC_AVR_8_HLO ... 99
BFD_RELOC_AVR_8_LO ... 99
BFD_RELOC_AVR_CALL ... 98
BFD_RELOC_AVR_DIFF16 ... 99
BFD_RELOC_AVR_DIFF32 ... 99
BFD_RELOC_AVR_DIFF8 ... 99
BFD_RELOC_AVR_HH8_LDI ... 97
BFD_RELOC_AVR_HH8_LDI_NEG ... 98
BFD_RELOC_AVR_HH8_LDI_PM ... 98
BFD_RELOC_AVR_HH8_LDI_PM_NEG ... 98
BFD_RELOC_AVR_HI8_LDI ... 97
BFD_RELOC_AVR_HI8_LDI_GS ... 98
BFD_RELOC_AVR_HI8_LDI_NEG ... 98
BFD_RELOC_AVR_HI8_LDI_PM ... 98
BFD_RELOC_AVR_HI8_LDI_PM_NEG ... 98
BFD_RELOC_AVR_LDI ... 98
BFD_RELOC_AVR_LDS_STS_16 ... 99
BFD_RELOC_AVR_LO8_LDI ... 97
BFD_RELOC_AVR_LO8_LDI_GS ... 98
BFD_RELOC_AVR_LO8_LDI_NEG ... 97
BFD_RELOC_AVR_LO8_LDI_PM ... 98
BFD_RELOC_AVR_LO8_LDI_PM_NEG ... 98
BFD_RELOC_AVR_MS8_LDI ... 97
BFD_RELOC_AVR_MS8_LDI_NEG ... 98
BFD_RELOC_AVR_PORT5 ... 99
BFD_RELOC_AVR_PORT6 ... 99
BFD_RELOC_BFIN_10_PCREL ... 83
BFD_RELOC_BFIN_11_PCREL ... 83
BFD_RELOC_BFIN_12_PCREL_JUMP ... 83
BFD_RELOC_BFIN_12_PCREL_JUMP_S ... 83
BFD_RELOC_BFIN_16_HIGH ... 82
BFD_RELOC_BFIN_16_IMM ... 82
BFD_RELOC_BFIN_16_LOW ... 83
BFD_RELOC_BFIN_24_PCREL_CALL_X ... 83
BFD_RELOC_BFIN_24_PCREL_JUMP_L ... 83
BFD_RELOC_BFIN_4_PCREL ... 82
BFD_RELOC_BFIN_5_PCREL ... 82
BFD_RELOC_BFIN_FUNCDESC ... 83
BFD_RELOC_BFIN_FUNCDESC_GOT17M4 ... 83
BFD_RELOC_BFIN_FUNCDESC_GOTHI ... 83
BFD_RELOC_BFIN_FUNCDESC_GOTLO ... 83
BFD_RELOC_BFIN_FUNCDESC_GOTOFF17M4 ... 83
BFD_RELOC_BFIN_FUNCDESC_GOTOFFHI ... 83
BFD_RELOC_BFIN_FUNCDESC_GOTOFFLO ... 83
BFD_RELOC_BFIN_FUNCDESC_VALUE ... 83
BFD_RELOC_BFIN_GOT ... 83
BFD_RELOC_BFIN_GOT17M4 ... 83
BFD_RELOC_BFIN_GOTHI ... 83
BFD_RELOC_BFIN_GOTLO ... 83
BFD_RELOC_BFIN_GOTOFF17M4 ... 83
BFD_RELOC_BFIN_GOTOFFHI ... 83
BFD_RELOC_BFIN_GOTOFFLO ... 83
BFD_RELOC_BFIN_PLTPC ... 83
BFD_RELOC_BPF_64 ... 134
BFD_RELOC_BPF_DISP16 ... 134
BFD_RELOC_BPF_DISP32 ... 134
BFD_RELOC_BPF_DISPCALL32 ... 134
BFD_RELOC_C6000_ABS_H16 ... 93
BFD_RELOC_C6000_ABS_L16 ... 93
BFD_RELOC_C6000_ABS_S16 ... 93
BFD_RELOC_C6000_ALIGN ... 94
BFD_RELOC_C6000_COPY ... 94
BFD_RELOC_C6000_DSBT_INDEX ... 94
BFD_RELOC_C6000_EHTYPE ... 94
BFD_RELOC_C6000_FPHEAD ... 94
BFD_RELOC_C6000_JUMP_SLOT ... 94
BFD_RELOC_C6000_NOCMP ... 94
BFD_RELOC_C6000_PCR_H16 ... 94
BFD_RELOC_C6000_PCR_L16 ... 94
BFD_RELOC_C6000_PCR_S10 ... 93
BFD_RELOC_C6000_PCR_S12 ... 93
BFD_RELOC_C6000_PCR_S21 ... 93
BFD_RELOC_C6000_PCR_S7 ... 93
BFD_RELOC_C6000_PREL31 ... 94
BFD_RELOC_C6000_SBR_GOT_H16_W ... 94
BFD_RELOC_C6000_SBR_GOT_L16_W ... 94
BFD_RELOC_C6000_SBR_GOT_U15_W ... 94
BFD_RELOC_C6000_SBR_H16_B ... 94
BFD_RELOC_C6000_SBR_H16_H ... 94
BFD_RELOC_C6000_SBR_H16_W ... 94
BFD_RELOC_C6000_SBR_L16_B ... 94
BFD_RELOC_C6000_SBR_L16_H ... 94
BFD_RELOC_C6000_SBR_L16_W ... 94
BFD_RELOC_C6000_SBR_S16 ... 94
BFD_RELOC_C6000_SBR_U15_B ... 93
BFD_RELOC_C6000_SBR_U15_H ... 93
BFD_RELOC_C6000_SBR_U15_W ... 94
BFD_RELOC_CKCORE_ADDR_HI16 ... 136

BFD_RELOC_CKCORE_ADDR_LO16 136
BFD_RELOC_CKCORE_ADDR32 135
BFD_RELOC_CKCORE_ADDRGOT 135
BFD_RELOC_CKCORE_ADDRGOT_HI16 136
BFD_RELOC_CKCORE_ADDRGOT_LO16 136
BFD_RELOC_CKCORE_ADDRPLT 135
BFD_RELOC_CKCORE_ADDRPLT_HI16 136
BFD_RELOC_CKCORE_ADDRPLT_LO16 136
BFD_RELOC_CKCORE_CALLGRAPH 136
BFD_RELOC_CKCORE_COPY 135
BFD_RELOC_CKCORE_DOFFSET_IMM18 136
BFD_RELOC_CKCORE_DOFFSET_IMM18BY2 136
BFD_RELOC_CKCORE_DOFFSET_IMM18BY4 136
BFD_RELOC_CKCORE_DOFFSET_LO16 136
BFD_RELOC_CKCORE_GLOB_DAT 135
BFD_RELOC_CKCORE_GNU_VTENTRY 135
BFD_RELOC_CKCORE_GNU_VTINHERIT 135
BFD_RELOC_CKCORE_GOT_HI16 136
BFD_RELOC_CKCORE_GOT_IMM18BY4 136
BFD_RELOC_CKCORE_GOT_LO16 136
BFD_RELOC_CKCORE_GOT12 136
BFD_RELOC_CKCORE_GOT32 135
BFD_RELOC_CKCORE_GOTOFF 135
BFD_RELOC_CKCORE_GOTOFF_HI16 136
BFD_RELOC_CKCORE_GOTOFF_IMM18 136
BFD_RELOC_CKCORE_GOTOFF_LO16 136
BFD_RELOC_CKCORE_GOTPC 135
BFD_RELOC_CKCORE_GOTPC_HI16 136
BFD_RELOC_CKCORE_GOTPC_LO16 136
BFD_RELOC_CKCORE_IRELATIVE 136
BFD_RELOC_CKCORE_JUMP_SLOT 135
BFD_RELOC_CKCORE_NOJSRI 136
BFD_RELOC_CKCORE_NONE 135
BFD_RELOC_CKCORE_PCREL_BLOOP_IMM12BY4 136
BFD_RELOC_CKCORE_PCREL_BLOOP_IMM4BY4 136
BFD_RELOC_CKCORE_PCREL_FLRW_IMM8BY4 136
BFD_RELOC_CKCORE_PCREL_IMM10BY2 136
BFD_RELOC_CKCORE_PCREL_IMM10BY4 136
BFD_RELOC_CKCORE_PCREL_IMM11BY2 135
BFD_RELOC_CKCORE_PCREL_IMM16BY2 136
BFD_RELOC_CKCORE_PCREL_IMM16BY4 136
BFD_RELOC_CKCORE_PCREL_IMM18BY2 136
BFD_RELOC_CKCORE_PCREL_IMM26BY2 135
BFD_RELOC_CKCORE_PCREL_IMM4BY2 135
BFD_RELOC_CKCORE_PCREL_IMM7BY4 136
BFD_RELOC_CKCORE_PCREL_IMM8BY4 135
BFD_RELOC_CKCORE_PCREL_JSR_IMM11BY2 135
BFD_RELOC_CKCORE_PCREL_JSR_IMM26BY2 136
BFD_RELOC_CKCORE_PCREL32 135
BFD_RELOC_CKCORE_PLT_HI16 136
BFD_RELOC_CKCORE_PLT_IMM18BY4 136
BFD_RELOC_CKCORE_PLT_LO16 136
BFD_RELOC_CKCORE_PLT12 136
BFD_RELOC_CKCORE_PLT32 135
BFD_RELOC_CKCORE_RELATIVE 135
BFD_RELOC_CKCORE_TLS_DTPMOD32 136
BFD_RELOC_CKCORE_TLS_DTPOFF32 136
BFD_RELOC_CKCORE_TLS_GD32 136
BFD_RELOC_CKCORE_TLS_IE32 136
BFD_RELOC_CKCORE_TLS_LDM32 136
BFD_RELOC_CKCORE_TLS_LDO32 136
BFD_RELOC_CKCORE_TLS_LE32 136
BFD_RELOC_CKCORE_TLS_TPOFF32 136
BFD_RELOC_CKCORE_TOFFSET_LO16 136
BFD_RELOC_CR16_ABS20 110
BFD_RELOC_CR16_ABS24 110
BFD_RELOC_CR16_DISP16 110
BFD_RELOC_CR16_DISP20 110
BFD_RELOC_CR16_DISP24 110
BFD_RELOC_CR16_DISP24a 110
BFD_RELOC_CR16_DISP4 110
BFD_RELOC_CR16_DISP8 110
BFD_RELOC_CR16_GLOB_DAT 110
BFD_RELOC_CR16_GOT_REGREL20 110
BFD_RELOC_CR16_GOTC_REGREL20 110
BFD_RELOC_CR16_IMM16 110
BFD_RELOC_CR16_IMM20 110
BFD_RELOC_CR16_IMM24 110
BFD_RELOC_CR16_IMM32 110
BFD_RELOC_CR16_IMM32a 110
BFD_RELOC_CR16_IMM4 110
BFD_RELOC_CR16_IMM8 110
BFD_RELOC_CR16_NUM16 109
BFD_RELOC_CR16_NUM32 109
BFD_RELOC_CR16_NUM32a 109
BFD_RELOC_CR16_NUM8 109
BFD_RELOC_CR16_REGREL0 109
BFD_RELOC_CR16_REGREL14 109
BFD_RELOC_CR16_REGREL14a 109
BFD_RELOC_CR16_REGREL16 109
BFD_RELOC_CR16_REGREL20 109
BFD_RELOC_CR16_REGREL20a 110
BFD_RELOC_CR16_REGREL4 109
BFD_RELOC_CR16_REGREL4a 109
BFD_RELOC_CR16_SWITCH16 110
BFD_RELOC_CR16_SWITCH32 110
BFD_RELOC_CR16_SWITCH8 110
BFD_RELOC_CRIS_16_DTPREL 111
BFD_RELOC_CRIS_16_GOT 111
BFD_RELOC_CRIS_16_GOT_GD 111
BFD_RELOC_CRIS_16_GOT_TPREL 111
BFD_RELOC_CRIS_16_GOTPLT 111
BFD_RELOC_CRIS_16_TPREL 111
BFD_RELOC_CRIS_32_DTPREL 111
BFD_RELOC_CRIS_32_GD 111
BFD_RELOC_CRIS_32_GOT 111
BFD_RELOC_CRIS_32_GOT_GD 111
BFD_RELOC_CRIS_32_GOT_TPREL 111
BFD_RELOC_CRIS_32_GOTPLT 111
BFD_RELOC_CRIS_32_GOTREL 111
BFD_RELOC_CRIS_32_IE 112
BFD_RELOC_CRIS_32_PLT_GOTREL 111
BFD_RELOC_CRIS_32_PLT_PCREL 111
BFD_RELOC_CRIS_32_TPREL 111
BFD_RELOC_CRIS_BDISP8 111
BFD_RELOC_CRIS_COPY 111

BFD_RELOC_CRIS_DTP ... 111
BFD_RELOC_CRIS_DTPMOD ... 111
BFD_RELOC_CRIS_GLOB_DAT ... 111
BFD_RELOC_CRIS_JUMP_SLOT ... 111
BFD_RELOC_CRIS_LAPCQ_OFFSET ... 111
BFD_RELOC_CRIS_RELATIVE ... 111
BFD_RELOC_CRIS_SIGNED_16 ... 111
BFD_RELOC_CRIS_SIGNED_6 ... 111
BFD_RELOC_CRIS_SIGNED_8 ... 111
BFD_RELOC_CRIS_UNSIGNED_16 ... 111
BFD_RELOC_CRIS_UNSIGNED_4 ... 111
BFD_RELOC_CRIS_UNSIGNED_5 ... 111
BFD_RELOC_CRIS_UNSIGNED_6 ... 111
BFD_RELOC_CRIS_UNSIGNED_8 ... 111
BFD_RELOC_CRX_ABS16 ... 110
BFD_RELOC_CRX_ABS32 ... 110
BFD_RELOC_CRX_IMM16 ... 110
BFD_RELOC_CRX_IMM32 ... 110
BFD_RELOC_CRX_NUM16 ... 110
BFD_RELOC_CRX_NUM32 ... 110
BFD_RELOC_CRX_NUM8 ... 110
BFD_RELOC_CRX_REGREL12 ... 110
BFD_RELOC_CRX_REGREL22 ... 110
BFD_RELOC_CRX_REGREL28 ... 110
BFD_RELOC_CRX_REGREL32 ... 110
BFD_RELOC_CRX_REL16 ... 110
BFD_RELOC_CRX_REL24 ... 110
BFD_RELOC_CRX_REL32 ... 110
BFD_RELOC_CRX_REL4 ... 110
BFD_RELOC_CRX_REL8 ... 110
BFD_RELOC_CRX_REL8_CMP ... 110
BFD_RELOC_CRX_SWITCH16 ... 110
BFD_RELOC_CRX_SWITCH32 ... 110
BFD_RELOC_CRX_SWITCH8 ... 110
BFD_RELOC_CTOR ... 75
BFD_RELOC_D10V_10_PCREL_L ... 85
BFD_RELOC_D10V_10_PCREL_R ... 84
BFD_RELOC_D10V_18 ... 85
BFD_RELOC_D10V_18_PCREL ... 85
BFD_RELOC_D30V_15 ... 85
BFD_RELOC_D30V_15_PCREL ... 85
BFD_RELOC_D30V_15_PCREL_R ... 85
BFD_RELOC_D30V_21 ... 85
BFD_RELOC_D30V_21_PCREL ... 85
BFD_RELOC_D30V_21_PCREL_R ... 85
BFD_RELOC_D30V_32 ... 85
BFD_RELOC_D30V_32_PCREL ... 85
BFD_RELOC_D30V_6 ... 85
BFD_RELOC_D30V_9_PCREL ... 85
BFD_RELOC_D30V_9_PCREL_R ... 85
BFD_RELOC_DLX_HI16_S ... 85
BFD_RELOC_DLX_JMP26 ... 85
BFD_RELOC_DLX_LO16 ... 85
BFD_RELOC_EPIPHANY_HIGH ... 134
BFD_RELOC_EPIPHANY_IMM11 ... 135
BFD_RELOC_EPIPHANY_IMM8 ... 135
BFD_RELOC_EPIPHANY_LOW ... 134
BFD_RELOC_EPIPHANY_SIMM11 ... 135
BFD_RELOC_EPIPHANY_SIMM24 ... 134
BFD_RELOC_EPIPHANY_SIMM8 ... 134
BFD_RELOC_FR30_10_IN_8 ... 94
BFD_RELOC_FR30_12_PCREL ... 94
BFD_RELOC_FR30_20 ... 94
BFD_RELOC_FR30_48 ... 94
BFD_RELOC_FR30_6_IN_4 ... 94
BFD_RELOC_FR30_8_IN_8 ... 94
BFD_RELOC_FR30_9_IN_8 ... 94
BFD_RELOC_FR30_9_PCREL ... 94
BFD_RELOC_FRV_FUNCDESC ... 67
BFD_RELOC_FRV_FUNCDESC_GOT12 ... 67
BFD_RELOC_FRV_FUNCDESC_GOTHI ... 68
BFD_RELOC_FRV_FUNCDESC_GOTLO ... 68
BFD_RELOC_FRV_FUNCDESC_GOTOFF12 ... 68
BFD_RELOC_FRV_FUNCDESC_GOTOFFHI ... 68
BFD_RELOC_FRV_FUNCDESC_GOTOFFLO ... 68
BFD_RELOC_FRV_FUNCDESC_VALUE ... 68
BFD_RELOC_FRV_GETTLSOFF ... 68
BFD_RELOC_FRV_GETTLSOFF_RELAX ... 68
BFD_RELOC_FRV_GOT12 ... 67
BFD_RELOC_FRV_GOTHI ... 67
BFD_RELOC_FRV_GOTLO ... 67
BFD_RELOC_FRV_GOTOFF12 ... 68
BFD_RELOC_FRV_GOTOFFHI ... 68
BFD_RELOC_FRV_GOTOFFLO ... 68
BFD_RELOC_FRV_GOTTLSDESC12 ... 68
BFD_RELOC_FRV_GOTTLSDESCHI ... 68
BFD_RELOC_FRV_GOTTLSDESCLO ... 68
BFD_RELOC_FRV_GOTTLSOFF12 ... 68
BFD_RELOC_FRV_GOTTLSOFFHI ... 68
BFD_RELOC_FRV_GOTTLSOFFLO ... 68
BFD_RELOC_FRV_GPREL12 ... 67
BFD_RELOC_FRV_GPREL32 ... 67
BFD_RELOC_FRV_GPRELHI ... 67
BFD_RELOC_FRV_GPRELLO ... 67
BFD_RELOC_FRV_GPRELU12 ... 67
BFD_RELOC_FRV_HI16 ... 67
BFD_RELOC_FRV_LABEL16 ... 67
BFD_RELOC_FRV_LABEL24 ... 67
BFD_RELOC_FRV_LO16 ... 67
BFD_RELOC_FRV_TLSDESC_RELAX ... 68
BFD_RELOC_FRV_TLSDESC_VALUE ... 68
BFD_RELOC_FRV_TLSMOFF ... 68
BFD_RELOC_FRV_TLSMOFF12 ... 68
BFD_RELOC_FRV_TLSMOFFHI ... 68
BFD_RELOC_FRV_TLSMOFFLO ... 68
BFD_RELOC_FRV_TLSOFF ... 68
BFD_RELOC_FRV_TLSOFF_RELAX ... 68
BFD_RELOC_FT32_10 ... 67
BFD_RELOC_FT32_15 ... 67
BFD_RELOC_FT32_17 ... 67
BFD_RELOC_FT32_18 ... 67
BFD_RELOC_FT32_20 ... 67
BFD_RELOC_FT32_DIFF32 ... 67
BFD_RELOC_FT32_RELAX ... 67
BFD_RELOC_FT32_SC0 ... 67
BFD_RELOC_FT32_SC1 ... 67

BFD_RELOC_GPREL16 60
BFD_RELOC_GPREL32 60
BFD_RELOC_H8_DIR16A8 112
BFD_RELOC_H8_DIR16R8 112
BFD_RELOC_H8_DIR24A8 112
BFD_RELOC_H8_DIR24R8 113
BFD_RELOC_H8_DIR32A16 113
BFD_RELOC_H8_DISP32A16 113
BFD_RELOC_HI16 64
BFD_RELOC_HI16_BASEREL 59
BFD_RELOC_HI16_GOTOFF 59
BFD_RELOC_HI16_PCREL 65
BFD_RELOC_HI16_PLTOFF 59
BFD_RELOC_HI16_S 64
BFD_RELOC_HI16_S_BASEREL 59
BFD_RELOC_HI16_S_GOTOFF 59
BFD_RELOC_HI16_S_PCREL 65
BFD_RELOC_HI16_S_PLTOFF 59
BFD_RELOC_HI22 60
BFD_RELOC_I370_D12 75
BFD_RELOC_IA64_COPY 107
BFD_RELOC_IA64_DIR32LSB 106
BFD_RELOC_IA64_DIR32MSB 106
BFD_RELOC_IA64_DIR64LSB 106
BFD_RELOC_IA64_DIR64MSB 106
BFD_RELOC_IA64_DTPMOD64LSB 107
BFD_RELOC_IA64_DTPMOD64MSB 107
BFD_RELOC_IA64_DTPREL14 107
BFD_RELOC_IA64_DTPREL22 107
BFD_RELOC_IA64_DTPREL32LSB 107
BFD_RELOC_IA64_DTPREL32MSB 107
BFD_RELOC_IA64_DTPREL64I 107
BFD_RELOC_IA64_DTPREL64LSB 107
BFD_RELOC_IA64_DTPREL64MSB 107
BFD_RELOC_IA64_FPTR32LSB 106
BFD_RELOC_IA64_FPTR32MSB 106
BFD_RELOC_IA64_FPTR64I 106
BFD_RELOC_IA64_FPTR64LSB 106
BFD_RELOC_IA64_FPTR64MSB 106
BFD_RELOC_IA64_GPREL22 106
BFD_RELOC_IA64_GPREL32LSB 106
BFD_RELOC_IA64_GPREL32MSB 106
BFD_RELOC_IA64_GPREL64I 106
BFD_RELOC_IA64_GPREL64LSB 106
BFD_RELOC_IA64_GPREL64MSB 106
BFD_RELOC_IA64_IMM14 106
BFD_RELOC_IA64_IMM22 106
BFD_RELOC_IA64_IMM64 106
BFD_RELOC_IA64_IPLTLSB 107
BFD_RELOC_IA64_IPLTMSB 107
BFD_RELOC_IA64_LDXMOV 107
BFD_RELOC_IA64_LTOFF_DTPMOD22 107
BFD_RELOC_IA64_LTOFF_DTPREL22 107
BFD_RELOC_IA64_LTOFF_FPTR22 106
BFD_RELOC_IA64_LTOFF_FPTR32LSB 106
BFD_RELOC_IA64_LTOFF_FPTR32MSB 106
BFD_RELOC_IA64_LTOFF_FPTR64I 106
BFD_RELOC_IA64_LTOFF_FPTR64LSB 106
BFD_RELOC_IA64_LTOFF_FPTR64MSB 106
BFD_RELOC_IA64_LTOFF_TPREL22 107
BFD_RELOC_IA64_LTOFF22 106
BFD_RELOC_IA64_LTOFF22X 107
BFD_RELOC_IA64_LTOFF64I 106
BFD_RELOC_IA64_LTV32LSB 107
BFD_RELOC_IA64_LTV32MSB 107
BFD_RELOC_IA64_LTV64LSB 107
BFD_RELOC_IA64_LTV64MSB 107
BFD_RELOC_IA64_PCREL21B 106
BFD_RELOC_IA64_PCREL21BI 106
BFD_RELOC_IA64_PCREL21F 106
BFD_RELOC_IA64_PCREL21M 106
BFD_RELOC_IA64_PCREL22 106
BFD_RELOC_IA64_PCREL32LSB 106
BFD_RELOC_IA64_PCREL32MSB 106
BFD_RELOC_IA64_PCREL60B 106
BFD_RELOC_IA64_PCREL64I 106
BFD_RELOC_IA64_PCREL64LSB 106
BFD_RELOC_IA64_PCREL64MSB 106
BFD_RELOC_IA64_PLTOFF22 106
BFD_RELOC_IA64_PLTOFF64I 106
BFD_RELOC_IA64_PLTOFF64LSB 106
BFD_RELOC_IA64_PLTOFF64MSB 106
BFD_RELOC_IA64_REL32LSB 107
BFD_RELOC_IA64_REL32MSB 107
BFD_RELOC_IA64_REL64LSB 107
BFD_RELOC_IA64_REL64MSB 107
BFD_RELOC_IA64_SECREL32LSB 107
BFD_RELOC_IA64_SECREL32MSB 107
BFD_RELOC_IA64_SECREL64LSB 107
BFD_RELOC_IA64_SECREL64MSB 107
BFD_RELOC_IA64_SEGREL32LSB 106
BFD_RELOC_IA64_SEGREL32MSB 106
BFD_RELOC_IA64_SEGREL64LSB 107
BFD_RELOC_IA64_SEGREL64MSB 106
BFD_RELOC_IA64_TPREL14 107
BFD_RELOC_IA64_TPREL22 107
BFD_RELOC_IA64_TPREL64I 107
BFD_RELOC_IA64_TPREL64LSB 107
BFD_RELOC_IA64_TPREL64MSB 107
BFD_RELOC_IP2K_ADDR16CJP 105
BFD_RELOC_IP2K_BANK 105
BFD_RELOC_IP2K_EX8DATA 105
BFD_RELOC_IP2K_FR_OFFSET 105
BFD_RELOC_IP2K_FR9 105
BFD_RELOC_IP2K_HI8DATA 105
BFD_RELOC_IP2K_HI8INSN 105
BFD_RELOC_IP2K_LO8DATA 105
BFD_RELOC_IP2K_LO8INSN 105
BFD_RELOC_IP2K_PAGE3 105
BFD_RELOC_IP2K_PC_SKIP 105
BFD_RELOC_IP2K_TEXT 105
BFD_RELOC_IQ2000_OFFSET_16 114
BFD_RELOC_IQ2000_OFFSET_21 114
BFD_RELOC_IQ2000_UHI16 114
BFD_RELOC_KVX_16 120
BFD_RELOC_KVX_32 120

BFD_RELOC_KVX_32_GOT 121
BFD_RELOC_KVX_32_GOTOFF 121
BFD_RELOC_KVX_32_PCREL 120
BFD_RELOC_KVX_64 120
BFD_RELOC_KVX_64_DTPMOD 121
BFD_RELOC_KVX_64_DTPOFF 121
BFD_RELOC_KVX_64_GOT 121
BFD_RELOC_KVX_64_GOTOFF 121
BFD_RELOC_KVX_64_PCREL 121
BFD_RELOC_KVX_64_TPOFF 122
BFD_RELOC_KVX_8 122
BFD_RELOC_KVX_COPY 121
BFD_RELOC_KVX_GLOB_DAT 121
BFD_RELOC_KVX_JMP_SLOT 121
BFD_RELOC_KVX_NONE 120
BFD_RELOC_KVX_PCREL17 120
BFD_RELOC_KVX_PCREL27 120
BFD_RELOC_KVX_RELATIVE 121
BFD_RELOC_KVX_RELOC_END 122
BFD_RELOC_KVX_RELOC_START 120
BFD_RELOC_KVX_S16 121
BFD_RELOC_KVX_S16_PCREL 120
BFD_RELOC_KVX_S32_LO5 121
BFD_RELOC_KVX_S32_UP27 121
BFD_RELOC_KVX_S37_GOT_LO10 121
BFD_RELOC_KVX_S37_GOT_UP27 121
BFD_RELOC_KVX_S37_GOTADDR_LO10 121
BFD_RELOC_KVX_S37_GOTADDR_UP27 121
BFD_RELOC_KVX_S37_GOTOFF_LO10 121
BFD_RELOC_KVX_S37_GOTOFF_UP27 121
BFD_RELOC_KVX_S37_LO10 121
BFD_RELOC_KVX_S37_PCREL_LO10 120
BFD_RELOC_KVX_S37_PCREL_UP27 120
BFD_RELOC_KVX_S37_TLS_DTPOFF_LO10 121
BFD_RELOC_KVX_S37_TLS_DTPOFF_UP27 121
BFD_RELOC_KVX_S37_TLS_GD_LO10 121
BFD_RELOC_KVX_S37_TLS_GD_UP27 122
BFD_RELOC_KVX_S37_TLS_IE_LO10 122
BFD_RELOC_KVX_S37_TLS_IE_UP27 122
BFD_RELOC_KVX_S37_TLS_LD_LO10 122
BFD_RELOC_KVX_S37_TLS_LD_UP27 122
BFD_RELOC_KVX_S37_TLS_LE_LO10 122
BFD_RELOC_KVX_S37_TLS_LE_UP27 122
BFD_RELOC_KVX_S37_UP27 121
BFD_RELOC_KVX_S43_EX6 121
BFD_RELOC_KVX_S43_GOT_EX6 121
BFD_RELOC_KVX_S43_GOT_LO10 121
BFD_RELOC_KVX_S43_GOT_UP27 121
BFD_RELOC_KVX_S43_GOTADDR_EX6 121
BFD_RELOC_KVX_S43_GOTADDR_LO10 121
BFD_RELOC_KVX_S43_GOTADDR_UP27 121
BFD_RELOC_KVX_S43_GOTOFF_EX6 121
BFD_RELOC_KVX_S43_GOTOFF_LO10 121
BFD_RELOC_KVX_S43_GOTOFF_UP27 121
BFD_RELOC_KVX_S43_LO10 121
BFD_RELOC_KVX_S43_PCREL_EX6 120
BFD_RELOC_KVX_S43_PCREL_LO10 120
BFD_RELOC_KVX_S43_PCREL_UP27 120
BFD_RELOC_KVX_S43_TLS_DTPOFF_EX6 121
BFD_RELOC_KVX_S43_TLS_DTPOFF_LO10 121
BFD_RELOC_KVX_S43_TLS_DTPOFF_UP27 121
BFD_RELOC_KVX_S43_TLS_GD_EX6 122
BFD_RELOC_KVX_S43_TLS_GD_LO10 122
BFD_RELOC_KVX_S43_TLS_GD_UP27 122
BFD_RELOC_KVX_S43_TLS_IE_EX6 122
BFD_RELOC_KVX_S43_TLS_IE_LO10 122
BFD_RELOC_KVX_S43_TLS_IE_UP27 122
BFD_RELOC_KVX_S43_TLS_LD_EX6 122
BFD_RELOC_KVX_S43_TLS_LD_LO10 122
BFD_RELOC_KVX_S43_TLS_LD_UP27 122
BFD_RELOC_KVX_S43_TLS_LE_EX6 122
BFD_RELOC_KVX_S43_TLS_LE_LO10 122
BFD_RELOC_KVX_S43_TLS_LE_UP27 122
BFD_RELOC_KVX_S43_UP27 121
BFD_RELOC_KVX_S64_EX27 121
BFD_RELOC_KVX_S64_GOTADDR_EX27 121
BFD_RELOC_KVX_S64_GOTADDR_LO10 121
BFD_RELOC_KVX_S64_GOTADDR_UP27 121
BFD_RELOC_KVX_S64_LO10 121
BFD_RELOC_KVX_S64_PCREL_EX27 121
BFD_RELOC_KVX_S64_PCREL_LO10 120
BFD_RELOC_KVX_S64_PCREL_UP27 120
BFD_RELOC_KVX_S64_UP27 121
BFD_RELOC_LARCH_32_PCREL 138
BFD_RELOC_LARCH_64_PCREL 138
BFD_RELOC_LARCH_ABS_HI20 138
BFD_RELOC_LARCH_ABS_LO12 138
BFD_RELOC_LARCH_ABS64_HI12 138
BFD_RELOC_LARCH_ABS64_LO20 138
BFD_RELOC_LARCH_ADD_ULEB128 138
BFD_RELOC_LARCH_ADD16 137
BFD_RELOC_LARCH_ADD24 137
BFD_RELOC_LARCH_ADD32 137
BFD_RELOC_LARCH_ADD6 138
BFD_RELOC_LARCH_ADD64 137
BFD_RELOC_LARCH_ADD8 137
BFD_RELOC_LARCH_ALIGN 138
BFD_RELOC_LARCH_B16 138
BFD_RELOC_LARCH_B21 138
BFD_RELOC_LARCH_B26 138
BFD_RELOC_LARCH_CALL36 138
BFD_RELOC_LARCH_CFA 138
BFD_RELOC_LARCH_DELETE 138
BFD_RELOC_LARCH_GOT_HI20 138
BFD_RELOC_LARCH_GOT_LO12 138
BFD_RELOC_LARCH_GOT_PC_HI20 138
BFD_RELOC_LARCH_GOT_PC_LO12 138
BFD_RELOC_LARCH_GOT64_HI12 138
BFD_RELOC_LARCH_GOT64_LO20 138
BFD_RELOC_LARCH_GOT64_PC_HI12 138
BFD_RELOC_LARCH_GOT64_PC_LO20 138
BFD_RELOC_LARCH_MARK_LA 137
BFD_RELOC_LARCH_MARK_PCREL 137
BFD_RELOC_LARCH_PCALA_HI20 138
BFD_RELOC_LARCH_PCALA_LO12 138
BFD_RELOC_LARCH_PCALA64_HI12 138

BFD_RELOC_LARCH_PCALA64_LO20 138
BFD_RELOC_LARCH_PCREL20_S2 138
BFD_RELOC_LARCH_RELAX 138
BFD_RELOC_LARCH_SOP_ADD 137
BFD_RELOC_LARCH_SOP_AND 137
BFD_RELOC_LARCH_SOP_ASSERT 137
BFD_RELOC_LARCH_SOP_IF_ELSE 137
BFD_RELOC_LARCH_SOP_NOT 137
BFD_RELOC_LARCH_SOP_POP_32_S_0_10_10_16_S2 137
BFD_RELOC_LARCH_SOP_POP_32_S_0_5_10_16_S2 137
BFD_RELOC_LARCH_SOP_POP_32_S_10_12 137
BFD_RELOC_LARCH_SOP_POP_32_S_10_16 137
BFD_RELOC_LARCH_SOP_POP_32_S_10_16_S2 137
BFD_RELOC_LARCH_SOP_POP_32_S_10_5 137
BFD_RELOC_LARCH_SOP_POP_32_S_5_20 137
BFD_RELOC_LARCH_SOP_POP_32_U 137
BFD_RELOC_LARCH_SOP_POP_32_U_10_12 137
BFD_RELOC_LARCH_SOP_PUSH_ABSOLUTE 137
BFD_RELOC_LARCH_SOP_PUSH_DUP 137
BFD_RELOC_LARCH_SOP_PUSH_GPREL 137
BFD_RELOC_LARCH_SOP_PUSH_PCREL 137
BFD_RELOC_LARCH_SOP_PUSH_PLT_PCREL 137
BFD_RELOC_LARCH_SOP_PUSH_TLS_GD 137
BFD_RELOC_LARCH_SOP_PUSH_TLS_GOT 137
BFD_RELOC_LARCH_SOP_PUSH_TLS_TPREL 137
BFD_RELOC_LARCH_SOP_SL 137
BFD_RELOC_LARCH_SOP_SR 137
BFD_RELOC_LARCH_SOP_SUB 137
BFD_RELOC_LARCH_SUB_ULEB128 138
BFD_RELOC_LARCH_SUB16 137
BFD_RELOC_LARCH_SUB24 137
BFD_RELOC_LARCH_SUB32 137
BFD_RELOC_LARCH_SUB6 138
BFD_RELOC_LARCH_SUB64 137
BFD_RELOC_LARCH_SUB8 137
BFD_RELOC_LARCH_TLS_DESC_CALL 139
BFD_RELOC_LARCH_TLS_DESC_HI20 139
BFD_RELOC_LARCH_TLS_DESC_LD 139
BFD_RELOC_LARCH_TLS_DESC_LO12 139
BFD_RELOC_LARCH_TLS_DESC_PC_HI20 139
BFD_RELOC_LARCH_TLS_DESC_PC_LO12 139
BFD_RELOC_LARCH_TLS_DESC_PCREL20_S2 139
BFD_RELOC_LARCH_TLS_DESC32 137
BFD_RELOC_LARCH_TLS_DESC64 137
BFD_RELOC_LARCH_TLS_DESC64_HI12 139
BFD_RELOC_LARCH_TLS_DESC64_LO20 139
BFD_RELOC_LARCH_TLS_DESC64_PC_HI12 139
BFD_RELOC_LARCH_TLS_DESC64_PC_LO20 139
BFD_RELOC_LARCH_TLS_DTPMOD32 137
BFD_RELOC_LARCH_TLS_DTPMOD64 137
BFD_RELOC_LARCH_TLS_DTPREL32 137
BFD_RELOC_LARCH_TLS_DTPREL64 137
BFD_RELOC_LARCH_TLS_GD_HI20 138
BFD_RELOC_LARCH_TLS_GD_PC_HI20 138
BFD_RELOC_LARCH_TLS_GD_PCREL20_S2 139
BFD_RELOC_LARCH_TLS_IE_HI20 138
BFD_RELOC_LARCH_TLS_IE_LO12 138
BFD_RELOC_LARCH_TLS_IE_PC_HI20 138
BFD_RELOC_LARCH_TLS_IE_PC_LO12 138
BFD_RELOC_LARCH_TLS_IE64_HI12 138
BFD_RELOC_LARCH_TLS_IE64_LO20 138
BFD_RELOC_LARCH_TLS_IE64_PC_HI12 138
BFD_RELOC_LARCH_TLS_IE64_PC_LO20 138
BFD_RELOC_LARCH_TLS_LD_HI20 138
BFD_RELOC_LARCH_TLS_LD_PC_HI20 138
BFD_RELOC_LARCH_TLS_LD_PCREL20_S2 139
BFD_RELOC_LARCH_TLS_LE_ADD_R 139
BFD_RELOC_LARCH_TLS_LE_HI20 138
BFD_RELOC_LARCH_TLS_LE_HI20_R 139
BFD_RELOC_LARCH_TLS_LE_LO12 138
BFD_RELOC_LARCH_TLS_LE_LO12_R 139
BFD_RELOC_LARCH_TLS_LE64_HI12 138
BFD_RELOC_LARCH_TLS_LE64_LO20 138
BFD_RELOC_LARCH_TLS_TPREL32 137
BFD_RELOC_LARCH_TLS_TPREL64 137
BFD_RELOC_LM32_16_GOT 117
BFD_RELOC_LM32_BRANCH 117
BFD_RELOC_LM32_CALL 117
BFD_RELOC_LM32_COPY 117
BFD_RELOC_LM32_GLOB_DAT 117
BFD_RELOC_LM32_GOTOFF_HI16 117
BFD_RELOC_LM32_GOTOFF_LO16 117
BFD_RELOC_LM32_JMP_SLOT 117
BFD_RELOC_LM32_RELATIVE 117
BFD_RELOC_LO10 60
BFD_RELOC_LO16 64
BFD_RELOC_LO16_BASEREL 59
BFD_RELOC_LO16_GOTOFF 59
BFD_RELOC_LO16_PCREL 65
BFD_RELOC_LO16_PLTOFF 59
BFD_RELOC_M32C_HI8 86
BFD_RELOC_M32C_RL_1ADDR 86
BFD_RELOC_M32C_RL_2ADDR 86
BFD_RELOC_M32C_RL_JUMP 86
BFD_RELOC_M32R_10_PCREL 86
BFD_RELOC_M32R_18_PCREL 86
BFD_RELOC_M32R_24 86
BFD_RELOC_M32R_26_PCREL 86
BFD_RELOC_M32R_26_PLTREL 86
BFD_RELOC_M32R_COPY 86
BFD_RELOC_M32R_GLOB_DAT 86
BFD_RELOC_M32R_GOT16_HI_SLO 86
BFD_RELOC_M32R_GOT16_HI_ULO 86
BFD_RELOC_M32R_GOT16_LO 86
BFD_RELOC_M32R_GOT24 86
BFD_RELOC_M32R_GOTOFF 86
BFD_RELOC_M32R_GOTOFF_HI_SLO 86
BFD_RELOC_M32R_GOTOFF_HI_ULO 86
BFD_RELOC_M32R_GOTOFF_LO 86
BFD_RELOC_M32R_GOTPC_HI_SLO 86
BFD_RELOC_M32R_GOTPC_HI_ULO 86
BFD_RELOC_M32R_GOTPC_LO 86
BFD_RELOC_M32R_GOTPC24 86
BFD_RELOC_M32R_HI16_SLO 86

BFD_RELOC_M32R_HI16_ULO 86
BFD_RELOC_M32R_JMP_SLOT 86
BFD_RELOC_M32R_LO16 86
BFD_RELOC_M32R_RELATIVE 86
BFD_RELOC_M32R_SDA16 86
BFD_RELOC_M68HC11_24 108
BFD_RELOC_M68HC11_3B 107
BFD_RELOC_M68HC11_HI8 107
BFD_RELOC_M68HC11_LO16 108
BFD_RELOC_M68HC11_LO8 107
BFD_RELOC_M68HC11_PAGE 108
BFD_RELOC_M68HC11_RL_GROUP 108
BFD_RELOC_M68HC11_RL_JUMP 108
BFD_RELOC_M68HC12_10_PCREL 109
BFD_RELOC_M68HC12_16B 109
BFD_RELOC_M68HC12_5B 108
BFD_RELOC_M68HC12_9_PCREL 109
BFD_RELOC_M68HC12_9B 109
BFD_RELOC_M68HC12_HI8XG 109
BFD_RELOC_M68HC12_LO8XG 109
BFD_RELOC_MACH_O_ARM64_ADDEND 118
BFD_RELOC_MACH_O_ARM64_GOT_LOAD_PAGE21 ... 118
BFD_RELOC_MACH_O_ARM64_GOT_LOAD_
PAGEOFF12 118
BFD_RELOC_MACH_O_ARM64_POINTER_TO_GOT 118
BFD_RELOC_MACH_O_LOCAL_SECTDIFF 118
BFD_RELOC_MACH_O_PAIR 118
BFD_RELOC_MACH_O_SECTDIFF 117
BFD_RELOC_MACH_O_SUBTRACTOR32 118
BFD_RELOC_MACH_O_SUBTRACTOR64 118
BFD_RELOC_MACH_O_X86_64_BRANCH32 118
BFD_RELOC_MACH_O_X86_64_BRANCH8 118
BFD_RELOC_MACH_O_X86_64_GOT 118
BFD_RELOC_MACH_O_X86_64_GOT_LOAD 118
BFD_RELOC_MACH_O_X86_64_PCREL32_1 118
BFD_RELOC_MACH_O_X86_64_PCREL32_2 118
BFD_RELOC_MACH_O_X86_64_PCREL32_4 118
BFD_RELOC_MACH_O_X86_64_TLV 118
BFD_RELOC_MCORE_PCREL_32 95
BFD_RELOC_MCORE_PCREL_IMM11BY2 95
BFD_RELOC_MCORE_PCREL_IMM4BY2 95
BFD_RELOC_MCORE_PCREL_IMM8BY4 95
BFD_RELOC_MCORE_PCREL_JSR_IMM11BY2 95
BFD_RELOC_MCORE_RVA 95
BFD_RELOC_MEP_16 95
BFD_RELOC_MEP_32 95
BFD_RELOC_MEP_8 95
BFD_RELOC_MEP_ADDR24A4 95
BFD_RELOC_MEP_GNU_VTENTRY 95
BFD_RELOC_MEP_GNU_VTINHERIT 95
BFD_RELOC_MEP_GPREL 95
BFD_RELOC_MEP_HI16S 95
BFD_RELOC_MEP_HI16U 95
BFD_RELOC_MEP_LOW16 95
BFD_RELOC_MEP_PCABS24A2 95
BFD_RELOC_MEP_PCREL12A2 95
BFD_RELOC_MEP_PCREL17A2 95
BFD_RELOC_MEP_PCREL24A2 95
BFD_RELOC_MEP_PCREL8A2 95
BFD_RELOC_MEP_TPREL 95
BFD_RELOC_MEP_TPREL7 95
BFD_RELOC_MEP_TPREL7A2 95
BFD_RELOC_MEP_TPREL7A4 95
BFD_RELOC_MEP_UIMM24 95
BFD_RELOC_METAG_COPY 96
BFD_RELOC_METAG_GETSET_GOT 95
BFD_RELOC_METAG_GETSET_GOTOFF 95
BFD_RELOC_METAG_GETSETOFF 95
BFD_RELOC_METAG_GLOB_DAT 96
BFD_RELOC_METAG_GOTOFF 95
BFD_RELOC_METAG_HI16_GOTOFF 95
BFD_RELOC_METAG_HI16_GOTPC 95
BFD_RELOC_METAG_HI16_PLT 95
BFD_RELOC_METAG_HIADDR16 95
BFD_RELOC_METAG_HIOG 95
BFD_RELOC_METAG_JMP_SLOT 96
BFD_RELOC_METAG_LO16_GOTOFF 95
BFD_RELOC_METAG_LO16_GOTPC 95
BFD_RELOC_METAG_LO16_PLT 95
BFD_RELOC_METAG_LOADDR16 95
BFD_RELOC_METAG_LOOG 95
BFD_RELOC_METAG_PLT 95
BFD_RELOC_METAG_REL16 95
BFD_RELOC_METAG_REL8 95
BFD_RELOC_METAG_RELATIVE 96
BFD_RELOC_METAG_RELBRANCH 95
BFD_RELOC_METAG_RELBRANCH_PLT 95
BFD_RELOC_METAG_TLS_DTPMOD 96
BFD_RELOC_METAG_TLS_DTPOFF 96
BFD_RELOC_METAG_TLS_GD 96
BFD_RELOC_METAG_TLS_IE 96
BFD_RELOC_METAG_TLS_IENONPIC 96
BFD_RELOC_METAG_TLS_IENONPIC_HI16 96
BFD_RELOC_METAG_TLS_IENONPIC_LO16 96
BFD_RELOC_METAG_TLS_LDM 96
BFD_RELOC_METAG_TLS_LDO 96
BFD_RELOC_METAG_TLS_LDO_HI16 96
BFD_RELOC_METAG_TLS_LDO_LO16 96
BFD_RELOC_METAG_TLS_LE 96
BFD_RELOC_METAG_TLS_LE_HI16 96
BFD_RELOC_METAG_TLS_LE_LO16 96
BFD_RELOC_METAG_TLS_TPOFF 96
BFD_RELOC_MICROBLAZE_32_GOTOFF 119
BFD_RELOC_MICROBLAZE_32_LO 118
BFD_RELOC_MICROBLAZE_32_LO_PCREL 118
BFD_RELOC_MICROBLAZE_32_NONE 119
BFD_RELOC_MICROBLAZE_32_ROSDA 119
BFD_RELOC_MICROBLAZE_32_RWSDA 119
BFD_RELOC_MICROBLAZE_32_SYM_OP_SYM 119
BFD_RELOC_MICROBLAZE_32_TLSDTPMOD 120
BFD_RELOC_MICROBLAZE_32_TLSDTPREL 120
BFD_RELOC_MICROBLAZE_64_GOT 119
BFD_RELOC_MICROBLAZE_64_GOTOFF 119
BFD_RELOC_MICROBLAZE_64_GOTPC 119
BFD_RELOC_MICROBLAZE_64_NONE 119
BFD_RELOC_MICROBLAZE_64_PLT 119

BFD_RELOC_MICROBLAZE_64_TEXTPCREL 120
BFD_RELOC_MICROBLAZE_64_TEXTREL 120
BFD_RELOC_MICROBLAZE_64_TLS 119
BFD_RELOC_MICROBLAZE_64_TLSDTPREL 120
BFD_RELOC_MICROBLAZE_64_TLSGD 119
BFD_RELOC_MICROBLAZE_64_TLSGOTTPREL 120
BFD_RELOC_MICROBLAZE_64_TLSLD 120
BFD_RELOC_MICROBLAZE_64_TLSTPREL 120
BFD_RELOC_MICROBLAZE_COPY 119
BFD_RELOC_MICROMIPS_10_PCREL_S1 65
BFD_RELOC_MICROMIPS_16_PCREL_S1 65
BFD_RELOC_MICROMIPS_7_PCREL_S1 65
BFD_RELOC_MICROMIPS_CALL_HI16 66
BFD_RELOC_MICROMIPS_CALL_LO16 66
BFD_RELOC_MICROMIPS_CALL16 66
BFD_RELOC_MICROMIPS_GOT_DISP 66
BFD_RELOC_MICROMIPS_GOT_HI16 66
BFD_RELOC_MICROMIPS_GOT_LO16 66
BFD_RELOC_MICROMIPS_GOT_OFST 66
BFD_RELOC_MICROMIPS_GOT_PAGE 66
BFD_RELOC_MICROMIPS_GOT16 66
BFD_RELOC_MICROMIPS_GPREL16 66
BFD_RELOC_MICROMIPS_HI16 66
BFD_RELOC_MICROMIPS_HI16_S 66
BFD_RELOC_MICROMIPS_HIGHER 66
BFD_RELOC_MICROMIPS_HIGHEST 66
BFD_RELOC_MICROMIPS_JALR 66
BFD_RELOC_MICROMIPS_JMP 64
BFD_RELOC_MICROMIPS_LITERAL 65
BFD_RELOC_MICROMIPS_LO16 66
BFD_RELOC_MICROMIPS_SCN_DISP 66
BFD_RELOC_MICROMIPS_SUB 66
BFD_RELOC_MICROMIPS_TLS_DTPREL_HI16 67
BFD_RELOC_MICROMIPS_TLS_DTPREL_LO16 67
BFD_RELOC_MICROMIPS_TLS_GD 66
BFD_RELOC_MICROMIPS_TLS_GOTTPREL 67
BFD_RELOC_MICROMIPS_TLS_LDM 67
BFD_RELOC_MICROMIPS_TLS_TPREL_HI16 67
BFD_RELOC_MICROMIPS_TLS_TPREL_LO16 67
BFD_RELOC_MIPS_16 66
BFD_RELOC_MIPS_18_PCREL_S3 65
BFD_RELOC_MIPS_19_PCREL_S2 65
BFD_RELOC_MIPS_21_PCREL_S2 65
BFD_RELOC_MIPS_26_PCREL_S2 65
BFD_RELOC_MIPS_CALL_HI16 66
BFD_RELOC_MIPS_CALL_LO16 66
BFD_RELOC_MIPS_CALL16 66
BFD_RELOC_MIPS_COPY 67
BFD_RELOC_MIPS_DELETE 66
BFD_RELOC_MIPS_EH 67
BFD_RELOC_MIPS_GOT_DISP 66
BFD_RELOC_MIPS_GOT_HI16 66
BFD_RELOC_MIPS_GOT_LO16 66
BFD_RELOC_MIPS_GOT_OFST 66
BFD_RELOC_MIPS_GOT_PAGE 66
BFD_RELOC_MIPS_GOT16 66
BFD_RELOC_MIPS_HIGHER 66
BFD_RELOC_MIPS_HIGHEST 66
BFD_RELOC_MIPS_INSERT_A 66
BFD_RELOC_MIPS_INSERT_B 66
BFD_RELOC_MIPS_JALR 66
BFD_RELOC_MIPS_JMP 64
BFD_RELOC_MIPS_JUMP_SLOT 67
BFD_RELOC_MIPS_LITERAL 65
BFD_RELOC_MIPS_RELGOT 66
BFD_RELOC_MIPS_SCN_DISP 66
BFD_RELOC_MIPS_SHIFT5 66
BFD_RELOC_MIPS_SHIFT6 66
BFD_RELOC_MIPS_SUB 66
BFD_RELOC_MIPS_TLS_DTPMOD32 66
BFD_RELOC_MIPS_TLS_DTPMOD64 66
BFD_RELOC_MIPS_TLS_DTPREL_HI16 67
BFD_RELOC_MIPS_TLS_DTPREL_LO16 67
BFD_RELOC_MIPS_TLS_DTPREL32 66
BFD_RELOC_MIPS_TLS_DTPREL64 66
BFD_RELOC_MIPS_TLS_GD 66
BFD_RELOC_MIPS_TLS_GOTTPREL 67
BFD_RELOC_MIPS_TLS_LDM 66
BFD_RELOC_MIPS_TLS_TPREL_HI16 67
BFD_RELOC_MIPS_TLS_TPREL_LO16 67
BFD_RELOC_MIPS_TLS_TPREL32 67
BFD_RELOC_MIPS_TLS_TPREL64 67
BFD_RELOC_MIPS16_16_PCREL_S1 65
BFD_RELOC_MIPS16_CALL16 65
BFD_RELOC_MIPS16_GOT16 65
BFD_RELOC_MIPS16_GPREL 64
BFD_RELOC_MIPS16_HI16 65
BFD_RELOC_MIPS16_HI16_S 65
BFD_RELOC_MIPS16_JMP 64
BFD_RELOC_MIPS16_LO16 65
BFD_RELOC_MIPS16_TLS_DTPREL_HI16 65
BFD_RELOC_MIPS16_TLS_DTPREL_LO16 65
BFD_RELOC_MIPS16_TLS_GD 65
BFD_RELOC_MIPS16_TLS_GOTTPREL 65
BFD_RELOC_MIPS16_TLS_LDM 65
BFD_RELOC_MIPS16_TLS_TPREL_HI16 65
BFD_RELOC_MIPS16_TLS_TPREL_LO16 65
BFD_RELOC_MMIX_ADDR19 97
BFD_RELOC_MMIX_ADDR27 97
BFD_RELOC_MMIX_BASE_PLUS_OFFSET 97
BFD_RELOC_MMIX_CBRANCH 96
BFD_RELOC_MMIX_CBRANCH_1 96
BFD_RELOC_MMIX_CBRANCH_2 96
BFD_RELOC_MMIX_CBRANCH_3 96
BFD_RELOC_MMIX_CBRANCH_J 96
BFD_RELOC_MMIX_GETA 96
BFD_RELOC_MMIX_GETA_1 96
BFD_RELOC_MMIX_GETA_2 96
BFD_RELOC_MMIX_GETA_3 96
BFD_RELOC_MMIX_JMP 96
BFD_RELOC_MMIX_JMP_1 96
BFD_RELOC_MMIX_JMP_2 96
BFD_RELOC_MMIX_JMP_3 96
BFD_RELOC_MMIX_LOCAL 97
BFD_RELOC_MMIX_PUSHJ 96
BFD_RELOC_MMIX_PUSHJ_1 96

BFD_RELOC_MMIX_PUSHJ_2 96
BFD_RELOC_MMIX_PUSHJ_3 96
BFD_RELOC_MMIX_PUSHJ_STUBBABLE 96
BFD_RELOC_MMIX_REG 97
BFD_RELOC_MMIX_REG_OR_BYTE 97
BFD_RELOC_MN10300_16_PCREL 69
BFD_RELOC_MN10300_32_PCREL 69
BFD_RELOC_MN10300_ALIGN 69
BFD_RELOC_MN10300_COPY 68
BFD_RELOC_MN10300_GLOB_DAT 68
BFD_RELOC_MN10300_GOT16 68
BFD_RELOC_MN10300_GOT24 68
BFD_RELOC_MN10300_GOT32 68
BFD_RELOC_MN10300_GOTOFF24 68
BFD_RELOC_MN10300_JMP_SLOT 69
BFD_RELOC_MN10300_RELATIVE 69
BFD_RELOC_MN10300_SYM_DIFF 69
BFD_RELOC_MN10300_TLS_DTPMOD 69
BFD_RELOC_MN10300_TLS_DTPOFF 69
BFD_RELOC_MN10300_TLS_GD 69
BFD_RELOC_MN10300_TLS_GOTIE 69
BFD_RELOC_MN10300_TLS_IE 69
BFD_RELOC_MN10300_TLS_LD 69
BFD_RELOC_MN10300_TLS_LDO 69
BFD_RELOC_MN10300_TLS_LE 69
BFD_RELOC_MN10300_TLS_TPOFF 69
BFD_RELOC_MOXIE_10_PCREL 67
BFD_RELOC_MSP430_10_PCREL 113
BFD_RELOC_MSP430_16 113
BFD_RELOC_MSP430_16_BYTE 113
BFD_RELOC_MSP430_16_PCREL 113
BFD_RELOC_MSP430_16_PCREL_BYTE 113
BFD_RELOC_MSP430_2X_PCREL 113
BFD_RELOC_MSP430_ABS_HI16 114
BFD_RELOC_MSP430_ABS8 113
BFD_RELOC_MSP430_PREL31 114
BFD_RELOC_MSP430_RL_PCREL 113
BFD_RELOC_MSP430_SET_ULEB128 114
BFD_RELOC_MSP430_SUB_ULEB128 114
BFD_RELOC_MSP430_SYM_DIFF 114
BFD_RELOC_MSP430X_ABS16 114
BFD_RELOC_MSP430X_ABS20_ADR_DST 114
BFD_RELOC_MSP430X_ABS20_ADR_SRC 114
BFD_RELOC_MSP430X_ABS20_EXT_DST 113
BFD_RELOC_MSP430X_ABS20_EXT_ODST 114
BFD_RELOC_MSP430X_ABS20_EXT_SRC 113
BFD_RELOC_MSP430X_PCR16 114
BFD_RELOC_MSP430X_PCR20_CALL 114
BFD_RELOC_MSP430X_PCR20_EXT_DST 113
BFD_RELOC_MSP430X_PCR20_EXT_ODST 113
BFD_RELOC_MSP430X_PCR20_EXT_SRC 113
BFD_RELOC_MT_GNU_VTENTRY 113
BFD_RELOC_MT_GNU_VTINHERIT 113
BFD_RELOC_MT_HI16 113
BFD_RELOC_MT_LO16 113
BFD_RELOC_MT_PC16 113
BFD_RELOC_MT_PCINSN8 113
BFD_RELOC_NDS32_10_UPCREL 89
BFD_RELOC_NDS32_10IFCU_PCREL 90
BFD_RELOC_NDS32_15_FIXED 88
BFD_RELOC_NDS32_15_PCREL 87
BFD_RELOC_NDS32_17_FIXED 88
BFD_RELOC_NDS32_17_PCREL 87
BFD_RELOC_NDS32_17IFC_PCREL 90
BFD_RELOC_NDS32_20 87
BFD_RELOC_NDS32_25_ABS 90
BFD_RELOC_NDS32_25_FIXED 88
BFD_RELOC_NDS32_25_PCREL 87
BFD_RELOC_NDS32_25_PLTREL 88
BFD_RELOC_NDS32_5 89
BFD_RELOC_NDS32_9_FIXED 88
BFD_RELOC_NDS32_9_PCREL 87
BFD_RELOC_NDS32_9_PLTREL 88
BFD_RELOC_NDS32_COPY 88
BFD_RELOC_NDS32_DATA 90
BFD_RELOC_NDS32_DIFF_ULEB128 90
BFD_RELOC_NDS32_DIFF16 90
BFD_RELOC_NDS32_DIFF32 90
BFD_RELOC_NDS32_DIFF8 90
BFD_RELOC_NDS32_DWARF2_LEB 89
BFD_RELOC_NDS32_DWARF2_OP1 89
BFD_RELOC_NDS32_DWARF2_OP2 89
BFD_RELOC_NDS32_EMPTY 90
BFD_RELOC_NDS32_GLOB_DAT 88
BFD_RELOC_NDS32_GOT_HI20 88
BFD_RELOC_NDS32_GOT_LO12 88
BFD_RELOC_NDS32_GOT_LO15 89
BFD_RELOC_NDS32_GOT_LO19 89
BFD_RELOC_NDS32_GOT_SUFF 90
BFD_RELOC_NDS32_GOT15S2 89
BFD_RELOC_NDS32_GOT17S2 89
BFD_RELOC_NDS32_GOT20 88
BFD_RELOC_NDS32_GOTOFF 88
BFD_RELOC_NDS32_GOTOFF_HI20 88
BFD_RELOC_NDS32_GOTOFF_LO12 88
BFD_RELOC_NDS32_GOTOFF_LO15 89
BFD_RELOC_NDS32_GOTOFF_LO19 89
BFD_RELOC_NDS32_GOTOFF_SUFF 90
BFD_RELOC_NDS32_GOTPC_HI20 88
BFD_RELOC_NDS32_GOTPC_LO12 88
BFD_RELOC_NDS32_GOTPC20 88
BFD_RELOC_NDS32_GOTTPOFF 90
BFD_RELOC_NDS32_GROUP 91
BFD_RELOC_NDS32_HI20 87
BFD_RELOC_NDS32_INSN16 88
BFD_RELOC_NDS32_JMP_SLOT 88
BFD_RELOC_NDS32_LABEL 88
BFD_RELOC_NDS32_LO12S0 87
BFD_RELOC_NDS32_LO12S0_ORI 87
BFD_RELOC_NDS32_LO12S1 87
BFD_RELOC_NDS32_LO12S2 87
BFD_RELOC_NDS32_LO12S2_DP 89
BFD_RELOC_NDS32_LO12S2_SP 89
BFD_RELOC_NDS32_LO12S3 87
BFD_RELOC_NDS32_LOADSTORE 88
BFD_RELOC_NDS32_LONGCALL1 88

BFD_RELOC_NDS32_LONGCALL2 ... 88
BFD_RELOC_NDS32_LONGCALL3 ... 88
BFD_RELOC_NDS32_LONGCALL4 ... 89
BFD_RELOC_NDS32_LONGCALL5 ... 89
BFD_RELOC_NDS32_LONGCALL6 ... 89
BFD_RELOC_NDS32_LONGJUMP1 ... 88
BFD_RELOC_NDS32_LONGJUMP2 ... 88
BFD_RELOC_NDS32_LONGJUMP3 ... 88
BFD_RELOC_NDS32_LONGJUMP4 ... 89
BFD_RELOC_NDS32_LONGJUMP5 ... 89
BFD_RELOC_NDS32_LONGJUMP6 ... 89
BFD_RELOC_NDS32_LONGJUMP7 ... 89
BFD_RELOC_NDS32_LSI ... 91
BFD_RELOC_NDS32_MINUEND ... 90
BFD_RELOC_NDS32_MULCALL_SUFF ... 90
BFD_RELOC_NDS32_PLT_GOT_SUFF ... 90
BFD_RELOC_NDS32_PLT_GOTREL_HI20 ... 89
BFD_RELOC_NDS32_PLT_GOTREL_LO12 ... 89
BFD_RELOC_NDS32_PLT_GOTREL_LO15 ... 89
BFD_RELOC_NDS32_PLT_GOTREL_LO19 ... 89
BFD_RELOC_NDS32_PLT_GOTREL_LO20 ... 89
BFD_RELOC_NDS32_PLTBLOCK ... 90
BFD_RELOC_NDS32_PLTREL_HI20 ... 89
BFD_RELOC_NDS32_PLTREL_LO12 ... 89
BFD_RELOC_NDS32_PTR ... 90
BFD_RELOC_NDS32_PTR_COUNT ... 90
BFD_RELOC_NDS32_PTR_RESOLVED ... 90
BFD_RELOC_NDS32_RELATIVE ... 88
BFD_RELOC_NDS32_RELAX_ENTRY ... 90
BFD_RELOC_NDS32_RELAX_REGION_BEGIN ... 90
BFD_RELOC_NDS32_RELAX_REGION_END ... 90
BFD_RELOC_NDS32_REMOVE ... 91
BFD_RELOC_NDS32_SDA_FP7U2_RELA ... 89
BFD_RELOC_NDS32_SDA12S2_DP ... 89
BFD_RELOC_NDS32_SDA12S2_SP ... 89
BFD_RELOC_NDS32_SDA15S0 ... 88
BFD_RELOC_NDS32_SDA15S1 ... 87
BFD_RELOC_NDS32_SDA15S2 ... 87
BFD_RELOC_NDS32_SDA15S3 ... 87
BFD_RELOC_NDS32_SDA16S3 ... 88
BFD_RELOC_NDS32_SDA17S2 ... 88
BFD_RELOC_NDS32_SDA18S1 ... 88
BFD_RELOC_NDS32_SDA19S0 ... 88
BFD_RELOC_NDS32_SUBTRAHEND ... 90
BFD_RELOC_NDS32_TLS_DESC ... 90
BFD_RELOC_NDS32_TLS_DESC_20 ... 91
BFD_RELOC_NDS32_TLS_DESC_ADD ... 91
BFD_RELOC_NDS32_TLS_DESC_CALL ... 91
BFD_RELOC_NDS32_TLS_DESC_FUNC ... 91
BFD_RELOC_NDS32_TLS_DESC_HI20 ... 90
BFD_RELOC_NDS32_TLS_DESC_LO12 ... 90
BFD_RELOC_NDS32_TLS_DESC_MEM ... 91
BFD_RELOC_NDS32_TLS_DESC_SDA17S2 ... 91
BFD_RELOC_NDS32_TLS_IE_HI20 ... 90
BFD_RELOC_NDS32_TLS_IE_LO12 ... 90
BFD_RELOC_NDS32_TLS_IE_LO12S2 ... 90
BFD_RELOC_NDS32_TLS_IEGP_HI20 ... 90
BFD_RELOC_NDS32_TLS_IEGP_LO12 ... 90
BFD_RELOC_NDS32_TLS_IEGP_LO12S2 ... 90
BFD_RELOC_NDS32_TLS_IEGP_LW ... 90
BFD_RELOC_NDS32_TLS_LE_15S0 ... 90
BFD_RELOC_NDS32_TLS_LE_15S1 ... 90
BFD_RELOC_NDS32_TLS_LE_15S2 ... 90
BFD_RELOC_NDS32_TLS_LE_20 ... 90
BFD_RELOC_NDS32_TLS_LE_ADD ... 90
BFD_RELOC_NDS32_TLS_LE_HI20 ... 90
BFD_RELOC_NDS32_TLS_LE_LO12 ... 90
BFD_RELOC_NDS32_TLS_LE_LS ... 90
BFD_RELOC_NDS32_TPOFF ... 90
BFD_RELOC_NDS32_TRAN ... 90
BFD_RELOC_NDS32_UPDATE_TA ... 89
BFD_RELOC_NDS32_WORD_9_PCREL ... 87
BFD_RELOC_NONE ... 60
BFD_RELOC_NS32K_DISP_16 ... 71
BFD_RELOC_NS32K_DISP_16_PCREL ... 71
BFD_RELOC_NS32K_DISP_32 ... 71
BFD_RELOC_NS32K_DISP_32_PCREL ... 71
BFD_RELOC_NS32K_DISP_8 ... 71
BFD_RELOC_NS32K_DISP_8_PCREL ... 71
BFD_RELOC_NS32K_IMM_16 ... 71
BFD_RELOC_NS32K_IMM_16_PCREL ... 71
BFD_RELOC_NS32K_IMM_32 ... 71
BFD_RELOC_NS32K_IMM_32_PCREL ... 71
BFD_RELOC_NS32K_IMM_8 ... 71
BFD_RELOC_NS32K_IMM_8_PCREL ... 71
BFD_RELOC_OR1K_COPY ... 112
BFD_RELOC_OR1K_GLOB_DAT ... 112
BFD_RELOC_OR1K_GOT_AHI16 ... 112
BFD_RELOC_OR1K_GOT_LO13 ... 112
BFD_RELOC_OR1K_GOT_PG21 ... 112
BFD_RELOC_OR1K_GOT16 ... 112
BFD_RELOC_OR1K_GOTOFF_SLO16 ... 112
BFD_RELOC_OR1K_GOTPC_HI16 ... 112
BFD_RELOC_OR1K_GOTPC_LO16 ... 112
BFD_RELOC_OR1K_JMP_SLOT ... 112
BFD_RELOC_OR1K_LO13 ... 112
BFD_RELOC_OR1K_PCREL_PG21 ... 112
BFD_RELOC_OR1K_PLT26 ... 112
BFD_RELOC_OR1K_PLTA26 ... 112
BFD_RELOC_OR1K_REL_26 ... 112
BFD_RELOC_OR1K_RELATIVE ... 112
BFD_RELOC_OR1K_SLO13 ... 112
BFD_RELOC_OR1K_SLO16 ... 112
BFD_RELOC_OR1K_TLS_DTPMOD ... 112
BFD_RELOC_OR1K_TLS_DTPOFF ... 112
BFD_RELOC_OR1K_TLS_GD_HI16 ... 112
BFD_RELOC_OR1K_TLS_GD_LO13 ... 112
BFD_RELOC_OR1K_TLS_GD_LO16 ... 112
BFD_RELOC_OR1K_TLS_GD_PG21 ... 112
BFD_RELOC_OR1K_TLS_IE_AHI16 ... 112
BFD_RELOC_OR1K_TLS_IE_HI16 ... 112
BFD_RELOC_OR1K_TLS_IE_LO13 ... 112
BFD_RELOC_OR1K_TLS_IE_LO16 ... 112
BFD_RELOC_OR1K_TLS_IE_PG21 ... 112
BFD_RELOC_OR1K_TLS_LDM_HI16 ... 112
BFD_RELOC_OR1K_TLS_LDM_LO13 ... 112

BFD_RELOC_OR1K_TLS_LDM_LO16 112
BFD_RELOC_OR1K_TLS_LDM_PG21 112
BFD_RELOC_OR1K_TLS_LDO_HI16 112
BFD_RELOC_OR1K_TLS_LDO_LO16 112
BFD_RELOC_OR1K_TLS_LE_AHI16 112
BFD_RELOC_OR1K_TLS_LE_HI16 112
BFD_RELOC_OR1K_TLS_LE_LO16 112
BFD_RELOC_OR1K_TLS_LE_SLO16 112
BFD_RELOC_OR1K_TLS_TPOFF 112
BFD_RELOC_PDP11_DISP_6_PCREL 71
BFD_RELOC_PDP11_DISP_8_PCREL 71
BFD_RELOC_PJ_CODE_DIR16 71
BFD_RELOC_PJ_CODE_DIR32 71
BFD_RELOC_PJ_CODE_HI16 71
BFD_RELOC_PJ_CODE_LO16 71
BFD_RELOC_PJ_CODE_REL16 71
BFD_RELOC_PJ_CODE_REL32 71
BFD_RELOC_PPC_16DX_HA 72
BFD_RELOC_PPC_B16 71
BFD_RELOC_PPC_B16_BRNTAKEN 71
BFD_RELOC_PPC_B16_BRTAKEN 71
BFD_RELOC_PPC_B26 71
BFD_RELOC_PPC_BA16 71
BFD_RELOC_PPC_BA16_BRNTAKEN 71
BFD_RELOC_PPC_BA16_BRTAKEN 71
BFD_RELOC_PPC_BA26 71
BFD_RELOC_PPC_COPY 71
BFD_RELOC_PPC_DTPMOD 74
BFD_RELOC_PPC_DTPREL 74
BFD_RELOC_PPC_DTPREL16 74
BFD_RELOC_PPC_DTPREL16_HA 74
BFD_RELOC_PPC_DTPREL16_HI 74
BFD_RELOC_PPC_DTPREL16_LO 74
BFD_RELOC_PPC_EMB_BIT_FLD 72
BFD_RELOC_PPC_EMB_MRKREF 72
BFD_RELOC_PPC_EMB_NADDR16 71
BFD_RELOC_PPC_EMB_NADDR16_HA 72
BFD_RELOC_PPC_EMB_NADDR16_HI 72
BFD_RELOC_PPC_EMB_NADDR16_LO 71
BFD_RELOC_PPC_EMB_NADDR32 71
BFD_RELOC_PPC_EMB_RELSDA 72
BFD_RELOC_PPC_EMB_RELSEC16 72
BFD_RELOC_PPC_EMB_RELST_HA 72
BFD_RELOC_PPC_EMB_RELST_HI 72
BFD_RELOC_PPC_EMB_RELST_LO 72
BFD_RELOC_PPC_EMB_SDA21 72
BFD_RELOC_PPC_EMB_SDA2I16 72
BFD_RELOC_PPC_EMB_SDA2REL 72
BFD_RELOC_PPC_EMB_SDAI16 72
BFD_RELOC_PPC_GLOB_DAT 71
BFD_RELOC_PPC_GOT_DTPREL16 74
BFD_RELOC_PPC_GOT_DTPREL16_HA 74
BFD_RELOC_PPC_GOT_DTPREL16_HI 74
BFD_RELOC_PPC_GOT_DTPREL16_LO 74
BFD_RELOC_PPC_GOT_TLSGD16 74
BFD_RELOC_PPC_GOT_TLSGD16_HA 74
BFD_RELOC_PPC_GOT_TLSGD16_HI 74
BFD_RELOC_PPC_GOT_TLSGD16_LO 74
BFD_RELOC_PPC_GOT_TLSLD16 74
BFD_RELOC_PPC_GOT_TLSLD16_HA 74
BFD_RELOC_PPC_GOT_TLSLD16_HI 74
BFD_RELOC_PPC_GOT_TLSLD16_LO 74
BFD_RELOC_PPC_GOT_TPREL16 74
BFD_RELOC_PPC_GOT_TPREL16_HA 74
BFD_RELOC_PPC_GOT_TPREL16_HI 74
BFD_RELOC_PPC_GOT_TPREL16_LO 74
BFD_RELOC_PPC_JMP_SLOT 71
BFD_RELOC_PPC_LOCAL24PC 71
BFD_RELOC_PPC_NEG 72
BFD_RELOC_PPC_REL16DX_HA 72
BFD_RELOC_PPC_RELATIVE 71
BFD_RELOC_PPC_TLS 73
BFD_RELOC_PPC_TLSGD 73
BFD_RELOC_PPC_TLSIE 73
BFD_RELOC_PPC_TLSLD 73
BFD_RELOC_PPC_TLSLE 73
BFD_RELOC_PPC_TLSM 73
BFD_RELOC_PPC_TLSML 73
BFD_RELOC_PPC_TOC16 71
BFD_RELOC_PPC_TOC16_HI 71
BFD_RELOC_PPC_TOC16_LO 71
BFD_RELOC_PPC_TPREL 74
BFD_RELOC_PPC_TPREL16 74
BFD_RELOC_PPC_TPREL16_HA 74
BFD_RELOC_PPC_TPREL16_HI 74
BFD_RELOC_PPC_TPREL16_LO 74
BFD_RELOC_PPC_VLE_HA16A 72
BFD_RELOC_PPC_VLE_HA16D 72
BFD_RELOC_PPC_VLE_HI16A 72
BFD_RELOC_PPC_VLE_HI16D 72
BFD_RELOC_PPC_VLE_LO16A 72
BFD_RELOC_PPC_VLE_LO16D 72
BFD_RELOC_PPC_VLE_REL15 72
BFD_RELOC_PPC_VLE_REL24 72
BFD_RELOC_PPC_VLE_REL8 72
BFD_RELOC_PPC_VLE_SDA21 72
BFD_RELOC_PPC_VLE_SDA21_LO 72
BFD_RELOC_PPC_VLE_SDAREL_HA16A 72
BFD_RELOC_PPC_VLE_SDAREL_HA16D 72
BFD_RELOC_PPC_VLE_SDAREL_HI16A 72
BFD_RELOC_PPC_VLE_SDAREL_HI16D 72
BFD_RELOC_PPC_VLE_SDAREL_LO16A 72
BFD_RELOC_PPC_VLE_SDAREL_LO16D 72
BFD_RELOC_PPC64_ADDR16_DS 72
BFD_RELOC_PPC64_ADDR16_HIGH 73
BFD_RELOC_PPC64_ADDR16_HIGHA 73
BFD_RELOC_PPC64_ADDR16_HIGHER34 73
BFD_RELOC_PPC64_ADDR16_HIGHERA34 73
BFD_RELOC_PPC64_ADDR16_HIGHEST34 73
BFD_RELOC_PPC64_ADDR16_HIGHESTA34 73
BFD_RELOC_PPC64_ADDR16_LO_DS 72
BFD_RELOC_PPC64_ADDR64_LOCAL 73
BFD_RELOC_PPC64_D28 73
BFD_RELOC_PPC64_D34 73
BFD_RELOC_PPC64_D34_HA30 73
BFD_RELOC_PPC64_D34_HI30 73

BFD_RELOC_PPC64_D34_LO 73
BFD_RELOC_PPC64_DTPREL16_DS 74
BFD_RELOC_PPC64_DTPREL16_HIGH 74
BFD_RELOC_PPC64_DTPREL16_HIGHA 74
BFD_RELOC_PPC64_DTPREL16_HIGHER 74
BFD_RELOC_PPC64_DTPREL16_HIGHERA 74
BFD_RELOC_PPC64_DTPREL16_HIGHEST 75
BFD_RELOC_PPC64_DTPREL16_HIGHESTA 75
BFD_RELOC_PPC64_DTPREL16_LO_DS 74
BFD_RELOC_PPC64_DTPREL34 75
BFD_RELOC_PPC64_ENTRY 73
BFD_RELOC_PPC64_GOT_DTPREL_PCREL34 75
BFD_RELOC_PPC64_GOT_PCREL34 73
BFD_RELOC_PPC64_GOT_TLSGD_PCREL34 75
BFD_RELOC_PPC64_GOT_TLSLD_PCREL34 75
BFD_RELOC_PPC64_GOT_TPREL_PCREL34 75
BFD_RELOC_PPC64_GOT16_DS 73
BFD_RELOC_PPC64_GOT16_LO_DS 73
BFD_RELOC_PPC64_HIGHER 72
BFD_RELOC_PPC64_HIGHER_S 72
BFD_RELOC_PPC64_HIGHEST 72
BFD_RELOC_PPC64_HIGHEST_S 72
BFD_RELOC_PPC64_PCREL28 73
BFD_RELOC_PPC64_PCREL34 73
BFD_RELOC_PPC64_PLT_PCREL34 73
BFD_RELOC_PPC64_PLT16_LO_DS 73
BFD_RELOC_PPC64_PLTGOT16 72
BFD_RELOC_PPC64_PLTGOT16_DS 73
BFD_RELOC_PPC64_PLTGOT16_HA 72
BFD_RELOC_PPC64_PLTGOT16_HI 72
BFD_RELOC_PPC64_PLTGOT16_LO 72
BFD_RELOC_PPC64_PLTGOT16_LO_DS 73
BFD_RELOC_PPC64_REL16_HIGH 73
BFD_RELOC_PPC64_REL16_HIGHA 73
BFD_RELOC_PPC64_REL16_HIGHER 73
BFD_RELOC_PPC64_REL16_HIGHER34 73
BFD_RELOC_PPC64_REL16_HIGHERA 73
BFD_RELOC_PPC64_REL16_HIGHERA34 73
BFD_RELOC_PPC64_REL16_HIGHEST 73
BFD_RELOC_PPC64_REL16_HIGHEST34 73
BFD_RELOC_PPC64_REL16_HIGHESTA 73
BFD_RELOC_PPC64_REL16_HIGHESTA34 73
BFD_RELOC_PPC64_REL24_NOTOC 73
BFD_RELOC_PPC64_REL24_P9NOTOC 73
BFD_RELOC_PPC64_SECTOFF_DS 73
BFD_RELOC_PPC64_SECTOFF_LO_DS 73
BFD_RELOC_PPC64_TLS_PCREL 75
BFD_RELOC_PPC64_TLSGD 74
BFD_RELOC_PPC64_TLSIE 74
BFD_RELOC_PPC64_TLSLD 74
BFD_RELOC_PPC64_TLSLE 74
BFD_RELOC_PPC64_TLSM 74
BFD_RELOC_PPC64_TLSML 74
BFD_RELOC_PPC64_TOC 72
BFD_RELOC_PPC64_TOC16_DS 73
BFD_RELOC_PPC64_TOC16_HA 72
BFD_RELOC_PPC64_TOC16_HI 72
BFD_RELOC_PPC64_TOC16_LO 72
BFD_RELOC_PPC64_TOC16_LO_DS 73
BFD_RELOC_PPC64_TPREL16_DS 74
BFD_RELOC_PPC64_TPREL16_HIGH 74
BFD_RELOC_PPC64_TPREL16_HIGHA 74
BFD_RELOC_PPC64_TPREL16_HIGHER 74
BFD_RELOC_PPC64_TPREL16_HIGHERA 74
BFD_RELOC_PPC64_TPREL16_HIGHEST 74
BFD_RELOC_PPC64_TPREL16_HIGHESTA 74
BFD_RELOC_PPC64_TPREL16_LO_DS 74
BFD_RELOC_PPC64_TPREL34 75
BFD_RELOC_PRU_16_PMEM 114
BFD_RELOC_PRU_32_PMEM 114
BFD_RELOC_PRU_GNU_DIFF16 114
BFD_RELOC_PRU_GNU_DIFF16_PMEM 114
BFD_RELOC_PRU_GNU_DIFF32 114
BFD_RELOC_PRU_GNU_DIFF32_PMEM 114
BFD_RELOC_PRU_GNU_DIFF8 114
BFD_RELOC_PRU_LDI32 114
BFD_RELOC_PRU_S10_PCREL 114
BFD_RELOC_PRU_U16 114
BFD_RELOC_PRU_U16_PMEMIMM 114
BFD_RELOC_PRU_U8_PCREL 114
BFD_RELOC_RELC 113
BFD_RELOC_RISCV_32_PCREL 100
BFD_RELOC_RISCV_ADD16 100
BFD_RELOC_RISCV_ADD32 100
BFD_RELOC_RISCV_ADD64 100
BFD_RELOC_RISCV_ADD8 100
BFD_RELOC_RISCV_ALIGN 100
BFD_RELOC_RISCV_CALL 99
BFD_RELOC_RISCV_CALL_PLT 99
BFD_RELOC_RISCV_CFA 100
BFD_RELOC_RISCV_GOT_HI20 100
BFD_RELOC_RISCV_GPREL12_I 99
BFD_RELOC_RISCV_GPREL12_S 99
BFD_RELOC_RISCV_HI20 99
BFD_RELOC_RISCV_JMP 100
BFD_RELOC_RISCV_LO12_I 99
BFD_RELOC_RISCV_LO12_S 99
BFD_RELOC_RISCV_PCREL_HI20 99
BFD_RELOC_RISCV_PCREL_LO12_I 99
BFD_RELOC_RISCV_PCREL_LO12_S 99
BFD_RELOC_RISCV_RELAX 100
BFD_RELOC_RISCV_RVC_BRANCH 100
BFD_RELOC_RISCV_RVC_JUMP 100
BFD_RELOC_RISCV_SET_ULEB128 100
BFD_RELOC_RISCV_SET16 100
BFD_RELOC_RISCV_SET32 100
BFD_RELOC_RISCV_SET6 100
BFD_RELOC_RISCV_SET8 100
BFD_RELOC_RISCV_SUB_ULEB128 100
BFD_RELOC_RISCV_SUB16 100
BFD_RELOC_RISCV_SUB32 100
BFD_RELOC_RISCV_SUB6 100
BFD_RELOC_RISCV_SUB64 100
BFD_RELOC_RISCV_SUB8 100
BFD_RELOC_RISCV_TLS_DTPMOD32 100
BFD_RELOC_RISCV_TLS_DTPMOD64 100

BFD_RELOC_RISCV_TLS_DTPREL32 100
BFD_RELOC_RISCV_TLS_DTPREL64 100
BFD_RELOC_RISCV_TLS_GD_HI20 100
BFD_RELOC_RISCV_TLS_GOT_HI20 100
BFD_RELOC_RISCV_TLS_TPREL32 100
BFD_RELOC_RISCV_TLS_TPREL64 100
BFD_RELOC_RISCV_TLSDESC_ADD_LO12 100
BFD_RELOC_RISCV_TLSDESC_CALL 100
BFD_RELOC_RISCV_TLSDESC_HI20 100
BFD_RELOC_RISCV_TLSDESC_LOAD_LO12 100
BFD_RELOC_RISCV_TPREL_ADD 99
BFD_RELOC_RISCV_TPREL_HI20 99
BFD_RELOC_RISCV_TPREL_LO12_I 99
BFD_RELOC_RISCV_TPREL_LO12_S 99
BFD_RELOC_RL78_16_OP 100
BFD_RELOC_RL78_16U 100
BFD_RELOC_RL78_24_OP 100
BFD_RELOC_RL78_24U 100
BFD_RELOC_RL78_32_OP 100
BFD_RELOC_RL78_8U 100
BFD_RELOC_RL78_ABS16 101
BFD_RELOC_RL78_ABS16_REV 101
BFD_RELOC_RL78_ABS16U 101
BFD_RELOC_RL78_ABS16UL 101
BFD_RELOC_RL78_ABS16UW 101
BFD_RELOC_RL78_ABS32 101
BFD_RELOC_RL78_ABS32_REV 101
BFD_RELOC_RL78_ABS8 101
BFD_RELOC_RL78_CODE 101
BFD_RELOC_RL78_DIFF 101
BFD_RELOC_RL78_DIR3U_PCREL 101
BFD_RELOC_RL78_GPRELB 101
BFD_RELOC_RL78_GPRELL 101
BFD_RELOC_RL78_GPRELW 101
BFD_RELOC_RL78_HI16 101
BFD_RELOC_RL78_HI8 101
BFD_RELOC_RL78_LO16 101
BFD_RELOC_RL78_NEG16 100
BFD_RELOC_RL78_NEG24 100
BFD_RELOC_RL78_NEG32 100
BFD_RELOC_RL78_NEG8 100
BFD_RELOC_RL78_OP_AND 101
BFD_RELOC_RL78_OP_NEG 101
BFD_RELOC_RL78_OP_SHRA 101
BFD_RELOC_RL78_OP_SUBTRACT 101
BFD_RELOC_RL78_RELAX 101
BFD_RELOC_RL78_SADDR 101
BFD_RELOC_RL78_SYM 101
BFD_RELOC_RVA 60
BFD_RELOC_RX_16_OP 101
BFD_RELOC_RX_16U 101
BFD_RELOC_RX_24_OP 101
BFD_RELOC_RX_24U 101
BFD_RELOC_RX_32_OP 101
BFD_RELOC_RX_8U 101
BFD_RELOC_RX_ABS16 101
BFD_RELOC_RX_ABS16_REV 101
BFD_RELOC_RX_ABS16U 102
BFD_RELOC_RX_ABS16UL 102
BFD_RELOC_RX_ABS16UW 102
BFD_RELOC_RX_ABS32 102
BFD_RELOC_RX_ABS32_REV 102
BFD_RELOC_RX_ABS8 101
BFD_RELOC_RX_DIFF 101
BFD_RELOC_RX_DIR3U_PCREL 101
BFD_RELOC_RX_GPRELB 101
BFD_RELOC_RX_GPRELL 101
BFD_RELOC_RX_GPRELW 101
BFD_RELOC_RX_NEG16 101
BFD_RELOC_RX_NEG24 101
BFD_RELOC_RX_NEG32 101
BFD_RELOC_RX_NEG8 101
BFD_RELOC_RX_OP_NEG 101
BFD_RELOC_RX_OP_SUBTRACT 101
BFD_RELOC_RX_RELAX 102
BFD_RELOC_RX_SYM 101
BFD_RELOC_S12Z_15_PCREL 109
BFD_RELOC_S12Z_OPR 137
BFD_RELOC_SCORE_BCMP 104
BFD_RELOC_SCORE_BRANCH 104
BFD_RELOC_SCORE_CALL15 105
BFD_RELOC_SCORE_DUMMY_HI16 105
BFD_RELOC_SCORE_DUMMY2 104
BFD_RELOC_SCORE_GOT_LO16 105
BFD_RELOC_SCORE_GOT15 105
BFD_RELOC_SCORE_GPREL15 104
BFD_RELOC_SCORE_IMM30 104
BFD_RELOC_SCORE_IMM32 104
BFD_RELOC_SCORE_JMP 104
BFD_RELOC_SCORE16_BRANCH 104
BFD_RELOC_SCORE16_JMP 104
BFD_RELOC_SH_ALIGN 79
BFD_RELOC_SH_CODE 79
BFD_RELOC_SH_COPY 79
BFD_RELOC_SH_COPY64 80
BFD_RELOC_SH_COUNT 79
BFD_RELOC_SH_DATA 79
BFD_RELOC_SH_DISP12 79
BFD_RELOC_SH_DISP12BY2 79
BFD_RELOC_SH_DISP12BY4 79
BFD_RELOC_SH_DISP12BY8 79
BFD_RELOC_SH_DISP20 79
BFD_RELOC_SH_DISP20BY8 79
BFD_RELOC_SH_FUNCDESC 81
BFD_RELOC_SH_GLOB_DAT 79
BFD_RELOC_SH_GLOB_DAT64 80
BFD_RELOC_SH_GOT_HI16 79
BFD_RELOC_SH_GOT_LOW16 79
BFD_RELOC_SH_GOT_MEDHI16 79
BFD_RELOC_SH_GOT_MEDLOW16 79
BFD_RELOC_SH_GOT10BY4 80
BFD_RELOC_SH_GOT10BY8 80
BFD_RELOC_SH_GOT20 81
BFD_RELOC_SH_GOTFUNCDESC 81
BFD_RELOC_SH_GOTFUNCDESC20 81
BFD_RELOC_SH_GOTOFF_HI16 80

BFD_RELOC_SH_GOTOFF_LOW16 80
BFD_RELOC_SH_GOTOFF_MEDHI16 80
BFD_RELOC_SH_GOTOFF_MEDLOW16 80
BFD_RELOC_SH_GOTOFF20 81
BFD_RELOC_SH_GOTOFFFUNCDESC 81
BFD_RELOC_SH_GOTOFFFUNCDESC20 81
BFD_RELOC_SH_GOTPC 79
BFD_RELOC_SH_GOTPC_HI16 80
BFD_RELOC_SH_GOTPC_LOW16 80
BFD_RELOC_SH_GOTPC_MEDHI16 80
BFD_RELOC_SH_GOTPC_MEDLOW16 80
BFD_RELOC_SH_GOTPLT_HI16 80
BFD_RELOC_SH_GOTPLT_LOW16 79
BFD_RELOC_SH_GOTPLT_MEDHI16 80
BFD_RELOC_SH_GOTPLT_MEDLOW16 79
BFD_RELOC_SH_GOTPLT10BY4 80
BFD_RELOC_SH_GOTPLT10BY8 80
BFD_RELOC_SH_GOTPLT32 80
BFD_RELOC_SH_IMM_HI16 80
BFD_RELOC_SH_IMM_HI16_PCREL 80
BFD_RELOC_SH_IMM_LOW16 80
BFD_RELOC_SH_IMM_LOW16_PCREL 80
BFD_RELOC_SH_IMM_MEDHI16 80
BFD_RELOC_SH_IMM_MEDHI16_PCREL 80
BFD_RELOC_SH_IMM_MEDLOW16 80
BFD_RELOC_SH_IMM_MEDLOW16_PCREL 80
BFD_RELOC_SH_IMM3 79
BFD_RELOC_SH_IMM3U 79
BFD_RELOC_SH_IMM4 79
BFD_RELOC_SH_IMM4BY2 79
BFD_RELOC_SH_IMM4BY4 79
BFD_RELOC_SH_IMM8 79
BFD_RELOC_SH_IMM8BY2 79
BFD_RELOC_SH_IMM8BY4 79
BFD_RELOC_SH_IMMS10 80
BFD_RELOC_SH_IMMS10BY2 80
BFD_RELOC_SH_IMMS10BY4 80
BFD_RELOC_SH_IMMS10BY8 80
BFD_RELOC_SH_IMMS16 80
BFD_RELOC_SH_IMMS6 80
BFD_RELOC_SH_IMMS6BY32 80
BFD_RELOC_SH_IMMU16 80
BFD_RELOC_SH_IMMU5 80
BFD_RELOC_SH_IMMU6 80
BFD_RELOC_SH_JMP_SLOT 79
BFD_RELOC_SH_JMP_SLOT64 80
BFD_RELOC_SH_LABEL 79
BFD_RELOC_SH_LOOP_END 79
BFD_RELOC_SH_LOOP_START 79
BFD_RELOC_SH_PCDISP12BY2 79
BFD_RELOC_SH_PCDISP8BY2 79
BFD_RELOC_SH_PCRELIMM8BY2 79
BFD_RELOC_SH_PCRELIMM8BY4 79
BFD_RELOC_SH_PLT_HI16 80
BFD_RELOC_SH_PLT_LOW16 80
BFD_RELOC_SH_PLT_MEDHI16 80
BFD_RELOC_SH_PLT_MEDLOW16 80
BFD_RELOC_SH_PT_16 80
BFD_RELOC_SH_RELATIVE 79
BFD_RELOC_SH_RELATIVE64 80
BFD_RELOC_SH_SHMEDIA_CODE 80
BFD_RELOC_SH_SWITCH16 79
BFD_RELOC_SH_SWITCH32 79
BFD_RELOC_SH_TLS_DTPMOD32 81
BFD_RELOC_SH_TLS_DTPOFF32 81
BFD_RELOC_SH_TLS_GD_32 80
BFD_RELOC_SH_TLS_IE_32 80
BFD_RELOC_SH_TLS_LD_32 80
BFD_RELOC_SH_TLS_LDO_32 80
BFD_RELOC_SH_TLS_LE_32 81
BFD_RELOC_SH_TLS_TPOFF32 81
BFD_RELOC_SH_USES 79
BFD_RELOC_SIZE32 59
BFD_RELOC_SIZE64 59
BFD_RELOC_SPARC_10 61
BFD_RELOC_SPARC_11 61
BFD_RELOC_SPARC_5 61
BFD_RELOC_SPARC_6 61
BFD_RELOC_SPARC_64 61
BFD_RELOC_SPARC_7 61
BFD_RELOC_SPARC_BASE13 61
BFD_RELOC_SPARC_BASE22 61
BFD_RELOC_SPARC_COPY 60
BFD_RELOC_SPARC_DISP64 61
BFD_RELOC_SPARC_GLOB_DAT 60
BFD_RELOC_SPARC_GOT10 60
BFD_RELOC_SPARC_GOT13 60
BFD_RELOC_SPARC_GOT22 60
BFD_RELOC_SPARC_GOTDATA_HIX22 60
BFD_RELOC_SPARC_GOTDATA_LOX10 60
BFD_RELOC_SPARC_GOTDATA_OP 60
BFD_RELOC_SPARC_GOTDATA_OP_HIX22 60
BFD_RELOC_SPARC_GOTDATA_OP_LOX10 60
BFD_RELOC_SPARC_H34 61
BFD_RELOC_SPARC_H44 61
BFD_RELOC_SPARC_HH22 61
BFD_RELOC_SPARC_HIX22 61
BFD_RELOC_SPARC_HM10 61
BFD_RELOC_SPARC_IRELATIVE 61
BFD_RELOC_SPARC_JMP_IREL 61
BFD_RELOC_SPARC_JMP_SLOT 60
BFD_RELOC_SPARC_L44 61
BFD_RELOC_SPARC_LM22 61
BFD_RELOC_SPARC_LOX10 61
BFD_RELOC_SPARC_M44 61
BFD_RELOC_SPARC_OLO10 61
BFD_RELOC_SPARC_PC_HH22 61
BFD_RELOC_SPARC_PC_HM10 61
BFD_RELOC_SPARC_PC_LM22 61
BFD_RELOC_SPARC_PC10 60
BFD_RELOC_SPARC_PC22 60
BFD_RELOC_SPARC_PLT32 61
BFD_RELOC_SPARC_PLT64 61
BFD_RELOC_SPARC_REGISTER 61
BFD_RELOC_SPARC_RELATIVE 60
BFD_RELOC_SPARC_REV32 61

BFD_RELOC_SPARC_SIZE32 61
BFD_RELOC_SPARC_SIZE64 61
BFD_RELOC_SPARC_TLS_DTPMOD32 62
BFD_RELOC_SPARC_TLS_DTPMOD64 62
BFD_RELOC_SPARC_TLS_DTPOFF32 62
BFD_RELOC_SPARC_TLS_DTPOFF64 62
BFD_RELOC_SPARC_TLS_GD_ADD 61
BFD_RELOC_SPARC_TLS_GD_CALL 61
BFD_RELOC_SPARC_TLS_GD_HI22 61
BFD_RELOC_SPARC_TLS_GD_LO10 61
BFD_RELOC_SPARC_TLS_IE_ADD 62
BFD_RELOC_SPARC_TLS_IE_HI22 62
BFD_RELOC_SPARC_TLS_IE_LD 62
BFD_RELOC_SPARC_TLS_IE_LDX 62
BFD_RELOC_SPARC_TLS_IE_LO10 62
BFD_RELOC_SPARC_TLS_LDM_ADD 62
BFD_RELOC_SPARC_TLS_LDM_CALL 62
BFD_RELOC_SPARC_TLS_LDM_HI22 61
BFD_RELOC_SPARC_TLS_LDM_LO10 61
BFD_RELOC_SPARC_TLS_LDO_ADD 62
BFD_RELOC_SPARC_TLS_LDO_HIX22 62
BFD_RELOC_SPARC_TLS_LDO_LOX10 62
BFD_RELOC_SPARC_TLS_LE_HIX22 62
BFD_RELOC_SPARC_TLS_LE_LOX10 62
BFD_RELOC_SPARC_TLS_TPOFF32 62
BFD_RELOC_SPARC_TLS_TPOFF64 62
BFD_RELOC_SPARC_UA16 60
BFD_RELOC_SPARC_UA32 60
BFD_RELOC_SPARC_UA64 60
BFD_RELOC_SPARC_WDISP10 61
BFD_RELOC_SPARC_WDISP16 61
BFD_RELOC_SPARC_WDISP19 61
BFD_RELOC_SPARC_WDISP22 60
BFD_RELOC_SPARC_WPLT30 60
BFD_RELOC_SPARC13 60
BFD_RELOC_SPARC22 60
BFD_RELOC_SPU_ADD_PIC 62
BFD_RELOC_SPU_HI16 62
BFD_RELOC_SPU_IMM10 62
BFD_RELOC_SPU_IMM10W 62
BFD_RELOC_SPU_IMM16 62
BFD_RELOC_SPU_IMM16W 62
BFD_RELOC_SPU_IMM18 62
BFD_RELOC_SPU_IMM7 62
BFD_RELOC_SPU_IMM8 62
BFD_RELOC_SPU_LO16 62
BFD_RELOC_SPU_PCREL16 62
BFD_RELOC_SPU_PCREL9a 62
BFD_RELOC_SPU_PCREL9b 62
BFD_RELOC_SPU_PPU32 62
BFD_RELOC_SPU_PPU64 62
BFD_RELOC_THUMB_PCREL_BFCSEL 75
BFD_RELOC_THUMB_PCREL_BLX 75
BFD_RELOC_THUMB_PCREL_BRANCH12 76
BFD_RELOC_THUMB_PCREL_BRANCH20 76
BFD_RELOC_THUMB_PCREL_BRANCH23 76
BFD_RELOC_THUMB_PCREL_BRANCH25 76
BFD_RELOC_THUMB_PCREL_BRANCH5 75
BFD_RELOC_THUMB_PCREL_BRANCH7 76
BFD_RELOC_THUMB_PCREL_BRANCH9 76
BFD_RELOC_TIC30_LDP 93
BFD_RELOC_TIC54X_16_OF_23 93
BFD_RELOC_TIC54X_23 93
BFD_RELOC_TIC54X_MS7_OF_23 93
BFD_RELOC_TIC54X_PARTLS7 93
BFD_RELOC_TIC54X_PARTMS9 93
BFD_RELOC_TILEGX_BROFF_X1 132
BFD_RELOC_TILEGX_COPY 132
BFD_RELOC_TILEGX_DEST_IMM8_X1 132
BFD_RELOC_TILEGX_GLOB_DAT 132
BFD_RELOC_TILEGX_HW0 132
BFD_RELOC_TILEGX_HW0_LAST 132
BFD_RELOC_TILEGX_HW1 132
BFD_RELOC_TILEGX_HW1_LAST 132
BFD_RELOC_TILEGX_HW2 132
BFD_RELOC_TILEGX_HW2_LAST 132
BFD_RELOC_TILEGX_HW3 132
BFD_RELOC_TILEGX_IMM16_X0_HW0 132
BFD_RELOC_TILEGX_IMM16_X0_HW0_GOT 133
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST 133
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_GOT ... 133
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_PCREL . 133
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_PLT_PCREL 134
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_TLS_GD 133
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_TLS_IE 134
BFD_RELOC_TILEGX_IMM16_X0_HW0_LAST_TLS_LE 133
BFD_RELOC_TILEGX_IMM16_X0_HW0_PCREL 133
BFD_RELOC_TILEGX_IMM16_X0_HW0_PLT_PCREL . 133
BFD_RELOC_TILEGX_IMM16_X0_HW0_TLS_GD 133
BFD_RELOC_TILEGX_IMM16_X0_HW0_TLS_IE 134
BFD_RELOC_TILEGX_IMM16_X0_HW0_TLS_LE 133
BFD_RELOC_TILEGX_IMM16_X0_HW1 132
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST 133
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_GOT ... 133
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_PCREL . 133
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_PLT_PCREL 134
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_TLS_GD 133
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_TLS_IE 134
BFD_RELOC_TILEGX_IMM16_X0_HW1_LAST_TLS_LE 133
BFD_RELOC_TILEGX_IMM16_X0_HW1_PCREL 133
BFD_RELOC_TILEGX_IMM16_X0_HW1_PLT_PCREL . 133
BFD_RELOC_TILEGX_IMM16_X0_HW2 132
BFD_RELOC_TILEGX_IMM16_X0_HW2_LAST 133
BFD_RELOC_TILEGX_IMM16_X0_HW2_LAST_PCREL . 133
BFD_RELOC_TILEGX_IMM16_X0_HW2_LAST_PLT_PCREL 134
BFD_RELOC_TILEGX_IMM16_X0_HW2_PCREL 133
BFD_RELOC_TILEGX_IMM16_X0_HW2_PLT_PCREL . 133

BFD_RELOC_TILEGX_IMM16_X0_HW3 132
BFD_RELOC_TILEGX_IMM16_X0_HW3_PCREL 133
BFD_RELOC_TILEGX_IMM16_X0_HW3_PLT_PCREL . 133
BFD_RELOC_TILEGX_IMM16_X1_HW0 132
BFD_RELOC_TILEGX_IMM16_X1_HW0_GOT 133
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST 133
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_GOT... 133
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_PCREL.133
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_PLT_
PCREL 134
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_TLS_
GD 133
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_TLS_
IE 134
BFD_RELOC_TILEGX_IMM16_X1_HW0_LAST_TLS_
LE 133
BFD_RELOC_TILEGX_IMM16_X1_HW0_PCREL 133
BFD_RELOC_TILEGX_IMM16_X1_HW0_PLT_PCREL . 133
BFD_RELOC_TILEGX_IMM16_X1_HW0_TLS_GD 133
BFD_RELOC_TILEGX_IMM16_X1_HW0_TLS_IE 134
BFD_RELOC_TILEGX_IMM16_X1_HW0_TLS_LE 133
BFD_RELOC_TILEGX_IMM16_X1_HW1 132
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST 133
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_GOT... 133
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_PCREL.133
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_PLT_
PCREL 134
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_TLS_
GD 133
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_TLS_
IE 134
BFD_RELOC_TILEGX_IMM16_X1_HW1_LAST_TLS_
LE 133
BFD_RELOC_TILEGX_IMM16_X1_HW1_PCREL 133
BFD_RELOC_TILEGX_IMM16_X1_HW1_PLT_PCREL . 133
BFD_RELOC_TILEGX_IMM16_X1_HW2 132
BFD_RELOC_TILEGX_IMM16_X1_HW2_LAST 133
BFD_RELOC_TILEGX_IMM16_X1_HW2_LAST_PCREL.133
BFD_RELOC_TILEGX_IMM16_X1_HW2_LAST_PLT_
PCREL 134
BFD_RELOC_TILEGX_IMM16_X1_HW2_PCREL 133
BFD_RELOC_TILEGX_IMM16_X1_HW2_PLT_PCREL . 133
BFD_RELOC_TILEGX_IMM16_X1_HW3 133
BFD_RELOC_TILEGX_IMM16_X1_HW3_PCREL 133
BFD_RELOC_TILEGX_IMM16_X1_HW3_PLT_PCREL . 133
BFD_RELOC_TILEGX_IMM8_X0 132
BFD_RELOC_TILEGX_IMM8_X0_TLS_ADD 134
BFD_RELOC_TILEGX_IMM8_X0_TLS_GD_ADD 134
BFD_RELOC_TILEGX_IMM8_X1 132
BFD_RELOC_TILEGX_IMM8_X1_TLS_ADD 134
BFD_RELOC_TILEGX_IMM8_X1_TLS_GD_ADD 134
BFD_RELOC_TILEGX_IMM8_Y0 132
BFD_RELOC_TILEGX_IMM8_Y0_TLS_ADD 134
BFD_RELOC_TILEGX_IMM8_Y0_TLS_GD_ADD 134
BFD_RELOC_TILEGX_IMM8_Y1 132
BFD_RELOC_TILEGX_IMM8_Y1_TLS_ADD 134
BFD_RELOC_TILEGX_IMM8_Y1_TLS_GD_ADD 134
BFD_RELOC_TILEGX_JMP_SLOT 132
BFD_RELOC_TILEGX_JUMPOFF_X1 132
BFD_RELOC_TILEGX_JUMPOFF_X1_PLT 132
BFD_RELOC_TILEGX_MF_IMM14_X1 132
BFD_RELOC_TILEGX_MMEND_X0 132
BFD_RELOC_TILEGX_MMSTART_X0 132
BFD_RELOC_TILEGX_MT_IMM14_X1 132
BFD_RELOC_TILEGX_RELATIVE 132
BFD_RELOC_TILEGX_SHAMT_X0 132
BFD_RELOC_TILEGX_SHAMT_X1 132
BFD_RELOC_TILEGX_SHAMT_Y0 132
BFD_RELOC_TILEGX_SHAMT_Y1 132
BFD_RELOC_TILEGX_TLS_DTPMOD32 134
BFD_RELOC_TILEGX_TLS_DTPMOD64 134
BFD_RELOC_TILEGX_TLS_DTPOFF32 134
BFD_RELOC_TILEGX_TLS_DTPOFF64 134
BFD_RELOC_TILEGX_TLS_GD_CALL 134
BFD_RELOC_TILEGX_TLS_IE_LOAD 134
BFD_RELOC_TILEGX_TLS_TPOFF32 134
BFD_RELOC_TILEGX_TLS_TPOFF64 134
BFD_RELOC_TILEPRO_BROFF_X1 130
BFD_RELOC_TILEPRO_COPY 130
BFD_RELOC_TILEPRO_DEST_IMM8_X1 130
BFD_RELOC_TILEPRO_GLOB_DAT 130
BFD_RELOC_TILEPRO_IMM16_X0 130
BFD_RELOC_TILEPRO_IMM16_X0_GOT 131
BFD_RELOC_TILEPRO_IMM16_X0_GOT_HA 131
BFD_RELOC_TILEPRO_IMM16_X0_GOT_HI 131
BFD_RELOC_TILEPRO_IMM16_X0_GOT_LO 131
BFD_RELOC_TILEPRO_IMM16_X0_HA 130
BFD_RELOC_TILEPRO_IMM16_X0_HA_PCREL 131
BFD_RELOC_TILEPRO_IMM16_X0_HI 130
BFD_RELOC_TILEPRO_IMM16_X0_HI_PCREL 131
BFD_RELOC_TILEPRO_IMM16_X0_LO 130
BFD_RELOC_TILEPRO_IMM16_X0_LO_PCREL 131
BFD_RELOC_TILEPRO_IMM16_X0_PCREL 131
BFD_RELOC_TILEPRO_IMM16_X0_TLS_GD 131
BFD_RELOC_TILEPRO_IMM16_X0_TLS_GD_HA 131
BFD_RELOC_TILEPRO_IMM16_X0_TLS_GD_HI 131
BFD_RELOC_TILEPRO_IMM16_X0_TLS_GD_LO 131
BFD_RELOC_TILEPRO_IMM16_X0_TLS_IE 131
BFD_RELOC_TILEPRO_IMM16_X0_TLS_IE_HA 131
BFD_RELOC_TILEPRO_IMM16_X0_TLS_IE_HI 131
BFD_RELOC_TILEPRO_IMM16_X0_TLS_IE_LO 131
BFD_RELOC_TILEPRO_IMM16_X0_TLS_LE 132
BFD_RELOC_TILEPRO_IMM16_X0_TLS_LE_HA 132
BFD_RELOC_TILEPRO_IMM16_X0_TLS_LE_HI 132
BFD_RELOC_TILEPRO_IMM16_X0_TLS_LE_LO 132
BFD_RELOC_TILEPRO_IMM16_X1 130
BFD_RELOC_TILEPRO_IMM16_X1_GOT 131
BFD_RELOC_TILEPRO_IMM16_X1_GOT_HA 131
BFD_RELOC_TILEPRO_IMM16_X1_GOT_HI 131
BFD_RELOC_TILEPRO_IMM16_X1_GOT_LO 131
BFD_RELOC_TILEPRO_IMM16_X1_HA 131
BFD_RELOC_TILEPRO_IMM16_X1_HA_PCREL 131
BFD_RELOC_TILEPRO_IMM16_X1_HI 130
BFD_RELOC_TILEPRO_IMM16_X1_HI_PCREL 131
BFD_RELOC_TILEPRO_IMM16_X1_LO 130
BFD_RELOC_TILEPRO_IMM16_X1_LO_PCREL 131

BFD_RELOC_TILEPRO_IMM16_X1_PCREL 131
BFD_RELOC_TILEPRO_IMM16_X1_TLS_GD 131
BFD_RELOC_TILEPRO_IMM16_X1_TLS_GD_HA 131
BFD_RELOC_TILEPRO_IMM16_X1_TLS_GD_HI 131
BFD_RELOC_TILEPRO_IMM16_X1_TLS_GD_LO 131
BFD_RELOC_TILEPRO_IMM16_X1_TLS_IE 131
BFD_RELOC_TILEPRO_IMM16_X1_TLS_IE_HA 131
BFD_RELOC_TILEPRO_IMM16_X1_TLS_IE_HI 131
BFD_RELOC_TILEPRO_IMM16_X1_TLS_IE_LO 131
BFD_RELOC_TILEPRO_IMM16_X1_TLS_LE 132
BFD_RELOC_TILEPRO_IMM16_X1_TLS_LE_HA 132
BFD_RELOC_TILEPRO_IMM16_X1_TLS_LE_HI 132
BFD_RELOC_TILEPRO_IMM16_X1_TLS_LE_LO 132
BFD_RELOC_TILEPRO_IMM8_X0 130
BFD_RELOC_TILEPRO_IMM8_X0_TLS_GD_ADD 131
BFD_RELOC_TILEPRO_IMM8_X1 130
BFD_RELOC_TILEPRO_IMM8_X1_TLS_GD_ADD 131
BFD_RELOC_TILEPRO_IMM8_Y0 130
BFD_RELOC_TILEPRO_IMM8_Y0_TLS_GD_ADD 131
BFD_RELOC_TILEPRO_IMM8_Y1 130
BFD_RELOC_TILEPRO_IMM8_Y1_TLS_GD_ADD 131
BFD_RELOC_TILEPRO_JMP_SLOT 130
BFD_RELOC_TILEPRO_JOFFLONG_X1 130
BFD_RELOC_TILEPRO_JOFFLONG_X1_PLT 130
BFD_RELOC_TILEPRO_MF_IMM15_X1 130
BFD_RELOC_TILEPRO_MMEND_X0 131
BFD_RELOC_TILEPRO_MMEND_X1 131
BFD_RELOC_TILEPRO_MMSTART_X0 131
BFD_RELOC_TILEPRO_MMSTART_X1 131
BFD_RELOC_TILEPRO_MT_IMM15_X1 130
BFD_RELOC_TILEPRO_RELATIVE 130
BFD_RELOC_TILEPRO_SHAMT_X0 131
BFD_RELOC_TILEPRO_SHAMT_X1 131
BFD_RELOC_TILEPRO_SHAMT_Y0 131
BFD_RELOC_TILEPRO_SHAMT_Y1 131
BFD_RELOC_TILEPRO_TLS_DTPMOD32 132
BFD_RELOC_TILEPRO_TLS_DTPOFF32 132
BFD_RELOC_TILEPRO_TLS_GD_CALL 131
BFD_RELOC_TILEPRO_TLS_IE_LOAD 131
BFD_RELOC_TILEPRO_TLS_TPOFF32 132
BFD_RELOC_V850_16_GOT 93
BFD_RELOC_V850_16_GOTOFF 93
BFD_RELOC_V850_16_PCREL 92
BFD_RELOC_V850_16_S1 92
BFD_RELOC_V850_16_SPLIT_OFFSET 92
BFD_RELOC_V850_17_PCREL 92
BFD_RELOC_V850_22_PCREL 91
BFD_RELOC_V850_22_PLT_PCREL 93
BFD_RELOC_V850_23 92
BFD_RELOC_V850_32_ABS 92
BFD_RELOC_V850_32_GOT 93
BFD_RELOC_V850_32_GOTOFF 93
BFD_RELOC_V850_32_GOTPCREL 93
BFD_RELOC_V850_32_PCREL 92
BFD_RELOC_V850_32_PLT_PCREL 93
BFD_RELOC_V850_9_PCREL 91
BFD_RELOC_V850_ALIGN 92
BFD_RELOC_V850_CALLT_15_16_OFFSET 92
BFD_RELOC_V850_CALLT_16_16_OFFSET 92
BFD_RELOC_V850_CALLT_6_7_OFFSET 92
BFD_RELOC_V850_CODE 93
BFD_RELOC_V850_COPY 93
BFD_RELOC_V850_DATA 93
BFD_RELOC_V850_GLOB_DAT 93
BFD_RELOC_V850_JMP_SLOT 93
BFD_RELOC_V850_LO16_S1 92
BFD_RELOC_V850_LO16_SPLIT_OFFSET 92
BFD_RELOC_V850_LONGCALL 92
BFD_RELOC_V850_LONGJUMP 92
BFD_RELOC_V850_RELATIVE 93
BFD_RELOC_V850_SDA_15_16_OFFSET 91
BFD_RELOC_V850_SDA_16_16_OFFSET 91
BFD_RELOC_V850_SDA_16_16_SPLIT_OFFSET 91
BFD_RELOC_V850_TDA_16_16_OFFSET 91
BFD_RELOC_V850_TDA_4_4_OFFSET 91
BFD_RELOC_V850_TDA_4_5_OFFSET 91
BFD_RELOC_V850_TDA_6_8_OFFSET 91
BFD_RELOC_V850_TDA_7_7_OFFSET 91
BFD_RELOC_V850_TDA_7_8_OFFSET 91
BFD_RELOC_V850_ZDA_15_16_OFFSET 91
BFD_RELOC_V850_ZDA_16_16_OFFSET 91
BFD_RELOC_V850_ZDA_16_16_SPLIT_OFFSET 92
BFD_RELOC_VAX_GLOB_DAT 113
BFD_RELOC_VAX_JMP_SLOT 113
BFD_RELOC_VAX_RELATIVE 113
BFD_RELOC_VISIUM_HI16 135
BFD_RELOC_VISIUM_HI16_PCREL 135
BFD_RELOC_VISIUM_IM16 135
BFD_RELOC_VISIUM_IM16_PCREL 135
BFD_RELOC_VISIUM_LO16 135
BFD_RELOC_VISIUM_LO16_PCREL 135
BFD_RELOC_VISIUM_REL16 135
BFD_RELOC_VPE4KMATH_DATA 105
BFD_RELOC_VPE4KMATH_INSN 105
BFD_RELOC_VTABLE_ENTRY 105
BFD_RELOC_VTABLE_INHERIT 105
BFD_RELOC_WASM32_ABS32_CODE 135
BFD_RELOC_WASM32_CODE_POINTER 135
BFD_RELOC_WASM32_COPY 135
BFD_RELOC_WASM32_INDEX 135
BFD_RELOC_WASM32_LEB128 135
BFD_RELOC_WASM32_LEB128_GOT 135
BFD_RELOC_WASM32_LEB128_GOT_CODE 135
BFD_RELOC_WASM32_LEB128_PLT 135
BFD_RELOC_WASM32_PLT_INDEX 135
BFD_RELOC_WASM32_PLT_SIG 135
BFD_RELOC_X86_64_32S 70
BFD_RELOC_X86_64_CODE_4_GOTPC32_TLSDESC ... 70
BFD_RELOC_X86_64_CODE_4_GOTPCRELX 70
BFD_RELOC_X86_64_CODE_4_GOTTPOFF 70
BFD_RELOC_X86_64_CODE_5_GOTPC32_TLSDESC ... 70
BFD_RELOC_X86_64_CODE_5_GOTPCRELX 70
BFD_RELOC_X86_64_CODE_5_GOTTPOFF 70
BFD_RELOC_X86_64_CODE_6_GOTPC32_TLSDESC ... 71
BFD_RELOC_X86_64_CODE_6_GOTPCRELX 70
BFD_RELOC_X86_64_CODE_6_GOTTPOFF 70

BFD_RELOC_X86_64_COPY 70
BFD_RELOC_X86_64_DTPMOD64 70
BFD_RELOC_X86_64_DTPOFF32 70
BFD_RELOC_X86_64_DTPOFF64 70
BFD_RELOC_X86_64_GLOB_DAT 70
BFD_RELOC_X86_64_GOT32 70
BFD_RELOC_X86_64_GOT64 70
BFD_RELOC_X86_64_GOTOFF64 70
BFD_RELOC_X86_64_GOTPC32 70
BFD_RELOC_X86_64_GOTPC32_TLSDESC 70
BFD_RELOC_X86_64_GOTPC64 70
BFD_RELOC_X86_64_GOTPCREL 70
BFD_RELOC_X86_64_GOTPCREL64 70
BFD_RELOC_X86_64_GOTPCRELX 70
BFD_RELOC_X86_64_GOTPLT64 70
BFD_RELOC_X86_64_GOTTPOFF 70
BFD_RELOC_X86_64_IRELATIVE 70
BFD_RELOC_X86_64_JUMP_SLOT 70
BFD_RELOC_X86_64_PC32_BND 70
BFD_RELOC_X86_64_PLT32 70
BFD_RELOC_X86_64_PLT32_BND 70
BFD_RELOC_X86_64_PLTOFF64 70
BFD_RELOC_X86_64_RELATIVE 70
BFD_RELOC_X86_64_REX_GOTPCRELX 70
BFD_RELOC_X86_64_TLSDESC 70
BFD_RELOC_X86_64_TLSDESC_CALL 70
BFD_RELOC_X86_64_TLSGD 70
BFD_RELOC_X86_64_TLSLD 70
BFD_RELOC_X86_64_TPOFF32 70
BFD_RELOC_X86_64_TPOFF64 70
BFD_RELOC_XGATE_24 108
BFD_RELOC_XGATE_GPAGE 108
BFD_RELOC_XGATE_IMM3 109
BFD_RELOC_XGATE_IMM4 109
BFD_RELOC_XGATE_IMM5 109
BFD_RELOC_XGATE_IMM8_HI 109
BFD_RELOC_XGATE_IMM8_LO 109
BFD_RELOC_XGATE_LO16 108
BFD_RELOC_XGATE_PCREL_10 108
BFD_RELOC_XGATE_PCREL_9 108
BFD_RELOC_XGATE_RL_GROUP 108
BFD_RELOC_XGATE_RL_JUMP 108
BFD_RELOC_XSTORMY16_12 113
BFD_RELOC_XSTORMY16_24 113
BFD_RELOC_XSTORMY16_FPTR16 113
BFD_RELOC_XSTORMY16_REL_12 113
BFD_RELOC_XTENSA_ASM_EXPAND 116
BFD_RELOC_XTENSA_ASM_SIMPLIFY 116
BFD_RELOC_XTENSA_DIFF16 115
BFD_RELOC_XTENSA_DIFF32 115
BFD_RELOC_XTENSA_DIFF8 115
BFD_RELOC_XTENSA_GLOB_DAT 115
BFD_RELOC_XTENSA_JMP_SLOT 115
BFD_RELOC_XTENSA_NDIFF16 116
BFD_RELOC_XTENSA_NDIFF32 116
BFD_RELOC_XTENSA_NDIFF8 116
BFD_RELOC_XTENSA_OP0 116
BFD_RELOC_XTENSA_OP1 116
BFD_RELOC_XTENSA_OP2 116
BFD_RELOC_XTENSA_PDIFF16 116
BFD_RELOC_XTENSA_PDIFF32 116
BFD_RELOC_XTENSA_PDIFF8 116
BFD_RELOC_XTENSA_PLT 115
BFD_RELOC_XTENSA_RELATIVE 115
BFD_RELOC_XTENSA_RTLD 115
BFD_RELOC_XTENSA_SLOT0_ALT 115
BFD_RELOC_XTENSA_SLOT0_OP 115
BFD_RELOC_XTENSA_SLOT1_ALT 115
BFD_RELOC_XTENSA_SLOT1_OP 115
BFD_RELOC_XTENSA_SLOT10_ALT 116
BFD_RELOC_XTENSA_SLOT10_OP 115
BFD_RELOC_XTENSA_SLOT11_ALT 116
BFD_RELOC_XTENSA_SLOT11_OP 115
BFD_RELOC_XTENSA_SLOT12_ALT 116
BFD_RELOC_XTENSA_SLOT12_OP 115
BFD_RELOC_XTENSA_SLOT13_ALT 116
BFD_RELOC_XTENSA_SLOT13_OP 115
BFD_RELOC_XTENSA_SLOT14_ALT 116
BFD_RELOC_XTENSA_SLOT14_OP 115
BFD_RELOC_XTENSA_SLOT2_ALT 115
BFD_RELOC_XTENSA_SLOT2_OP 115
BFD_RELOC_XTENSA_SLOT3_ALT 115
BFD_RELOC_XTENSA_SLOT3_OP 115
BFD_RELOC_XTENSA_SLOT4_ALT 115
BFD_RELOC_XTENSA_SLOT4_OP 115
BFD_RELOC_XTENSA_SLOT5_ALT 115
BFD_RELOC_XTENSA_SLOT5_OP 115
BFD_RELOC_XTENSA_SLOT6_ALT 116
BFD_RELOC_XTENSA_SLOT6_OP 115
BFD_RELOC_XTENSA_SLOT7_ALT 116
BFD_RELOC_XTENSA_SLOT7_OP 115
BFD_RELOC_XTENSA_SLOT8_ALT 116
BFD_RELOC_XTENSA_SLOT8_OP 115
BFD_RELOC_XTENSA_SLOT9_ALT 116
BFD_RELOC_XTENSA_SLOT9_OP 115
BFD_RELOC_XTENSA_TLS_ARG 116
BFD_RELOC_XTENSA_TLS_CALL 116
BFD_RELOC_XTENSA_TLS_DTPOFF 116
BFD_RELOC_XTENSA_TLS_FUNC 116
BFD_RELOC_XTENSA_TLS_TPOFF 116
BFD_RELOC_XTENSA_TLSDESC_ARG 116
BFD_RELOC_XTENSA_TLSDESC_FN 116
BFD_RELOC_Z80_16_BE 117
BFD_RELOC_Z80_BYTE0 117
BFD_RELOC_Z80_BYTE1 117
BFD_RELOC_Z80_BYTE2 117
BFD_RELOC_Z80_BYTE3 117
BFD_RELOC_Z80_DISP8 117
BFD_RELOC_Z80_WORD0 117
BFD_RELOC_Z80_WORD1 117
BFD_RELOC_Z8K_CALLR 117
BFD_RELOC_Z8K_DISP7 117
BFD_RELOC_Z8K_IMM4L 117
Byte swapping routines 180

C

`char` ... 13, 15, 40, 51, 139, 141, 154, 167, 168, 175
coff_symbol_type ... 200
core_file_matches_executable_p ... 141

G

generic_core_file_matches_executable_p ... 141

H

Hash tables ... 189

I

`int` ... 16, 18, 168, 169, 180, 193
internal object-file format ... 3

L

Linker ... 182
`long` ... 168

M

`machine_type` ... 197

O

Other functions ... 19

P

`per_xvec_messages` ... 15

S

struct bfd_iovec ... 22

T

target vector (_bfd_final_link) ... 184
target vector (_bfd_link_add_symbols) ... 182
target vector (_bfd_link_hash_table_create) ... 182
The HOWTO Macro ... 56

W

what is it? ... 1

The body of this manual is set in
cmr10,
with headings in **cmbx10**
and examples in `cmtt10`.
cmti10 and
cmsl10
are used for emphasis.